


Qun mk2 cheat Sheet

Next/Previous
Sequencer pattern
Yes or No



Sequencer
Play/Stop

Looper
buttons

Major mode

Parameter shortcut

Looper shortcut

Sub modes(Shift + B[1-8], YES or No)

Sequencer shortcut

Major mode	S+B1	S+B2	S+B3	S+B4	S+B5	S+B6	S+B7	S+B8	S+NO	S+YES
Play	Piano	Mod	ON/OFF	VEL	TUNE	WIDTH	Config	Granular	Mixer	Probability
System	bank 1	Bank 2	Bank 3	Bank 4	Bank 5	Bank 6	Bank 7	Bank 8	System	System2
Param	OSC1	OSC2	MIX	ENV1/2	Switch	LFO	VCF	Other	FM	Other/Env3/4

Basic shortcuts

Major mode	Shortcut	Description
Any	S+SEQ play + Dial	BPM
	Param + Dial	Cutoff
	Mode Play + Dial	Record volume
	System + Dial	VCF Volume
	Rec + Dial	LFO tune
	S + Looper Play + Dial	Load session (When not in System mode)
	Seq Play + B[1-8]	Select seq pattern
	Seq Play + B[1-8] + Dial	Copy seq pattern
	Mode Play + B[1-8]	Select Preset Bucket (Quick preset recall)
	Param + B[1-3]	Mute Looper Tracks
	Rec + B[1-3]	Select Looper Track
	Looper Play + B[1-5]	Select Looper Scene
	Rec + No	Looper track cut
	Rec + Yes	Looper track paste
	S + Looper Stop	Delete looper Scene
	Param + No	Toggle Extra Processing
	S + Param	Initialize preset
Play	Seq Play + No	Previous page
	Seq Play + Yes	Next page
System (Bank1 to 8)	S + Looper Play	Load preset
	S + Rec	Save preset

Basic parameters

Modulation parameters

Effector parameters

Modulation matrix parameters (Advanced)

Parameter list in param mode

Press button to select parameter
Press button + Turn dial to change parameter
(-) = long press

Sub Mode	B1	B2	B3	B4	B5	B6	B7	B8
OSC1	Shape	Width	Tune	Octave	Mod tune	Mod width	LFO tune	LFO width
OSC2	Shape	Width	Tune	Octave	Mod tune	Mod width	LFO tune	LFO width
Mix	Mix	FM	VCF volume	AUX gain	Effect type	Effect speed	Effect depth	Effect feedback
Env1/2	Env1 Attack	Env1 Decay	Env1 Sustain	Env1 Release	Env2 Attack	Env2 Decay	Env2 Sustain	Env2 Release
Switches	OSC1 Env sel	OSC1 Wide tune	OSC1 Mod sel	ENV1 Invert	OSC2 Env sel	OSC2 Wide tune	OSC2 Mod sel	ENV2 Invert
LFO	Tune	Shape	Width	Mod tune	Mod width	Keysplit	Gatesync	Mod sel
VCF	Cutoff	Resonance	Type	Mod cutoff	LFO cutoff	LFO Volume	OSC1 bypass	Keysync
Other	VCF pole	VCF Mod sel	Glide	Bend range	OSC1/OSC2 Keysync	Velocity Switch	Mono/Poly (OSC sync)	LFO sync Switch
FM	Algorithm	A amp	A freq	B amp	B freq	C amp	C freq	D amp
Other Env3/4	2nd filter	FM freq snap	Wave folding	FM env3 Connection	Env3/4 Attack	Env3/4 Decay	Env3/4 Sustain	Env3/4 Release

Press button to select parameter

Press button + Turn dial to change parameter
(-) = long press

Parameter list in Play mode

Sub Mode	B1	B2	B3	B4	B5	B6	B7	B8
Mod (Modifiers)	Pattern shuffle	Transpose	Width Shift	Random	Arp	Rewind Period	Rewind Steps	Apply
Config	Swing (MIDI ch)	Key	Scale	Seq count	BPM factor	Velocity Period	Low Velocity	Velocity Offset
Granular	-	AUX gain	Position	Length	Speed	Grain	Detune	Granular mode
Mix	Track A vol (Track A pan)	Track B vol (Track B pan)	Track C vol (Track C pan)	Record volume (Pan)	Compressor Threshold	Compressor Makeup	Extra processing ON/OFF	Looper vol

Visit <https://github.com/raspy135/Qun-mk2>
for full documentation.