

BILL OF MATERIALS

Document No :

HWPT011X6 BOM

1.0



Item	Qty	REFERENCE	TYPE	VALUE	TOLERANCE	RATING	DESCRIPTION	PACKAGE	VENDOR	VENDOR PART No
1	1	C39	CAPACITOR	2p7	+0p25	50V	CERAMIC COG	402	ANY	
2	2	C40 L15	CAPACITOR	3p2	+0p25	50V	CERAMIC COG	402	ANY	
3	1	R60	CAPACITOR	0p4	+0p05	50V	CERAMIC COG	402	MURATA	GJM1555C1HR40WB01
4	1	C37	CAPACITOR	0p8	+0p05	50V	CERAMIC COG	402	MURATA	GJM1555C1HR80WB01
5	3	C20 C22 C26	CAPACITOR	4u7		20% 6V3	CERAMIC X5R	402	PANASONIC	ECJ-0EB0J475M
6	5	C3-7	CAPACITOR	10u		20% 6V3	CERAMIC X5R	603	ANY	
7	2	C54-55	CAPACITOR	NF		20% 6V3	CERAMIC X5R	603	ANY	
8	1	C53	CAPACITOR	NF		5% 25V	CERAMIC COG	201	ANY	
9	1	C28	CAPACITOR	33p		5% 25V	CERAMIC COG	201	ANY	
10	1	C27	CAPACITOR	39p		5% 25V	CERAMIC COG	201	ANY	
11	1	C52	CAPACITOR	56p		5% 16V	CERAMIC COG	201	ANY	
12	1	C29	CAPACITOR	1n0		10% 50V	CERAMIC X7R	201	ANY	
13	4	C35 C45-46 C67	CAPACITOR	100n		10% 10V	CERAMIC X5R	201	ANY	
14	16	C1 C8-12 C15-19 C21 C23-25 C43	CAPACITOR	100n	+80%,-20%	6V3	CERAMIC Y5V	201	ANY	
15	1	C56	CAPACITOR	NF		0.6 5V	AL EL,RADIAL LOW ESR	11.3 x 13.0 x 6.0 mm	EATON	PB-5R0H104-R
16	1	F1	FILTER	DLP0NSN900HL2		100mA	COMMON MODE CHOKE	SMD0.65x0.85x0.45mm	MURATA	DLP0NSN900HL2
17	1	F2	FILTER	SAFFB1G58KA0 F0A			SAW GPS+GLONASS+BEID OU2	SMD 1.105mmx0.90mm	MURATA	SAFFB1G58KB0F0A
18	2	L3-4	FILTER	30R@100M		300mA	FERRITE BEAD	402	WURTH	74279274
19	1	L8	INDUCTOR	10n		2% 500mA	WIREWOUND	402	MURATA	LQW15AN10NG00
20	2	L7 R56	INDUCTOR	12n		2% 500mA	WIREWOUND	402	MURATA	LQW15AN12NG00
21	1	L2	INDUCTOR	15N	+0n2	1400mA	WIREWOUND	402	MURATA	LQW15AN15NG8ZD
22	1	L14	INDUCTOR	2n9	+0n2	1400mA	WIREWOUND	402	MURATA	LQW15AN2N9G8ZD
23	1	R15	INDUCTOR	5n1	+0n2	600mA	WIREWOUND	402	MURATA	LQW15AN5N1C00
24	1	L1	INDUCTOR	8n7	+0n2	1400mA	WIREWOUND	402	MURATA	LQW15AN8N7G8ZD
25	1	L5	INDUCTOR	8n4		2% 1600mA	WIREWOUND	603	MURATA	LQW18AN8N4G8ZD
26	1	L16	INDUCTOR	39n		5% 120mA	FILM	201	MURATA	LQP03TN39NJ02
27	1	L17	INDUCTOR	10n		5% 250mA	WIREWOUND	201	MURATA	LQW03AW10NJ00
28	1	D5	DIODE	ESD8472		12V	ESD PROTECTION	SMD 0201	ON-SEMI	ESD8472MUT5G
29	12	C38 C47 L6 L9 L12-13 R8 R16-17 R45-46 R50	RESISTOR	0R0		5% 0.063W		402	ANY	
30	4	C48-49 L10-11	RESISTOR	NF		5% 0.063W		402	ANY	
31	1	R1	RESISTOR	0R0		5% 0.10W		603	ANY	
32	1	R61	RESISTOR	NF		5% 0.10W		603	ANY	
33	12	R3 R6 R36-38 R57 R62 R64-68	RESISTOR	NF		5% 0.05W		201	ANY	
34	8	R58 R54 R63 R18 R69-70 R98 R100	RESISTOR	0R0		5% 0.05W		201	ANY	
35	1	R24	RESISTOR	1K0		5% 0.05W		201	ANY	
36	3	R20-21 R48	RESISTOR	10K		5% 0.05W		201	ANY	
37	11	R2 R5 R13-14 R25-28 R39 R74-75	RESISTOR	100K		5% 0.05W		201	ANY	
38	2	R29 R4	RESISTOR	NF		5% 0.05W		201	ANY	
39	1	R49	RESISTOR	220R		5% 0.05W		201	ANY	
40	1	R47	RESISTOR	2K2		5% 0.05W		201	ANY	
41	1	R22	RESISTOR	330R		5% 0.05W		201	ANY	
42	2	R12 R35	RESISTOR	4K7		5% 0.05W		201	ANY	
43	1	R23	RESISTOR	12K		1% 0.05W		201	ANY	
44	1	S1	SWITCH	TPA11CGRA0			PUSHBUTTON MOMENTARY	PTH SIDE ACTUATOR	ALCOSWITCH	TPA11CGRA0
45	1	U21	IC	74LVC1G04			INVERTER	DSBGA	TEXAS	SN74LVC1G04YZV
46	1	U16	IC	NF			EEPROM 2K SERIAL	SO8	ST MICROELECTRONICS	M93C56
47	1	U5	IC	FT4232HL			QUAD HS USB TO SERIAL UART	LQFP64	FTDI	FT4232HL-R

BILL OF MATERIALS	Document No :	HWPT011X6 BOM	1.0
--------------------------	---------------	---------------	-----

BILL OF MATERIALS	Document No :	HWPT011X6 BOM	1.0
--------------------------	---------------	---------------	-----

BILL OF MATERIALS	Document No :	HWPT011X6 BOM	1.0
--------------------------	---------------	---------------	-----

BILL OF MATERIALS	Document No :	HWPT011X6 BOM	1.0
--------------------------	---------------	---------------	-----

[illegible]