

## HOW IT WORKS

### *The Visilert device is extremely simple to use*

To operate the device in **Mode I**, the staff member simply turns the Visilert device on, presses the appropriate numbers, i.e., 6 then 0 for 60 minute rounding, then presses the “start/stop” button. The “Green” lights come on. The staff member would then place the device into the wall bracket outside of the patient room. They would then go about taking care of their other patients.

Internally the Visilert device calculates three different notification times. At 90%, or after 54 minutes in this example, the “Green” lights turn off and the “Yellow” lights come on. This tells the staff member they should begin preparing to round on the patient. If the staff member is not able to round on the patient by the 100% time or after 60 minutes in this example, the “Yellow” lights begin flashing. This reminds the staff the prescribed rounding time frame is about over. At 110% or after 66 minutes in this example, the flashing “Yellow” lights turn to “Red” indicating a failure to meet the patients’ expectations.

To reset the device, simply press the “start/stop” button, then the “reset” button. The timer will automatically revert back to the previous rounding time. Then simply press the “start/stop” button again. The process begins over. It couldn’t be simpler. To learn more, watch our video’s.

The beauty of the device in mode I is that you can select any rounding time you desire. For example, 120 minutes (every 2 hours at night), or 30 minutes to check back on the patient after giving them pain medication.

**Mode II** is designed to be infinitely programmable for any time frame up to 9999 minutes. For example, some hospitals are working diligently to manage their 24 hour observation patients. One health system has set a target that a final disposition will be made on all of their observation patients within the first 18 hours. They set the device to be “Green” for 900 minutes (15 hours), Yellow for 90 minutes (1.5 hours) and flashing yellow for 90 minutes (1.5 hours), for a total time frame of 18 hours. Note, just follow our instructions to set the time to what works best for you.

To operate the device in **Mode II**, once programmed (see instruction sheet), the staff member would simply turn the Visilert device on. Once turned on, they would press the “Mode” button one time. “II” will appear under the battery indicator. Once the “II” bars show, the staff member would simply press the “reset” button, then the “start/stop” button to begin the countdown process previously set. The “Green,” “Yellow,” and then the flashing “Yellow” lights will illuminate as programmed.