RESILIENT CURIOSITY
US.HERE.NOW.

Pre-Exercise Checks

Purpose:
Test functionality of all equipment required to receive and transmit on radio. Ensure local repeater information is still accurate. Build familiarity with your radio by configuring frequently used settings.

Required Equipment:

- Transceiver
- Antenna
- Power source

Required Information:

- Weather station frequencies
- Repeater locations, frequencies, tones, CTCSS

Location	Frequency (Transmit/Receive)	Offset	Tone

Steps:

1. Assemble radio
2. Turn on transceiver
3. Set power to high
4. Set frequency to weather station frequency
5. Program local repeater information into transceiver, save to memory
6. Confirm positive contact with repeater
7. Change to frequency to monitoring frequency on VHF (2m) / UHF (70cm)

Date								
Radio								
Antenna								
Power								
Location								

RESILIENT CURIOSITY
US.HERE.NOW.

Quick Reference Information

	Calling Frequencies	
	Band	**Freq (MHz)**
HF	80m	3.985
	40m	7.185
	20m	14.285
	10m	28.385
VHF	2m	146.520
UHF	70cm	446.000

Weather Channels	
Channel	**Freq (MHz)**
WX1	162.550
WX2	162.400
WX3	162.475
WX4	162.425
WX5	162.450
WX6	162.500
WX7	162.525

GMRS, FRS Channels	
Channel	**Freq(MHz)**
1	462.5625
2	462.5875
3	462.6125
4	462.6375
5	462.6625
6	462.6875
7	462.7125
8	467.5625
9	467.5875
10	467.6125
11	467.6375
12	467.6625
13	467.6875
14	467.7125
15	462.550
16	462.575
17	462.600
18	462.625
19	462.650
20	462.675
21	462.700
22	462.725

GMRS Repeaters		
Channel	**Receive (MHz)**	**Transmit (MHz)**
15R	462.550	467.550
16R	462.575	467.575
17R	462.600	467.600
18R	462.625	467.625
19R	462.650	467.650
20R	462.675	467.675
21R	462.700	467.700
22R	462.725	467.725

Q Codes	
Code	**Meaning**
QRM	Man-made interference
QRN	Natural noise (static, lightning)
QRO	High power
QRP	Low power (≤5 W)
QRS	Send slower
QRQ	Send faster
QRT	Stopping transmission
QRV	Ready to receive / available
QRX	Stand by, wait
QRZ	Who is calling me?
QSB	Fading
QSL	Acknowledge receipt
QSO	A contact or conversation
QSP	Relay a message
QST	Message to all amateurs
QSY	Change frequency
QTH	Location