

Quillmere AirPure AP200 Air Purifier User Manual

1. Specifications

- Recommended room size: up to 300 sq ft.
- Clean air delivery rate (CADR): 190 cubic feet per minute for smoke.
- Noise level: 28 dB in Night mode to 55 dB in Max mode.
- Replacement filter: AP-F200 two-stage filter (true HEPA and activated carbon).
- Fan modes: Night, Auto, and Max.

2. Operation and Maintenance

Child lock: press and hold the Power and Mode buttons together for 3 seconds.

Night mode: the fan runs quietly and the display dims to 10 percent brightness.

Replace the AP-F200 filter every 4 to 6 months. The filter light turns orange when a replacement is due. To reset it, hold the Filter button for 3 seconds.

3. Error Codes

- E04: Power supply fault. Use a different wall outlet. If E04 continues, contact support.
- E11: Air quality sensor fault. Contact support for a sensor replacement.
- E17: Fan speed sensor fault. Contact support. Do not replace the filter; the filter is not the cause.
- E21: Back cover open. Close the back cover until it clicks.