ShopSphere AX-204 Wireless ANC Headphones — User Manual

Model: AX-204 | Category: Electronics | Audio & Sound

1. Product Overview & Key Features

The ShopSphere AX-204 is a premium over-ear wireless headset engineered with Hybrid Active Noise Cancellation (ANC) reducing background noise by up to 35dB. Equipped with custom-tuned 40mm titanium diaphragm drivers, it delivers Hi-Res certified sound with deep bass and high treble clarity.

- Bluetooth 5.3 wireless technology with Multi-point pairing (connect up to 2 devices simultaneously).
- Battery Life: Up to 40 hours with Active Noise Cancellation enabled; up to 60 hours in standard Bluetooth mode.
- Fast USB-C Charging: A 10-minute quick charge yields 5 hours of playback. Full charge takes approximately 90 minutes.
- Microphones: 4 beamforming microphones with ENC (Environmental Noise Cancellation) for crystal clear voice calls.
- Water Resistance: Rated IPX4 splash and sweat resistance for workout and outdoor use.

2. Controls & Button Functions

All controls are located on the right earcup for easy access:

- Power Button: Hold 3 seconds to turn ON/OFF. When powered off, hold for 5 seconds to enter Bluetooth pairing mode (LED flashes red/blue).
- ANC Button: Single press cycles between: ANC Mode (Active Noise Cancellation) -> Transparency Mode (pass-through ambient voices) -> Normal Mode (ANC Off).
- Volume (+) & (-): Press once to step volume up or down. Hold Volume (+) for 2 seconds to skip to Next Track. Hold Volume (-) for 2 seconds for Previous Track.
- Multi-Function Button (Center): Press once to Play/Pause media or Answer/End incoming calls. Double press activates Voice Assistant (Siri / Google Assistant). Triple press toggles Low Latency Gaming Mode (50ms).

3. Factory Reset & Troubleshooting

If experiencing audio cutting, Bluetooth pairing failures, or unresponsive buttons, perform a factory reset:

- Ensure the headphones are powered off.
- Press and hold the Power Button and Volume Down (-) simultaneously for 10 seconds until the LED flashes red 3 times.
- Delete 'ShopSphere AX-204' from your phone/computer Bluetooth list and pair again.
- Charging Issue: Use the included USB-C cable and a 5V/1A or 5V/2A standard charger. Do not use high-wattage laptop chargers exceeding 65W.

4. Technical Specifications

Parameter	Specification
Bluetooth Version	v5.3 (Protocols: A2DP, AVRCP, HFP, HSP)
Driver Size	40mm Titanium Dynamic Drivers
Frequency Response	20 Hz - 20,000 Hz
Impedance	32 Ohms
Battery Capacity	750 mAh Li-ion rechargeable

Weight	260 grams (Lightweight ergonomic build)