

# Half-Day Reversal - IBKR Paper Setup

**Dashboard:** <https://half-day-reversal-production.up.railway.app>

1. Download version 1.2.6 from the dashboard again and replace the older July 31 copy. On Mac, open the DMG and double-click the connector. It installs itself into Applications and opens automatically.
2. If macOS blocks the first launch, use System Settings - Privacy & Security - Open Anyway, then double-click the connector in the download window once more. This is required only once.
3. Open Half-Day Reversal Connector. Saved keys remain after upgrades. If setup appears, enter the dashboard access key and Databento key supplied by Andrii, keep live mode locked, and save.
4. Open TWS Paper and sign in to paper account DUH450551.
5. In TWS open Global Configuration - API - Settings. Enable ActiveX and Socket Clients, disable Read-Only API, use port 7497, allow localhost/127.0.0.1, click Apply, then restart TWS.
6. Wait until the connector says Online. Keep TWS and the connector open through the next market open. The dashboard controls become available automatically.
7. In dashboard Settings choose IBKR Paper, host 127.0.0.1, port 7497, client ID 17, and account DUH450551. Click Use current S&P 400 beside Universe.
8. For the first safe paper cycle use 1% total capital, 1% maximum per position, one maximum position, and automatic runs off. Save settings.
9. Click Connect IBKR. Confirm the account label ends in 0551, then click Test paper order path. A green result means IBKR accepted the MOC what-if; no order is sent.
10. Click Preview scan during regular US market hours. Confirm the dashboard shows the current mid-cap universe and selected worst intraday performer.
11. For a real paper cycle, run between 3:37 and 3:44 PM New York time. Review the selection, arm with PAPER, then click Scan & execute. Confirm the MOC buy in TWS. The app stores the fill and submits the MKT/OPG sell at about 8:00 AM New York time for the next 9:30 AM opening auction.
12. After the safe paper cycle is signed off, the full 400-stock bottom-decile configuration uses maximum positions 40. Choose the total capital allocation deliberately and keep automatic runs off until the full settings are reviewed.

**If it does not connect:** click Open diagnostics in the connector and send connector.log to Andrii. If the setup screen cannot open, send startup-error.log from Library/Application Support/Half-Day Reversal. The logs do not contain either access key.

**Safety:** keep live mode locked until the complete MOC/MOO paper cycle has been reviewed. Auction orders do not guarantee a price.