

Accumulated Instrumentation

Register offset	Name	Minimum value	Maximum value	Scaling factor	Units	Bits/Sign	Register Address	Variables
6-7	Engine run time	0	4.29×10^9	1	Seconds	32	1798	E_Run_Time_1
94-95	Load kWh	0	4.29×10^9	0.1	kW hour	32	1886	L_KWH_1

Basic Instrumentation

Register offset	Name	Minimum value	Maximum value	Scaling factor	Units	Bits/Sign	Register Address	Variables
0	Oil pressure	0	10000	1	Kpa	16	1024	Oil_P_1
1	Coolant temperature	-50	200	1	Degree C	16 S	1025	Coolant_temp_1
3	Fuel Level	0	130	1	%	16	1027	F_Lev_1
5	Engine Battery voltage	0	40	0.1	V	16	1029	batt_V_1
6	Engine speed	0	6000	1	RPM	16	1030	e_Speed_1
7	Generator frequency	0	70	0.1	Hz	16	1031	g_Frequency_1
8-9	Generator L1-N voltage	0	18,000	0.1	V	32	1032	L1_N_1
10-11	Generator L2-N voltage	0	18,000	0.1	V	32	1034	L2_N_1
12-13	Generator L3-N voltage	0	18,000	0.1	V	32	1036	L3_N_1
14-15	Generator L1-L2 voltage	0	30,000	0.1	V	32	1038	L1_L2_1
16-17	Generator L2-L3 voltage	0	30,000	0.1	V	32	1040	L2_L3_1
18-19	Generator L3-L1 voltage	0	30,000	0.1	V	32	1042	L3_L1_1
35	Mains frequency	0	70	0.1	Hz	16	1059	
36-37	Mains L1-N voltage	0	18,000	0.1	V	32	1060	ML1_N_1
38-39	Mains L2-N voltage	0	18,000	0.1	V	32	1062	ML2_N_1
40-41	Mains L3-N voltage	0	18,000	0.1	V	32	1064	ML3_N_1
42-43	Mains L1-L2 voltage	0	30,000	0.1	V	32	1066	ML1_ML2_1
44-45	Mains L2-L3 voltage	0	30,000	0.1	V	32	1068	ML2_ML3_1
46-47	Mains L3-L1 voltage	0	30,000	0.1	V	32	1070	ML3_ML1_1

Derived Instrumentation

Register offset	Name	Minimum value	Maximum value	Scaling factor	Units	Bits/Sign	Register Address	Variables
0-1	Generator total watts	-99,999,999	99,999,999	1	W	32S	1536	G_total_W_1
21	Generator average power factor	-1	1	0.1		16S	1557	G_A_PF_1
94-95	Generator percentage of full power	-999.9	+999.9	0.1	%	16S	1630	G_FP_1

Extended Instrumentation

Register offset	Name	Minimum value	Maximum value	Scaling factor	Units	Bits/Sign	Register Address	Variables
79	Coolant level	0	100	1	%	16 U	1359	Coolant_level_1
128	Engine Operating State	0	15	See Table page 52		16U	1408	Engine_Status_1

Generating Set Status Information

Register offset	Name	Minimum value	Maximum value	Scaling factor	Units	Bits/Sign	Register Address	Variables
4	Control Mode	0	65535	See Table page 41		16	772	Control_Mode_1