Package 'ohun'

November 13, 2023
Title Optimizing Acoustic Signal Detection
Version 1.0.1
Maintainer Marcelo Araya-Salas <marcelo.araya@ucr.ac.cr></marcelo.araya@ucr.ac.cr>
Description Facilitates the automatic detection of acoustic signals, providing functions to diagnose and optimize the performance of detection routines. Detections from other software can also be explored and optimized. Araya-Salas et al. (2022) <doi:10.1101 2022.12.13.520253="">.</doi:10.1101>
License GPL (>= 2)
Encoding UTF-8
<pre>URL https://docs.ropensci.org/ohun/, https://github.com/ropensci/ohun/</pre>
<pre>BugReports https://github.com/ropensci/ohun/issues/</pre>
VignetteBuilder knitr
RoxygenNote 7.2.3
Language en-US
Imports tuneR, warbleR (>= 1.1.29), cli, methods, stats, utils, seewave (>= 2.0.1), fftw, rlang, sf, igraph, checkmate, ggplot2
Depends R (>= $3.2.1$)
Suggests knitr, rmarkdown, testthat, viridis, Sim.DiffProc, vdiffr
NeedsCompilation no
Author Marcelo Araya-Salas [aut, cre] (https://orcid.org/0000-0003-3594-619X), Alec L. Robitaille [rev] (https://orcid.org/0000-0003-1637-6822), Sam Lapp [rev] (https://orcid.org/0000-0003-1637-6822)
R topics documented:
consensus_detection diagnose_detection energy_detector get_envelopes

2 consensus_detection

cons	ensus_detection Remove ambiguous detections	
Index		44
	template_detector	41
	template_correlator	
	summarize_reference	
	summarize_diagnostic	34
	summarize_acoustic_data	33
	split_acoustic_data	32
	plot_detection	30
	optimize_template_detector	27
	optimize_energy_detector	22
	merge_overlaps	21
	lbh_reference	20
	lbh2	20
	lbh1	
	label_spectro	17
	label_detection	
	get_templates	13

Description

consensus_detection removes ambiguous detections

Usage

```
consensus_detection(detection, by = "overlap", filter = "max", cores = 1, pb = TRUE)
```

Arguments

detection	Data frame or selection table (using the warbleR package's format, see selection_table) with the output of label_detection containing the start and end of the signals. Must contained at least the following columns: "sound.files", "selec", "start", "end" and "detection.class" (the last one is generated by label_detection). It must also contained the column indicated in the 'by' argument (which is 'overlap' by default).
by	Character vector of length 1 indicating a column in 'detection' that will be used to filter detections. Must refer to a numeric column. Default is 'overlap', which is return by label_detection.
filter	Character vector of length 1 indicating the criterium used to filter the column refer to by the 'by' argument. Current options are 'max' (maximum) and 'min' (minimum). Default is 'max'.
cores	Numeric. Controls whether parallel computing is applied. It specifies the number of cores to be used. Default is 1 (i.e. no parallel computing).
pb	Logical argument to control progress bar. Default is TRUE.

consensus_detection 3

Details

This function removes ambiguous detections keeping only the one that maximizes a criterium given by 'filter'. By default it keeps the detection with the highest overlap to the reference signal. It works on the output of label_detection. Useful when several detections match the same reference as in the case of template detection with multiple templates (see template_detector).

Value

A data frame or selection table (if 'detection' was also a selection table, warbleR package's format, see selection_table) as in 'X' but removing ambiguous detections (split and merged positives).

Author(s)

Marcelo Araya-Salas (<marcelo.araya@ucr.ac.cr>).

References

#' Araya-Salas, M., Smith-Vidaurre, G., Chaverri, G., Brenes, J. C., Chirino, F., Elizondo-Calvo, J., & Rico-Guevara, A. 2022. ohun: an R package for diagnosing and optimizing automatic sound event detection. BioRxiv, 2022.12.13.520253. https://doi.org/10.1101/2022.12.13.520253

See Also

```
label_detection, template_detector
```

```
# load example data
data("lbh1", "lbh_reference")
# save sound files
tuneR::writeWave(lbh1, file.path(tempdir(), "lbh2.wav"))
# template for the first sound file in 'lbh_reference'
templ1 <- lbh_reference[1, ]</pre>
# generate template correlations
tc <- template_correlator(</pre>
  templates = templ1, path = tempdir(),
  files = "lbh2.wav"
)
# template detection
td <- template_detector(template.correlations = tc, threshold = 0.12)
# this detection generates 2 split positives
diagnose_detection(
  reference = lbh_reference[lbh_reference == "lbh2.wav", ],
  detection = td
)
```

4 diagnose_detection

```
# label detection
ltd <- label_detection(
    reference = lbh_reference[lbh_reference == "lbh2.wav", ],
    detection = td
)

# now they can be filter to keep the detection with the highest score for each split
ftd <- consensus_detection(ltd, by = "scores")

# splits must be 0
diagnose_detection(
    reference = lbh_reference[lbh_reference == "lbh2.wav", ],
    detection = ftd
)
}</pre>
```

diagnose_detection

Evaluate the performance of a sound event detection procedure

Description

diagnose_detection evaluates the performance of a sound event detection procedure comparing the output selection table to a reference selection table

Usage

```
diagnose_detection(reference, detection, by.sound.file = FALSE,
time.diagnostics = FALSE, cores = 1, pb = TRUE, path = NULL, by = NULL,
macro.average = FALSE, min.overlap = 0.5)
```

Arguments

reference

Data frame or 'selection.table' (following the warbleR package format) with the reference selections (start and end of the sound events) that will be used to evaluate the performance of the detection, represented by those selections in 'detection'. Must contained at least the following columns: "sound.files", "selec", "start" and "end". It must contain the reference selections that will be used for detection optimization.

detection

Data frame or 'selection.table' with the detections (start and end of the sound events) that will be compared against the 'reference' selections. Must contained at least the following columns: "sound.files", "selec", "start" and "end". It can contain data for additional sound files not found in 'references'. In this case the routine assumes that no sound events are found in those files, so detection from those files are all false positives.

by.sound.file

Logical argument to control whether performance diagnostics are summarized across sound files (when by . sound . file = FALSE, when more than 1 sound file is included in 'reference') or shown separated by sound file. Default is FALSE.

diagnose_detection 5

time.diagnostics

cores

Logical argument to control if diagnostics related to the duration of the sound

events ("mean.duration.true.positives", "mean.duration.false.positives", "mean.duration.false.negatives"

and "proportional.duration.true.positives") are returned (if TRUE). Default is FALSE.

Numeric. Controls whether parallel computing is applied. It specifies the num-

ber of cores to be used. Default is 1 (i.e. no parallel computing).

pb Logical argument to control progress bar. Default is TRUE.

path Character string containing the directory path where the sound files are located.

If supplied then duty cycle (fraction of a sound file in which sounds were detected)is also returned. This feature is more helpful for tuning an energy-based

detection. Default is NULL.

by Character vector with the name of a column in 'reference' for splitting diagnos-

tics. Diagnostics will be returned separated for each level in 'by'. Default is

NULL.

macro.average Logical argument to control if diagnostics are first calculated for each sound

file and then averaged across sound files, which can minimize the effect of unbalanced sample sizes between sound files. If FALSE (default) diagnostics are based on aggregated statistics irrespective of sound files. The following indices can be estimated by macro-averaging: overlap, mean.duration.true.positives,

mean.duration.false.positives, mean.duration.false.positives, mean.duration.false.negatives,

proportional.duration.true.positives, recall and precision (f.score is always derived from recall and precision). Note that when applying macro-averaging, recall and precision are not derived from the true positive, false positive and

false negative values returned by the function.

min.overlap Numeric. Controls the minimum amount of overlap required for a detection and

a reference sound for it to be counted as true positive. Default is 0.5. Overlap is

measured as intersection over union.

Details

The function evaluates the performance of a sound event detection procedure by comparing its output selection table to a reference selection table in which all sound events of interest have been selected. The function takes any overlap between detected sound events and target sound events as true positives. Note that all sound files located in the supplied 'path' will be analyzed even if not all of them are listed in 'reference'. When several possible matching pairs of sound event and detections are found, the optimal set of matching pairs is found through maximum bipartite matching (using the R package igraph). Priority for assigning a detection to a reference is given by the amount of time overlap. 'splits' and 'merge.positives' are also counted (i.e. counted twice) as 'true.positives'. Therefore "true.positives + false.positives = detections".

Value

A data frame including the following detection performance diagnostics:

- detections: total number of detections
- true.positives: number of sound events in 'reference' that correspond to any detection. Matching is defined as some degree of overlap in time. In a perfect detection routine it should be equal to the number of rows in 'reference'.

6 diagnose_detection

• false.positives: number of detections that don't match (i.e. don't overlap with) any of the sound events in 'reference'. In a perfect detection routine it should be 0.

- false.negatives: number of sound events in 'reference' that were not detected (not found in 'detection'. In a perfect detection routine it should be 0.
- splits: number of detections overlapping reference sounds that also overlap with other detections. In a perfect detection routine it should be 0.
- merges: number of detections that overlap with two or more reference sounds. In a perfect detection routine it should be 0.
- mean.duration.true.positives: mean duration of true positives (in ms). Only included when time.diagnostics = TRUE.
- mean.duration.false.positives: mean duration of false positives (in ms). Only included when time.diagnostics = TRUE.
- mean.duration.false.negatives: mean duration of false negatives (in ms). Only included when time.diagnostics = TRUE.
- overlap: mean intersection over union overlap of true positives.
- proportional.duration.true.positives: ratio of duration of true positives to the duration of sound events in 'reference'. In a perfect detection routine it should be 1. Based only on true positives that were not split or merged.
- duty.cycle: proportion of a sound file in which sounds were detected. Only included when time.diagnostics = TRUE and path is supplied. Useful when conducting energy-based detection as a perfect detection can be obtained with a very low amplitude threshold, which will detect everything, but will produce a duty cycle close to 1.
- recall: Proportion of sound events in 'reference' that were detected. In a perfect detection routine it should be 1.
- precision: Proportion of detections that correspond to sound events in 'reference'. In a perfect detection routine it should be 1.
- f. score: Combines recall and precision as the harmonic mean of these two. Provides a single value for evaluating performance. In a perfect detection routine it should be 1.

Author(s)

Marcelo Araya-Salas <marcelo.araya@ucr.ac.cr>)

References

Araya-Salas, M., Smith-Vidaurre, G., Chaverri, G., Brenes, J. C., Chirino, F., Elizondo-Calvo, J., & Rico-Guevara, A. 2022. ohun: an R package for diagnosing and optimizing automatic sound event detection. BioRxiv, 2022.12.13.520253. https://doi.org/10.1101/2022.12.13.520253

See Also

optimize_energy_detector, optimize_template_detector

Examples

```
# load data
 data("lbh_reference")
 # perfect detection
 diagnose_detection(reference = lbh_reference, detection = lbh_reference)
 # missing one in detection
 diagnose_detection(reference = lbh_reference, detection = lbh_reference[-1, ])
 # an extra one in detection
 diagnose_detection(reference = lbh_reference[-1, ], detection = lbh_reference)
 # with time diagnostics
 diagnose_detection(
    reference = lbh_reference[-1, ],
   detection = lbh_reference, time.diagnostics = TRUE
 )
 # and extra sound file in reference
 diagnose_detection(
    reference = 1bh_reference,
   detection =
     lbh_reference[lbh_reference$sound.files != "lbh1", ]
 )
 # and extra sound file in detection
 diagnose_detection(
    reference =
     lbh_reference[lbh_reference$sound.files != "lbh1", ],
   detection = lbh_reference
 )
 # and extra sound file in detection by sound file
 dd <- diagnose_detection(</pre>
    reference =
     lbh_reference[lbh_reference$sound.files != "lbh1", ],
   detection = lbh_reference, time.diagnostics = TRUE, by.sound.file = TRUE
 )
 # get summary
 summarize_diagnostic(dd)
}
```

energy_detector

Detects the start and end of sound events

Description

energy_detector detects the start and end of sound events based on energy and time attributes

Usage

```
energy_detector(files = NULL, envelopes = NULL, path = ".", hop.size = 11.6, wl = NULL,
thinning = 1, bp = NULL, smooth = 5, threshold = 5, peak.amplitude = 0,
hold.time = 0, min.duration = 0, max.duration = Inf, cores = 1, pb = TRUE)
```

Arguments

smooth

files Character vector indicating the sound files that will be analyzed. Optional. If

'files' and 'envelopes' are not supplied then the function will work on all supported format sound files in the working directory. Supported file formats:'.wav', '.mp3', '.flac' and '.wac'. If not supplied the function will work on all sound

files (in the supported format) in 'path'.

envelopes An object of class 'envelopes' (generated by get_envelopes) containing the

amplitude envelopes of the sound files to be analyzed. If 'files' and 'envelopes' are not supplied then the function will work on all supported format sound files

in the working directory.

path Character string containing the directory path where the sound files are located.

The current working directory is used as default.

hop.size A numeric vector of length 1 specifying the time window duration (in ms). De-

fault is 11.6 ms, which is equivalent to 512 wl for a 44.1 kHz sampling rate.

Ignored if 'wl' is supplied.

wl A numeric vector of length 1 specifying the window length of the spectrogram.

Default is NULL. If supplied, 'hop.size' is ignored. Used internally for bandpass

filtering (so only applied when 'bp' is supplied).

thinning Numeric vector of length 1 in the range 0~1 indicating the proportional reduc-

tion of the number of samples used to represent amplitude envelopes (i.e. the thinning of the envelopes). Usually amplitude envelopes have many more samples than those needed to accurately represent amplitude variation in time, which affects the size of the output (usually very large R objects / files). Default is 1 (no thinning). Higher sampling rates can afford higher size reduction (e.g. lower thinning values). Reduction is conducted by interpolation using approx. Note that thinning may decrease time precision, and the higher the thinning the less precise the time detection. This argument is used internally by get_envelopes.

Not used if 'envelopes' are supplied.

bp Numeric vector of length 2 giving the lower and upper limits of a frequency bandpass filter (in kHz). Default is NULL. This argument is used internally by

get_envelopes. Not used if 'envelopes' are supplied. Bandpass is done using the function codeffilter, which applies a short-term Fourier transformation to first create a spectrogram in which the target frequencies are filtered and then is

back transformed into a wave object using a reverse Fourier transformation.

A numeric vector of length 1 to smooth the amplitude envelope with a sum smooth function. It controls the time 'neighborhood' (in ms) in which amplitude samples are smoothed (i.e. averaged with neighboring samples). Default is 5. 0 means no smoothing is applied. Note that smoothing is applied before thinning (see 'thinning' argument). The function envelope is used internally which is analogous to sum smoothing in codeeny. This argument is used internally by

get_envelopes. Not used if 'envelopes' are supplied.

threshold Numeric vector of length 1 with a value between 0 and 100 specifying the ampli-

tude threshold for detecting sound event occurrences. Amplitude is represented as a percentage so 0 and 100 represent the lowest amplitude and highest ampli-

tude respectively. Default is 5.

peak.amplitude Numeric vector of length 1 with the minimum peak amplitude value. Detections

below that value are excluded. Peak amplitude is the maximum sound pressure level (in decibels) across the sound event (see sound_pressure_level). This can be useful when expecting higher peak amplitude in the target sound events compared to non-target sound events or when keeping only the best examples of

the target sound events. Default is 0.

hold.time Numeric vector of length 1. Specifies the time range (in ms) at which selec-

tions will be merged (i.e. if 2 selections are separated by less than the specified 'hold.time' they will be merged in to a single selection). Default is θ (no hold

time applied).

min.duration Numeric vector of length 1 giving the shortest duration (in ms) of the sound

events to be detected. It removes sound events below that threshold. If 'hold.time' is supplied sound events are first merged and then filtered by duration. Default

is 0 (i.e. no filtering based on minimum duration).

max.duration Numeric vector of length 1 giving the longest duration (in ms) of the sound

events to be detected. It removes sound events above that threshold. If 'hold.time' is supplied sound events are first merged and then filtered by duration. Default

is Inf (i.e. no filtering based on maximum duration).

cores Numeric. Controls whether parallel computing is applied. It specifies the num-

ber of cores to be used. Default is 1 (i.e. no parallel computing).

pb Logical argument to control progress bar. Default is TRUE.

Details

This function detects the time position of target sound events based on energy and time thresholds. It first detect all sound above a given energy threshold (argument 'energy'). If 'hold.time' is supplied then detected sounds are merged if necessary. Then the sounds detected are filtered based on duration attributes ('min.duration' and 'max.duration'). If 'peak.amplitude' is higher than 0 then only those sound events with higher peak amplitude are kept. Band pass filtering ('bp'), thinning ('thinning') and envelope smoothing ('smooth') are applied (if supplied) before threshold detection.

Value

The function returns a 'selection_table' (warbleR package's formats, see selection_table) or data frame (if sound files can't be found) containing the start and end of each sound event by sound file. If no sound event was detected for a sound file it is not included in the output data frame.

Author(s)

Marcelo Araya-Salas (<marcelo.araya@ucr.ac.cr>). Implements a

References

Araya-Salas, M., Smith-Vidaurre, G., Chaverri, G., Brenes, J. C., Chirino, F., Elizondo-Calvo, J., & Rico-Guevara, A. 2022. ohun: an R package for diagnosing and optimizing automatic sound event detection. BioRxiv, 2022.12.13.520253. https://doi.org/10.1101/2022.12.13.520253

See Also

```
optimize_energy_detector
```

```
# Save example files into temporary working directory
data("lbh1", "lbh2", "lbh_reference")
tuneR::writeWave(lbh1, file.path(tempdir(), "lbh1.wav"))
tuneR::writeWave(lbh2, file.path(tempdir(), "lbh2.wav"))
# using smoothing and minimum duration
detec <- energy_detector(files = c("lbh1.wav", "lbh2.wav"),</pre>
path = tempdir(), threshold = 6, smooth = 6.8,
bp = c(2, 9), hop.size = 3, min.duration = 0.05)
# diagnose detection
diagnose_detection(reference = lbh_reference,
detection = detec)
# without declaring 'files'
detec <- energy_detector(path = tempdir(), threshold = 60, smooth = 6.8,</pre>
bp = c(2, 9), hop.size = 6.8, min.duration = 90)
# diagnose detection
diagnose_detection(reference = 1bh_reference,
detection = detec)
# using hold time
detec <- energy_detector(threshold = 10, hold.time = 150,</pre>
bp = c(2, 9), hop.size = 6.8, path = tempdir())
# diagnose detection
diagnose_detection(reference = lbh_reference, detection = detec)
# calculate envelopes first
envs <- get_envelopes(bp = c(2, 9), hop.size = 6.8, path = tempdir())
# then run detection providing 'envelopes' (but no 'files')
detec <- energy_detector(envelopes = envs, threshold = 10, hold.time = 150, min.duration = 50)
# diagnose detection
diagnose_detection(reference = lbh_reference, detection = detec, time.diagnostics = TRUE)
# USIN OTHER SOUND FILE FORMAT (flac program must be installed)
# fisrt convert files to flac
warbleR::wav_2_flac(path = tempdir())
```

get_envelopes 11

```
# change sound file extension to flac
flac_reference <- lbh_reference
flac_reference$sound.files <- gsub(".wav", ".flac", flac_reference$sound.files)

# run detection
detec <- energy_detector(files = c("lbh1.flac", "lbh2.flac"), path = tempdir(), threshold = 60,
smooth = 6.8, bp = c(2, 9), hop.size = 6.8, min.duration = 90)

# diagnose detection
diagnose_detection(reference = flac_reference, detection = detec)</pre>
```

get_envelopes

Extract absolute amplitude envelopes

Description

get_envelopes extracts absolute amplitude envelopes to speed up energy detection

Usage

```
get_envelopes(path = ".", files = NULL, bp = NULL, hop.size = 11.6, wl = NULL,
cores = 1, thinning = 1, pb = TRUE, smooth = 5, normalize = TRUE)
```

Arguments

path	Character string containing the directory path where the sound files are located. The current working directory is used as default.
files	character vector or indicating the sound files that will be analyzed. Supported file formats:'.wav', '.mp3', '.flac' and '.wac'. If not supplied the function will work on all sound files (in the supported format) in 'path'.
bp	Numeric vector of length 2 giving the lower and upper limits of a frequency bandpass filter (in kHz). Default is NULL. Bandpass is done using the function codeffilter, which applies a short-term Fourier transformation to first create a spectrogram in which the target frequencies are filtered and then is back transformed into a wave object using a reverse Fourier transformation.
hop.size	A numeric vector of length 1 specifying the time window duration (in ms). Default is 11.6 ms, which is equivalent to 512 wl for a 44.1 kHz sampling rate. Ignored if 'wl' is supplied.
wl	A numeric vector of length 1 specifying the window length of the spectrogram. Default is NULL. If supplied, 'hop.size' is ignored. Used internally for bandpass filtering (so only applied when 'bp' is supplied).
cores	Numeric. Controls whether parallel computing is applied. It specifies the number of cores to be used. Default is 1 (i.e. no parallel computing).

12 get_envelopes

thinning

Numeric vector of length 1 in the range 0~1 indicating the proportional reduction of the number of samples used to represent amplitude envelopes (i.e. the thinning of the envelopes). Usually amplitude envelopes have many more samples than those needed to accurately represent amplitude variation in time, which affects the size of the output (usually very large R objects / files). Default is 1 (no thinning). Higher sampling rates can afford higher size reduction (e.g. lower thinning values). Reduction is conducted by linear interpolation using approx. Note that thinning may decrease time precision and that the higher the thinning the less precise the time detection. It's generally not advised if no smoothing ('smooth' argument) is applied.

pb

Logical argument to control progress bar. Default is TRUE.

smooth

A numeric vector of length 1 to smooth the amplitude envelope with a sum smooth function. It controls the time 'neighborhood' (in ms) in which amplitude samples are smoothed (i.e. averaged with neighboring samples). Default is 5. 0 means no smoothing is applied. Note that smoothing is applied before thinning (see 'thinning' argument). The function envelope is used internally which is analogous to sum smoothing in codeenv. This argument is used internally by get_envelopes.

normalize

Logical argument to control if envelopes are normalized to a 0-1 range.

Details

This function extracts the absolute amplitude envelopes of sound files. Can be used to manipulate envelopes before running energy_detector.

Value

An object of class 'envelopes'.

Author(s)

Marcelo Araya-Salas (<marcelo.araya@ucr.ac.cr>).

References

Araya-Salas, M., Smith-Vidaurre, G., Chaverri, G., Brenes, J. C., Chirino, F., Elizondo-Calvo, J., & Rico-Guevara, A. 2022. ohun: an R package for diagnosing and optimizing automatic sound event detection. BioRxiv, 2022.12.13.520253. https://doi.org/10.1101/2022.12.13.520253

See Also

```
energy_detector
```

```
# Save to temporary working directory
data(list = c("lbh1", "lbh2"))
tuneR::writeWave(lbh1, file.path(tempdir(), "lbh1.wav"))
```

get_templates 13

```
tuneR::writeWave(lbh2, file.path(tempdir(), "lbh2.wav"))
 # get raw absolute amplitude envelopes
 envs <- get_envelopes(path = tempdir())</pre>
 # extract segment for the first sound event in the first sound file
 x <- envs[[1]]$envelope</pre>
 # and plot it
 plot(x[(length(x) / 9):(length(x) / 4)], type = "l", xlab = "samples", ylab = "amplitude")
 # smoothing envelopes
 envs <- get_envelopes(path = tempdir(), smooth = 6.8)</pre>
 x <- envs[[1]]$envelope</pre>
 plot(x[(length(x) / 9):(length(x) / 4)], type = "1", xlab = "samples", ylab = "amplitude")
 # smoothing and thinning
 envs <- get_envelopes(path = tempdir(), thinning = 1 / 10, smooth = 6.8)</pre>
 x <- envs[[1]]$envelope</pre>
 plot(x[(length(x) / 9):(length(x) / 4)], type = "l", xlab = "samples", ylab = "amplitude")
 # no normalization
 envs <- get_envelopes(path = tempdir(), thinning = 1 / 10, smooth = 6.8)</pre>
 x <- envs[[1]]$envelope</pre>
 plot(x[(length(x) / 9):(length(x) / 4)],
    type = "1", xlab = "samples", ylab = "amplitude",
    normalize = FALSE
 )
}
```

get_templates

Find templates representative of the structural variation of sound events

Description

get_templates find the sound events that are closer to the acoustic space centroid (i.e. close to the average acoustic structure) in a reference table.

Usage

```
get_templates(reference, acoustic.space = NULL, path = ".",
n.sub.spaces = 1, plot = TRUE, color = "#21908C4D", ...)
```

Arguments

reference

Selection table (using the warbleR package's format, see selection_table) or data frame with columns for sound file name (sound.files), selection number (selec), and start and end time of sound event (start and end).

14 get_templates

acoustic.space Numeric matrix or data frame with the two dimensions of a custom acoustic

space to be used for finding templates. if not supplied the acoustic space is calculated internally (default). Optional. Note that the function assumes that 'reference' and 'acoustic.space' refer to the same sound events and similarly

ordered.

path Character string containing the directory path where the sound files are located.

The current working directory is used as default.

n.sub.spaces Integer vector of length 1 with the number of sub-spaces to split the total acous-

tic space. If n.sub.spaces = 1, only the sound event closer to the centroid is returned. If n.sub.spaces > 1 the function returns additional sound events, corresponding to those closer to the centroids of the sub-spaces. To do this, the function defines sub-spaces as equal-size slices of a circle centered at the

centroid of the acoustic space.

plot Logical to control if the plot is created. Default is TRUE.

color Character string with the point color. Default is '#21908C4D'.

.. Additional arguments to be passed to spectro_analysis for further customiza-

tion when measuring parameters to calculate the acoustic space.

Details

This function finds sound events (from a reference table) that are representative of the acoustic structure variation of all sound events. This is done by finding the events closer to the centroid of the acoustic space. If the acoustic space is not supplied ('acoustic.space' argument) then the function will estimate it by measuring several acoustic features using the function spectro_analysis (features related to energy distribution in the frequency and time domain as well as features of the dominant frequency contours, see spectro_analysis for more details) and summarizing it with Principal Component Analysis (after z-transforming parameters) using the function prcomp. The rationale is that a sound event close to the average structure is more likely to share structural features with most events across the acoustic space than a sound event in the periphery of the space. If only 1 template is required the function returns the sound event closest to the acoustic space centroid. If more than 1 template is required additional sound events are returned that are representative of the acoustic space. To do this, the function defines sub-spaces as equal-size slices of a circle centered at the centroid of the acoustic space. A column 'template' is included in the output selection table that identifies each template. Custom acoustic spaces can be supplied with argument 'acoustic.space'. Notice that the function aims to partition spaces in which sounds are somehow homogeneously distributed. When clear clusters are found in the distribution of the acoustic space thus clusters might not match the sub-spaces defined by the function.

Value

The function returns a 'selection_table' (warbleR package's formats, see selection_table) or data frame (if sound files can't be found) containing the start and end of each sound event by sound file.

Author(s)

Marcelo Araya-Salas (<marcelo.araya@ucr.ac.cr>). Implements a modified version of the timer function from seewave.

label_detection 15

References

Araya-Salas, M., Smith-Vidaurre, G., Chaverri, G., Brenes, J. C., Chirino, F., Elizondo-Calvo, J., & Rico-Guevara, A. 2022. ohun: an R package for diagnosing and optimizing automatic sound event detection. BioRxiv, 2022.12.13.520253. https://doi.org/10.1101/2022.12.13.520253

See Also

```
template_detector
```

Examples

```
{
  # Save example files into temporary working directory
  data("lbh1", "lbh2", "lbh_reference")
  tuneR::writeWave(lbh1, file.path(tempdir(), "lbh1.wav"))
  tuneR::writeWave(lbh2, file.path(tempdir(), "lbh2.wav"))

# get a single mean template
  template <- get_templates(reference = lbh_reference, path = tempdir())

# get 3 templates
  template <- get_templates(reference = lbh_reference, n.sub.spaces = 3, path = tempdir())
}</pre>
```

label_detection

Label detections from a sound event detection procedure

Description

label_detection labels the performance of a sound event detection procedure comparing the output selection table to a reference selection table

Usage

```
label_detection(reference, detection, cores = 1, pb = TRUE, min.overlap = 0.5,
by = NULL)
```

Arguments

reference

Data frame or 'selection.table' (following the warbleR package format) with the reference selections (start and end of the sound events) that will be used to evaluate the performance of the detection, represented by those selections in 'detection'. Must contained at least the following columns: "sound.files", "selec", "start" and "end". It must contain the reference selections that will be used for detection optimization.

16 label_detection

detection Data frame or 'selection.table' with the detections (start and end of the sound

events) that will be compared against the 'reference' selections. Must contained at least the following columns: "sound.files", "selec", "start" and "end". It can contain data for additional sound files not found in 'references'. In this case the routine assumes that no sound events are found in those files, so detection from

those files are all false positives.

cores Numeric. Controls whether parallel computing is applied. It specifies the num-

ber of cores to be used. Default is 1 (i.e. no parallel computing).

pb Logical argument to control progress bar. Default is TRUE.

min.overlap Numeric. Controls the minimum amount of overlap required for a detection and

a reference sound for it to be counted as true positive. Default is 0.5. Overlap is

measured as intersection over union.

by Character vector with the name of a categorical column in 'reference' for run-

ning a stratified. Labels will be returned separated for each level in 'by'. Default

is NULL.

Details

The function identifies the rows in the output of a detection routine as true or false positives. This is achieved by comparing the data frame to a reference selection table in which all sound events of interest have been selected.

Value

A data frame or selection table (if 'detection' was also a selection table, warbleR package's format, see selection_table) including three additional columns, 'detection.class', which indicates the class of each detection, 'reference' which identifies the event in the 'reference' table that was detected and 'overlap' which refers to the amount overlap to the reference sound. See diagnose_detection for a description of the labels used in 'detection.class'. The output data frame also contains an additional data frame with the overlap for each pair of overlapping detection/reference. Overlap is measured as intersection over union.

Author(s)

Marcelo Araya-Salas <marcelo.araya@ucr.ac.cr>)

References

Araya-Salas, M., Smith-Vidaurre, G., Chaverri, G., Brenes, J. C., Chirino, F., Elizondo-Calvo, J., & Rico-Guevara, A. 2022. ohun: an R package for diagnosing and optimizing automatic sound event detection. BioRxiv, 2022.12.13.520253. https://doi.org/10.1101/2022.12.13.520253

See Also

diagnose_detection, summarize_diagnostic

label_spectro 17

Examples

```
# load data
 data("lbh_reference")
 # an extra one in detection (1 false positive)
 label_detection(reference = lbh_reference[-1, ], detection = lbh_reference)
 # missing one in detection (all true positives)
 label_detection(reference = lbh_reference, detection = lbh_reference[-1, ])
 # perfect detection (all true positives)
 label_detection(reference = lbh_reference, detection = lbh_reference)
 # and extra sound file in reference (all true positives)
 label_detection(
    reference = 1bh_reference, detection =
     lbh_reference[lbh_reference$sound.files != "lbh1.wav", ]
 # and extra sound file in detection (some false positives)
 label_detection(
    reference =
      lbh_reference[lbh_reference$sound.files != "lbh1.wav", ],
   detection = lbh_reference
 )
 # duplicate 1 detection row (to get 2 splits)
 detec <- lbh_reference[c(1, seq_len(nrow(lbh_reference))), ]</pre>
 detecselec[1] <- 1.2
 label_detection(
    reference = 1bh_reference,
    detection = detec
 )
 # merge 2 detections (to get split and merge)
 Y <- lbh_reference
 Y$end[1] <- 1.2
 label_detection(reference = lbh_reference, detection = Y)
 # remove split to get only merge
 Y \leftarrow Y[-2,]
 label_detection(reference = lbh_reference, detection = Y)
}
```

label_spectro

Plot a labeled spectrogram

Description

label_spectro plot a spectrogram along with amplitude envelopes or cross-correlation scores

18 label_spectro

Usage

```
label_spectro(wave, reference = NULL, detection = NULL,
envelope = FALSE, threshold = NULL, smooth = 5, collevels = seq(-100, 0, 5),
palette = viridis::viridis, template.correlation = NULL,
line.x.position = 2, hop.size = NULL, ...)
```

Arguments

wave A 'wave' class object.

reference Data frame or 'selection.table' (following the warbleR package format) with the

reference selections (start and end of the sound events). Must contained at least

the following columns: "sound.files", "selec", "start" and "end".

detection Data frame or 'selection.table' with the detection (start and end of the sound

events) Must contained at least the following columns: "sound.files", "selec",

"start" and "end".

envelope Logical to control whether the amplitude envelope is plotted. Default is FALSE.

threshold A numeric vector on length 1 indicated the amplitude or correlation threshold

to plot on the envelope or correlation scores respectively. Default is NULL. Note that for amplitude the range of valid values is 0-1, while for correlations the

range is 0-100.

smooth A numeric vector of length 1 to smooth the amplitude envelope with a sum

smooth function. It controls the time range (in ms) in which amplitude samples are smoothed (i.e. averaged with neighboring samples). Default is 5. 0 means

no smoothing is applied.

collevels Numeric sequence of negative numbers to control color partitioning and ampli-

tude values that are shown (as in spectro).

palette Function with the color palette to be used on the spectrogram (as in spectro)

template.correlation

List extracted from the output of template_correlator containing the correlation scores and metadata for an specific sound file/template dyad. For instance 'correlations[[1]]' where 'correlations' is the output of a template_correlator

call. If supplied the correlation is also plotted. Default is NULL.

line.x.position

Numeric vector of length 1 with the position in the frequency axis (so in kHz)

of the lines highlighting sound events. Default is 2.

hop.size A numeric vector of length 1 specifying the time window duration (in ms). De-

fault is 11.6 ms, which is equivalent to 512 'wl' for a 44.1 kHz sampling rate.

... Additional arguments to be passed to spectro for further spectrogram cus-

tomization.

Details

This function plots spectrograms annotated with the position of sound events. **Created for graphs included in the vignette, and probably only useful for that or for very short recordings**. Only works on a single 'wave' object at the time.

lbh1 19

Value

A spectrogram along with lines highlighting the position of sound events in 'reference' and/or 'detection'. If supplied it will also plot the amplitude envelope or corelation scores below the spectrogram.

Author(s)

Marcelo Araya-Salas (<marcelo.araya@ucr.ac.cr>).

References

#' Araya-Salas, M., Smith-Vidaurre, G., Chaverri, G., Brenes, J. C., Chirino, F., Elizondo-Calvo, J., & Rico-Guevara, A. 2022. ohun: an R package for diagnosing and optimizing automatic sound event detection. BioRxiv, 2022.12.13.520253. https://doi.org/10.1101/2022.12.13.520253

See Also

```
energy_detector, template_correlator, template_detector
```

Examples

```
{
    # load example data
    data(list = "lbh1", "lbh_reference")

# adding labels
label_spectro(
    wave = lbh1,
    reference = lbh_reference[lbh_reference$sound.files == "lbh1.wav", ],
    wl = 200, ovlp = 50, flim = c(1, 10)
)

# adding envelope
label_spectro(
    wave = lbh1,
    detection = lbh_reference[lbh_reference$sound.files == "lbh1.wav", ],
    wl = 200, ovlp = 50, flim = c(1, 10)
)

# see the package vignette for more examples
}
```

1bh1

Long-billed hermit recording

Description

1bh1 a wave object with long-billed hermit (*Phaethornis longirostris*) songs extracted from xeno-canto's '154138' recording.

20 lbh_reference

Usage

```
data(lbh1)
```

Format

An object of class Wave of length 110250.

Source

Marcelo Araya-Salas

1bh2

Long-billed hermit recording

Description

1bh2 a wave object with long-billed hermit (*Phaethornis longirostris*) songs extracted from xeno-canto's '154129' recording.

Usage

```
data(1bh2)
```

Format

An object of class Wave of length 110250.

Source

Marcelo Araya-Salas

1bh_reference

Example data frame of a selection table including all sound events of interests.

Description

1bh_reference is a data frame containing the start, end, bottom and top frequency of all songs in 'lbh_1.wav' and 'lbh_2.wav' recordings. #'

Usage

```
data(lbh_reference)
```

merge_overlaps 21

Format

A data frame with 19 rows and 6 variables:

sound.files recording names
selec selection numbers within recording
start start times of selected sound event
end end times of selected sound event
bottom.freq lower limit of frequency range
top.freq upper limit of frequency range

Details

A data frame containing the start, end, low and high frequency of *Phaethornis longirostris* (Long-billed Hermit) songs from the 2 example sound files included in this package ('lbh_1' and 'lbh_2'). These two files are clips extracted from the xeno-canto's '154138' and '154129' recordings respectively.

Source

Marcelo Araya-Salas, ohun

Merge overlapping selections

Description

merge_overlaps merges several overlapping selections into a single selection

Usage

```
merge_overlaps(X, pb = TRUE, cores = 1)
```

Arguments

Χ	Data frame or 'selection.table' (following the warbleR package format) with se-
	lections (start and end of the sound events). Must contained at least the following columns: "sound.files", "selec", "start" and "end".
pb	Logical argument to control progress bar. Default is TRUE.
cores	Numeric. Controls whether parallel computing is applied. It specifies the number of cores to be used. Default is 1 (i.e. no parallel computing).

Details

The function finds time-overlapping selection in reference tables and collapses them into a single selection. It can be useful to prepare reference tables to be used in an energy detection routine. In such cases overlapping selections are expected to be detected as a single sound. Therefore, merging them can be useful to prepare references in a format representing a more realistic expectation of how a perfect energy detection routine would look like.

Value

If any time-overlapping selection is found it returns a data frame in which overlapping selections are collapse into a single selection.

Author(s)

Marcelo Araya-Salas <marcelo.araya@ucr.ac.cr>)

References

Araya-Salas, M., Smith-Vidaurre, G., Chaverri, G., Brenes, J. C., Chirino, F., Elizondo-Calvo, J., & Rico-Guevara, A. 2022. ohun: an R package for diagnosing and optimizing automatic sound event detection. BioRxiv, 2022.12.13.520253. https://doi.org/10.1101/2022.12.13.520253

See Also

```
summarize_diagnostic, label_detection
```

Examples

```
{
    # load data
    data("lbh_reference")

# nothing to merge
merge_overlaps(lbh_reference)

# create artificial overlapping selections
lbh_ref2 <- rbind(as.data.frame(lbh_reference[c(3, 10), ]), lbh_reference[c(3, 10), ])
lbh_ref2$selec <- seq_len(nrow(lbh_ref2))

merge_overlaps(lbh_ref2)
}</pre>
```

optimize_energy_detector

Optimize energy-based sound event detection

Description

Optimize energy-based sound event detection under different correlation threshold values

Usage

```
optimize_energy_detector(reference, files = NULL, threshold = 5, peak.amplitude = 0, hop.size = 11.6, wl = NULL, smooth = 5, hold.time = 0, min.duration = NULL, max.duration = NULL, thinning = 1, cores = 1, pb = TRUE, by.sound.file = FALSE, bp = NULL, path = ".", previous.output = NULL, envelopes = NULL, macro.average = FALSE, min.overlap = 0.5)
```

Arguments

files

reference Selection table (using the warbleR package's format, see selection_table) or

data frame with columns for sound file name (sound.files), selection number (selec), and start and end time of sound event (start and end). It must contain

the reference selections that will be used for detection optimization.

Character vector indicating the sound files that will be analyzed. Optional. If not supplied the function will work on the sound files in 'reference'. It can be used to include sound files with no target sound events. Supported file formats:'.wav', '.mp3', '.flac' and '.wac'. If not supplied the function will work on all sound

files (in the supported format) in 'path'.

threshold A numeric vector specifying the amplitude threshold for detecting sound events

(in %). Default is 5. **Several values can be supplied for optimization**.

peak.amplitude Numeric vector of length 1 with the minimum peak amplitude value. A detec-

tion below that value would be excluded. Peak amplitude is the maximum sound pressure level (in decibels) across the sound event (see sound_pressure_level). This can be useful when expecting higher peak amplitude in the target sound events compared to non-target sound events or when keeping only the best examples of the target sound events (i.e. high precision and low recall). Default is

0. Several values can be supplied for optimization.

hop.size A numeric vector of length 1 specifying the time window duration (in ms). De-

fault is 11.6 ms, which is equivalent to 512 wl for a 44.1 kHz sampling rate.

Ignored if 'wl' is supplied.

wl A numeric vector of length 1 specifying the window length of the spectrogram.

Default is NULL. If supplied, 'hop.size' is ignored. Used internally for bandpass

filtering (so only applied when 'bp' is supplied).

smooth A numeric vector of length 1 to smooth the amplitude envelope with a sum

smooth function. It controls the time 'neighborhood' (in ms) in which amplitude samples are smoothed (i.e. averaged with neighboring samples). Default is 5. 0 means no smoothing is applied. Note that smoothing is applied before thinning (see 'thinning' argument). The function envelope is used internally which is analogous to sum smoothing in codeenv. This argument is used internally by

get_envelopes. Several values can be supplied for optimization.

hold.time Numeric vector of length 1. Specifies the time range (in ms) at which selec-

tions will be merged (i.e. if 2 selections are separated by less than the specified 'hold.time' they will be merged in to a single selection). Default is \emptyset (no hold

time applied). Several values can be supplied for optimization.

min.duration Numeric vector giving the shortest duration (in ms) of the sound events to be

detected. It removes sound events below that threshold. Several values can be

supplied for optimization.

max.duration Numeric vector giving the longest duration (in ms) of the sound events to be

detected. It removes sound events above that threshold. Several values can be

supplied for optimization.

thinning Numeric vector in the range 0~1 indicating the proportional reduction of the number of samples used to represent amplitude envelopes (i.e. the thinning of

the envelopes). Usually amplitude envelopes have many more samples than

those needed to accurately represent amplitude variation in time, which affects the size of the output (usually very large R objects / files). Default is 1 (no thinning). Higher sampling rates may afford higher size reduction (e.g. lower thinning values). Reduction is conducted by interpolation using approx. Note that thinning may decrease time precision, and the higher the thinning the less precise the time detection. Several values can be supplied for optimization.

cores

Numeric. Controls whether parallel computing is applied. It specifies the number of cores to be used. Default is 1 (i.e. no parallel computing).

pb

Logical argument to control progress bar and messages. Default is TRUE.

by.sound.file

Logical argument to control whether performance diagnostics are summarized across sound files (when by . sound . file = FALSE and more than 1 sound file is included in 'reference') or shown separated by sound file. Default is FALSE.

bp

Numeric vector of length 2 giving the lower and upper limits of a frequency bandpass filter (in kHz). Default is NULL. This argument is used internally by get_envelopes. Not used if 'envelopes' are supplied. Bandpass is done using the function codeffilter, which applies a short-term Fourier transformation to first create a spectrogram in which the target frequencies are filtered and then is back transformed into a wave object using a reverse Fourier transformation.

path

Character string containing the directory path where the sound files are located. The current working directory is used as default.

previous.output

Data frame with the output of a previous run of this function. This will be used to include previous results in the new output and avoid recalculating detection performance for parameter combinations previously evaluated.

envelopes

An object of class 'envelopes' (generated by get_envelopes) containing the amplitude envelopes of the sound files to be analyzed. If 'files' and 'envelopes' are not supplied then the function will work on all supported format sound files in the working directory.

macro.average

Logical argument to control if diagnostics are first calculated for each sound file and then averaged across sound files, which can minimize the effect of unbalanced sample sizes between sound files. If FALSE (default) diagnostics are based on aggregated statistics irrespective of sound files. The following indices can be estimated by macro-averaging: overlap, mean.duration.true.positives, mean.duration.false.positives, mean.duration.false.positives, mean.duration.false.positives, recall and precision (f.score is always derived from recall and precision). Note that when applying macro-averaging, recall and precision are not derived from the true positive, false positive and false negative values returned by the function.

min.overlap

Numeric. Controls the minimum amount of overlap required for a detection and a reference sound for it to be counted as true positive. Default is 0.5. Overlap is measured as intersection over union.

Details

This function takes a selections data frame or 'selection_table' ('reference') estimates the detection performance of a energy detector under different detection parameter combinations. This is done

by comparing the position in time of the detection to those of the reference selections in 'reference'. The function returns several diagnostic metrics to allow user to determine which parameter values provide a detection that more closely matches the selections in 'reference'. Those parameters can be later used for performing a more efficient detection using energy_detector.

Value

A data frame in which each row shows the result of a detection job with a particular combination of tuning parameters (including in the data frame). It also includes the following diagnostic metrics:

- true.positives: number of sound events in 'reference' that correspond to any detection. Matching is defined as some degree of overlap in time. In a perfect detection routine it should be equal to the number of rows in 'reference'.
- false.positives: number of detections that don't match any of the sound events in 'reference'. In a perfect detection routine it should be 0.
- false.negatives: number of sound events in 'reference' that were not detected (not found in 'detection'. In a perfect detection routine it should be 0.
- splits: number of detections overlapping reference sounds that also overlap with other detections. In a perfect detection routine it should be 0.
- merges: number of detections that overlap with two or more reference sounds. In a perfect detection routine it should be 0.
- mean.duration.true.positives: mean duration of true positives (in ms). Only included when time.diagnostics = TRUE.
- mean.duration.false.positives: mean duration of false positives (in ms). Only included when time.diagnostics = TRUE.
- mean.duration.false.negatives: mean duration of false negatives (in ms). Only included when time.diagnostics = TRUE.
- overlap: mean intersection over union overlap of true positives.
- proportional.duration.true.positives: ratio of duration of true positives to th duration of sound events in 'reference'. In a perfect detection routine it should be 1. Based only on true positives that were not split or merged. Only included when time.diagnostics = TRUE.
- duty.cycle: proportion of a sound file in which sounds were detected. Only included when time.diagnostics = TRUE and path is supplied.
- recall: Proportion of sound events in 'reference' that were detected. In a perfect detection routine it should be 1.
- precision: Proportion of detections that correspond to sound events in 'reference'. In a perfect detection routine it should be 1.

Author(s)

Marcelo Araya-Salas (<marcelo.araya@ucr.ac.cr>).

References

Araya-Salas, M., Smith-Vidaurre, G., Chaverri, G., Brenes, J. C., Chirino, F., Elizondo-Calvo, J., & Rico-Guevara, A. 2022. ohun: an R package for diagnosing and optimizing automatic sound event detection. BioRxiv, 2022.12.13.520253. https://doi.org/10.1101/2022.12.13.520253

```
# Save example files into temporary working directory
data("lbh1", "lbh2", "lbh_reference")
tuneR::writeWave(lbh1, file.path(tempdir(), "lbh1.wav"))
tuneR::writeWave(lbh2, file.path(tempdir(), "lbh2.wav"))
# using smoothing and minimum duration
optimize_energy_detector(
  reference = lbh_reference, path = tempdir(),
  threshold = c(6, 10), smooth = 6.8, bp = c(2, 9), hop.size = 6.8,
  min.duration = 90
)
# with thinning and smoothing
optimize_energy_detector(
  reference = lbh_reference, path = tempdir(),
  threshold = c(6, 10, 15), smooth = c(7, 10), thinning = c(0.1, 0.01),
  bp = c(2, 9), hop.size = 6.8, min.duration = 90
)
# by sound file
(opt_ed <- optimize_energy_detector(</pre>
  reference = lbh_reference,
  path = tempdir(), threshold = c(6, 10, 15), smooth = 6.8, bp = c(2, 9),
  hop.size = 6.8, min.duration = 90, by.sound.file = TRUE
))
# summarize
summarize_diagnostic(opt_ed)
# using hold time
(op_ed <- optimize_energy_detector(</pre>
  reference = 1bh_reference,
  threshold = 10, hold.time = c(100, 150), bp = c(2, 9), hop.size = 6.8,
  path = tempdir()
))
# including previous output in new call
optimize_energy_detector(
  reference = lbh_reference, threshold = 10,
  hold.time = c(50, 200), previous.output = op_ed, smooth = 6.8,
  bp = c(2, 9), hop.size = 7, path = tempdir()
)
# having and extra file in files (simulating a file that should have no detetions)
sub_reference <- lbh_reference[lbh_reference$sound.files != "lbh1.wav", ]</pre>
optimize_energy_detector(
  reference = sub_reference, files = unique(lbh_reference$sound.files),
  threshold = 10, hold.time = c(1, 150), bp = c(2, 9), smooth = 6.8,
  hop.size = 7, path = tempdir()
)
```

optimize_template_detector

Optimize acoustic template detection

Description

optimize_template_detector optimizes acoustic template detection

Usage

```
optimize_template_detector(template.correlations, reference, threshold,
cores = 1, pb = TRUE, by.sound.file = FALSE, previous.output = NULL,
macro.average = FALSE, min.overlap = 0.5)
```

Arguments

template.correlations

An object of class 'template_correlations' (generated by template_correlator) in which to optimize detections. Must contain data for all sound files as in 'reference'. It can also contain data for additional sound files. In this case the routine assumes that no sound events are found in those files, so detection from those files are all false positives.

reference

Data frame or 'selection.table' (following the warbleR package format) with the reference selections (start and end of the sound events) that will be used to evaluate the performance of the detection, represented by those selections in 'detection'. Must contained at least the following columns: "sound.files", "selec", "start" and "end". It must contain the reference selections that will be used for detection optimization.

threshold

Numeric vector of length > 1 with values between 0 and 1 specifying the correlation threshold for detecting sound event occurrences (i.e. correlation peaks). Must be supplied. Several values should be supplied for optimization.

cores

Numeric. Controls whether parallel computing is applied. It specifies the number of cores to be used. Default is 1 (i.e. no parallel computing).

da

Logical argument to control progress bar and messages. Default is TRUE.

by.sound.file

Logical to control if diagnostics are calculated for each sound file independently (TRUE) or for all sound files combined (FALSE, default).

previous.output

Data frame with the output of a previous run of this function. This will be used to include previous results in the new output and avoid recalculating detection performance for parameter combinations previously evaluated.

macro.average

Logical argument to control if diagnostics are first calculated for each sound file and then averaged across sound files, which can minimize the effect of unbalanced sample sizes between sound files. If FALSE (default) diagnostics are based on aggregated statistics irrespective of sound files. The following indices can be estimated by macro-averaging: overlap, mean.duration.true.positives, mean.duration.false.positives, mean.duration.false.positives, mean.duration.false.negatives, proportional.duration.true.positives, recall and precision (f.score is always derived from recall and precision). Note that when applying macro-averaging, recall and precision are not derived from the true positive, false positive and false negative values returned by the function.

min.overlap

Numeric. Controls the minimum amount of overlap required for a detection and a reference sound for it to be counted as true positive. Default is 0.5. Overlap is measured as intersection over union.

Details

This function takes a a reference data frame or 'selection_table' ('X') and the output of template_correlator and estimates the detection performance for different detection parameter combinations. This is done by comparing the position in time of the detection to those of the reference selections. The function returns several diagnostic metrics to allow user to determine which parameter values provide a detection that more closely matches the selections in 'reference'. Those parameters can be later used for performing a more efficient detection using template_detector. Supported file formats:'.wav', '.mp3', '.flac' and '.wac'.

Value

A data frame in which each row shows the result of a detection job for each cutoff value, including the following diagnostic metrics:

- true.positives: number of sound events in 'reference' that correspond to any detection. Matching is defined as some degree of overlap in time. In a perfect detection routine it should be equal to the number of rows in 'reference'.
- false.positives: number of detections that don't match any of the sound events in 'reference'. In a perfect detection routine it should be 0.
- false.negatives: number of sound events in 'reference' that were not detected (not found in 'detection'. In a perfect detection routine it should be 0.
- splits: number of detections overlapping reference sounds that also overlap with other detections. In a perfect detection routine it should be 0.
- merges: number of sound events in 'detection' that overlap with more than one sound event in 'reference'. In a perfect detection routine it should be 0.
- recall: Proportion of sound events in 'reference' that were detected. In a perfect detection routine it should be 1.
- precision: Proportion of detections that correspond to sound events in 'reference' that were detected. In a perfect detection routine it should be 1.

Author(s)

Marcelo Araya-Salas (<marcelo.araya@ucr.ac.cr>).

References

Araya-Salas, M., Smith-Vidaurre, G., Chaverri, G., Brenes, J. C., Chirino, F., Elizondo-Calvo, J., & Rico-Guevara, A. 2022. ohun: an R package for diagnosing and optimizing automatic sound event detection. BioRxiv, 2022.12.13.520253. https://doi.org/10.1101/2022.12.13.520253

See Also

optimize_energy_detector, template_correlator, template_detector

```
# Save sound files to temporary working directory
data("lbh1", "lbh2", "lbh_reference")
tuneR::writeWave(lbh1, file.path(tempdir(), "lbh1.wav"))
tuneR::writeWave(lbh2, file.path(tempdir(), "lbh2.wav"))
# template for the second sound file in 'lbh_reference'
templ <- lbh_reference[11, ]</pre>
# generate template correlations
tc <- template_correlator(templates = templ, path = tempdir(),</pre>
files = "lbh2.wav")
# using 2 threshold
optimize_template_detector(template.correlations = tc, reference =
lbh_reference[lbh_reference$sound.files == "lbh2.wav", ],
threshold = c(0.2, 0.5))
# using several thresholds
optimize_template_detector(template.correlations = tc,
reference = 1bh_reference[lbh_reference$sound.files == "lbh2.wav", ],
 threshold = seq(0.5, 0.9, by = 0.05))
 # template for the first and second sound file in 'lbh_reference'
 templ <- lbh_reference[c(1, 11), ]</pre>
 # generate template correlations
 tc <- template_correlator(templates = templ, path = tempdir(),</pre>
 files = c("lbh1.wav", "lbh2.wav"))
optimize_template_detector(template.correlations = tc, reference =
  lbh_reference, threshold = seq(0.5, 0.7, by = 0.1))
 # showing diagnostics by sound file
 optimize_template_detector(template.correlations = tc, reference =
 1bh_reference,
 threshold = seq(0.5, 0.7, by = 0.1), by sound.file = TRUE)
}
```

30 plot_detection

plot_detection	Plot detection and reference annotations	

Description

plot_detection evaluates the performance of a sound event detection procedure comparing the output selection table to a reference selection table

Usage

```
plot_detection(reference, detection, mid.point = FALSE, size = 20, positions = c(1, 2))
```

Arguments

reference	Data frame or 'selection.table' (following the warbleR package format) with the reference selections (start and end of the sound events) that will be used to evaluate the performance of the detection, represented by those selections in 'detection'. Must contained at least the following columns: "sound.files", "selec", "start" and "end". It must contain the reference selections that will be used for detection optimization.
detection	Data frame or 'selection.table' with the detections (start and end of the sound events) that will be compared against the 'reference' selections. Must contained at least the following columns: "sound.files", "selec", "start" and "end". It can contain data for additional sound files not found in 'references'. In this case the routine assumes that no sound events are found in those files, so detection from those files are all false positives.
mid.point	Logical argument to control if each annotations is shown as a rectangle with fix width center at the mid point of the time position (if TRUE) or the true time range of the annotations is used (if FALSE, default). 'mid.point' can be useful to make visible annotations in very long sound files that would otherwise look to thin.
size	Numeric. Controls the size of the rectangles if mid.point = TRUE. Default is 20.
positions	Numeric. Controls the vertical position of the rectangles representing anotations. Default is $c(1, 2)$. This can be used to get reference and detection annotations closer in the vertical axis. Note that the height of rectangles is 0.5.

Details

The function helps to visualize the match between reference and detection annotations by plotting them next to each other as rectangles along the time axis. If the annotations contain data for several sound files each sound file will be plotted in its own panel. The plot can be further modify by users using regular ggplot syntax.

Value

A ggplot graph (i.e. an object of class "ggplot").

plot_detection 31

Author(s)

Marcelo Araya-Salas <marcelo.araya@ucr.ac.cr>)

References

Araya-Salas, M., Smith-Vidaurre, G., Chaverri, G., Brenes, J. C., Chirino, F., Elizondo-Calvo, J., & Rico-Guevara, A. 2022. ohun: an R package for diagnosing and optimizing automatic sound event detection. BioRxiv, 2022.12.13.520253. https://doi.org/10.1101/2022.12.13.520253

See Also

label_spectro, diagnose_detection

```
{
 # load data
 data("lbh_reference")
 # mid point and regular size
 plot_detection(
   reference = lbh_reference[-14, ],
   detection = lbh_reference[-1, ], mid.point = TRUE
 # mid point and larger size
 plot_detection(
   reference = lbh_reference[-14, ],
   detection = lbh_reference[-1, ], mid.point = TRUE, size = 25
 # true time rectangles
 plot_detection(
   reference = lbh_reference[-14, ],
   detection = lbh_reference[-1, ]
 # use position to make reference and anotations overlap vertically
 plot_detection(
   reference = lbh_reference[-14, ],
   detection = lbh_reference[-1, ], positions = c(1, 1.4)
 )
 # modified using ggplot
 gg_pd <- plot_detection(</pre>
   reference = lbh_reference[-14, ],
   detection = lbh_reference[-1, ], positions = c(1, 1.4)
 gg_pd + ggplot2::theme_classic(base_size = 25)
```

32 split_acoustic_data

Description

split_acoustic_data splits sound files (and corresponding selection tables) in shorter segments

Usage

```
split_acoustic_data(path = ".", sgmt.dur = 10, sgmts = NULL, files = NULL,
cores = 1, pb = TRUE, only.sels = FALSE, X = NULL)
```

Arguments

path	Directory path where sound files are found. The current working directory is used as default.
sgmt.dur	Numeric. Duration (in s) of segments in which sound files would be split. Sound files shorter than 'sgmt.dur' won't be split. Ignored if 'sgmts' is supplied.
sgmts	Numeric. Number of segments in which to split each sound file. If supplied 'sgmt.dur' is ignored.
files	Character vector indicating the subset of files that will be split. Supported file formats: '.wav', '.mp3', '.flac' and '.wac'. If not supplied the function will work on all sound files (in the supported format) in 'path'.
cores	Numeric. Controls whether parallel computing is applied. It specifies the number of cores to be used. Default is 1 (i.e. no parallel computing).
pb	Logical argument to control progress bar. Default is TRUE. Only used when
only.sels	Logical argument to control if only the data frame is returned (no wave files are saved). Default is FALSE.
X	'selection_table' object or a data frame with columns for sound file name (sound.files), selection number (selec), and start and end time of signal (start and end). If supplied the data frame/selection table is modified to reflect the position of the selections in the new sound files. Note that some selections could split between 2 segments. To deal with this, a 'split.sels' column is added to the data frame in which those selection are labeled as 'split'. Default is NULL.

Details

This function aims to reduce the size of sound files in order to simplify some processes that are limited by sound file size (big files can be manipulated, e.g. energy_detector).

Value

Wave files for each segment in the working directory (if only.sels = FALSE, named as 'sound.file.name#.wav') and a data frame in the R environment containing the name of the original sound files (original.sound.files), the name of the clips (sound.files) and the start and end of clips in the original files. Clips are saved in .wav format. If 'X' is supplied then a data frame with the position of the selections in the newly created clips is returned instead.

Author(s)

Marcelo Araya-Salas (<marcelo.araya@ucr.ac.cr>)

References

Araya-Salas, M., Smith-Vidaurre, G., Chaverri, G., Brenes, J. C., Chirino, F., Elizondo-Calvo, J., & Rico-Guevara, A. 2022. ohun: an R package for diagnosing and optimizing automatic sound event detection. BioRxiv, 2022.12.13.520253. https://doi.org/10.1101/2022.12.13.520253

See Also

```
cut_sels
```

Examples

```
{
  # load data and save to temporary working directory
  data("lbh1", "lbh2")
  tuneR::writeWave(lbh1, file.path(tempdir(), "lbh1.wav"))
  tuneR::writeWave(lbh2, file.path(tempdir(), "lbh2.wav"))

# split files in 1 s files
  split_acoustic_data(sgmt.dur = 1, path = tempdir())

# Check this folder
  tempdir()
}
```

summarize_acoustic_data

Summarize information about file format in an acoustic data set

Description

summarize_acoustic_data summarizes information about file format in an acoustic data set

Usage

```
summarize_acoustic_data(path = ".", digits = 2)
```

Arguments

Default is "." (current working directory).

Numeric vector of length 1 with the number of decimals to include. Default is 2.

Details

The function summarizes information about file format in an acoustic data set. It provides information about the number of files, file formats, sampling rates, bit depts, channels, duration and file size (in MB). For file format, sampling rate, bit depth and number of channels the function includes information about the number of files for each format (e.g. '44.1 kHz (2)' means 2 files with a sampling rate of 44.1 kHz).

Value

The function prints a summary of the format of the files in an acoustic data set.

Author(s)

Marcelo Araya-Salas <marcelo.araya@ucr.ac.cr>)

References

Araya-Salas, M., Smith-Vidaurre, G., Chaverri, G., Brenes, J. C., Chirino, F., Elizondo-Calvo, J., & Rico-Guevara, A. 2022. ohun: an R package for diagnosing and optimizing automatic sound event detection. BioRxiv, 2022.12.13.520253. https://doi.org/10.1101/2022.12.13.520253

See Also

```
summarize_reference
```

Examples

```
{
  # load data and save example files into temporary working directory
  data("lbh1", "lbh2", "lbh_reference")
  tuneR::writeWave(lbh1, file.path(tempdir(), "lbh1.wav"))
  tuneR::writeWave(lbh2, file.path(tempdir(), "lbh2.wav"))

  # summary across sound files
  summarize_acoustic_data(path = tempdir())
}
```

summarize_diagnostic Summarize detection diagnostics

Description

summarize_diagnostic summarizes detection diagnostics

Usage

```
summarize_diagnostic(diagnostic, time.diagnostics = FALSE, macro.average = FALSE)
```

summarize_diagnostic 35

Arguments

diagnostic

A data frame with the output of a detection optimization function (diagnose_detection, optimize_energy_detector or optimize_template_detector)

time.diagnostics

Logical argument to control if diagnostics related to the duration of the sound events ("mean.duration.true.positives", "mean.duration.false.positives", "mean.duration.false.negatives" and "proportional.duration.true.positives") are returned (if TRUE). Default is FALSE.

macro.average

Logical argument to control if diagnostics are first calculated for each sound file and then averaged across sound files, which can minimize the effect of unbalanced sample sizes between sound files. If FALSE (default) diagnostics are based on aggregated statistics irrespective of sound files. The following indices can be estimated by macro-averaging: overlap, mean.duration.true.positives, mean.duration.false.positives, mean.duration.false.positives, mean.duration.false.negatives, proportional.duration.true.positives, recall and precision (f.score is always derived from recall and precision). Note that when applying macro-averaging, recall and precision are not derived from the true positive, false positive and false negative values returned by the function.

Details

The function summarizes a detection diagnostic data frame in which diagnostic parameters are shown split by (typically) a categorical column, usually sound files. This function is used internally by diagnose_detection. 'splits' and 'merge.positives' are also counted (i.e. counted twice) as 'true.positives'. Therefore "true.positives + false.positives = detections".

Value

A data frame, similar to the output of a detection optimization function (diagnose_detection, optimize_energy_detector, optimize_template_detector) including the following detection performance diagnostics:

- detections: total number of detections
- true.positives: number of sound events in 'reference' that correspond to any detection. Matching is defined as some degree of overlap in time. In a perfect detection routine it should be equal to the number of rows in 'reference'.
- false.positives: number of detections that don't match (i.e. don't overlap with) any of the sound events in 'reference'. In a perfect detection routine it should be 0.
- false.negatives: number of sound events in 'reference' that were not detected (not found in 'detection'. In a perfect detection routine it should be 0.
- splits: number of detections overlapping reference sounds that also overlap with other detections. In a perfect detection routine it should be 0.
- merges: number of detections that overlap with two or more reference sounds. In a perfect detection routine it should be 0.
- mean.duration.true.positives: mean duration of true positives (in s). Only included when time.diagnostics = TRUE.
- mean.duration.false.positives: mean duration of false positives (in ms). Only included when time.diagnostics = TRUE.

- mean.duration.false.negatives: mean duration of false negatives (in ms). Only included when time.diagnostics = TRUE.
- overlap: mean intersection over union overlap of true positives.
- proportional.duration.true.positives: ratio of duration of true positives to the duration of sound events in 'reference'. In a perfect detection routine it should be 1. Based only on true positives that were not split or merged.
- duty.cycle: proportion of a sound file in which sounds were detected. Only included when time.diagnostics = TRUE and path is supplied. Useful when conducting energy-based detection as a perfect detection can be obtained with a very low amplitude threshold, which will detect everything, but will produce a duty cycle close to 1.
- recall: Proportion of sound events in 'reference' that were detected. In a perfect detection routine it should be 1.
- precision: Proportion of detections that correspond to sound events in 'reference'. In a perfect detection routine it should be 1.
- f. score: Combines recall and precision as the harmonic mean of these two. Provides a single value for evaluating performance. In a perfect detection routine it should be 1.

Author(s)

Marcelo Araya-Salas <marcelo.araya@ucr.ac.cr>)

References

Araya-Salas, M., Smith-Vidaurre, G., Chaverri, G., Brenes, J. C., Chirino, F., Elizondo-Calvo, J., & Rico-Guevara, A. 2022. ohun: an R package for diagnosing and optimizing automatic sound event detection. BioRxiv, 2022.12.13.520253. Mesaros, A., Heittola, T., & Virtanen, T. (2016). Metrics for polyphonic sound event detection. Applied Sciences, 6(6), 162.

See Also

diagnose_detection

```
# load example selection tables

data("lbh_reference")

# run diagnose_detection() by sound file
diag <- diagnose_detection(
  reference = lbh_reference,
  detection = lbh_reference[-1, ], by.sound.file = TRUE
)

# summarize
summarize_diagnostic(diagnostic = diag)

# should be the same as this:</pre>
```

summarize_reference 37

```
diagnose_detection(
    reference = lbh_reference,
    detection = lbh_reference[-1, ], by.sound.file = FALSE
)
}
```

summarize_reference

Summarize temporal and frequency dimensions of annotations and gaps

Description

summarize_reference summarizes temporal and frequency dimensions of annotations and gaps

Usage

```
summarize_reference(reference, path = NULL, by.sound.file = FALSE,
units = c("ms", "kHz"), digits = 2)
```

Arguments

reference	Data frame or 'selection.table' (following the warbleR package format) with the reference selections (start and end of the sound events) that will be used to evaluate the performance of the detection, represented by those selections in 'detection'. Must contained at least the following columns: "sound.files", "selec", "start" and "end". If frequency range columns are included ("bottom.freq" and "top.freq") these are also used to characterize reference selections.
path	Character string containing the directory path where the sound files are located. If supplied then duty cycle and peak frequency features are returned. These features are more helpful for tuning a energy-based detection. Default is NULL.
by.sound.file	Logical argument to control whether features are summarized across sound files (when by . sound . file = FALSE, and more than 1 sound file is included in 'reference') or shown separated by sound file. Default is FALSE.
units	A character vector of length 2 with the units to be used for time and frequency parameters, in that order. Default is c("ms","kHz"). It can also take 's' and 'Hz'.
digits	Numeric vector of length 1 with the number of decimals to include. Default is 2.

Details

The function extracts quantitative features from reference tables that can inform the range of values to be used in a energy-based detection optimization routine. Features related to selection duration can be used to set the 'max.duration' and 'min.duration' values, frequency related features can inform bandpass values, gap related features inform hold time values and duty cycle can be used to evaluate performance.

38 template_correlator

Value

The function returns the mean, minimum and maximum duration of selections and gaps (time intervals between selections) and of the number of annotations by sound file. If frequency range columns are included in the reference table (i.e. "bottom.freq" and "top.freq") the minimum bottom frequency ('min.bottom.freq') and the maximum top frequency ('max.top.freq') are also estimated. Finally, if the path to the sound files in 'reference' is supplied the duty cycle (fraction of a sound file corresponding to target sound events) and peak amplitude (highest amplitude in a detection) are also returned. If 'by.sound.file = FALSE' a matrix with features in rows is returned. Otherwise a data frame is returned in which each row correspond to a sound file. By default, time features are returned in 'ms' while frequency features in 'kHz' (but see 'units' argument).

Author(s)

Marcelo Araya-Salas <marcelo.araya@ucr.ac.cr>)

References

Araya-Salas, M., Smith-Vidaurre, G., Chaverri, G., Brenes, J. C., Chirino, F., Elizondo-Calvo, J., & Rico-Guevara, A. 2022. ohun: an R package for diagnosing and optimizing automatic sound event detection. BioRxiv, 2022.12.13.520253. https://doi.org/10.1101/2022.12.13.520253

See Also

```
optimize_energy_detector, optimize_template_detector
```

Examples

```
{
  # load data and save example files into temporary working directory
  data("lbh1", "lbh2", "lbh_reference")
  tuneR::writeWave(lbh1, file.path(tempdir(), "lbh1.wav"))
  tuneR::writeWave(lbh2, file.path(tempdir(), "lbh2.wav"))

# summary across sound files
  summarize_reference(reference = lbh_reference, path = tempdir())

# summary across sound files
  summarize_reference(reference = lbh_reference, by.sound.file = TRUE, path = tempdir())
}
```

template_correlator

Acoustic templates correlator using time-frequency cross-correlation

Description

template_correlator estimates templates cross-correlation across multiple sound files.

39 template_correlator

Usage

```
template_correlator(templates, files = NULL, hop.size = 11.6, wl = NULL, ovlp = 0,
wn = 'hanning', cor.method = "pearson", cores = 1, path = ".",
pb = TRUE, type = "fourier", fbtype = "mel", ...)
```

Arguments

templates

'selection_table', 'extended_selection_table' (warbleR package's formats, see selection_table) or data frame with time and frequency information of the sound event(s) to be used as templates (1 template per row). The object must contain columns for sound files (sound.files), selection number (selec), and start and end time of sound event (start and end). If frequency range columns are included ('bottom.freq' and 'top.freq', in kHz) the correlation will be run on those frequency ranges. All templates must have the same sampling rate and both templates and 'files' (in which to find templates) must also have the same sampling rate.

files

Character vector with name of the files in which to run the cross-correlation with the supplied template(s). Supported file formats:'.wav', '.mp3', '.flac' and '.wac'. If not supplied the function will work on all sound files (in the supported formats) in 'path'.

hop.size

A numeric vector of length 1 specifying the time window duration (in ms). Default is 11.6 ms, which is equivalent to 512 wl for a 44.1 kHz sampling rate. Ignored if 'wl' is supplied.

wl

A numeric vector of length 1 specifying the window length of the spectrogram. Default is NULL. If supplied, 'hop.size' is ignored.

ovlp

Numeric vector of length 1 specifying % of overlap between two consecutive windows, as in spectro. Default is 0. High values of ovlp slow down the function but may produce more accurate results.

wn

A character vector of length 1 specifying the window name as in ftwindow.

cor.method

A character vector of length 1 specifying the correlation method as in cor.

cores

Numeric. Controls whether parallel computing is applied. It specifies the number of cores to be used. Default is 1 (i.e. no parallel computing).

path

Character string containing the directory path where the sound files are located. The current working directory is used as default.

pb

Logical argument to control progress bar. Default is TRUE.

type

A character vector of length 1 specifying the type of cross-correlation: "fourier" (i.e. spectrographic cross-correlation using Fourier transform; internally using spectro; default), "mfcc" (auditory scale coefficient matrix cross-correlation; internally using melfcc) or "mel-auditory" (cross-correlation of auditory spectrum, i.e. spectrum after transformation to an auditory scale; internally using melfcc). The argument 'fbtype' controls the auditory scale to be used. Note that the last 2 methods have not been widely used in this context so can be regarded as experimental.

Character vector indicating the auditory frequency scale to use: "mel", "bark", "htkmel", "fcmel".

fbtype

40 template_correlator

... Additional arguments to be passed to melfcc for further customization when using auditory scales.

Details

This function calculates the similarity of acoustic templates across sound files by means of time-frequency cross-correlation. Fourier spectrograms or time-frequency representations from auditory scales (including cepstral coefficients) can be used. Several templates can be run over several sound files. Note that template-based detection is divided in two steps: template correlation (using this function) and template detection (or peak detection as it infers detection based on peak correlation scores, using the function template_detector). So the output of this function (and object of 'template_correlations') must be input into template_detector for inferring sound event occurrences. optimize_template_detector can be used to optimize template detection.

Value

The function returns an object of class 'template_correlations' which is a list with the correlation scores for each combination of templates and files. 'template_correlations' objects must be used to infer sound event occurrences using template_detector or to graphically explore template correlations across sound files using full_spectrograms.

Author(s)

Marcelo Araya-Salas <marcelo.araya@ucr.ac.cr>)

References

Araya-Salas, M., Smith-Vidaurre, G., Chaverri, G., Brenes, J. C., Chirino, F., Elizondo-Calvo, J., & Rico-Guevara, A. 2022. ohun: an R package for diagnosing and optimizing automatic sound event detection. BioRxiv, 2022.12.13.520253. https://doi.org/10.1101/2022.12.13.520253

Khanna H., Gaunt S.L.L. & McCallum D.A. (1997). Digital spectrographic cross-correlation: tests of recall. Bioacoustics 7(3): 209-234.

Lyon, R. H., & Ordubadi, A. (1982). Use of cepstra in acoustical signal analysis. Journal of Mechanical Design, 104(2), 303-306.

See Also

```
energy_detector, template_detector, optimize_template_detector
```

```
{
  # load example data
  data("lbh1", "lbh2", "lbh_reference")

# save sound files
  tuneR::writeWave(lbh1, file.path(tempdir(), "lbh1.wav"))
  tuneR::writeWave(lbh2, file.path(tempdir(), "lbh2.wav"))

# create template
```

template_detector 41

```
templ <- lbh_reference[4, ]</pre>
 templ2 <- warbleR::selection_table(templ,</pre>
    extended = TRUE, confirm.extended = FALSE,
   path = tempdir()
 )
 # fourier spectrogram
 (tc_fr <- template_correlator(templates = templ, path = tempdir(), type = "fourier"))</pre>
 # mel auditory spectrograms
 (tc_ma <- template_correlator(templates = templ, path = tempdir(), type = "mel-auditory"))</pre>
 # mfcc spectrograms
 (tc_mfcc <- template_correlator(templates = templ, path = tempdir(), type = "mfcc"))</pre>
 # similar results (but no exactly the same) are found with the 3 methods
 # these are the correlation of the correlation vectors
 # fourier vs mel-auditory
 cor(
    tc_fr$`lbh2.wav-4/lbh2.wav`$correlation.scores,
    tc_ma$`lbh2.wav-4/lbh2.wav`$correlation.scores
 )
 # fourier vs mfcc
 cor(
    tc_fr$`lbh2.wav-4/lbh2.wav`$correlation.scores,
    tc_mfcc$`lbh2.wav-4/lbh2.wav`$correlation.scores
 # mel-auditory vs mfcc
    tc_ma$`lbh2.wav-4/lbh2.wav`$correlation.scores,
    tc_mfcc$`lbh2.wav-4/lbh2.wav`$correlation.scores
 )
 # using an extended selection table
 templ_est <- warbleR::selection_table(templ,</pre>
    extended = TRUE, confirm.extended = FALSE,
    path = tempdir()
 tc_fr_est <- template_correlator(templates = templ_est, path = tempdir(), type = "fourier")</pre>
 # produces the same result as templates in a regular data frame
    tc_fr$`lbh2.wav-4/lbh2.wav`$correlation.scores,
    tc_fr_est$`lbh2.wav_4-1/lbh2.wav`$correlation.scores
 )
}
```

42 template_detector

Description

template_detector find sound event occurrences in cross-correlation vectors from template_correlator

Usage

```
template_detector(template.correlations, cores = 1, threshold, pb = TRUE,
  verbose = TRUE)
```

Arguments

template.correlations

object of class 'template_correlations' generated by template_correlator con-

taining the correlation score vectors.

cores Numeric. Controls whether parallel computing is applied. It specifies the num-

ber of cores to be used. Default is 1 (i.e. no parallel computing).

threshold Numeric vector of length 1 with a value between 0 and 1 specifying the corre-

lation threshold for detecting sound event occurrences (i.e. correlation peaks). Must be supplied. Correlation scores are forced to between 0 and 1 (by converting negative scores to 0). 0 and 1 represent the lowest and highest similarity to

the template respectively.

pb Logical argument to control progress bar. Default is TRUE.

verbose Logical argument to control if some summary messages are printed to the con-

sole.

Details

This function infers sound events occurrences from cross-correlation scores along sound files. Correlation scores must be generated first using template_correlator. The output is a data frame (or selection table if sound files are still found in the original path supplied to template_correlator, using the warbleR package's format, see selection_table) containing the start and end of the detected sound events as well as the cross-correlation score ('scores' column) for each detection. Note that the detected sounds are assumed to have the same duration as the template, so their start and end correspond to the correlation peak position +/- half the template duration.

Value

The function returns a 'selection_table' (warbleR package's formats, see selection_table) or data frame (if sound files can't be found) with the start and end and correlation score for the detected sound events.

Author(s)

Marcelo Araya-Salas <marcelo.araya@ucr.ac.cr>)

References

Araya-Salas, M., Smith-Vidaurre, G., Chaverri, G., Brenes, J. C., Chirino, F., Elizondo-Calvo, J., & Rico-Guevara, A. 2022. ohun: an R package for diagnosing and optimizing automatic sound event detection. BioRxiv, 2022.12.13.520253. https://doi.org/10.1101/2022.12.13.520253

template_detector 43

See Also

energy_detector, template_correlator, optimize_template_detector

```
{
 # load example data
 data("lbh1", "lbh2", "lbh_reference")
 # save sound files
 tuneR::writeWave(lbh1, file.path(tempdir(), "lbh1.wav"))
 tuneR::writeWave(lbh2, file.path(tempdir(), "lbh2.wav"))
 # template for the first sound file in 'lbh_reference'
 templ1 <- lbh_reference[1, ]</pre>
 # generate template correlations
 tc <- template_correlator(templates = templ1, path = tempdir(), files = "lbh1.wav")</pre>
 # template detection
 td <- template_detector(template.correlations = tc, threshold = 0.4)</pre>
 # diagnose detection
 diagnose_detection(
    reference =
      lbh_reference[lbh_reference$sound.files == "lbh1.wav", ],
    detection = td
 )
 # template for the second and third sound file in 'lbh_reference'
 # which have similar song types
 templ2 <- lbh_reference[4, ]</pre>
 # generate template correlations
 tc <- template_correlator(</pre>
    templates = templ2, path = tempdir(),
    files = c("lbh1.wav", "lbh2.wav")
 )
 # template detection
 td <- template_detector(template.correlations = tc, threshold = 0.3)</pre>
 # diagnose detection
 diagnose_detection(reference = lbh_reference, detection = td)
}
```

Index

```
* data manipulation
                                                   prcomp, 14
    split_acoustic_data, 32
                                                   selection_table, 2, 3, 9, 13, 14, 16, 23, 39,
* datasets
    1bh1, 19
                                                   sound_pressure_level, 9, 23
    1bh2, 20
                                                   spectro, 18, 39
    1bh_reference, 20
                                                   spectro_analysis, 14
                                                   split_acoustic_data, 32
approx, 8, 12, 24
                                                    summarize_acoustic_data, 33
consensus_detection, 2
                                                   summarize_diagnostic, 16, 22, 34
cor, 39
                                                   summarize_reference, 34, 37
cut_sels, 33
                                                    template_correlator, 18, 19, 27-29, 38, 42,
diagnose_detection, 4, 16, 31, 35, 36
                                                    template_detector, 3, 15, 19, 28, 29, 40, 41
energy_detector, 7, 12, 19, 25, 32, 40, 43
env, 8, 12, 23
envelope, 8, 12, 23
ffilter, 8, 11, 24
ftwindow, 39
full_spectrograms, 40
get_envelopes, 8, 11, 12, 23, 24
get_templates, 13
label_detection, 2, 3, 15, 22
label_spectro, 17, 31
1bh1, 19
1bh2, 20
1bh_reference, 20
melfcc, 39, 40
merge_overlaps, 21
optimize_energy_detector, 6, 10, 22, 29,
         35, 38
optimize_template_detector, 6, 27, 27, 35,
         38, 40, 43
\verb|plot_detection|, 30|
```