

How to Build the Dementia Friendly Music Player

Standard Model – Use with Headphones or External Powered Speakers

24 September 2023, <http://DementiaMusicPlayer.org>, Ross Porter rosswesleyporter@gmail.com



I was inspired to design this by the documentary [Alive Inside](#) which shows the profound joy felt by some with dementia when listening to their favorite music.

My Dad could no longer operate the home stereo. But he could operate this music player because it operates like a familiar two-knob radio. The vintage style fit with his old intact memories – for most people with dementia, the old memories are the strong memories.

It's easier than you think to make one. Everything I did is open source. This document contains all the information you need. You can order the parts online, including the cut & engraved wood. It's a good family project – kids do well with this. It's also a project that friends would love to help you with.

Parts cost	~\$135 + tax + shipping (~\$70 if you make 10+ at a time, see Appendix 1)
Music cost	Minimal as you should use the recipient's existing music collection
Build time	About 3 hours once you have the parts & music, Best if those 3 hours are spread across two days
Parts source	All parts can be mail ordered, links below
Soldering?	No
Woodworking?	No
Laser cutter needed?	No, you can mail order the pre-cut pieces for the wood case
With a friend?	Good idea, especially if your friend has the basic tools required
Beverage?	I recommend a hoppy IPA while you are assembling



No warranty

USE THESE DEMENTIA FRIENDLY MUSIC PLAYER PLANS AND SYSTEM AT YOUR OWN RISK. THE DEMENTIA FRIENDLY MUSIC PLAYER PLANS ARE PROVIDED AS IS WITHOUT WARRANTY OF ANY KIND EITHER EXPRESSED OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. THE ENTIRE RISK AS TO THE QUALITY AND PERFORMANCE OF THE PLANS AND SYSTEM IS WITH YOU. SHOULD THE PLANS OR SYSTEM PROVE DEFECTIVE, YOU ASSUME THE COST OF ALL NECESSARY SERVICING, REPAIR OR CORRECTION. IN NO EVENT WILL ANY PARTY BE LIABLE TO YOU FOR DAMAGES, INCLUDING ANY GENERAL, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES ARISING OUT OF THE USE OR INABILITY TO USE THE PLANS OR SYSTEM.

Acknowledgements

People were very generous with their time, and I really enjoyed the experience. This is certainly an incomplete list: Alex & Mike & others at [Ada's](#), the super smart staff at [Metrix](#), neighbor Randy, [Stephen Christopher Phillips](#), [Bob Rathbone](#), [Stephen Rusk](#), [Graham Hill](#), support at [Ponoko](#), [Florian Festi](#), and my son.

How it works



Preview of the steps

STEP 1: Order or make the case



STEP 2: Order parts



STEP 2: Assemble music




STEP 4: Flash the micro SD card



STEP 5: Add the Pi



STEP 6: Wire it



STEP 7: Test it



STEP 8: Glue it




STEP 9: Enjoy!



STEP 1: Find a friend to do this with



STEP 2: Decide about making vs. ordering the case



If you have access to a laser cutter, you can use my free plans to cut & engrave the case pieces

If you don't have a laser cutter, you can send my free plans to Ponoko, who will cut & engrave the case pieces for ~\$50 and mail the case pieces to you.


Unless you are an experienced maker or woodworker, I recommend the Ponoko option as it will make your life easier.

Ponoko is a company that laser cuts wood and sends you the precisely cut pieces. You don't need to use Ponoko – you are welcome to download my case design files from [github](#) and go to your local maker space and use the laser cutter there. Or buy yourself a laser cutter (if you do, will you be my friend?). In other words, Ponoko is convenient but not necessary. I have no affiliation with them, other than being a happy customer. Unless you are an experienced maker or woodworker, I recommend ordering the case – it will make the build process much easier.

STEP 3: Get the case file

1. Go to <https://drive.google.com/drive/u/0/folders/1OfONeFgfn9vb6FGjCZ25Al0I-HxRqxYo>


2. Get the file you want:




3. Right-click on the desired file, choose “Download”

STEP 4: Order the case

1. Go to <https://www.ponoko.com/>
2. Login (create an account if you haven't already)
3. Choose “Upload your design” and upload the file that you downloaded just above




4. Set the design colors as per below:



5. Choose “Confirm design size & colors”

6. Choose “Amber Bamboo Plywood”



7. Choose thickness = 6.7mm and then “Confirm material”

Amber Bamboo Plywood

Thicknesses available:

<input type="radio"/> 0.9mm thick	\$34.79
<input type="radio"/> 1.8mm thick	\$36.41
<input type="radio"/> 2.7mm thick	\$37.51
<input checked="" type="radio"/> 6.7mm thick	\$55.30

Confirm material

8. Make sure that everything looks as expected especially the check that the horizontal bar above SONGS is colored in

DementiaFriendlyMusicPlayer_6point7mm_Ponoko.svg
365mm x 209.1mm

[Update design →](#)

Amber Bamboo Plywood
6.7mm

[Update material →](#)

Quantity: 1 Price USD: **\$55.31**

Quantity	Price USD	Savings
<input type="radio"/> 1	\$55.31	
<input type="radio"/> 5	\$36.53	Save 34%
<input type="radio"/> 10	\$33.92	Save 39%
<input type="radio"/> 50	\$26.89	Save 51%
<input type="radio"/> 100	\$24.48	Save 56%
<input type="radio"/> 500	\$18.05	Save 67%
<input type="radio"/> 1,000	\$15.23	Save 72%
<input type="radio"/> 5,000	\$12.22	Save 78%

\$9 setup per order for human powered stuff

[Submit pricing feedback \(get 20% off\)](#)

Add to Cart

209.1mm


9. Click “Add to Cart”

STEP 5: Make the case (if you didn't order it)

If you want to make the case rather than order the case:


1. Use the file that you downloaded earlier
2. If you like, you can customize the case
3. Cut on your laser cutter or go to a makerspace and use a laser cutter there

If you are curious, this is what a design file looks like (showing the .lbrn Lightburn file):



STEP 6: Order the parts

If you plan to make 10+ units, see [Appendix 1](#), rather than the table below.



Item	Supplier	Cost	Notes & alternatives
Bamboo case	Ponoko	\$64.68	See instructions above.
Raspberry Pi 1 A+ single board computer	Newark	\$20.00	Also tested with a 2B, 3A+, 3B, 3B+, 4B. Do not use Pi Zero.
Power supply	Newark	\$4.99	Or Newark 81AC2845. Or order one for your region/plug.
Female-female jumper wires	Newark	\$3.95	Or Amazon B01L5ULRUA
Panel mount 3.5mm headphone jack	Newark	\$2.69	Or Amazon B004JX64FE
M2.5 standoffs (screws) – 8 of them	Newark	\$7.12	Or Amazon B06XXV8RTR
16GB or greater micro SD card	Amazon	\$7.49	Or buy Amazon B06XWN9Q99 or other 16GB+ card
USB thumb drive	Amazon	\$7.19	Or Amazon B07MDXBT87 or other physically small USB drive
Audio cable	Amazon	\$6.59	Or buy Amazon B00SUIKMJ8 or other cable with right angle bend
KY-016 indicator LED	Banggood	\$4.61	ALLOW 3+ WEEKS TO ARRIVE FROM CHINA. Due to COVID, it's hard to find these in the US. You can get it quickly from Amazon B07KJYR8K1, but costs \$18.
KY-040 rotary encoders (knobs)	Amazon	\$7.99	Or buy Amazon B06XQTHDRR
		\$137.30	Prices will vary. Does not include tax, shipping.

STEP 7: Decide between headphones and speakers



The device is designed to be used with either headphones or external powered speakers. But not both at the same time. It does not automatically switch between headphones and speakers. You can make the change, but you must actually unplug one device from the headphone jack and plug in another. Thus, for the sake of the users, I suggest choosing one device and sticking with it.

For the purposes of these instructions, I'll assume that you chose to use headphones.


STEP 8: Get headphones (optional)



Some headphone choices

Item	Cost	Notes and alternatives
The recipient's existing headphone	\$0.00	The best headphones are the headphones that the recipient is already used to.
Monoprice On-Ear headphones	\$10.99	Very good sound. High sensitivity (which is important). Also available from Amazon for a slightly higher price but with Prime shipping: B014399CWK .
Monoprice Over-the-Ear headphones	\$15.99	Amazing sound. High sensitivity (which is important). Also available from Amazon for a slightly higher price but with Prime shipping: B007SP2CO2 .
Other		Look for high sensitivity headphones, as the Pi's output is a bit weak.

STEP 9: Get speakers (optional)



Some speaker choices

Item	Cost	Notes and alternatives
ARVICKA Computer Speakers	\$19.99	Surprisingly good sound for the tiny size. I quite like them. Simple – no visible controls on the front. USB powered, so if you choose a Pi 3 or Pi 4 (above), you can power these speakers from the device. Otherwise, you'll also need a USB charger e.g. Amazon B0773J79KC.
Creative Pebble	\$19.99	I have not tried this. Highly rated on Amazon. USB powered (see note in the row above).
Other – Amazon search		Lots of other speakers to choose from.

STEP 10: Get wood finish product (optional)

Optional. Bamboo is quite nice unfinished. But you can give it a golden look and a bit of protection.

You only need one. If you don't have any wood finishes, you probably have a friend who does.



Easiest. Done in minutes. But needs re-application from time to time. Baby oil can also work if the main ingredient is mineral oil.

Fast. ~15 minutes of work spread across two hours.

Easy. One coat is enough, but best to let it dry overnight. Any linseed oil is fine, except raw linseed oil.

STEP 11: Gather tools & supplies



STEP 12: Get a computer with an SD card slot



You'll need a PC or Mac or Linux computer with an SD card slot. If you don't have one, you probably have a friend who does.

STEP 13: Assemble the personalized collection of music

Choosing the music – go for familiar favorites

This is the most important step. The personalized (familiar) music is the fundamental magic. You don't need much music, perhaps 6-10 albums. But only familiar favorites. In my case, my Mom mailed me my Dad's favorite CDs. It will take two weeks for the parts above to arrive, so you have time to do this well. Though it is easy to change the set of music later.

Put the music on the USB memory stick


Organize the digitized music into folders on the USB memory stick, one folder per album. MP3, iTunes, and FLAC files are supported i.e. files with extensions .mp3, .m4a, .flac. In the end, you should have a set of folders that looks something like this:

Name	Date modified	Type
A_Beethoven9	10/24/2015 6:25 PM	File folder
B_Eli_Porter_-_Eli_Porter	10/24/2015 6:25 PM	File folder
C_Mozart_-_Overtures	10/24/2015 6:25 PM	File folder
D_Tchaikovsky_-_Concerto for Violin i...	10/24/2015 6:25 PM	File folder
E_Vivaldi_Telemann_Bach_Mercadante...	10/24/2015 6:25 PM	File folder
F_Samuel Barber_-_Barber; Adagio for ...	10/24/2015 6:26 PM	File folder
G_James Galway_-_Serenade	10/24/2015 6:26 PM	File folder
H_Giacomo Puccini_-_Madama Butter...	10/24/2015 6:26 PM	File folder
I_Giacomo Puccini_-_Madama Butterfl...	10/24/2015 6:26 PM	File folder
J_Giacomo Puccini_-_Madama Butterfl...	10/24/2015 6:26 PM	File folder
K_Leontyne Price_-_Arias	10/24/2015 6:26 PM	File folder

STEP 14: Copy software to the micro-SD memory card

I prepared a disk image for you. It has all the required software. Your job is to download this disk image and then write it to the micro-SD card. The steps:

1. Install [Balena Etcher](#) on your PC or Mac or Linux computer. [Win32 Disk Imager](#) also works.
2. Download the [Dementia Friendly Music Player disk image](#).
3. Confirm download – “Download anyway”



4. Put the micro-SD memory card & adapter into the SD reader/writer in your computer.
5. Start Balena Etcher, instruct it to write the image file to the SD card:



6. Wait for the writing to complete, ~10 minutes. This would be a good time to make a sandwich.

STEP 15: Apply a wood finish (optional)




Bamboo is pretty good without a finish. But to give it some protection and improve the look, just apply some oil or lacquer.

I applied one coat of linseed oil, which yielded a nice golden color when compared to the unoiled piece. Spray lacquer achieves a similar effect and can be done quickly (see note below).


Alternatively, make the music box, then apply mineral oil to the completed unit. But note that you'll need to re-apply mineral oil from time to time.

If you choose to use spray lacquer, see this [short video from Woodworking for Mere Mortals](#). The method shown is much faster than the instructions on the spray bottle. It takes about 15 minutes of work spread across two hours.



STEP 16: Add the Pi




STEP 17: Test it




STEP 18: Wire it




STEP 19: Add front panel components



STEP 20: Wire up front panel components




STEP 21: Verify wiring




STEP 22: Test it again




STEP 23: Adjust the knob wiring (if necessary)




STEP 24: Add glue



STEP 25: Add audio cable




STEP 26: Glue it



STEP 27: Sand the clasp (if necessary)


If the clasp won't close i.e. is too tight, then very lightly sand as per below. You can also do this after you have clamped & glued. So if your glue is starting to set as you read this, skip to the next step. Then return here after you take the clamp/tape off.




STEP 28: Clamp it



STEP 29: Glue the knobs




STEP 30: Place knobs on shafts



Place knobs on shafts

STEP 31: Let the glue dry





STEP 32: Remove the tape




STEP 33: Add glue to the clasp (if necessary)

If the clasp does not latch securely i.e. is a bit loose, then very slightly increase the size of the tabs by applying a thin layer of glue and allowing it to dry before re-latching. If you ordered from Ponoko, it's unlikely that you will have to do this. But if you do, then use a very thin layer of glue and perhaps only on the top of the latch. That is, if the Ponoko sizing is off, it's only going to be off by a fraction of a millimeter.



STEP 34: Adjust the knobs (if necessary)



STEP 35: Tape instructions

Print this page and tape the instructions in the box below to the bottom of your new Dementia Friendly Music Player:

To create personalized music

Organize the music on your computer

- A_Beethoven_9th
- B_AndrewsSisters_Hits
- C_GlennMiller_Hits

One folder per album. Use MP3 files, must have .mp3 file extension. Or iTunes files (.m4a). Or FLAC files (.flac). Optionally, use folder names prefixes to specify the play order e.g. A_, B_

Copy the music to the USB thumb drive



1. Unplug the Dementia Friendly Music Player.
2. Remove the USB thumb drive and place in your computer.
3. Copy music files from your computer to the USB thumb drive.
4. Put the USB thumb drive back in.
5. Plug in your Dementia Friendly Music Player.

STEP 36: Done!

Congratulations! You should have a fully functional Dementia Friendly Music Player.

Appendix 1: Building 10+ units at a time

Notes & assumptions:

- You want to build 10 or more units at a time
- You are planning this far enough in advance (8 weeks or more) that you can order some of the parts directly from China
- Two ways to make the case – laser cut it yourself or order with a quantity discount from Ponoko
- If Ponoko
 - The cost is ~\$35
 - I recommend switching to 3.5mm cherry veneer wood:
 - It is significantly less expensive
 - It's thinner so it's a little harder to work with and a little less durable, but I think it's fine for the 10+ purpose
 - It is pre-finished, which is a nice time saver
 - It will look like this:



- Be sure to use the matching laser cutting 3.5mm file from [github](#)
- You'll need the rubber feet (see below) as the 6mm shaft of the standoffs will protrude slightly from the bottom of the case
- If you are planning to laser cut the case yourself, or in conjunction with a maker space, I suggest using 5.2mm cherry MDF wood
 - Looks great, is commonly available, laser cuts well
 - Ideally apply some wood finish (see above)
 - At my supplier, a 4'x8' sheet is \$55, and you can make as many as 12 cases from it
 - For the cost estimate below, I'm assuming 15 minutes of laser time at \$1 per minute
 - For laser cutting, be sure to use the matching 5.2mm file from [github](#)

# units to make	10					
Item	Supplier	Quan	Each	Total	Per unit	Notes
Wood case	Maker space	10	\$22.00	\$220.00	\$22.00	Or order from Ponoko for ~\$35
Raspberry Pi 1 A+ single board computer	Newark	10	\$20.00	\$200.00	\$20.00	
Power supply	Newark	10	\$4.99	\$49.90	\$4.99	
Panel mount 3.5mm headphone jack	Newark	10	\$2.42	\$24.20	\$2.42	
Female-female jumper wires	Ali Express	10	\$0.60	\$6.00	\$0.60	
M2.5 6mm thread + 6mm standoff screws (100 pieces)	Ali Express	1	\$1.98	\$1.98	\$0.20	
Audio cable	Ali Express	10	\$2.79	\$27.90	\$2.79	
KY-016 indicator LED (10 pieces)	Ali Express	1	\$1.92	\$1.92	\$0.19	
KY-040 rotary encoders (knobs)	Ali Express	20	\$0.72	\$14.40	\$1.44	
16GB micro SD card	Amazon	10	\$7.49	\$74.90	\$7.49	
USB thumb drive	Amazon	10	\$7.19	\$71.90	\$7.19	
Sticky back rubber feet (100 pieces)	Ali Express	1	\$1.09	\$1.09	\$0.11	Only needed for wood < 6mm thick
					\$69.42	+ tax + shipping