

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Receiver
Manufacturer: Anthem
Firmware Version: N/A
Model(s): MRX 500, MRX 300, MRX 700

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.00.0000-b022	2.0.0

Version History

Module Version	Date	Notes
1_0_1_0	10/15/2018	Fixed SurroundModeStereoInput status.
1_0_0_0	7/19/2018	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`

Supported Classes and Examples

SerialClass
<code>InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='MRX 500')</code>
SerialOverEthernetClass
<code>InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='MRX 500')</code>

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command AudioMute	Value 'On'	Value 'Off'	
# AudioMute example InterfaceName.Set('AudioMute', 'On')			
Command Input	Value 'BDP' 'SAT' 'Media' 'USB'	Value 'CD' 'Game' 'AM/FM' 'Internet Radio'	Value 'TV' 'AUX' 'iPod' 'Current Main Zone Source'
# Input example InterfaceName.Set('Input', 'BDP')			
Command MultimediaMenu	Value 'Up' 'Right' '1' '4' '7' 'Page Up' 'Play/Pause' 'Next' 'Green'	Value 'Down' 'Select' '2' '5' '8' 'Page Down' 'Rewind' 'Previous' 'Blue'	Value 'Left' '0' '3' '6' '9' 'Menu' 'Fast Forward' 'Preset Scan'
# MultimediaMenu example InterfaceName.Set('MultimediaMenu', 'Up')			
Command Power	Value 'On'	Value 'Off'	
# Power example InterfaceName.Set('Power', 'On')			
Command PresetRecall	Value '1' – '30'		
Qualifier Key 'Mode'	Qualifier Value 'AM'	Qualifier Value 'FM'	

Global Scriptor Module Communication Sheet

Revision: 10/15/2018

# PresetRecall example InterfaceName.Set('PresetRecall', '1', {'Mode': 'AM'})			
Command SetupMenu	Value 'Up'	Value 'Down'	Value 'Left'
	'Right'	'Select'	'0'
	'1'	'2'	'3'
	'4'	'5'	'6'
	'7'	'8'	'9'
# SetupMenu example InterfaceName.Set('SetupMenu', 'Up')			
Command SetupMenuCall	Value 'Open'	Value 'Quit'	
# SetupMenuCall example InterfaceName.Set('SetupMenuCall', 'Open')			
Command SurroundModeChannelInput	Value 'None'	Value 'PLIIx Movie'	Value 'PLIIx Music'
	'Dolby Digital EX'	'Dolby Virtual Speaker Wide'	'Dolby Virtual Speaker Reference'
	'Neo:6 Cinema'	'Neo:6 Music'	'Last Used'
Qualifier Key 'Input'	Qualifier Value 'BDP'	Qualifier Value 'CD'	Qualifier Value 'TV'
	'SAT'	'Game'	'AUX'
	'Media'	'AM/FM'	'iPod'
	'USB'	'Internet Radio'	'Current Main Zone Source'
# SurroundModeChannelInput example InterfaceName.Set('SurroundModeChannelInput', None, {'Input': 'BDP'})			
Command SurroundModeStereoInput	Value 'Stereo'	Value 'AnthemLogic Music'	Value 'AnthemLogic Cinema'
	'PLIIx Movie'	'PLIIx Music'	'Neo:6 Cinema'
	'Neo:6 Music'	'Dolby Virtual Speaker Wide'	'Dolby Virtual Speaker Reference'
	'All Channel Stereo'	'Last Used'	
Qualifier Key 'Input'	Qualifier Value 'BDP'	Qualifier Value 'CD'	Qualifier Value 'TV'
	'SAT'	'Game'	'AUX'
	'Media'	'AM/FM'	'iPod'
	'USB'	'Internet Radio'	'Current Main Zone Source'

Global Scripter Module Communication Sheet

Revision: 10/15/2018

# SurroundModeStereoInput example InterfaceName.Set('SurroundModeStereoInput', 'Stereo', {'Input': 'BDP'})			
Command Tuner	Value 'Up'	Value 'Down'	
# Tuner example InterfaceName.Set('Tuner', 'Up')			
Command Volume	Value -90 to 26 in steps of 1 dB		
# Volume example InterfaceName.Set('Volume', 26)			
Command Zone2AudioMute	Value 'On'	Value 'Off'	
# Zone2AudioMute example InterfaceName.Set('Zone2AudioMute', 'On')			
Command Zone2Input	Value 'BDP'	Value 'CD'	Value 'TV'
	'SAT'	'Game'	'AUX'
	'Media'	'AM/FM'	'iPod'
	'USB'	'Internet Radio'	'Current Main Zone Source'
# Zone2Input example InterfaceName.Set('Zone2Input', 'BDP')			
Command Zone2Power	Value 'On'	Value 'Off'	
# Zone2Power example InterfaceName.Set('Zone2Power', 'On')			
Command Zone2Volume	Value -90 to 26 in steps of 1 dB		
# Zone2Volume example InterfaceName.Set('Zone2Volume', 26)			

Status Available

For all commands, call Update to receive the latest status. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'}, FeedbackHandler)
FeedbackHandler will be called only when the specified qualifier gets a new status.
```

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command	Value	Value	
AudioMute ¹	'On'	'Off'	
# AudioMute examples InterfaceName.Update('AudioMute') Value = InterfaceName.ReadStatus('AudioMute') InterfaceName.SubscribeStatus('AudioMute', None, FeedbackHandler)			
Command	Value	Value	
ConnectionStatus	'Connected'	'Disconnected'	
# ConnectionStatus examples Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)			
Command	Value	Value	Value
DecoderStatus	'No Signal'	'1-Channel'	'2-Channel'
	'Dolby Digital Surround'	'Multi Channel PCM'	'Dolby Digital'
	'Dolby Digital Surround EX'	'DTS 5.1'	'DTS-ES'
	'7.1-Channel'		
Qualifier Key	Qualifier Value	Qualifier Value	Qualifier Value
'Input'	'BDP'	'CD'	'TV'
	'SAT'	'Game'	'AUX'
	'Media'	'AM/FM'	'iPod'
	'USB'	'Internet Radio'	'Current Main Zone Source'
# DecoderStatus examples InterfaceName.Update('DecoderStatus', {'Input': 'BDP'}) Value = InterfaceName.ReadStatus('DecoderStatus', {'Input': 'BDP'}) InterfaceName.SubscribeStatus('DecoderStatus', None, FeedbackHandler)			

Global Scripter Module Communication Sheet

Revision: 10/15/2018

Command Input ¹	Value 'BDP' 'SAT' 'Media' 'USB'	Value 'CD' 'Game' 'AM/FM' 'Internet Radio'	Value 'TV' 'AUX' 'iPod' 'Current Main Zone Source'
# Input examples InterfaceName.Update('Input') Value = InterfaceName.ReadStatus('Input') InterfaceName.SubscribeStatus('Input', None, FeedbackHandler)			
Command Power	Value 'On'	Value 'Off'	
# Power examples InterfaceName.Update('Power') Value = InterfaceName.ReadStatus('Power') InterfaceName.SubscribeStatus('Power', None, FeedbackHandler)			
Command SurroundModeChannelInput	Value None 'Dolby Digital EX' 'Neo:6 Cinema'	Value 'PLIIx Movie' 'Dolby Virtual Speaker Wide' 'Neo:6 Music'	Value 'PLIIx Music' 'Dolby Virtual Speaker Reference' 'Last Used'
Qualifier Key 'Input'	Qualifier Value 'BDP' 'SAT' 'Media' 'USB'	Qualifier Value 'CD' 'Game' 'AM/FM' 'Internet Radio'	Qualifier Value 'TV' 'AUX' 'iPod' 'Current Main Zone Source'
# SurroundModeChannelInput examples InterfaceName.Update('SurroundModeChannelInput', {'Input': 'BDP'}) Value = InterfaceName.ReadStatus('SurroundModeChannelInput', {'Input': 'BDP'}) InterfaceName.SubscribeStatus('SurroundModeChannelInput', None, FeedbackHandler)			
Command SurroundModeStereoInput	Value 'Stereo' 'PLIIx Movie' 'Neo:6 Music' 'All Channel Stereo'	Value 'AnthemLogic Music' 'PLIIx Music' 'Dolby Virtual Speaker Wide' 'Last Used'	Value 'AnthemLogic Cinema' 'Neo:6 Cinema' 'Dolby Virtual Speaker Reference'
Qualifier Key 'Input'	Qualifier Value 'BDP' 'SAT' 'Media'	Qualifier Value 'CD' 'Game' 'AM/FM'	Qualifier Value 'TV' 'AUX' 'iPod'

Global Scripter Module Communication Sheet

Revision: 10/15/2018

	'USB'	'Internet Radio'	'Current Main Zone Source'
<pre># SurroundModeStereoInput examples InterfaceName.Update('SurroundModeStereoInput', {'Input': 'BDP'}) Value = InterfaceName.ReadStatus('SurroundModeStereoInput', {'Input': 'BDP'}) InterfaceName.SubscribeStatus('SurroundModeStereoInput', None, FeedbackHandler)</pre>			
Command Volume ¹	Value -90 to 26 in steps of 1 dB		
<pre># Volume examples InterfaceName.Update('Volume') Value = InterfaceName.ReadStatus('Volume') InterfaceName.SubscribeStatus('Volume', None, FeedbackHandler)</pre>			
Command Zone2AudioMute ²	Value 'On'	Value 'Off'	
<pre># Zone2AudioMute examples InterfaceName.Update('Zone2AudioMute') Value = InterfaceName.ReadStatus('Zone2AudioMute') InterfaceName.SubscribeStatus('Zone2AudioMute', None, FeedbackHandler)</pre>			
Command Zone2Input ²	Value 'BDP' 'SAT' 'Media' 'USB'	Value 'CD' 'Game' 'AM/FM' 'Internet Radio'	Value 'TV' 'AUX' 'iPod' 'Current Main Zone Source'
<pre># Zone2Input examples InterfaceName.Update('Zone2Input') Value = InterfaceName.ReadStatus('Zone2Input') InterfaceName.SubscribeStatus('Zone2Input', None, FeedbackHandler)</pre>			
Command Zone2Power	Value 'On'	Value 'Off'	
<pre># Zone2Power examples InterfaceName.Update('Zone2Power') Value = InterfaceName.ReadStatus('Zone2Power') InterfaceName.SubscribeStatus('Zone2Power', None, FeedbackHandler)</pre>			
Command Zone2Volume ²	Value -90 to 26 in steps of 1 dB		
<pre># Zone2Volume examples InterfaceName.Update('Zone2Volume') Value = InterfaceName.ReadStatus('Zone2Volume') InterfaceName.SubscribeStatus('Zone2Volume', None, FeedbackHandler)</pre>			

¹ Calling Update method with one of these commands will provide statuses for the other commands with this superscript note.

² Calling Update method with one of these commands will provide statuses for the other commands with this superscript note.

Cable and Adapter Requirements

Captive Screw to Male DB9 RS-232 Serial Cable

Notes for the Device

Serial communication

Port Type: RS-232

Baud Rate: 115200


Data Bits: 8

Parity: None


Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
TxD	→	2	RxD
RxD	←	3	TxD
GND	→	5	GND



Appendix A. Set Commands

Audio Mute Off	P1M0\x0A
Audio Mute On	P1M1\x0A
Input AM/FM	P1S8\x0A
Input AUX	P1S6\x0A
Input BDP	P1S1\x0A
Input CD	P1S2\x0A
Input Current Main Zone Source	P1Sc\x0A
Input Game	P1S5\x0A
Input Internet Radio	P1Se\x0A
Input iPod	P1S9\x0A
Input Media	P1S7\x0A
Input SAT	P1S4\x0A
Input TV	P1S3\x0A
Input USB	P1Sd\x0A
Multimedia Menu 0	P1G0\x0A
Multimedia Menu 9	P1G9\x0A
Multimedia Menu Blue	P1Gb\x0A
Multimedia Menu Down	P1Gd\x0A
Multimedia Menu Fast Forward	P1GF\x0A
Multimedia Menu Green	P1Gg\x0A
Multimedia Menu Left	P1Gl\x0A
Multimedia Menu Menu	P1GM\x0A
Multimedia Menu Next	P1Gn\x0A
Multimedia Menu Page Down	P1GD\x0A
Multimedia Menu Page Up	P1GU\x0A
Multimedia Menu Play/Pause	P1GP\x0A
Multimedia Menu Preset Scan	P1Gs\x0A
Multimedia Menu Previous	P1Gp\x0A
Multimedia Menu Rewind	P1GR\x0A
Multimedia Menu Right	P1Gr\x0A
Multimedia Menu Select	P1GS\x0A
Multimedia Menu Up	P1Gu\x0A
Power Off	P1P0\x0A
Power On	P1P1\x0A
Preset Recall 1 Mode AM	TAP01
Preset Recall 1 Mode FM	TFP01

Global Scripter Module Communication Sheet

Revision: 10/15/2018

Preset Recall 30 Mode AM	TAP30
Preset Recall 30 Mode FM	TFP30
Setup Menu 0	P1U0\x0A
Setup Menu 9	P1U9\x0A
Setup Menu Call Open	P1Uo\x0A
Setup Menu Call Quit	P1Uq\x0A
Setup Menu Down	P1Ud\x0A
Setup Menu Left	P1U1\x0A
Setup Menu Right	P1Ur\x0A
Setup Menu Select	P1Us\x0A
Setup Menu Up	P1Uu\x0A
Surround Mode Channel Input Dolby Digital EX Input AM/FM	P1MM83\x0A
Surround Mode Channel Input Dolby Digital EX Input AUX	P1MM63\x0A
Surround Mode Channel Input Dolby Digital EX Input BDP	P1MM13\x0A
Surround Mode Channel Input Dolby Digital EX Input CD	P1MM23\x0A
Surround Mode Channel Input Dolby Digital EX Input Current Main Zone Source	P1MMc3\x0A
Surround Mode Channel Input Dolby Digital EX Input Game	P1MM53\x0A
Surround Mode Channel Input Dolby Digital EX Input Internet Radio	P1MMe3\x0A
Surround Mode Channel Input Dolby Digital EX Input iPod	P1MM93\x0A
Surround Mode Channel Input Dolby Digital EX Input Media	P1MM73\x0A
Surround Mode Channel Input Dolby Digital EX Input SAT	P1MM43\x0A
Surround Mode Channel Input Dolby Digital EX Input TV	P1MM33\x0A
Surround Mode Channel Input Dolby Digital EX Input USB	P1MMd3\x0A
Surround Mode Channel Input Dolby Virtual Speaker Reference Input AM/FM	P1MM85\x0A
Surround Mode Channel Input Dolby Virtual Speaker Reference Input AUX	P1MM65\x0A

Global Scripter Module Communication Sheet

Revision: 10/15/2018

Surround Mode Channel Input Dolby Virtual Speaker Reference Input BDP	P1MM15*x0A
Surround Mode Channel Input Dolby Virtual Speaker Reference Input CD	P1MM25*x0A
Surround Mode Channel Input Dolby Virtual Speaker Reference Input Current Main Zone Source	P1MMc5*x0A
Surround Mode Channel Input Dolby Virtual Speaker Reference Input Game	P1MM55*x0A
Surround Mode Channel Input Dolby Virtual Speaker Reference Input Internet Radio	P1MMe5*x0A
Surround Mode Channel Input Dolby Virtual Speaker Reference Input iPod	P1MM95*x0A
Surround Mode Channel Input Dolby Virtual Speaker Reference Input Media	P1MM75*x0A
Surround Mode Channel Input Dolby Virtual Speaker Reference Input SAT	P1MM45*x0A
Surround Mode Channel Input Dolby Virtual Speaker Reference Input TV	P1MM35*x0A
Surround Mode Channel Input Dolby Virtual Speaker Reference Input USB	P1MMd5*x0A
Surround Mode Channel Input Dolby Virtual Speaker Wide Input AM/FM	P1MM84*x0A
Surround Mode Channel Input Dolby Virtual Speaker Wide Input AUX	P1MM64*x0A
Surround Mode Channel Input Dolby Virtual Speaker Wide Input BDP	P1MM14*x0A
Surround Mode Channel Input Dolby Virtual Speaker Wide Input CD	P1MM24*x0A
Surround Mode Channel Input Dolby Virtual Speaker Wide Input Current Main Zone Source	P1MMc4*x0A
Surround Mode Channel Input Dolby Virtual Speaker Wide Input Game	P1MM54*x0A
Surround Mode Channel Input Dolby Virtual Speaker Wide Input Internet Radio	P1MMe4*x0A
Surround Mode Channel Input Dolby Virtual Speaker Wide Input iPod	P1MM94*x0A
Surround Mode Channel Input Dolby Virtual Speaker Wide Input Media	P1MM74*x0A
Surround Mode Channel Input Dolby Virtual Speaker Wide Input SAT	P1MM44*x0A

Global Scripter Module Communication Sheet

Revision: 10/15/2018

Surround Mode Channel Input Dolby Virtual Speaker Wide Input TV	P1MM34\x0A
Surround Mode Channel Input Dolby Virtual Speaker Wide Input USB	P1MMd4\x0A
Surround Mode Channel Input Last Used Input AM/FM	P1MM88\x0A
Surround Mode Channel Input Last Used Input AUX	P1MM68\x0A
Surround Mode Channel Input Last Used Input BDP	P1MM18\x0A
Surround Mode Channel Input Last Used Input CD	P1MM28\x0A
Surround Mode Channel Input Last Used Input Current Main Zone Source	P1MMc8\x0A
Surround Mode Channel Input Last Used Input Game	P1MM58\x0A
Surround Mode Channel Input Last Used Input Internet Radio	P1MMe8\x0A
Surround Mode Channel Input Last Used Input iPod	P1MM98\x0A
Surround Mode Channel Input Last Used Input Media	P1MM78\x0A
Surround Mode Channel Input Last Used Input SAT	P1MM48\x0A
Surround Mode Channel Input Last Used Input TV	P1MM38\x0A
Surround Mode Channel Input Last Used Input USB	P1MMd8\x0A
Surround Mode Channel Input Neo:6 Cinema Input AM/FM	P1MM86\x0A
Surround Mode Channel Input Neo:6 Cinema Input AUX	P1MM66\x0A
Surround Mode Channel Input Neo:6 Cinema Input BDP	P1MM16\x0A
Surround Mode Channel Input Neo:6 Cinema Input CD	P1MM26\x0A
Surround Mode Channel Input Neo:6 Cinema Input Current Main Zone Source	P1MMc6\x0A
Surround Mode Channel Input Neo:6 Cinema Input Game	P1MM56\x0A
Surround Mode Channel Input Neo:6 Cinema Input Internet Radio	P1MMe6\x0A
Surround Mode Channel Input Neo:6 Cinema Input iPod	P1MM96\x0A
Surround Mode Channel Input Neo:6 Cinema Input Media	P1MM76\x0A
Surround Mode Channel Input Neo:6 Cinema Input SAT	P1MM46\x0A

Global Scripter Module Communication Sheet

Revision: 10/15/2018

Surround Mode Channel Input Neo:6 Cinema Input TV	P1MM36\x0A
Surround Mode Channel Input Neo:6 Cinema Input USB	P1MMd6\x0A
Surround Mode Channel Input Neo:6 Music Input AM/FM	P1MM87\x0A
Surround Mode Channel Input Neo:6 Music Input AUX	P1MM67\x0A
Surround Mode Channel Input Neo:6 Music Input BDP	P1MM17\x0A
Surround Mode Channel Input Neo:6 Music Input CD	P1MM27\x0A
Surround Mode Channel Input Neo:6 Music Input Current Main Zone Source	P1MMc7\x0A
Surround Mode Channel Input Neo:6 Music Input Game	P1MM57\x0A
Surround Mode Channel Input Neo:6 Music Input Internet Radio	P1MMe7\x0A
Surround Mode Channel Input Neo:6 Music Input iPod	P1MM97\x0A
Surround Mode Channel Input Neo:6 Music Input Media	P1MM77\x0A
Surround Mode Channel Input Neo:6 Music Input SAT	P1MM47\x0A
Surround Mode Channel Input Neo:6 Music Input TV	P1MM37\x0A
Surround Mode Channel Input Neo:6 Music Input USB	P1MMd7\x0A
Surround Mode Channel Input None Input AM/FM	P1MM80\x0A
Surround Mode Channel Input None Input AUX	P1MM60\x0A
Surround Mode Channel Input None Input BDP	P1MM10\x0A
Surround Mode Channel Input None Input CD	P1MM20\x0A
Surround Mode Channel Input None Input Current Main Zone Source	P1MMc0\x0A
Surround Mode Channel Input None Input Game	P1MM50\x0A
Surround Mode Channel Input None Input Internet Radio	P1MMe0\x0A
Surround Mode Channel Input None Input iPod	P1MM90\x0A
Surround Mode Channel Input None Input Media	P1MM70\x0A
Surround Mode Channel Input None Input SAT	P1MM40\x0A
Surround Mode Channel Input None Input TV	P1MM30\x0A
Surround Mode Channel Input None Input USB	P1MMd0\x0A

Global Scripter Module Communication Sheet

Revision: 10/15/2018

Surround Mode Channel Input PLIIx Movie Input AM/FM	P1MM81\x0A
Surround Mode Channel Input PLIIx Movie Input AUX	P1MM61\x0A
Surround Mode Channel Input PLIIx Movie Input BDP	P1MM11\x0A
Surround Mode Channel Input PLIIx Movie Input CD	P1MM21\x0A
Surround Mode Channel Input PLIIx Movie Input Current Main Zone Source	P1MMc1\x0A
Surround Mode Channel Input PLIIx Movie Input Game	P1MM51\x0A
Surround Mode Channel Input PLIIx Movie Input Internet Radio	P1MMe1\x0A
Surround Mode Channel Input PLIIx Movie Input iPod	P1MM91\x0A
Surround Mode Channel Input PLIIx Movie Input Media	P1MM71\x0A
Surround Mode Channel Input PLIIx Movie Input SAT	P1MM41\x0A
Surround Mode Channel Input PLIIx Movie Input TV	P1MM31\x0A
Surround Mode Channel Input PLIIx Movie Input USB	P1MMd1\x0A
Surround Mode Channel Input PLIIx Music Input AM/FM	P1MM82\x0A
Surround Mode Channel Input PLIIx Music Input AUX	P1MM62\x0A
Surround Mode Channel Input PLIIx Music Input BDP	P1MM12\x0A
Surround Mode Channel Input PLIIx Music Input CD	P1MM22\x0A
Surround Mode Channel Input PLIIx Music Input Current Main Zone Source	P1MMc2\x0A
Surround Mode Channel Input PLIIx Music Input Game	P1MM52\x0A
Surround Mode Channel Input PLIIx Music Input Internet Radio	P1MMe2\x0A
Surround Mode Channel Input PLIIx Music Input iPod	P1MM92\x0A
Surround Mode Channel Input PLIIx Music Input Media	P1MM72\x0A
Surround Mode Channel Input PLIIx Music Input SAT	P1MM42\x0A
Surround Mode Channel Input PLIIx Music Input TV	P1MM32\x0A
Surround Mode Channel Input PLIIx Music Input USB	P1MMd2\x0A
Surround Mode Stereo Input All Channel Stereo Input AM/FM	P1MS89\x0A
Surround Mode Stereo Input All Channel Stereo Input AUX	P1MS69\x0A
Surround Mode Stereo Input All Channel Stereo Input BDP	P1MS19\x0A

Global Scripter Module Communication Sheet

Revision: 10/15/2018

Surround Mode Stereo Input All Channel Stereo Input CD	P1MS29\x0A
Surround Mode Stereo Input All Channel Stereo Input Current Main Zone Source	P1MSc9\x0A
Surround Mode Stereo Input All Channel Stereo Input Game	P1MS59\x0A
Surround Mode Stereo Input All Channel Stereo Input Internet Radio	P1MSe9\x0A
Surround Mode Stereo Input All Channel Stereo Input iPod	P1MS99\x0A
Surround Mode Stereo Input All Channel Stereo Input Media	P1MS79\x0A
Surround Mode Stereo Input All Channel Stereo Input SAT	P1MS49\x0A
Surround Mode Stereo Input All Channel Stereo Input TV	P1MS39\x0A
Surround Mode Stereo Input All Channel Stereo Input USB	P1MSd9\x0A
Surround Mode Stereo Input AnthemLogic Cinema Input AM/FM	P1MS82\x0A
Surround Mode Stereo Input AnthemLogic Cinema Input AUX	P1MS62\x0A
Surround Mode Stereo Input AnthemLogic Cinema Input BDP	P1MS12\x0A
Surround Mode Stereo Input AnthemLogic Cinema Input CD	P1MS22\x0A
Surround Mode Stereo Input AnthemLogic Cinema Input Current Main Zone Source	P1MSc2\x0A
Surround Mode Stereo Input AnthemLogic Cinema Input Game	P1MS52\x0A
Surround Mode Stereo Input AnthemLogic Cinema Input Internet Radio	P1MSe2\x0A
Surround Mode Stereo Input AnthemLogic Cinema Input iPod	P1MS92\x0A
Surround Mode Stereo Input AnthemLogic Cinema Input Media	P1MS72\x0A
Surround Mode Stereo Input AnthemLogic Cinema Input SAT	P1MS42\x0A
Surround Mode Stereo Input AnthemLogic Cinema Input TV	P1MS32\x0A

Global Scriptor Module Communication Sheet

Revision: 10/15/2018

Surround Mode Stereo Input AnthemLogic Cinema Input USB	P1MSd2\x0A
Surround Mode Stereo Input AnthemLogic Music Input AM/FM	P1MS81\x0A
Surround Mode Stereo Input AnthemLogic Music Input AUX	P1MS61\x0A
Surround Mode Stereo Input AnthemLogic Music Input BDP	P1MS11\x0A
Surround Mode Stereo Input AnthemLogic Music Input CD	P1MS21\x0A
Surround Mode Stereo Input AnthemLogic Music Input Current Main Zone Source	P1MSc1\x0A
Surround Mode Stereo Input AnthemLogic Music Input Game	P1MS51\x0A
Surround Mode Stereo Input AnthemLogic Music Input Internet Radio	P1MSe1\x0A
Surround Mode Stereo Input AnthemLogic Music Input iPod	P1MS91\x0A
Surround Mode Stereo Input AnthemLogic Music Input Media	P1MS71\x0A
Surround Mode Stereo Input AnthemLogic Music Input SAT	P1MS41\x0A
Surround Mode Stereo Input AnthemLogic Music Input TV	P1MS31\x0A
Surround Mode Stereo Input AnthemLogic Music Input USB	P1MSd1\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Reference Input AM/FM	P1MS88\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Reference Input AUX	P1MS68\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Reference Input BDP	P1MS18\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Reference Input CD	P1MS28\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Reference Input Current Main Zone Source	P1MSc8\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Reference Input Game	P1MS58\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Reference Input Internet Radio	P1MSe8\x0A

Global Scriptor Module Communication Sheet

Revision: 10/15/2018

Surround Mode Stereo Input Dolby Virtual Speaker Reference Input iPod	P1MS98\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Reference Input Media	P1MS78\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Reference Input SAT	P1MS48\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Reference Input TV	P1MS38\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Reference Input USB	P1MSd8\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Wide Input AM/FM	P1MS87\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Wide Input AUX	P1MS67\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Wide Input BDP	P1MS17\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Wide Input CD	P1MS27\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Wide Input Current Main Zone Source	P1MSc7\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Wide Input Game	P1MS57\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Wide Input Internet Radio	P1MSe7\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Wide Input iPod	P1MS97\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Wide Input Media	P1MS77\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Wide Input SAT	P1MS47\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Wide Input TV	P1MS37\x0A
Surround Mode Stereo Input Dolby Virtual Speaker Wide Input USB	P1MSd7\x0A
Surround Mode Stereo Input Last Used Input AM/FM	P1MS8a\x0A
Surround Mode Stereo Input Last Used Input AUX	P1MS6a\x0A
Surround Mode Stereo Input Last Used Input BDP	P1MS1a\x0A
Surround Mode Stereo Input Last Used Input CD	P1MS2a\x0A
Surround Mode Stereo Input Last Used Input Current Main Zone Source	P1MSca\x0A

Global Scriptor Module Communication Sheet

Revision: 10/15/2018

Surround Mode Stereo Input Last Used Input Game	P1MS5a\x0A
Surround Mode Stereo Input Last Used Input Internet Radio	P1MS5a\x0A
Surround Mode Stereo Input Last Used Input iPod	P1MS9a\x0A
Surround Mode Stereo Input Last Used Input Media	P1MS7a\x0A
Surround Mode Stereo Input Last Used Input SAT	P1MS4a\x0A
Surround Mode Stereo Input Last Used Input TV	P1MS3a\x0A
Surround Mode Stereo Input Last Used Input USB	P1MSda\x0A
Surround Mode Stereo Input Neo:6 Cinema Input AM/FM	P1MS86\x0A
Surround Mode Stereo Input Neo:6 Cinema Input AUX	P1MS66\x0A
Surround Mode Stereo Input Neo:6 Cinema Input BDP	P1MS16\x0A
Surround Mode Stereo Input Neo:6 Cinema Input CD	P1MS26\x0A
Surround Mode Stereo Input Neo:6 Cinema Input Current Main Zone Source	P1MSc6\x0A
Surround Mode Stereo Input Neo:6 Cinema Input Game	P1MS56\x0A
Surround Mode Stereo Input Neo:6 Cinema Input Internet Radio	P1MS66\x0A
Surround Mode Stereo Input Neo:6 Cinema Input iPod	P1MS96\x0A
Surround Mode Stereo Input Neo:6 Cinema Input Media	P1MS76\x0A
Surround Mode Stereo Input Neo:6 Cinema Input SAT	P1MS46\x0A
Surround Mode Stereo Input Neo:6 Cinema Input TV	P1MS36\x0A
Surround Mode Stereo Input Neo:6 Cinema Input USB	P1MSd6\x0A
Surround Mode Stereo Input Neo:6 Music Input AM/FM	P1MS85\x0A
Surround Mode Stereo Input Neo:6 Music Input AUX	P1MS65\x0A
Surround Mode Stereo Input Neo:6 Music Input BDP	P1MS15\x0A
Surround Mode Stereo Input Neo:6 Music Input CD	P1MS25\x0A
Surround Mode Stereo Input Neo:6 Music Input Current Main Zone Source	P1MSc5\x0A
Surround Mode Stereo Input Neo:6 Music Input Game	P1MS55\x0A
Surround Mode Stereo Input Neo:6 Music Input Internet Radio	P1MS65\x0A

Global Scripter Module Communication Sheet

Revision: 10/15/2018

Surround Mode Stereo Input Neo:6 Music Input iPod	P1MS95\x0A
Surround Mode Stereo Input Neo:6 Music Input Media	P1MS75\x0A
Surround Mode Stereo Input Neo:6 Music Input SAT	P1MS45\x0A
Surround Mode Stereo Input Neo:6 Music Input TV	P1MS35\x0A
Surround Mode Stereo Input Neo:6 Music Input USB	P1MSd5\x0A
Surround Mode Stereo Input PLIIx Movie Input AM/FM	P1MS83\x0A
Surround Mode Stereo Input PLIIx Movie Input AUX	P1MS63\x0A
Surround Mode Stereo Input PLIIx Movie Input BDP	P1MS13\x0A
Surround Mode Stereo Input PLIIx Movie Input CD	P1MS23\x0A
Surround Mode Stereo Input PLIIx Movie Input Current Main Zone Source	P1MSc3\x0A
Surround Mode Stereo Input PLIIx Movie Input Game	P1MS53\x0A
Surround Mode Stereo Input PLIIx Movie Input Internet Radio	P1MSe3\x0A
Surround Mode Stereo Input PLIIx Movie Input iPod	P1MS93\x0A
Surround Mode Stereo Input PLIIx Movie Input Media	P1MS73\x0A
Surround Mode Stereo Input PLIIx Movie Input SAT	P1MS43\x0A
Surround Mode Stereo Input PLIIx Movie Input TV	P1MS33\x0A
Surround Mode Stereo Input PLIIx Movie Input USB	P1MSd3\x0A
Surround Mode Stereo Input PLIIx Music Input AM/FM	P1MS84\x0A
Surround Mode Stereo Input PLIIx Music Input AUX	P1MS64\x0A
Surround Mode Stereo Input PLIIx Music Input BDP	P1MS14\x0A
Surround Mode Stereo Input PLIIx Music Input CD	P1MS24\x0A
Surround Mode Stereo Input PLIIx Music Input Current Main Zone Source	P1MSc4\x0A
Surround Mode Stereo Input PLIIx Music Input Game	P1MS54\x0A
Surround Mode Stereo Input PLIIx Music Input Internet Radio	P1MSe4\x0A
Surround Mode Stereo Input PLIIx Music Input iPod	P1MS94\x0A
Surround Mode Stereo Input PLIIx Music Input Media	P1MS74\x0A
Surround Mode Stereo Input PLIIx Music Input SAT	P1MS44\x0A
Surround Mode Stereo Input PLIIx Music Input TV	P1MS34\x0A
Surround Mode Stereo Input PLIIx Music Input USB	P1MSd4\x0A
Surround Mode Stereo Input Stereo Input AM/FM	P1MS80\x0A
Surround Mode Stereo Input Stereo Input AUX	P1MS60\x0A

Global Scriptor Module Communication Sheet

Revision: 10/15/2018

Surround Mode Stereo Input Stereo Input BDP	P1MS10\x0A
Surround Mode Stereo Input Stereo Input CD	P1MS20\x0A
Surround Mode Stereo Input Stereo Input Current Main Zone Source	P1MSc0\x0A
Surround Mode Stereo Input Stereo Input Game	P1MS50\x0A
Surround Mode Stereo Input Stereo Input Internet Radio	P1MSe0\x0A
Surround Mode Stereo Input Stereo Input iPod	P1MS90\x0A
Surround Mode Stereo Input Stereo Input Media	P1MS70\x0A
Surround Mode Stereo Input Stereo Input SAT	P1MS40\x0A
Surround Mode Stereo Input Stereo Input TV	P1MS30\x0A
Surround Mode Stereo Input Stereo Input USB	P1MSd0\x0A
Tuner Down	T-\x0A
Tuner Up	T+\x0A
Volume 26	P1V26\x0A
Volume -90	P1V-90\x0A
Zone 2 Audio Mute Off	P2M0\x0A
Zone 2 Audio Mute On	P2M1\x0A
Zone 2 Input AM/FM	P2S8\x0A
Zone 2 Input AUX	P2S6\x0A
Zone 2 Input BDP	P2S1\x0A
Zone 2 Input CD	P2S2\x0A
Zone 2 Input Current Main Zone Source	P2Sc\x0A
Zone 2 Input Game	P2S5\x0A
Zone 2 Input Internet Radio	P2Se\x0A
Zone 2 Input iPod	P2S9\x0A
Zone 2 Input Media	P2S7\x0A
Zone 2 Input SAT	P2S4\x0A
Zone 2 Input TV	P2S3\x0A
Zone 2 Input USB	P2Sd\x0A
Zone 2 Power Off	P2P0\x0A
Zone 2 Power On	P2P1\x0A
Zone 2 Volume 26	P2V26\x0A
Zone 2 Volume -90	P2V-90\x0A

Appendix B. Update Commands

Audio Mute	P1?\x0A
Decoder Status Input AM/FM	P1D?\x0A
Decoder Status Input AUX	P1D?\x0A
Decoder Status Input BDP	P1D?\x0A
Decoder Status Input CD	P1D?\x0A
Decoder Status Input Current Main Zone Source	P1D?\x0A
Decoder Status Input Game	P1D?\x0A
Decoder Status Input Internet Radio	P1D?\x0A
Decoder Status Input iPod	P1D?\x0A
Decoder Status Input Media	P1D?\x0A
Decoder Status Input SAT	P1D?\x0A
Decoder Status Input TV	P1D?\x0A
Decoder Status Input USB	P1D?\x0A
Input	P1?\x0A
Power	P1P?\x0A
Surround Mode Channel Input Input AM/FM	P1MM?\x0A
Surround Mode Channel Input Input AUX	P1MM?\x0A
Surround Mode Channel Input Input BDP	P1MM?\x0A
Surround Mode Channel Input Input CD	P1MM?\x0A
Surround Mode Channel Input Input Current Main Zone Source	P1MM?\x0A
Surround Mode Channel Input Input Game	P1MM?\x0A
Surround Mode Channel Input Input Internet Radio	P1MM?\x0A
Surround Mode Channel Input Input iPod	P1MM?\x0A
Surround Mode Channel Input Input Media	P1MM?\x0A
Surround Mode Channel Input Input SAT	P1MM?\x0A
Surround Mode Channel Input Input TV	P1MM?\x0A
Surround Mode Channel Input Input USB	P1MM?\x0A
Surround Mode Stereo Input Input AM/FM	P1MS?\x0A
Surround Mode Stereo Input Input AUX	P1MS?\x0A
Surround Mode Stereo Input Input BDP	P1MS?\x0A
Surround Mode Stereo Input Input CD	P1MS?\x0A
Surround Mode Stereo Input Input Current Main Zone Source	P1MS?\x0A
Surround Mode Stereo Input Input Game	P1MS?\x0A
Surround Mode Stereo Input Input Internet Radio	P1MS?\x0A

Global Scripter Module Communication Sheet

Revision: 10/15/2018

Surround Mode Stereo Input Input iPod	P1MS?\x0A
Surround Mode Stereo Input Input Media	P1MS?\x0A
Surround Mode Stereo Input Input SAT	P1MS?\x0A
Surround Mode Stereo Input Input TV	P1MS?\x0A
Surround Mode Stereo Input Input USB	P1MS?\x0A
Volume	P1?\x0A
Zone 2 Audio Mute	P2?\x0A
Zone 2 Input	P2?\x0A
Zone 2 Power	P2P?\x0A
Zone 2 Volume	P2?\x0A