

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Audio Processor
Manufacturer: Behringer
Firmware Version: 2.08
Model(s): X32

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.03.0000-b006	2.01.0001-b001	1.1.1

Version History

Module Version	Date	Notes
1_4_0_0	11/8/2016	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example:
InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example:
InterfaceName.connectionCounter = 5

Control Commands, States, and Qualifiers:

AuxinFaderLevel	0 to 100 in steps of 1
['Auxin']	'1' – '8'
AuxinFaderMute	'On' 'Off'
['Auxin']	'1' – '8'
BusFaderLevel	0 to 100 in steps of 1
['Bus']	'1' – '16'
BusFaderMute	'On' 'Off'
['Bus']	'1' – '16'
ChannelFaderLevel	0 to 100 in steps of 1
['Channel']	'1' – '32'
ChannelFaderMute	'On' 'Off'
['Channel']	'1' – '32'
DCAFaderLevel	0 to 100 in steps of 1
['DCA']	'1' – '8'
DCAFaderMute	'On' 'Off'
['DCA']	'1' – '8'
FXReturnFaderLevel	0 to 100 in steps of 1
['FX Return']	'1' – '8'
FXReturnFaderMute	'On' 'Off'
['FX Return']	'1' – '8'
GroupMute	'On' 'Off'
['Group']	'1' – '6'
MainFaderLevel	0 to 100 in steps of 1
['Type']	'Mono' 'Stereo'
MainFaderMute	'On' 'Off'
['Type']	'Mono' 'Stereo'
MatrixFaderLevel	0 to 100 in steps of 1
['Matrix']	'1' – '6'
MatrixFaderMute	'On' 'Off'
['Matrix']	'1' – '6'

Status Available:

AuxinFaderLevel	0 to 100 in steps of 1
['Auxin']	'1' – '8'
AuxinFaderMute	'On' 'Off'
['Auxin']	'1' – '8'
BusFaderLevel	0 to 100 in steps of 1
['Bus']	'1' – '16'
BusFaderMute	'On' 'Off'
['Bus']	'1' – '16'
ChannelFaderLevel	0 to 100 in steps of 1
['Channel']	'1' – '32'
ChannelFaderMute	'On' 'Off'
['Channel']	'1' – '32'
ConnectionStatus	'Connected' 'Disconnected'
DCAFaderLevel	0 to 100 in steps of 1
['DCA']	'1' – '8'
DCAFaderMute	'On' 'Off'
['DCA']	'1' – '8'
FXReturnFaderLevel	0 to 100 in steps of 1
['FX Return']	'1' – '8'
FXReturnFaderMute	'On' 'Off'
['FX Return']	'1' – '8'
GroupMute	'On' 'Off'
['Group']	'1' – '6'
MainFaderLevel	0 to 100 in steps of 1
['Type']	'Mono' 'Stereo'
MainFaderMute	'On' 'Off'
['Type']	'Mono' 'Stereo'
MatrixFaderLevel	0 to 100 in steps of 1
['Matrix']	'1' – '6'
MatrixFaderMute	'On' 'Off'
['Matrix']	'1' – '6'

Network communication:

When configuring the Ethernet interface, be sure the device settings match that of the GS interface settings.

Port Type:	Ethernet
Default Port:	10023
Logon Credentials Supported:	No
Multi-Connection Capabilities:	Yes
Port Changeability:	No

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device:

Appendix A. Set Commands

AuxinFaderLevel Auxin 1 0	/auxin/01/mix/fader\x00,f\x00\x00\x00\x00\x00
AuxinFaderLevel Auxin 1 100	/auxin/01/mix/fader\x00,f\x00\x00?\x80\x00\x00
AuxinFaderLevel Auxin 2 0	/auxin/02/mix/fader\x00,f\x00\x00\x00\x00\x00
AuxinFaderLevel Auxin 2 100	/auxin/02/mix/fader\x00,f\x00\x00?\x80\x00\x00
AuxinFaderLevel Auxin 3 0	/auxin/03/mix/fader\x00,f\x00\x00\x00\x00\x00
AuxinFaderLevel Auxin 3 100	/auxin/03/mix/fader\x00,f\x00\x00?\x80\x00\x00
AuxinFaderLevel Auxin 4 0	/auxin/04/mix/fader\x00,f\x00\x00\x00\x00\x00
AuxinFaderLevel Auxin 4 100	/auxin/04/mix/fader\x00,f\x00\x00?\x80\x00\x00
AuxinFaderLevel Auxin 5 0	/auxin/05/mix/fader\x00,f\x00\x00\x00\x00\x00
AuxinFaderLevel Auxin 5 100	/auxin/05/mix/fader\x00,f\x00\x00?\x80\x00\x00
AuxinFaderLevel Auxin 6 0	/auxin/06/mix/fader\x00,f\x00\x00\x00\x00\x00
AuxinFaderLevel Auxin 6 100	/auxin/06/mix/fader\x00,f\x00\x00?\x80\x00\x00
AuxinFaderLevel Auxin 7 0	/auxin/07/mix/fader\x00,f\x00\x00\x00\x00\x00
AuxinFaderLevel Auxin 7 100	/auxin/07/mix/fader\x00,f\x00\x00?\x80\x00\x00
AuxinFaderLevel Auxin 8 0	/auxin/08/mix/fader\x00,f\x00\x00\x00\x00\x00
AuxinFaderLevel Auxin 8 100	/auxin/08/mix/fader\x00,f\x00\x00?\x80\x00\x00
AuxinFaderMute Auxin 1 Off	/auxin/01/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
AuxinFaderMute Auxin 1 On	/auxin/01/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
AuxinFaderMute Auxin 2 Off	/auxin/02/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
AuxinFaderMute Auxin 2 On	/auxin/02/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
AuxinFaderMute Auxin 3 Off	/auxin/03/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
AuxinFaderMute Auxin 3 On	/auxin/03/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
AuxinFaderMute Auxin 4 Off	/auxin/04/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
AuxinFaderMute Auxin 4 On	/auxin/04/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
AuxinFaderMute Auxin 5 Off	/auxin/05/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
AuxinFaderMute Auxin 5 On	/auxin/05/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
AuxinFaderMute Auxin 6 Off	/auxin/06/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
AuxinFaderMute Auxin 6 On	/auxin/06/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
AuxinFaderMute Auxin 7 Off	/auxin/07/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
AuxinFaderMute Auxin 7 On	/auxin/07/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
AuxinFaderMute Auxin 8 Off	/auxin/08/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
AuxinFaderMute Auxin 8 On	/auxin/08/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
BusFaderLevel Bus 1 0	/bus/01/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00
BusFaderLevel Bus 1 100	/bus/01/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
BusFaderLevel Bus 10 0	/bus/10/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00
BusFaderLevel Bus 10 100	/bus/10/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
BusFaderLevel Bus 11 0	/bus/11/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00
BusFaderLevel Bus 11 100	/bus/11/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
BusFaderLevel Bus 12 0	/bus/12/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00
BusFaderLevel Bus 12 100	/bus/12/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
BusFaderLevel Bus 13 0	/bus/13/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00
BusFaderLevel Bus 13 100	/bus/13/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
BusFaderLevel Bus 14 0	/bus/14/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00
BusFaderLevel Bus 14 100	/bus/14/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
BusFaderLevel Bus 15 0	/bus/15/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00
BusFaderLevel Bus 15 100	/bus/15/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
BusFaderLevel Bus 16 0	/bus/16/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00

Global Scriptor Module Communication Sheet

BusFaderLevel Bus 16 100	/bus/16/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
BusFaderLevel Bus 2 0	/bus/02/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00\x00
BusFaderLevel Bus 2 100	/bus/02/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
BusFaderLevel Bus 3 0	/bus/03/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00\x00
BusFaderLevel Bus 3 100	/bus/03/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
BusFaderLevel Bus 4 0	/bus/04/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00\x00
BusFaderLevel Bus 4 100	/bus/04/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
BusFaderLevel Bus 5 0	/bus/05/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00\x00
BusFaderLevel Bus 5 100	/bus/05/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
BusFaderLevel Bus 6 0	/bus/06/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00\x00
BusFaderLevel Bus 6 100	/bus/06/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
BusFaderLevel Bus 7 0	/bus/07/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00\x00
BusFaderLevel Bus 7 100	/bus/07/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
BusFaderLevel Bus 8 0	/bus/08/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00\x00
BusFaderLevel Bus 8 100	/bus/08/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
BusFaderLevel Bus 9 0	/bus/09/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00\x00
BusFaderLevel Bus 9 100	/bus/09/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
BusFaderMute Bus 1 Off	/bus/01/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
BusFaderMute Bus 1 On	/bus/01/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
BusFaderMute Bus 10 Off	/bus/10/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
BusFaderMute Bus 10 On	/bus/10/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
BusFaderMute Bus 11 Off	/bus/11/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
BusFaderMute Bus 11 On	/bus/11/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
BusFaderMute Bus 12 Off	/bus/12/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
BusFaderMute Bus 12 On	/bus/12/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
BusFaderMute Bus 13 Off	/bus/13/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
BusFaderMute Bus 13 On	/bus/13/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
BusFaderMute Bus 14 Off	/bus/14/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
BusFaderMute Bus 14 On	/bus/14/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
BusFaderMute Bus 15 Off	/bus/15/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
BusFaderMute Bus 15 On	/bus/15/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
BusFaderMute Bus 16 Off	/bus/16/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
BusFaderMute Bus 16 On	/bus/16/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
BusFaderMute Bus 2 Off	/bus/02/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
BusFaderMute Bus 2 On	/bus/02/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
BusFaderMute Bus 3 Off	/bus/03/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
BusFaderMute Bus 3 On	/bus/03/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
BusFaderMute Bus 4 Off	/bus/04/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
BusFaderMute Bus 4 On	/bus/04/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
BusFaderMute Bus 5 Off	/bus/05/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
BusFaderMute Bus 5 On	/bus/05/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
BusFaderMute Bus 6 Off	/bus/06/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
BusFaderMute Bus 6 On	/bus/06/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
BusFaderMute Bus 7 Off	/bus/07/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
BusFaderMute Bus 7 On	/bus/07/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
BusFaderMute Bus 8 Off	/bus/08/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
BusFaderMute Bus 8 On	/bus/08/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
BusFaderMute Bus 9 Off	/bus/09/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01

[illegible]

Global Scripter Module Communication Sheet

ChannelFaderLevel Channel 30 100	/ch/30/mix/fader\x00\x00\x00\x00,f\x00\x00?\x80\x00\x00
ChannelFaderLevel Channel 31 0	/ch/31/mix/fader\x00\x00\x00\x00,f\x00\x00\x00\x00\x00\x00
ChannelFaderLevel Channel 31 100	/ch/31/mix/fader\x00\x00\x00\x00,f\x00\x00?\x80\x00\x00
ChannelFaderLevel Channel 32 0	/ch/32/mix/fader\x00\x00\x00\x00,f\x00\x00\x00\x00\x00\x00
ChannelFaderLevel Channel 32 100	/ch/32/mix/fader\x00\x00\x00\x00,f\x00\x00?\x80\x00\x00
ChannelFaderLevel Channel 4 0	/ch/04/mix/fader\x00\x00\x00\x00,f\x00\x00\x00\x00\x00\x00
ChannelFaderLevel Channel 4 100	/ch/04/mix/fader\x00\x00\x00\x00,f\x00\x00?\x80\x00\x00
ChannelFaderLevel Channel 5 0	/ch/05/mix/fader\x00\x00\x00\x00,f\x00\x00\x00\x00\x00\x00
ChannelFaderLevel Channel 5 100	/ch/05/mix/fader\x00\x00\x00\x00,f\x00\x00?\x80\x00\x00
ChannelFaderLevel Channel 6 0	/ch/06/mix/fader\x00\x00\x00\x00,f\x00\x00\x00\x00\x00\x00
ChannelFaderLevel Channel 6 100	/ch/06/mix/fader\x00\x00\x00\x00,f\x00\x00?\x80\x00\x00
ChannelFaderLevel Channel 7 0	/ch/07/mix/fader\x00\x00\x00\x00,f\x00\x00\x00\x00\x00\x00
ChannelFaderLevel Channel 7 100	/ch/07/mix/fader\x00\x00\x00\x00,f\x00\x00?\x80\x00\x00
ChannelFaderLevel Channel 8 0	/ch/08/mix/fader\x00\x00\x00\x00,f\x00\x00\x00\x00\x00\x00
ChannelFaderLevel Channel 8 100	/ch/08/mix/fader\x00\x00\x00\x00,f\x00\x00?\x80\x00\x00
ChannelFaderLevel Channel 9 0	/ch/09/mix/fader\x00\x00\x00\x00,f\x00\x00\x00\x00\x00\x00
ChannelFaderLevel Channel 9 100	/ch/09/mix/fader\x00\x00\x00\x00,f\x00\x00?\x80\x00\x00
ChannelFaderMute Channel 1 Off	/ch/01/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
ChannelFaderMute Channel 1 On	/ch/01/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
ChannelFaderMute Channel 10 Off	/ch/10/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
ChannelFaderMute Channel 10 On	/ch/10/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
ChannelFaderMute Channel 11 Off	/ch/11/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
ChannelFaderMute Channel 11 On	/ch/11/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
ChannelFaderMute Channel 12 Off	/ch/12/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
ChannelFaderMute Channel 12 On	/ch/12/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
ChannelFaderMute Channel 13 Off	/ch/13/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
ChannelFaderMute Channel 13 On	/ch/13/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
ChannelFaderMute Channel 14 Off	/ch/14/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
ChannelFaderMute Channel 14 On	/ch/14/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
ChannelFaderMute Channel 15 Off	/ch/15/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
ChannelFaderMute Channel 15 On	/ch/15/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
ChannelFaderMute Channel 16 Off	/ch/16/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
ChannelFaderMute Channel 16 On	/ch/16/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
ChannelFaderMute Channel 17 Off	/ch/17/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
ChannelFaderMute Channel 17 On	/ch/17/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
ChannelFaderMute Channel 18 Off	/ch/18/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
ChannelFaderMute Channel 18 On	/ch/18/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
ChannelFaderMute Channel 19 Off	/ch/19/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
ChannelFaderMute Channel 19 On	/ch/19/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
ChannelFaderMute Channel 2 Off	/ch/02/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
ChannelFaderMute Channel 2 On	/ch/02/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
ChannelFaderMute Channel 20 Off	/ch/20/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
ChannelFaderMute Channel 20 On	/ch/20/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
ChannelFaderMute Channel 21 Off	/ch/21/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
ChannelFaderMute Channel 21 On	/ch/21/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
ChannelFaderMute Channel 22 Off	/ch/22/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
ChannelFaderMute Channel 22 On	/ch/22/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
ChannelFaderMute Channel 23 Off	/ch/23/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01

Global Scripter Module Communication Sheet

ChannelFaderMute Channel 23 On	/ch/23/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00
ChannelFaderMute Channel 24 Off	/ch/24/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x01
ChannelFaderMute Channel 24 On	/ch/24/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00
ChannelFaderMute Channel 25 Off	/ch/25/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x01
ChannelFaderMute Channel 25 On	/ch/25/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00
ChannelFaderMute Channel 26 Off	/ch/26/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x01
ChannelFaderMute Channel 26 On	/ch/26/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00
ChannelFaderMute Channel 27 Off	/ch/27/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x01
ChannelFaderMute Channel 27 On	/ch/27/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00
ChannelFaderMute Channel 28 Off	/ch/28/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x01
ChannelFaderMute Channel 28 On	/ch/28/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00
ChannelFaderMute Channel 29 Off	/ch/29/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x01
ChannelFaderMute Channel 29 On	/ch/29/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00
ChannelFaderMute Channel 3 Off	/ch/03/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x01
ChannelFaderMute Channel 3 On	/ch/03/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00
ChannelFaderMute Channel 30 Off	/ch/30/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x01
ChannelFaderMute Channel 30 On	/ch/30/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00
ChannelFaderMute Channel 31 Off	/ch/31/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x01
ChannelFaderMute Channel 31 On	/ch/31/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00
ChannelFaderMute Channel 32 Off	/ch/32/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x01
ChannelFaderMute Channel 32 On	/ch/32/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00
ChannelFaderMute Channel 4 Off	/ch/04/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x01
ChannelFaderMute Channel 4 On	/ch/04/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00
ChannelFaderMute Channel 5 Off	/ch/05/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x01
ChannelFaderMute Channel 5 On	/ch/05/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00
ChannelFaderMute Channel 6 Off	/ch/06/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x01
ChannelFaderMute Channel 6 On	/ch/06/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00
ChannelFaderMute Channel 7 Off	/ch/07/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x01
ChannelFaderMute Channel 7 On	/ch/07/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00
ChannelFaderMute Channel 8 Off	/ch/08/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x01
ChannelFaderMute Channel 8 On	/ch/08/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00
ChannelFaderMute Channel 9 Off	/ch/09/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x01
ChannelFaderMute Channel 9 On	/ch/09/mix/on\x00\x00\x00,i\x00\x00\x00\x00\x00
DCAFaderLevel DCA 1 0	/dca/1/fader\x00\x00\x00\x00,f\x00\x00\x00\x00\x00
DCAFaderLevel DCA 1 100	/dca/1/fader\x00\x00\x00\x00,f\x00\x00?\x80\x00\x00
DCAFaderLevel DCA 2 0	/dca/2/fader\x00\x00\x00\x00,f\x00\x00\x00\x00\x00
DCAFaderLevel DCA 2 100	/dca/2/fader\x00\x00\x00\x00,f\x00\x00?\x80\x00\x00
DCAFaderLevel DCA 3 0	/dca/3/fader\x00\x00\x00\x00,f\x00\x00\x00\x00\x00
DCAFaderLevel DCA 3 100	/dca/3/fader\x00\x00\x00\x00,f\x00\x00?\x80\x00\x00
DCAFaderLevel DCA 4 0	/dca/4/fader\x00\x00\x00\x00,f\x00\x00\x00\x00\x00
DCAFaderLevel DCA 4 100	/dca/4/fader\x00\x00\x00\x00,f\x00\x00?\x80\x00\x00
DCAFaderLevel DCA 5 0	/dca/5/fader\x00\x00\x00\x00,f\x00\x00\x00\x00\x00
DCAFaderLevel DCA 5 100	/dca/5/fader\x00\x00\x00\x00,f\x00\x00?\x80\x00\x00
DCAFaderLevel DCA 6 0	/dca/6/fader\x00\x00\x00\x00,f\x00\x00\x00\x00\x00
DCAFaderLevel DCA 6 100	/dca/6/fader\x00\x00\x00\x00,f\x00\x00?\x80\x00\x00
DCAFaderLevel DCA 7 0	/dca/7/fader\x00\x00\x00\x00,f\x00\x00\x00\x00\x00
DCAFaderLevel DCA 7 100	/dca/7/fader\x00\x00\x00\x00,f\x00\x00?\x80\x00\x00
DCAFaderLevel DCA 8 0	/dca/8/fader\x00\x00\x00\x00,f\x00\x00\x00\x00\x00

Global Scripter Module Communication Sheet

DCAFaderLevel DCA 8 100	/dca/8/fader\x00\x00\x00\x00,f\x00\x00?\x80\x00\x00
DCAFaderMute DCA 1 Off	/dca/1/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
DCAFaderMute DCA 1 On	/dca/1/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
DCAFaderMute DCA 2 Off	/dca/2/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
DCAFaderMute DCA 2 On	/dca/2/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
DCAFaderMute DCA 3 Off	/dca/3/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
DCAFaderMute DCA 3 On	/dca/3/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
DCAFaderMute DCA 4 Off	/dca/4/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
DCAFaderMute DCA 4 On	/dca/4/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
DCAFaderMute DCA 5 Off	/dca/5/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
DCAFaderMute DCA 5 On	/dca/5/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
DCAFaderMute DCA 6 Off	/dca/6/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
DCAFaderMute DCA 6 On	/dca/6/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
DCAFaderMute DCA 7 Off	/dca/7/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
DCAFaderMute DCA 7 On	/dca/7/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
DCAFaderMute DCA 8 Off	/dca/8/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
DCAFaderMute DCA 8 On	/dca/8/on\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
FXReturnFaderLevel FX Return 1 0	/fxrtn/01/mix/fader\x00,f\x00\x00\x00\x00\x00\x00
FXReturnFaderLevel FX Return 1 100	/fxrtn/01/mix/fader\x00,f\x00\x00?\x80\x00\x00
FXReturnFaderLevel FX Return 2 0	/fxrtn/02/mix/fader\x00,f\x00\x00\x00\x00\x00\x00
FXReturnFaderLevel FX Return 2 100	/fxrtn/02/mix/fader\x00,f\x00\x00?\x80\x00\x00
FXReturnFaderLevel FX Return 3 0	/fxrtn/03/mix/fader\x00,f\x00\x00\x00\x00\x00\x00
FXReturnFaderLevel FX Return 3 100	/fxrtn/03/mix/fader\x00,f\x00\x00?\x80\x00\x00
FXReturnFaderLevel FX Return 4 0	/fxrtn/04/mix/fader\x00,f\x00\x00\x00\x00\x00\x00
FXReturnFaderLevel FX Return 4 100	/fxrtn/04/mix/fader\x00,f\x00\x00?\x80\x00\x00
FXReturnFaderLevel FX Return 5 0	/fxrtn/05/mix/fader\x00,f\x00\x00\x00\x00\x00\x00
FXReturnFaderLevel FX Return 5 100	/fxrtn/05/mix/fader\x00,f\x00\x00?\x80\x00\x00
FXReturnFaderLevel FX Return 6 0	/fxrtn/06/mix/fader\x00,f\x00\x00\x00\x00\x00\x00
FXReturnFaderLevel FX Return 6 100	/fxrtn/06/mix/fader\x00,f\x00\x00?\x80\x00\x00
FXReturnFaderLevel FX Return 7 0	/fxrtn/07/mix/fader\x00,f\x00\x00\x00\x00\x00\x00
FXReturnFaderLevel FX Return 7 100	/fxrtn/07/mix/fader\x00,f\x00\x00?\x80\x00\x00
FXReturnFaderLevel FX Return 8 0	/fxrtn/08/mix/fader\x00,f\x00\x00\x00\x00\x00\x00
FXReturnFaderLevel FX Return 8 100	/fxrtn/08/mix/fader\x00,f\x00\x00?\x80\x00\x00
FXReturnFaderMute FX Return 1 Off	/fxrtn/01/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
FXReturnFaderMute FX Return 1 On	/fxrtn/01/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
FXReturnFaderMute FX Return 2 Off	/fxrtn/02/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
FXReturnFaderMute FX Return 2 On	/fxrtn/02/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
FXReturnFaderMute FX Return 3 Off	/fxrtn/03/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
FXReturnFaderMute FX Return 3 On	/fxrtn/03/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
FXReturnFaderMute FX Return 4 Off	/fxrtn/04/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
FXReturnFaderMute FX Return 4 On	/fxrtn/04/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
FXReturnFaderMute FX Return 5 Off	/fxrtn/05/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
FXReturnFaderMute FX Return 5 On	/fxrtn/05/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
FXReturnFaderMute FX Return 6 Off	/fxrtn/06/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
FXReturnFaderMute FX Return 6 On	/fxrtn/06/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
FXReturnFaderMute FX Return 7 Off	/fxrtn/07/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x01
FXReturnFaderMute FX Return 7 On	/fxrtn/07/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x00
FXReturnFaderMute FX Return 8 Off	/fxrtn/08/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00\x01

Global Scripter Module Communication Sheet

FXReturnFaderMute FX Return 8 On	/fxrtn/08/mix/on\x00\x00\x00\x00,i\x00\x00\x00\x00\x00
GroupMute Group 1 Off	/config/mute/1\x00\x00,s\x00\x00OFF\x00
GroupMute Group 1 On	/config/mute/1\x00\x00,s\x00\x00ON\x00\x00
GroupMute Group 2 Off	/config/mute/2\x00\x00,s\x00\x00OFF\x00
GroupMute Group 2 On	/config/mute/2\x00\x00,s\x00\x00ON\x00\x00
GroupMute Group 3 Off	/config/mute/3\x00\x00,s\x00\x00OFF\x00
GroupMute Group 3 On	/config/mute/3\x00\x00,s\x00\x00ON\x00\x00
GroupMute Group 4 Off	/config/mute/4\x00\x00,s\x00\x00OFF\x00
GroupMute Group 4 On	/config/mute/4\x00\x00,s\x00\x00ON\x00\x00
GroupMute Group 5 Off	/config/mute/5\x00\x00,s\x00\x00OFF\x00
GroupMute Group 5 On	/config/mute/5\x00\x00,s\x00\x00ON\x00\x00
GroupMute Group 6 Off	/config/mute/6\x00\x00,s\x00\x00OFF\x00
GroupMute Group 6 On	/config/mute/6\x00\x00,s\x00\x00ON\x00\x00
MainFaderLevel Type Mono 0	/main/m/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00
MainFaderLevel Type Mono 100	/main/m/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
MainFaderLevel Type Stereo 0	/main/st/mix/fader\x00\x00,f\x00\x00\x00\x00\x00
MainFaderLevel Type Stereo 100	/main/st/mix/fader\x00\x00,f\x00\x00?\x80\x00\x00
MainFaderMute Type Mono Off	/main/m/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
MainFaderMute Type Mono On	/main/m/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
MainFaderMute Type Stereo Off	/main/st/mix/on\x00,i\x00\x00\x00\x00\x00\x01
MainFaderMute Type Stereo On	/main/st/mix/on\x00,i\x00\x00\x00\x00\x00\x00
MatrixFaderLevel Matrix 1 0	/mtx/01/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00
MatrixFaderLevel Matrix 1 100	/mtx/01/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
MatrixFaderLevel Matrix 2 0	/mtx/02/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00
MatrixFaderLevel Matrix 2 100	/mtx/02/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
MatrixFaderLevel Matrix 3 0	/mtx/03/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00
MatrixFaderLevel Matrix 3 100	/mtx/03/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
MatrixFaderLevel Matrix 4 0	/mtx/04/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00
MatrixFaderLevel Matrix 4 100	/mtx/04/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
MatrixFaderLevel Matrix 5 0	/mtx/05/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00
MatrixFaderLevel Matrix 5 100	/mtx/05/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
MatrixFaderLevel Matrix 6 0	/mtx/06/mix/fader\x00\x00\x00,f\x00\x00\x00\x00\x00
MatrixFaderLevel Matrix 6 100	/mtx/06/mix/fader\x00\x00\x00,f\x00\x00?\x80\x00\x00
MatrixFaderMute Matrix 1 Off	/mtx/01/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
MatrixFaderMute Matrix 1 On	/mtx/01/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
MatrixFaderMute Matrix 2 Off	/mtx/02/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
MatrixFaderMute Matrix 2 On	/mtx/02/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
MatrixFaderMute Matrix 3 Off	/mtx/03/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
MatrixFaderMute Matrix 3 On	/mtx/03/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
MatrixFaderMute Matrix 4 Off	/mtx/04/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
MatrixFaderMute Matrix 4 On	/mtx/04/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
MatrixFaderMute Matrix 5 Off	/mtx/05/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
MatrixFaderMute Matrix 5 On	/mtx/05/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00
MatrixFaderMute Matrix 6 Off	/mtx/06/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x01
MatrixFaderMute Matrix 6 On	/mtx/06/mix/on\x00\x00,i\x00\x00\x00\x00\x00\x00

Appendix B. Query Commands

AuxinFaderLevel Auxin 1	/auxin/01/mix/fader\x00
AuxinFaderLevel Auxin 2	/auxin/02/mix/fader\x00
AuxinFaderLevel Auxin 3	/auxin/03/mix/fader\x00
AuxinFaderLevel Auxin 4	/auxin/04/mix/fader\x00
AuxinFaderLevel Auxin 5	/auxin/05/mix/fader\x00
AuxinFaderLevel Auxin 6	/auxin/06/mix/fader\x00
AuxinFaderLevel Auxin 7	/auxin/07/mix/fader\x00
AuxinFaderLevel Auxin 8	/auxin/08/mix/fader\x00
AuxinFaderMute Auxin 1	/auxin/01/mix/\x00\x00
AuxinFaderMute Auxin 2	/auxin/02/mix/\x00\x00
AuxinFaderMute Auxin 3	/auxin/03/mix/\x00\x00
AuxinFaderMute Auxin 4	/auxin/04/mix/\x00\x00
AuxinFaderMute Auxin 5	/auxin/05/mix/\x00\x00
AuxinFaderMute Auxin 6	/auxin/06/mix/\x00\x00
AuxinFaderMute Auxin 7	/auxin/07/mix/\x00\x00
AuxinFaderMute Auxin 8	/auxin/08/mix/\x00\x00
BusFaderLevel Bus 1	/bus/01/mix/fader\x00\x00\x00
BusFaderLevel Bus 10	/bus/10/mix/fader\x00\x00\x00
BusFaderLevel Bus 11	/bus/11/mix/fader\x00\x00\x00
BusFaderLevel Bus 12	/bus/12/mix/fader\x00\x00\x00
BusFaderLevel Bus 13	/bus/13/mix/fader\x00\x00\x00
BusFaderLevel Bus 14	/bus/14/mix/fader\x00\x00\x00
BusFaderLevel Bus 15	/bus/15/mix/fader\x00\x00\x00
BusFaderLevel Bus 16	/bus/16/mix/fader\x00\x00\x00
BusFaderLevel Bus 2	/bus/02/mix/fader\x00\x00\x00
BusFaderLevel Bus 3	/bus/03/mix/fader\x00\x00\x00
BusFaderLevel Bus 4	/bus/04/mix/fader\x00\x00\x00
BusFaderLevel Bus 5	/bus/05/mix/fader\x00\x00\x00
BusFaderLevel Bus 6	/bus/06/mix/fader\x00\x00\x00
BusFaderLevel Bus 7	/bus/07/mix/fader\x00\x00\x00
BusFaderLevel Bus 8	/bus/08/mix/fader\x00\x00\x00
BusFaderLevel Bus 9	/bus/09/mix/fader\x00\x00\x00
BusFaderMute Bus 1	/bus/01/mix/\x00\x00\x00\x00
BusFaderMute Bus 10	/bus/10/mix/\x00\x00\x00\x00
BusFaderMute Bus 11	/bus/11/mix/\x00\x00\x00\x00
BusFaderMute Bus 12	/bus/12/mix/\x00\x00\x00\x00
BusFaderMute Bus 13	/bus/13/mix/\x00\x00\x00\x00
BusFaderMute Bus 14	/bus/14/mix/\x00\x00\x00\x00
BusFaderMute Bus 15	/bus/15/mix/\x00\x00\x00\x00
BusFaderMute Bus 16	/bus/16/mix/\x00\x00\x00\x00
BusFaderMute Bus 2	/bus/02/mix/\x00\x00\x00\x00
BusFaderMute Bus 3	/bus/03/mix/\x00\x00\x00\x00
BusFaderMute Bus 4	/bus/04/mix/\x00\x00\x00\x00
BusFaderMute Bus 5	/bus/05/mix/\x00\x00\x00\x00
BusFaderMute Bus 6	/bus/06/mix/\x00\x00\x00\x00
BusFaderMute Bus 7	/bus/07/mix/\x00\x00\x00\x00
BusFaderMute Bus 8	/bus/08/mix/\x00\x00\x00\x00

BusFaderMute Bus 9	/bus/09/mix/\x00\x00\x00\x00
ChannelFaderLevel Channel 1	/ch/01/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 10	/ch/10/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 11	/ch/11/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 12	/ch/12/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 13	/ch/13/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 14	/ch/14/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 15	/ch/15/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 16	/ch/16/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 17	/ch/17/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 18	/ch/18/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 19	/ch/19/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 2	/ch/02/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 20	/ch/20/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 21	/ch/21/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 22	/ch/22/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 23	/ch/23/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 24	/ch/24/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 25	/ch/25/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 26	/ch/26/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 27	/ch/27/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 28	/ch/28/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 29	/ch/29/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 3	/ch/03/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 30	/ch/30/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 31	/ch/31/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 32	/ch/32/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 4	/ch/04/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 5	/ch/05/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 6	/ch/06/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 7	/ch/07/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 8	/ch/08/mix/fader\x00\x00\x00\x00
ChannelFaderLevel Channel 9	/ch/09/mix/fader\x00\x00\x00\x00
ChannelFaderMute Channel 1	/ch/01/mix/\x00
ChannelFaderMute Channel 10	/ch/10/mix/\x00
ChannelFaderMute Channel 11	/ch/11/mix/\x00
ChannelFaderMute Channel 12	/ch/12/mix/\x00
ChannelFaderMute Channel 13	/ch/13/mix/\x00
ChannelFaderMute Channel 14	/ch/14/mix/\x00
ChannelFaderMute Channel 15	/ch/15/mix/\x00
ChannelFaderMute Channel 16	/ch/16/mix/\x00
ChannelFaderMute Channel 17	/ch/17/mix/\x00
ChannelFaderMute Channel 18	/ch/18/mix/\x00
ChannelFaderMute Channel 19	/ch/19/mix/\x00
ChannelFaderMute Channel 2	/ch/02/mix/\x00
ChannelFaderMute Channel 20	/ch/20/mix/\x00
ChannelFaderMute Channel 21	/ch/21/mix/\x00
ChannelFaderMute Channel 22	/ch/22/mix/\x00

ChannelFaderMute Channel 23	/ch/23/mix/\x00
ChannelFaderMute Channel 24	/ch/24/mix/\x00
ChannelFaderMute Channel 25	/ch/25/mix/\x00
ChannelFaderMute Channel 26	/ch/26/mix/\x00
ChannelFaderMute Channel 27	/ch/27/mix/\x00
ChannelFaderMute Channel 28	/ch/28/mix/\x00
ChannelFaderMute Channel 29	/ch/29/mix/\x00
ChannelFaderMute Channel 3	/ch/03/mix/\x00
ChannelFaderMute Channel 30	/ch/30/mix/\x00
ChannelFaderMute Channel 31	/ch/31/mix/\x00
ChannelFaderMute Channel 32	/ch/32/mix/\x00
ChannelFaderMute Channel 4	/ch/04/mix/\x00
ChannelFaderMute Channel 5	/ch/05/mix/\x00
ChannelFaderMute Channel 6	/ch/06/mix/\x00
ChannelFaderMute Channel 7	/ch/07/mix/\x00
ChannelFaderMute Channel 8	/ch/08/mix/\x00
ChannelFaderMute Channel 9	/ch/09/mix/\x00
DCAFaderLevel DCA 1	/dca/1/fader\x00\x00\x00\x00
DCAFaderLevel DCA 2	/dca/2/fader\x00\x00\x00\x00
DCAFaderLevel DCA 3	/dca/3/fader\x00\x00\x00\x00
DCAFaderLevel DCA 4	/dca/4/fader\x00\x00\x00\x00
DCAFaderLevel DCA 5	/dca/5/fader\x00\x00\x00\x00
DCAFaderLevel DCA 6	/dca/6/fader\x00\x00\x00\x00
DCAFaderLevel DCA 7	/dca/7/fader\x00\x00\x00\x00
DCAFaderLevel DCA 8	/dca/8/fader\x00\x00\x00\x00
DCAFaderMute DCA 1	/dca/1/on/\x00\x00
DCAFaderMute DCA 2	/dca/2/on/\x00\x00
DCAFaderMute DCA 3	/dca/3/on/\x00\x00
DCAFaderMute DCA 4	/dca/4/on/\x00\x00
DCAFaderMute DCA 5	/dca/5/on/\x00\x00
DCAFaderMute DCA 6	/dca/6/on/\x00\x00
DCAFaderMute DCA 7	/dca/7/on/\x00\x00
DCAFaderMute DCA 8	/dca/8/on/\x00\x00
FXReturnFaderLevel FX Return 1	/fxrtn/01/mix/fader\x00
FXReturnFaderLevel FX Return 2	/fxrtn/02/mix/fader\x00
FXReturnFaderLevel FX Return 3	/fxrtn/03/mix/fader\x00
FXReturnFaderLevel FX Return 4	/fxrtn/04/mix/fader\x00
FXReturnFaderLevel FX Return 5	/fxrtn/05/mix/fader\x00
FXReturnFaderLevel FX Return 6	/fxrtn/06/mix/fader\x00
FXReturnFaderLevel FX Return 7	/fxrtn/07/mix/fader\x00
FXReturnFaderLevel FX Return 8	/fxrtn/08/mix/fader\x00
FXReturnFaderMute FX Return 1	/fxrtn/01/mix/\x00\x00
FXReturnFaderMute FX Return 2	/fxrtn/02/mix/\x00\x00
FXReturnFaderMute FX Return 3	/fxrtn/03/mix/\x00\x00
FXReturnFaderMute FX Return 4	/fxrtn/04/mix/\x00\x00
FXReturnFaderMute FX Return 5	/fxrtn/05/mix/\x00\x00
FXReturnFaderMute FX Return 6	/fxrtn/06/mix/\x00\x00
FXReturnFaderMute FX Return 7	/fxrtn/07/mix/\x00\x00

FXReturnFaderMute FX Return 8	/fxrtn/08/mix/\x00\x00
GroupMute Group 1	/config/mute/1\x00\x00
GroupMute Group 2	/config/mute/2\x00\x00
GroupMute Group 3	/config/mute/3\x00\x00
GroupMute Group 4	/config/mute/4\x00\x00
GroupMute Group 5	/config/mute/5\x00\x00
GroupMute Group 6	/config/mute/6\x00\x00
MainFaderLevel Type Mono	/main/m/mix/fader\x00\x00\x00
MainFaderLevel Type Stereo	/main/st/mix/fader\x00\x00
MainFaderMute Type Mono	/main/m/mix/\x00\x00\x00\x00
MainFaderMute Type Stereo	/main/st/mix/\x00\x00\x00
MatrixFaderLevel Matrix 1	/mtx/01/mix/fader\x00\x00\x00
MatrixFaderLevel Matrix 2	/mtx/02/mix/fader\x00\x00\x00
MatrixFaderLevel Matrix 3	/mtx/03/mix/fader\x00\x00\x00
MatrixFaderLevel Matrix 4	/mtx/04/mix/fader\x00\x00\x00
MatrixFaderLevel Matrix 5	/mtx/05/mix/fader\x00\x00\x00
MatrixFaderLevel Matrix 6	/mtx/06/mix/fader\x00\x00\x00
MatrixFaderMute Matrix 1	/mtx/01/mix/\x00\x00\x00\x00
MatrixFaderMute Matrix 2	/mtx/02/mix/\x00\x00\x00\x00
MatrixFaderMute Matrix 3	/mtx/03/mix/\x00\x00\x00\x00
MatrixFaderMute Matrix 4	/mtx/04/mix/\x00\x00\x00\x00
MatrixFaderMute Matrix 5	/mtx/05/mix/\x00\x00\x00\x00
MatrixFaderMute Matrix 6	/mtx/06/mix/\x00\x00\x00\x00