POUNCer quick reference · the PC window

Windows / macOS

Click

a spot	QSY + the call into N1MM's Entry Window (the station keeps its place 60 s)
a band chip	list that band (▶); click again or change band = follow the radio
✓ **READY badge**	the pre-contest checks: ✓ good · ⚠ look at it · ✗ not working
the address (top bar)	QR code for the phone, one per address (LAN, ZeroTier)
Radio A / B badge	switch the radio that clicks and F-keys go to (SO2R / SO2V)
SLAVE badge	become the team master (asks first)
Update light	check GitHub now; blue = new version ready → Restart
a column heading	sort by it (▼ / ▲)

Keys

↑ ↓ Space	select a spot (yellow frame) · Space = tap it
Ctrl+M	compact window beside N1MM (the arrow = back)
Ctrl+T	spot list as tiles (like the phone)
Ctrl+Z	ZO mode: three columns ⚡ Urgent / Medium / Normal
Ctrl+H	hide worked stations
Ctrl+L	clear spots (CLR ALL); the phone's Undo brings them back
Ctrl+,	Settings (Ctrl+F search · Ctrl+S save · Esc clears the search / closes)
Ctrl+Shift+D	traffic console: raw lines of every source

Shortcuts do nothing while you type in a box.

Lights

green	working: this stream delivers
yellow	on hold: ready, not needed now (RBN on SSB ...)
amber	waiting, connecting, partly working · HamFiles: one file missing
red	not working · HamFiles NOK: cty.dat and MASTER.DTA both missing
grey	switched off (the clean layout hides these)
blue	Update: a new version is downloaded

RBN · N1MM · Log · Team · Phone · Cluster · HTTP · N1MM spots · Warm-up · HamFiles · Update - then the **Radio A/B** badge.

Top bar badges

✓ **READY** / ⚠ **CHECK** / ✗ **NOT READY**	all good / look at something / something needed is down
MASTER · SLAVE	team: holds RBN and feeds the others · gets spots from the master
ALONE · TEAM OFF	no other POUNCer found · team switched off
orange team badge	a team POUNCer runs another version (hover: IP + version)
CLR BAND · CLR ALL	forget the spots of this band / of every band

A spot (list or tile)

K1ABC	red bold call = new multiplier on this band; **M** single, **MM** double (tile: pink bar, thin / thick)
K1ABC	grey = already worked on this band and mode
warm row / yellow call	DX: another continent
⚡	historical opportunity: rarely runs, or few hours in past logs of this contest
R84% ~23h	ran 84 % of its QSOs, ~23 h on the air (its past logs); * = reconstructed
?	not in Super Check Partial: maybe a busted call
↻3m×2	you tapped it 3 min ago, twice
★ TK0C-1	your own skimmer heard it
blue frame	the radio is on this frequency (0.5 kHz)
green tile · dark tile	20 dB or more · not re-spotted lately, probably gone
cq3m · 1200Z · 22dB	calling 3 min · first heard (UTC) · skimmer SNR

Band chips

20m: 34 DX 85%	34 DX stations heard by your continent's skimmers in 10 min, 85 % of all; 5+ DX = open
· 6 mults	6 spots there would be new multipliers
80m: EU only · 160m: –	only your own continent · nothing heard
colour	orange (own continent) → yellow → green (DX) · grey = nothing
thin / thick ▶ frame	the radio's band / the band listed

ZO mode (View › ZO mode, Ctrl+Z)

⚡ **Urgent**	historical hint: catch it now
Medium · Normal	the rest by the same history; unknown history below Normal

Hints from past logs, not a prediction of who leaves the band.

Menus

File	config folder, Autostart ▸, Windows Firewall, restart, exit
N1MM	reconnect log, also enter callsign, station test
View	compact, always on top, detailed layout, tiles, ZO mode, rate line, look ▸
Spots / Spotters / Spotted	sources on / off · whose spots (skimmers) · which DX
Tools	summary, CQ zones, timeline, phone page ▸ (QR), alerts ▸, traffic console
Team	password, become master, master after restart, update all
Settings	All settings... or straight to a page: Display, Alerts & history, N1MM & radios, Phone page, Spots, Cluster server, Startup & updates
Help	Versions ▸ (check for a new version, go back), Troubleshooting ▸

Something wrong?

Help › Troubleshooting	Save diagnostics: one zip (log, settings without passwords, perf log, team settings) - send it
N1MM › Station test	QSY and callsign entry, per radio
cache\pouncer.log	what POUNCer did · cache\perf.csv: CPU / memory per minute

First time

Open	scan the QR code (PC: Tools › Phone page › QR code…), same Wi-Fi or ZeroTier
Look only (dimmed keys)	a phone starts look-only: tap the frequency → band menu → **Control N1MM**
on for all phones	the PC (team: the master) set Phones may control N1MM = all
Reset	acts oddly in one browser only: **?** › **Reset this page**

Tap and hold

tap a tile	QSY + call into N1MM (yellow ring: keeps its place until logged, or 60 s)
hold a tile 2 s	Remove (off the list) · Debug (why it looks like this)
tap the frequency / title	band menu: pick a band, several bands, ALL bands, alerts on / off
hold SNR 1.3 s	set the minimum SNR (≥10 shown under SNR)
hold ENTER 1.3 s	CW keyboard: type = sent as you type · DONE ⏎ · STOP (Esc)
tap ping 23ms	min / avg / max of the last 10 min (green < 150 ms, amber < 500)

Keys

A / B	which radio this phone works (blue A, orange B)
CLR	clear all spots; Undo for 5 s
Time · Freq · SNR	sort (green = active)
DX · MLT · ⚡	put DX / new mults / rare CQs on top
F-keys · ENTER	N1MM's keys: they **transmit** · ENTER logs
SPOTit	N1MM's Spot It (Alt+P), no TX
WPM − / +	CW speed (PgDn / PgUp)
−25 Hz / +25 Hz	move the VFO, no TX
NEXT ▶	the next station: QSY + call, no TX
↻ Log	re-read which log N1MM has open

CQ zones page

blue box (hears me)	skimmers in that zone spotted you on that band; number = best SNR
green box (I hear)	your continent's skimmers heard stations from that zone
brighter · dark	stronger (3 → 30 dB) · nothing in the time chosen (15 min)
yellow column	your own CQ zone

Band opening timeline

a row · a box	one band (160 m on top) · 10 min, or 1 hour, UTC left to right
orange → green	only your continent → mostly DX; brighter = more spots
dark · yellow frame	nothing heard · now

A tile

green / grey	20 dB or more / weaker
yellow call	DX (another continent); white = your continent
pink stripe	new multiplier: thin single, thick double
light blue outline	your radio is on this frequency
darker tile	not re-spotted for 5 min, probably gone
⚡ · ? · ↻3m	rare CQ · not in SCP · you tapped it 3 min ago
R6% ~4h	run share and hours in this contest's past logs
1132Z · 22dB · cq3m	first heard · SNR · calling 3 min

After a tap

✓ radio on 7012.0 · call in	done: N1MM moved and the call is in
waiting for N1MM…	N1MM slow to confirm; QSY sent again, watching 8 s
⚠ never reported	no confirmation in 10 s: look at the radio
⚠ no answer from POUNCer	no answer in 8 s: is POUNCer running?

Status line

(+12 weak)	hidden by the minimum SNR
calm	tiles keep their place, re-sorted every 15 s
⚠ cty (or another)	a pre-contest check found something - tap it
20m list · ALL bands list	you picked a band / all bands - tap to follow the radio
⚠ backup skimmers	main skimmer quiet: others on your continent used

Band menu (tap the frequency)

dot by a band	band open light: orange (own continent) → green (DX), DX count when open
pink 6M	6 spots there would be new multipliers
Select multiple bands	then Show selected bands: their spots on one list
ALL bands	every band on one list, for hunting mults (MLT puts them on top)
Control N1MM	this phone may tune and send keys (off = look only)
Alerts	pop-up and sound for a rare CQ that is a new mult, each on its own