```
def to_8bit(num):
    return format(num & 0xFF, '08b')


def binary_subtraction(a, b):
    binary_a = to_8bit(a)
    binary_b = to_8bit(b)

    # Perform subtraction using 2's complement
    result = (a - b) & 0xFF

    # Convert unsigned result to signed decimal
    if result >= 128:
        decimal_result = result - 256
    else:
        decimal_result = result

    # Check arithmetic overflow
    overflow = (a >= 0 and b < 0 and decimal_result < 0) or \
               (a < 0 and b >= 0 and decimal_result >= 0)

    print("Operand A:", binary_a)
    print("Operand B:", binary_b)
    print("Binary Result:", to_8bit(result))
    print("Decimal Result:", decimal_result)

    if overflow:
        print("Arithmetic Overflow: Yes")
    else:
        print("Arithmetic Overflow: No")


print("Expression (a): 45 - (+19)")
binary_subtraction(45, 19)

print("\nExpression (b): (-35) - (-12)")
binary_subtraction(-35, -12)


//Output//
Expression (a): 45 - (+19)
Operand A: 00101101
Operand B: 00010011
```

Binary Result: 00011010
Decimal Result: 26
Arithmetic Overflow: No

Expression (b): (-35) - (-12)
Operand A: 11011101
Operand B: 11110100
Binary Result: 11101001
Decimal Result: -23
Arithmetic Overflow: No