The decision

Bianca and I recommend building the rolling production workstation and the Wing case. The one-time cost is about $4,600 ($4,641.84).

Why this matters

Our production rig is deployed once or twice a week at different venues. We set it up and strike it under time pressure.

What we'd build

A rolling workstation case holds the video, network and control gear, with two monitors on the flip-up lid. Bay A is the active system. Bay B is storage and camera charging.

The Wing sits beside it in the ProX BXWING hydraulic flip case (the Wing case), joined by five short cables. Every field cable and those five plug into one labeled, color-coded panel on the back.

The design is decided.

What it saves

~40 → ~15	**~30 min**
loose connections become labeled cables	saved at setup, and again at teardown

Both figures are estimates, and we'll measure them. I'll time setup and teardown before the cutover and again after it.

What it costs

About $4,600, one time. This total is an estimate. Most prices are estimated, and it includes the cases and freight line below.	**$4,641.84**
Cases and freight. We're still waiting on Matt's quote.	$1,650.00
A connector plate for the Wing case, bought only if the Wing case can take it. We'll check when the case arrives. It isn't in the first order.	+$100.00

Almost all the gear inside is already owned and isn't in any total. Stage power is a separate project.

Risks

The rollout is staged, and that's decided. The owned gear moves into the cases in stages, starting from a setup closest to today's, and each stage is proved before the next.

Weather is an accepted risk, because we often set up outside with no cover. The plan for it is still open. The plan is a fitted rain cover or poly sheet and clamps in the case, with a two-minute cover-and-kill routine. I'll have it in place before the first live deploy.

Who decides

You give the final sign-off, and Bianca makes the go/no-go decision on ordering. I design and lead the build. Matt quotes the cases and freight. This approval chain is decided.

The ask

Sunny, do you approve a one-time spend of about $4,600 ($4,641.84)? Bianca will release the order once Matt's quote comes in under the ceiling she and I agree on before we meet.

The connector parts check must also clear before those parts are ordered. All open items are on page 3.

The picture DECIDED design locked, DESIGN section 1

Lids

Left screen	Right screen	Wireless camera receiver
every camera at once	ProPresenter second screen	on top of the lid when open

Desk

Switcher	Audio adapter	Two laptops
on the desk	beside it	ProPresenter + streaming

Bay A: the active system

left open
Cooling fan
Streaming encoder (Resi)
Recorder + audio switch
LED wall transcoder
Network switch + router
Cable management
Airflow + growth
Power strip (backed)
Battery backup (UPS)

Bay B: storage + charging

left open
Metered strip + charger strip
Left open
Drawer
Drawer

Back of Bay A: the connection panel

8 camera inputs	Confidence out	LED wall x2	Internet in	Network to Wing
Audio network to Wing	Talkback + in-ears	Power to Wing		

Bay A holds the active system and Bay B holds storage and charging power; colors are the cable colors, and the Wing sits beside the workstation in its own case, joined by five short cables.



The product listing photo of the workstation case, with the seller's labels.

Cable colors

- Camera / SDI: Blue
- HDMI: White
- Dante: Green
- Production net: Yellow
- Internet: Red
- LED data: Purple
- XLR + AES50: Orange
- Power: Black

Decided The second long power cord feeds the Bay B metered strip, which passes power on to a separate charging station on a quad box.

What it costs, by category

Category	Cost	Status
Cases and freight both cases, consolidated freight	$1,650.00	OPEN Placeholder until Matt's quote (G1)
Panel and connectors AVPRO panel, spares, cable ends	$473.41	ESTIMATE Connector part numbers checked before ordering (G2)
Cabling jumpers, trunks, short Wing power link	$276.10	ESTIMATE
Power rack power, two venue drops, charging quad box	$1,241.34	ESTIMATE QUAD BOX: DECIDED 2 lines firm, 1 quoted. Quad box decided; extension: details open, not costed. Listing check (G5).
Cooling and mounting fan, blanks, shelves, drawers, cable management, screws	$661.00	ESTIMATE Screw type waits on the rail check (G6)
Network Bay A Dante satellite switch, 8-port PoE	$19.99	PLACEHOLDER PoE model not priced
Monitors two lid monitors, right-angle adapters	$320.00	ESTIMATE
First order total	**$4,641.84**	
Conditional items Wing block	$100.00	CONDITIONAL Only if the Wing case can take the plate (N1). If it can't, the connections run out the side of the case, and a TRUE1-to-IEC jumper (not costed) carries the Wing power link to the Wing's IEC inlet.
All lines	**$4,741.84**	
Already owned almost all the gear inside	not in any total	

Open items

These items gate the order or change cost or scope. If an item gates the order, it must close before the first order goes in.

Item	Owner	Due	Gates the order	Status
G1 Case and freight quote: AVPRO price, BXWING price, consolidated freight for both (closed AVPRO is 51.5 × 48.2 × 31.6in). BOM placeholders: $500 / $900 / $250	Matt	2026-10-19	Yes: the order gate	OPEN
G2 One matched powerCON TRUE1 family: AVPRO chassis outlet, both umbilical cable ends, and the Wing chassis inlet (only if the Wing panel happens). Plus the etherCON pair: NE8FDP-B panel jacks with NE8MX-1 carriers (standard etherCON), checked against the Neutrik compatibility table before the BOM calls them firm	Matt / vendor; Sam checks the datasheets	2026-10-19	Yes, for the connector lines	OPEN
G5 CPS1215RM listing: confirm Amazon B00077IG3O is the CPS1215RM	Sam	2026-10-19	That line only	OPEN
G6 Rack rails and thread: tapped 10-32, or square-hole for M6 cage nuts? Both are open. Also confirm whether the AVPRO comes with rails built in or they're added after purchase. Matt may know; otherwise it's checked at delivery	Sam (ask Matt first)	on case delivery (assumed by 2026-11-15)	Screw line only. Order it after delivery if Matt doesn't know	OPEN
N1 BXWING inspection: can it take a panel-mount D-series plate? Yes → buy the Wing block. No → the connections run out the side of the case.	Sam (ask Matt first)	on case delivery (assumed by 2026-11-15)	Wing block only	OPEN WING BLOCK
N8 Camera-cable trial: Emily runs the SDI cables we already own (100ft) over a real deploy. Checks pull-through, cable and connector reliability, and picture over length. No camera control. *Whether to switch field camera cable to AOC is an open decision. AOC would let the BMD converters live in the Wing case.*	Emily (trial); Sam, with Matt (spec and cost)	No date set	No	OPEN
N15 Measure today's setup and teardown time before the cutover, and again after, to test the ~40 → ~15 connections and ~30 minutes each way estimates	Sam	2026-10-04, then at the first event after cutover	No	OPEN
N16 Weather: accepted risk. Setups are often outside with no cover. Keep a fitted rain cover or poly sheet + clamps in the case and a two-minute cover-and-kill plan. A powered open-back rack in sudden rain is the one fast path to a big loss	Sam	before the first live deploy (assumed by 2026-11-15)	No	RISK ACCEPTED PLAN: OPEN

Closed items

N19 Where is the AV charging station? Drop 2 feeds the Bay B CPPDU511, which passes power through to a separate charging station on a quad box. The quad box is in the first order. Details of the extension are open. A second wall circuit is preferred, not required.	Sam	Closed	No	DECIDED
N6 Wing talkback and IEM: Wing XLR In 8 is Bianca's talkback; Out 8 is her IEM, per the ELIM Production App.	Tyler	Closed	No	CLOSED
N13 Streaming laptop The app's "video stream laptop" and the switcher laptop are the same machine, now called the streaming laptop.	Sam	Closed	No	CLOSED
G7 Laptop power The desk laptops plug into the battery-backed CPS1215RM strip. The separate laptop strip is dropped from the BOM.	Sam	Closed	No	CLOSED

G3 and G4 closed on 2026-09-28. Every other open item is in the appendix.

Supporting detail

What goes where DECIDED design locked, DESIGN section 1

Bay A	The active system: fan, Resi, the recorder and the new 8-port PoE Dante satellite switch, the LED wall transcoder, production switch and router, cable management, reserve blanks, the UPS-backed strip and the UPS. Every network jumper stays in Bay A. Its 4U top is left open, and the Hollyland RX mounts on top of the flip-up lid.
Bay B	Storage and utility power: the metered CPPDU511 at the front (drawer lights) and the RS1215-RA at the rear (camera chargers), three U's left open, and two 4U drawers with heavier items low. No signal. Its 4U top is left open. All cabling is stored with the two cases.
Wing case	The ProX BXWING hydraulic flip case (the Wing case) holds the Wing, the owned 5-port TL-SG1005P Dante switch and the ProTools Mac. The ProTools Mac has USB-C to the Wing for recording, plus a Dante patch, and handles both the live event mix and the stream mix. The case sits beside the AVPRO, joined by five short cables.
Rear panel	Three Neutrik D-series plates on the Bay A rear rails: video, data/audio/power, and a spare row. It is the one face anyone setting up touches. Field cables land here; short jumpers run to the gear.

Rack layout with part names (front) DECIDED design locked, DESIGN section 1

LEFT lid
ATEM hardware multiview, day one. LG 24GS60F-B (model open)

RIGHT lid
ProPresenter Mac second screen. LG 24GS60F-B (model open)

ATEM TV Studio Pro 4K
over the 3in grommet (retention tray open); I/O drops into Bay A

AVIO (Dante)
XLR pigtails to ATEM Ch 1-2; PoE from the satellite switch

UltraStudio Monitor
placement open; ProPresenter USB-C > SDI > ATEM IN 8

Streaming laptop
ATEM Software Control + HyperDeck + Resi

ProPresenter Mac (Bianca)
HDMI > LED wall transcoder; Anker hub > prod ETH + CONF OUT; USB-C > Dante

Laptop power
battery-backed CPS1215RM strip

Bay A: active system

4U top	left open (the Hollyland RX mounts on top of the flip-up lid)
U12	**Fan, 1U thermostatic** AC Infinity CLOUDPLATE T1
U11	**Resi** 1U vented shelf
U10	**HD Mini + Dante satellite (new 8-port PoE switch)** 1U vented shelf
U9	**LED wall transcoder** rack-mounted
U8	**Production switch (TL-SG105) + AX21** 1U vented shelf
U7	**Cable management** lacing bar
U6-4	**Vented blanks (reserve)** airflow + growth
U3	**CPS1215RM strip (from UPS)** basic 1U, no surge, no meter
U2-1	**UPS, CP1500PFCRM2U (2U)** pure sine; backs booth + Wing

Bay B: storage + utility power

4U top	left open
U12	**CPPDU511 front / RS1215-RA rear** CPPDU511 metered, drawer lights, fed from drop 2; RS1215-RA camera chargers
U11-9	**Left open** room for a bigger switch or Mac Minis
U8-5	**4U drawer (upper)** storage
U4-1	**4U drawer (lower)** heavier items here to balance the case

The same layout as page 2 with part names, matching BUILD-SPEC section 8; colors are the cable colors.

Rear I/O panel (3U, three plates) DECIDED design locked, DESIGN section 1

PANEL 1: VIDEO

CAM 1	CAM 2	CAM 3	CAM 4	CAM 5	CAM 6	CAM 7	CAM 8	CONF OUT	blank	blank	blank
BNC	BNC	BNC	BNC	BNC	BNC	BNC	BNC	HDMI	-	-	-

PANEL 2: DATA / AUDIO / POWER

DANTE TRUNK	LED 1	LED 2	INTERNET IN	PROD TRUNK	TALKBACK	IEM	SPARE	blank	blank	blank	POWER > WING
etherCON	etherCON	etherCON	etherCON	etherCON	XLR-F	XLR-M	etherCON	-	-	-	powerCON

Panel 3: spare row (12 holes). All eight camera jacks stay so every switcher input is visible. ATEM IN 2 is always the Hollyland RX and IN 8 the UltraStudio; how each connects is open, with CAM 2 one option for the Hollyland.

WING PANEL CONDITIONAL **pending BXWING inspection (N1); without it the connections run out the side of the case**

CONTROL	DANTE TRUNK	AES50	TALKBACK	IEM	POWER IN	blank	blank
etherCON	etherCON	etherCON	XLR-M	XLR-F	powerCON	-	-

Cable map DECIDED design locked, DESIGN section 1

Each row is one signal chain and panel names match the rear panel.

VIDEO

Pocket 4K (wired) —HDMI— Converter —SDI 100ft— Panel CAM 1 —SDI jumper— ATEM IN 1

Pocket 4K —HDMI— Hollyland TX —wireless— Hollyland RX (on the lid) —SDI (route open)— ATEM IN 2

DJI —HDMI— Converter —SDI 100ft— Panel CAM 3 —SDI jumper— ATEM IN 3

Rented cameras —SDI— Panel CAM 4-7 —SDI jumper— ATEM IN 4-7

ProPresenter Mac —USB-C— UltraStudio (placement open) —SDI— ATEM IN 8

ATEM AUX —SDI— HyperDeck HD Mini —USB-C— SSD

ATEM OUT 8 —SDI— Resi —Cat— AX21 > internet

ATEM multiview —HDMI— LEFT lid

ProPresenter Mac —HDMI— LED wall transcoder —Cat x2— Panel LED 1-2 —field— LED wall

ProPresenter Mac —USB-C— Anker hub —HDMI— Panel CONF OUT —HDMI field— Confidence monitor

ProPresenter Mac —second screen (route open)— RIGHT lid

AUDIO AND DANTE

Stage box (DL251) —AES50— Wing

Wing Dante card —Cat— Wing case switch (TL-SG1005P, 5-port) —trunk 15ft— DANTE TRUNK —Cat— Bay A satellite —Cat + PoE— AVIO (PoE)

AVIO —XLR pigtails— ATEM Ch 1-2

ProPresenter Mac —USB-C Cat— Bay A satellite

ProTools Mac (in case) —Cat (Dante)— Wing case switch

Bianca's talkback mic —XLR— Panel TALKBACK —XLR 15ft— Wing In 8

Wing Out 8 —XLR 15ft— Panel IEM —XLR— Bianca's IEM

Wing —USB-C— ProTools Mac (in case)

Cable map, continued

PRODUCTION NETWORK AND INTERNET

Venue / Starlink —Cat field— Panel INTERNET IN —Cat— AX21 WAN

AX21 LAN —Cat— TL-SG105 —Cat— ATEM, HD Mini, streaming laptop, Anker hub

AX21 LAN —Cat— Resi

AX21 LAN —Cat— PROD TRUNK —trunk 15ft— Wing CONTROL

AX21 LAN —Cat— Panel SPARE

POWER

Wall outlet —5-15P— Drop 1 (125ft 12/3 SOOW) —5-15R— UPS CP1500PFCRM2U —mains— CPS1215RM —5-15P > C13— Bay A + desk gear, lids

CPS1215RM —feed cord— POWER > WING outlet —powerCON 15ft 14/3— Wing

Wall outlet (2nd circuit preferred, not required) —5-15P— Drop 2 (125ft 12/3 SOOW) —5-15R— CPPDU511 (Bay B front) —chained— RS1215-RA (rear) —mains— Camera chargers

CPPDU511 —extension (details open, not costed)— Quad box —mains— Separate charging station

CPS1215RM (battery-backed) —mains— Laptops

Locked decisions

From DESIGN.md section 5. All are decided. Each one changes only through a written proposal that I accept.

#	DECISION	REASON
1	We implement with the SDI we already own: a BMD converter at each camera, 1080p, coax to the panel. Whether to switch to AOC is open.	HDMI out, SDI in; locking, rugged and already owned
2	Owned SDI field runs are 100ft. Any power, HDMI or data field cables we add should be 125ft or more.	Venue distances vary widely; long is the safe default
3	Three cameras at every event: two Pocket 4K + DJI; more only when rented	That's what runs today (D9)
4	One rear I/O panel, three Neutrik D-series 12-hole plates on Bay A	One touchpoint; field wear never reaches the gear
5	Panel order and labels (POWER > WING last, TRUNK names)	The fabrication drawing (D13)
6	Genders: AVPRO TALKBACK female, IEM male, POWER an outlet; the Wing panel mirrors them	A mic plugs into the talkback jack; the IEM jack feeds a pack; power flows AVPRO → Wing
7	ATEM IN 2 is always the Hollyland RX, and IN 8 is always the UltraStudio. How each connects is open.	Matches the running ATEM
8	Color code (BUILD-SPEC §12); green vs yellow is the split that matters	Anyone setting up matches colors, not port names
9	Labeling: "match the color, match the number"	Anyone setting up matches colors, not port names
10	One UPS (CP1500PFCRM2U) backs the booth and the Wing over the umbilical	The BXWING can't carry a UPS; this is the only way to back the Wing

Locked decisions, continued

#	DECISION	REASON
11	No surge behind the UPS; the ProX X-PC10ASTRO was passed on	Stacked surge behind a UPS isn't good practice, and Bay B's metered CPPDU511 already gives us a meter
12	Runs on one 15A circuit, two preferred, never tied. Power arrives on two 125ft 12/3 SOOW drops with Edison ends: drop 1 → AVPRO (and the Wing through it), drop 2 → the charging station	The whole rig draws well under 15A; venue circuit counts are unknowable (D20)
13	Bay B power: CPPDU511 front (metered, drawer lights) + RS1215-RA rear (camera chargers), chained, utility side	Front lights the drawers; rear outlets face the chargers; one meter (D3)
14	The desk laptops plug into the battery-backed CPS1215RM strip. Decided.	They keep running if venue power drops
15	Switches: owned TL-SG1005P (5-port) = Wing case Dante switch, 3 ports used; owned TL-SG105 = Bay A production switch; new 8-port PoE switch = Bay A Dante satellite at U10, powers the AVIO	The AVIO needs PoE in Bay A, and the Wing case needs only 3 ports
16	Bay A mounting: Resi U11; HD Mini + new 8-port PoE switch U10; TL-SG105 + AX21 U8; all on the same 1U vented shelf; Etsy dual mount and Teranex shelf dropped	Every network jumper stays in Bay A; cheapest shelf (D5, D19)
17	Two networks, not three: Dante (isolated) and Production; internet is the AX21's WAN	That's the physical wiring; "three" was a zoning aid
18	Router is the AX21 (older docs say AX55 for the same router)	D11
19	UltraStudio placement is open: rack-mounted or near the Mac Mini, or the desk near the ATEM. The Hollyland RX mounts on top of the flip-up lid when open and stows in a drawer or with the cameras until setup. The Bay A 4U top is left open.	The receiver won't get good signal inside the rack
20	Lid monitors: 2 × LG 24GS60F-B, 300 nit matte. It may not be bright enough even under a tent or canopy, and direct sun needs angling. Model reopened for brightness research	D14; right-angle adapters for lid clearance
21	LEFT lid = ATEM multiview day one; RIGHT lid = the ProPresenter Mac's second screen, ready for a later move to a Mac Mini	Multiview can't depend on a laptop
22	Cooling: open back primary; 1U thermostatic fan at U12 exhausting to the back; vented blanks in reserve U's	Low heat load; blanks stop airflow short-circuits
23	Umbilical = 5 short cables: PROD, DANTE, TALKBACK, IEM, POWER (15ft powerCON TRUE1 link, 14/3 SJOOW)	The cases sit side by side; TRUE1 cable ends take 6-12mm cable (D20). AES50 is stage-side
24	All five trunks are short; the cases always sit side by side	Q3, D20. Longer runs can be added later
25	The Wing panel is conditional: planned, pending BXWING inspection. If the case can't take one, the connections run out the side of the case	Nobody has confirmed the case takes a panel, but it's likely doable
26	Stage power is out of the build BOM	Separate subsystem; doesn't gate the order (D8)
27	Case + freight figure comes from the BOM ($1,650), labeled placeholder until Matt quotes	One number everywhere (D6)

Remaining open items

None of these gate the order. Running-config items are left out.

ITEM	OWNER	DUE	GATES	STATUS
N2 M7: LED wall and internet ends. The LED wall receiver takes standard Ethernet. The internet drop's far end is still open. It sets the etherCON end count; the BOM already buys the high count.	Sam	2026-10-04 (next service)	No	OPEN
N3 M3: side compartments. Do the AVPRO side doors open to usable storage, and what are the inside dimensions? The design doesn't use them.	Sam (ask Matt/ProX)	On case delivery (assumed by 2026-11-15)	No	OPEN
N4 U10 shelf fit. The 10in AC Infinity shelf takes the HD Mini and the new 8-port PoE switch side by side.	Sam	On shelf delivery (assumed by 2026-10-15)	No	OPEN
N5 M5: monitor fit. LG 24GS60F-B panel height without stand + right-angle adapter depth vs the 16.1in lid; two widths vs 49.6in.	Sam	On case delivery (assumed by 2026-11-15)	No	OPEN
N7 ProTools Mac recording path. Wing USB-C to the ProTools Mac, inside the BXWING, settled for the case layout. The ProTools Mac is also a Dante endpoint on the Wing case switch, so the case needs room for both cables.	Tyler	2026-10-04	No	OPEN
N10 M2: AVIO label. Read the AVIO model label (AVIOAO2 per the port map). It's confirmed PoE-powered.	Sam	2026-10-04	No	OPEN
N11 R-019: drum kit Dante. Does Omar have a separate Dante device at the drum kit? (yes/no)	Sam	2026-10-04	No	OPEN
N12 R-024: Shure combiner label. Read the Shure transmit combiner label (UA844+SWB? typed "ua344").	Sam	2026-10-04	No	OPEN
N14 The "regret ask". Long-lead items, freight consolidation, anything hard to add later.	Matt	2026-10-19, with the quote	No	OPEN

Stage power items (N17, N18) are tracked with the separate stage-power project.

Full BOM (BOM v7, 2026-09-28): first order

Owned gear is not in any total. Not in this BOM: camera field SDI cable (already owned, 100ft runs), stage power, and the XLR trunk cables (owned). "est" = estimated price.

GROUP	ITEM	MODEL / SKU	QTY	UNIT	EXT	PRICE STATUS
Cases	Rolling dual-bay workstation	ProX XZF-AVPRO2X12U2X4U	1	$500.00	**$500.00**	placeholder, to verify (Matt)
Cases	Wing hydraulic flip case	ProX XZF-BXWING	1	$900.00	**$900.00**	placeholder, to verify (Matt)
Cases	Freight, both cases (consolidated)	-	1	$250.00	**$250.00**	placeholder, to verify (Matt)
AVPRO panel	1U 12-hole D-series plate	My Cable Mart D-series	3	$20.00	**$60.00**	est
AVPRO panel	BNC 75 ohm feedthrough (camera SDI)	Neutrik NBB75DFI	8	$8.00	**$64.00**	est
AVPRO panel	HDMI feedthrough	Neutrik NAHDMI-W-B	1	$25.00	**$25.00**	est
AVPRO panel	etherCON feedthrough	Neutrik NE8FDP-B	6	$12.00	**$72.00**	est
AVPRO panel	XLR female chassis	Neutrik NC3FD-L-B-1	1	$6.00	**$6.00**	est
AVPRO panel	XLR male chassis	Neutrik NC3MD-L-B-1	1	$6.00	**$6.00**	est
AVPRO panel	powerCON TRUE1 chassis outlet	Neutrik NAC3FPX (family TBC, D7)	1	$20.00	**$20.00**	est
AVPRO panel	Feed cord for the POWER > WING outlet	12/3 cord with 5-15P, wired to the outlet	1	$12.00	**$12.00**	est
AVPRO panel	D-hole blanking plate	Neutrik DBA-BL	18	$2.00	**$36.00**	est
Spares	BNC feedthrough, spare	Neutrik NBB75DFI	2	$8.00	**$16.00**	est
Spares	etherCON feedthrough, spare	Neutrik NE8FDP-B	2	$12.00	**$24.00**	est
Spares	XLR female chassis, spare	Neutrik NC3FD-L-B-1	1	$6.00	**$6.00**	est
Spares	XLR male chassis, spare	Neutrik NC3MD-L-B-1	1	$6.00	**$6.00**	est
Cable ends	etherCON cable carrier (standard etherCON, over an RJ45 plug)	Neutrik NE8MX-1 (TBC, D7)	11	$3.31	**$36.41**	est
Cable ends	RJ45 plugs, shielded (pack), for the carrier ends	Shielded Cat6A RJ45 plugs, 10-pk	1	$12.00	**$12.00**	est
Cable ends	powerCON TRUE1 cable connector, male	Neutrik NAC3MX-W (TBC, D7)	2	$18.00	**$36.00**	est
Cable ends	powerCON TRUE1 cable connector, female	Neutrik NAC3FX-W (TBC, D7)	2	$18.00	**$36.00**	est
Power	UPS, 2U pure sine (backs booth + Wing)	CyberPower CP1500PFCRM2U	1	$375.00	**$375.00**	est
Power	Rack PDU from the UPS (basic, no surge)	CyberPower CPS1215RM	1	$59.99	**$59.99**	firm; listing check (G5)
Power	Bay B front PDU, metered, drawer lights	Clear Power CPPDU511	1	$149.99	**$149.99**	firm
Power	Bay B rear strip, camera chargers	Tripp Lite RS1215-RA	1	$94.98	**$94.98**	quoted 2026-08-20

Full BOM, continued

GROUP	ITEM	MODEL / SKU	QTY	UNIT	EXT	PRICE STATUS
Cooling	1U thermostatic exhaust fan	AC Infinity CLOUDPLATE T1	1	$150.00	**$150.00**	est
Cooling	1U perforated blank panel	Steel perforated (Amazon)	3	$12.00	**$36.00**	est
Mounting	1U vented cantilever shelf, 10in deep	AC Infinity 1U vented (B01C9KYUG8)	3	$25.00	**$75.00**	est
Network	Bay A Dante satellite switch, 8-port PoE	PoE model open	1	$19.99	**$19.99**	placeholder: PoE model not priced
Storage	4U rack drawer	StarTech 4UDRAWER	2	$155.00	**$310.00**	est
Cable mgmt	1U cable lacing bar	StarTech 12S-CABLE-LACING-BAR	1	$25.00	**$25.00**	est
Cable mgmt	Hook-and-loop straps	ONE-WRAP + WrapStrap	1	$40.00	**$40.00**	est
Hardware	Rack screws + cage nuts	M6 or 10-32 (open; check the rails)	1	$25.00	**$25.00**	est; waits on G6
Cabling	SDI BNC jumpers, panel to ATEM	Belden 1855A / premade BNC-BNC	8	$10.00	**$80.00**	est
Cabling	Cat6A patch, color-coded (lot)	Monoprice SlimRun Cat6A 10-pk	1	$80.00	**$80.00**	est
Cabling	Trunk cable, shielded Cat6A, 15ft	Shielded Cat6A patch, 15ft	2	$12.00	**$24.00**	est
Cabling	HDMI 2.0 jumper, short	HDMI 2.0, 6-10ft	3	$12.00	**$36.00**	est
Cabling	Short power cord, 5-15P to IEC C13	2-3ft	6	$7.00	**$42.00**	est
Cabling	Umbilical power cable (AVPRO > Wing), 14/3 SJOOW	14/3 SJOOW, cut to length (ft)	15	$0.94	**$14.10**	est
Venue power	Power drop cable, 12/3 SOOW (2 x 125ft)	12/3 SOOW, cut to length (ft)	250	$1.63	**$407.50**	est
Venue power	Edison plug, 5-15P (wall end)	Hubbell HBL5266C	2	$14.00	**$28.00**	est
Venue power	Edison connector body, 5-15R (rig end)	Hubbell HBL5269C	2	$18.00	**$36.00**	est
Venue power	Quad box, 4 outlets, 2ft 12/3 tail with 5-15P	BarnDoor QB-M-2FT metal quad box	1	$89.88	**$89.88**	decided *
Monitors	Lid monitor, 24in matte IPS	LG UltraGear 24GS60F-B	2	$150.00	**$300.00**	est
Monitors	Right-angle HDMI + DC adapters (lot)	90-deg HDMI + DC barrel	1	$20.00	**$20.00**	est
First order total					**$4,641.84**	of which $1,650.00 case + freight placeholders

* BOM v7 lists the quad box as "tentative, may drop (N19)". Shown as decided.

Wing block CONDITIONAL

Bought only if the BXWING can take a panel (N1). Not in the first order.

Wing panel	Small D-series plate (8 holes)	D-series plate	1	$20.00	**$20.00**	est
Wing panel	etherCON feedthrough	Neutrik NE8FDP-B	3	$12.00	**$36.00**	est
Wing panel	XLR male chassis	Neutrik NC3MD-L-B-1	1	$6.00	**$6.00**	est
Wing panel	XLR female chassis	Neutrik NC3FD-L-B-1	1	$6.00	**$6.00**	est
Wing panel	powerCON TRUE1 chassis inlet	Neutrik NAC3MPX (family TBC, D7)	1	$20.00	**$20.00**	est
Wing panel	Inlet-to-Wing power pigtail	IEC C13 cord, cut and wired to the inlet	1	$8.00	**$8.00**	est
Wing panel	D-hole blanking plate	Neutrik DBA-BL	2	$2.00	**$4.00**	est
Wing panel	FALLBACK ONLY: powerCON TRUE1 to IEC C13 jumper	TRUE1 male to C13, short	0	$30.00	**$0.00**	est; qty 0. Only if the connections run out the side of the case: the Wing power link then needs it to reach the Wing's IEC inlet
Wing block total					**$100.00**	
All lines total					**$4,741.84**	