The ELIM production workstation: what we'd build and why

1. The whole picture

This build puts our video, network and control gear into the ProX AVPRO rolling workstation (the AVPRO). It has two 12U bays, two 4U tops and a work surface. Of its three lids, the flip-up lid holds the two monitors and the other two come off the case. The Behringer Wing sits beside it in the ProX BXWING hydraulic flip case (the Wing case), joined by five short cables. Every field cable and those five land on one labeled, color-coded panel on the back of the AVPRO.

Right now our rig deploys once or twice a week at different venues, and we set up and tear down under time pressure. The build also removes the need for extra tables. The Wing flips up in its own case, and the AVPRO brings its own work surface and pop-up lid tables. The design puts the physical job first. The system has to set up, run the event and tear down reliably before anything else matters.

~40 → ~15 loose connections become labeled cables	**~30 min** saved at setup, and again at teardown

Both figures are estimates, and we'll measure them. I'll time setup and teardown before the cutover and again after it.

The order is about $4,600 ($4,641.84). That's an estimate. Most prices are estimated based on online pricing, and the cases and freight are placeholders until locked in with Matt. Almost all the gear inside is already owned, so it isn't in the total. A $125.88 Wing panel block (connector plate, jacks and power adapter) comes on top, only if the Wing case can take a plate.

Flip-up lid

Left screen every camera at once	**Right screen** ProPresenter second screen	**Wireless camera receiver** on top of the lid when open

Desk

Switcher on the desk	**Audio adapter** beside it	**Two laptops** ProPresenter + streaming

Bay A: the active system

left open
Cooling fan
Streaming encoder (Resi)
Recorder + audio switch
LED wall transcoder
Network switch + router
Cable management
Airflow + growth
Power strip (backed)
Battery backup (UPS)

Bay B: storage + charging

left open
Metered strip + charger strip
Left open
Drawer
Drawer



The AVPRO product listing photo, with the seller's labels.

- Camera / SDI: Blue
- HDMI: White
- Dante: Green
- Production net: Yellow
- Internet: Red
- LED data: Purple
- XLR + AES50: Orange
- Power: Black

Back of Bay A: the connection panel

8 camera inputs	Confidence out	LED wall x2	Internet in	Network to Wing
Audio network to Wing	Talkback + in-ears	Power to Wing		

The layout is decided but can be adapted and changed. Colors are cable colors. The two removable lids should have legs inside to pop up as tables, open until Matt confirms.

2. Walking the build

This section walks the build from the outside in. Each starts with what happens there at a service or event. Then there's a short card for each part: what it does, why it's there, what we passed on if build/ records it, what it costs, what we give up, and where it stands.

a. The AVPRO station

The AVPRO is the production position. Streaming and presentation work is done at this desk under the two monitors on the flip-up lid, and audio mixing at the Wing case beside it. This creates a space for three stations at the production position.

The case: ProX AVPRO rolling workstation

What it does. It holds everything but the Wing. It has two 12U bays, two 4U tops, a work surface and three lids, and it rolls. The flip-up lid holds the two monitors.

Why it's there. The build centers on one workstation and everything that connects to it. Our design principles also favor commercial cases and mounts over DIY where they work.

Cost. About $500, a placeholder until Matt's quote.

What we give up. Closed, it's large enough to drive freight cost. The side compartments aren't used in the design.

Status. The design is decided. The price is open until Matt's quote, and side-door storage gets checked on delivery.

Two lid monitors: LG UltraGear 24GS60F-B

What it does. Both monitors are on the flip-up lid. The LEFT lid monitor shows the ATEM multiview, every camera at once, from day one. The RIGHT lid monitor is for the ProPresenter Mac, as its second screen now and ready for a later move to a Mac Mini.

Why it's there. The multiview can't depend on a laptop, so the left screen runs straight from the switcher. Together the two monitors replace the mobile monitor setup we use today.

Why not another. A 2000-nit tier was considered and dropped on cost (section 3).

Cost. About $320 with adapters, estimates. A brighter or used option would change this.

What we give up. At 300 nit matte, the LG is the minimum worth considering and may not be bright enough even under a tent.

Status. The model is open on brightness (section 4), and lid fit gets checked on delivery.

Wireless camera receiver: Hollyland RX

What it does. It receives the wireless Pocket 4K and sends SDI to ATEM IN 2. When the case is open it mounts on top of the flip-up lid. Until setup it stows in a drawer or with the cameras.

Why it's there. It can't live in the rack, because it won't get good signal there.

Cost. Already owned. The lid mount isn't costed.

Status. The placement is decided. The lid mount and its route to ATEM IN 2 are open (section 4).

The two removable lids as pop-up tables

What it does. The AVPRO has three lids. The flip-up lid stays on the case and holds the two monitors. The other two lids come off the case, and each has legs inside it so it can pop up into an accessory table, for example for the camera charging area or other needs.

Why it's there. They give us extra surface at a venue without bringing tables.

Cost. Expected to come with the case. If not, we add them (not costed).

Status. Assumed: legs come with the removable lids. Open until Matt confirms.

b. The desk

The ATEM switcher, the ProPresenter Mac and the streaming laptop run from the desk. The switcher's I/O cables drop through a 3in grommet into the Bay A rack space.

Switcher: ATEM Television Studio Pro 4K

What it does. It switches all eight SDI inputs. Its multiview feeds the LEFT lid monitor, its AUX feeds the HyperDeck HD Mini recorder, and OUT 8 feeds the stream encoder. It sits over the 3in grommet, and its I/O drops into Bay A.

Why it's there. It's the switcher we run today.

Cost. Already owned. The retention tray isn't costed.

Status. The placement is decided. The retention tray is open (section 4).

Audio adapter: Dante AVIO

What it does. It takes Dante from the Bay A satellite switch and feeds two XLR pigtails into ATEM audio channels 1 and 2. It runs on PoE from that switch.

Why it's there. The new 8-port PoE switch in Bay A powers it, so it needs no injector.

Cost. Already owned.

Status. Decided and confirmed PoE-powered. Reading its model label is open.

Video interface: UltraStudio Monitor 3G

What it does. It takes ProPresenter from the ProPresenter Mac over USB-C and sends SDI to ATEM IN 8.

Why it's there. It puts ProPresenter on the switcher as a clean SDI input.

Cost. Already owned.

Status. Placement is open (section 4). The current plan has it velcro'd behind the lid monitors.

The laptops and their power

What it does. The streaming laptop runs ATEM Software Control, the HyperDeck and Resi. The ProPresenter Mac runs ProPresenter and plays music and media in house over Dante. It sends HDMI to the LED wall transcoder and uses an Anker hub for production Ethernet and the confidence monitor. Both laptops plug into the battery-backed CPS1215RM strip.

Why it's there. These are the laptops we use now. On the battery-backed strip they keep running if venue power drops.

Cost. Already owned.

Status. Decided.

c. Bay A, the active system

Nobody touches Bay A for setup. It's wired once and left alone, and every network jumper stays inside it. All connection work is done from the rear panel instead.

Battery backup and backed strip: CyberPower CP1500PFCRM2U + CPS1215RM

What it does. The 2U pure-sine UPS sits at the bottom of Bay A, fed from power drop 1. The basic 1U CPS1215RM strip above it, with no surge and no meter, feeds the Bay A and desk gear, the lid monitors, the laptops and the POWER > WING outlet. The UPS side carries 14 loads, an estimated 280 to 470W not counting the ProTools Mac, whose draw is open. It's assumed to fit with the Mac included.

Why it's there. One UPS backs both the booth and the Wing. The Wing case can't carry its own UPS, so this is the only way to back the Wing.

Why not another. The ProX X-PC10ASTRO strip was passed on (section 3).

Cost. About $435, mostly estimated.

Status. Decided. The CPS1215RM listing still needs confirming (section 4).

Recorder and Dante satellite (U10)

What it does. The HyperDeck Studio HD Mini records the clean feed from ATEM AUX. A new 8-port PoE switch is the Bay A Dante satellite. It takes the DANTE TRUNK, powers the AVIO and connects the ProPresenter Mac's Dante adapter. Both share one 1U vented shelf.

Why it's there. Every network jumper stays in Bay A, and one shelf model is the cheapest mount.

Why not another. An Etsy dual mount and a Teranex shelf were both dropped (section 3).

Cost. The HD Mini is owned. The PoE switch carries a placeholder of about $20 until its model is priced (section 4). The shelf is in the small-parts card.

Status. Decided. The PoE model is open, and shelf fit gets checked on delivery.

Owned gear moved into Bay A

What it does. Resi takes SDI from ATEM OUT 8 and streams out through the router. The LED wall transcoder takes HDMI from ProPresenter and sends two Ethernet runs to LED 1 and LED 2. The TL-SG105 production switch and the AX21 router run the production network, and wired internet from the venue or Starlink connects to the router. Dante stays on its own isolated network.

Why it's there. It's the gear we run today, moved into the rack, and every network jumper stays in Bay A.

Cost. Already owned.

What we give up. Every wired production port is used, so adding a device later means a bigger switch.

Status. Decided. The Bay A 4U top is left open.

Small parts: shelves, cable management, screws and jumpers

What it does. This covers the vented shelves, a lacing bar, hook-and-loop straps, rack screws and cage nuts, short power cords, color-coded patch cables and short HDMI jumpers.

Why it's there. The lacing bar holds the cable runs, power on one side and signal on the other, and velcro straps keep the rest tidy.

Why not another. Zip ties were ruled out in favor of hook-and-loop.

Cost. About $320, estimates.

Status. The parts list is decided. The screw thread and built-in rails are open (section 4).

Cooling: 1U thermostatic fan and vented blanks

What it does. A 1U thermostatic fan at the top of Bay A exhausts toward the open back. Perforated blanks fill the reserve spaces.

Why it's there. The open back does most of the cooling, and the heat load is low. The fan is insurance for hot outdoor events, and the blanks stop intake air from short-circuiting around the gear.

Why not another. Open gaps were rejected in favor of blanks (section 3).

Cost. About $190, estimates.

What we give up. At a venue the open back has to stay clear, so the case can't be pushed against a wall.

Status. Decided.

d. Bay B, storage and charging

Bay B charges the camera batteries. It carries no signal. The rest of it is storage, and all cabling is stored with the two cases.

Bay B power: Clear Power CPPDU511 + Tripp Lite RS1215-RA

What it does. The metered CPPDU511 at the front lights the drawers. The RS1215-RA at the rear feeds the camera chargers and plugs into the CPPDU511, so both read on one meter. Power drop 2 feeds them.

Why it's there. The front lights the drawers, the rear outlets face the chargers, and there's one meter.

Cost. About $245, one firm price and one quoted.

What we give up. This side isn't battery-backed, so nothing that must stay on plugs in here.

Status. Decided. Dropping the RS1215-RA is an open proposal (section 4).

Pass-through to the separate charging station

What it does. The CPPDU511 passes power through an extension to a quad box at a separate charging station. One of the removable lids, popped up as a table, could hold that charging area.

Why it's there. It gives a separate charging area its own outlets.

Cost. About $90 for the quad box. The extension isn't costed.

Status. The quad box is decided. The extension details are open.

Storage: two 4U drawers

What it does. Two 4U drawers fill the lower half of Bay B, with heavier items in the lower drawer to balance the case. All cabling is stored with the two cases, not elsewhere. The upper spaces and Top B are left open, with room for a bigger switch or the Mac Minis later.

Why it's there. Bay B is the storage side of the rack.

Cost. About $310, an estimate.

Status. Decided.

e. The rear panel

This is the only face anyone touches during setup. Anyone setting up matches the color and number on each cable to a jack, and plugs in. Nothing plugs into a device directly, so field wear never reaches the gear.

Panel 1: video

CAM 1 BNC	CAM 2 BNC	CAM 3 BNC	CAM 4 BNC	CAM 5 BNC	CAM 6 BNC	CAM 7 BNC	CAM 8 BNC	CONF OUT HDMI	blank -	blank -	blank -

Panel 2: data, audio and power

DANTE TRUNK etherCON	LED 1 etherCON	LED 2 etherCON	INTERNET IN etherCON	PROD TRUNK etherCON	TALKBACK XLR-F	IEM XLR-M	SPARE etherCON	blank -	blank -	blank -	POWER > WING powerCON

Panel 3 is a spare row of 12 holes. The panel layout is decided. All eight camera jacks stay on the panel, so every switcher input is visible. Today ATEM IN 2 is the Hollyland RX and IN 8 is the UltraStudio. With the Hollyland on the flip-up lid, its SDI still has to reach IN 2, and one option is to run it through the CAM 2 jack. How both connect is open and may change.

One panel, three plates

What it does. Three Neutrik D-series 12-hole plates sit on the Bay A rear rails. Panel 1 is video, panel 2 is data, audio and power, and panel 3 is a spare row.

Why it's there. It gives us one place to connect, and field wear never reaches the gear.

Cost. About $60, an estimate.

Status. Decided, including the panel order and labels.

The connectors

What it does. There are eight BNC camera jacks, an HDMI confidence output, six etherCON jacks, a female TALKBACK XLR, a male IEM XLR and a powerCON outlet for the Wing. Blanking plates fill the empty holes. The panel note above covers how the camera jacks map to the switcher.

Why it's there. A mic plugs into the talkback jack, the IEM jack feeds a pack, and power flows from the AVPRO to the Wing.

Why not another. A CAT6A etherCON cable connector was dropped because it doesn't mate with the panel jacks.

Cost. About $240, estimates.

Status. The layout is decided. The powerCON and etherCON parts are open until they're checked (section 4).

Cable ends, jumpers and spares

What it does. etherCON cable carriers and RJ45 plugs fit the trunk, LED and internet ends. powerCON cable ends make the Wing power link. SDI jumpers run from the panel to the switcher, and loose spares cover both panels.

Why it's there. Each carrier end gets a fresh crimp, and spares cover both panels.

Cost. About $250, estimates.

Status. The carrier count is bought high. The internet drop's far end is open (section 4).

Color code and labels

What it does. Every cable has a color and a number, and the jack it lands on has the same color and number. Blue is camera SDI, green is Dante, yellow is production network, red is internet, purple is LED data, white is HDMI, orange is XLR and AES50, and black is power.

Why it's there. Anyone setting up matches colors, not port names. Green against yellow is the split that matters most.

Cost. Covered by the straps and labeling in the small-parts card.

Status. Decided.

f. The five short cables between the cases

At a service or event the two cases sit side by side, and five short cables join them. That's the whole connection between the AVPRO and the Wing case.

Two data trunks and two audio lines

What it does. The PROD trunk carries Wing control from the router. The DANTE trunk joins the two Dante switches. Both are 15ft shielded Cat6A with etherCON ends. TALKBACK carries Bianca's mic to Wing In 8, and IEM carries Wing Out 8 back to her pack, both on 15ft XLR.

Why it's there. The cases always sit side by side, so short cables are enough. The AES50 to the stage box runs stage-side.

Cost. About $25 for the trunk cables, an estimate. The XLR cables are owned.

What we give up. If a venue ever needs the cases apart, we'd add longer trunks then.

Status. Decided. Wing In 8 and Out 8 are closed.

The Wing power link

What it does. A 15ft powerCON TRUE1 cable runs from the AVPRO's POWER > WING outlet to the Wing case. There it feeds the Wing case strip, and the Wing, the ProTools Mac and the TL-SG1005P plug into the strip.

Why it's there. It carries battery-backed power from the AVPRO's UPS to the Wing case. The TRUE1 ends twist-lock, so the feed can't be pulled by accident.

Why not another. The 12/3 SOOW used for the wall drops is too thick for the TRUE1 cable ends (section 3).

Cost. About $15, an estimate.

Status. Decided. The matched TRUE1 family is open until it's confirmed.

g. The Wing case

At a service or event the Wing is operated from its case and records to the ProTools Mac over USB-C. The ProTools Mac is planned to take over the stream mix as well as the live event mix. Until it does, the separate stream-mix laptop stays in use. That's open.

Wing panel (if the case can take one)

CONTROL etherCON	DANTE TRUNK etherCON	AES50 etherCON	TALKBACK XLR-M	IEM XLR-F	POWER IN powerCON	blank -	blank -

Otherwise cables route out the side of the case.



The BXWING product listing photo.

The case: ProX BXWING hydraulic flip case

What it does. It holds the Behringer Wing beside the AVPRO.

Why it's there. Today the Wing travels in a wheeled case that has to be set on a table before we can use it. The BXWING's hydraulic lid flips the Wing up into its working position, so it doesn't need a table at all. Removing that table is one of the main reasons for this upgrade.

Cost. About $900, a placeholder until Matt's quote.

What we give up. None recorded.

Status. The design is decided. The price is open until Matt's quote.

Inside: the Wing, its Dante switch and the ProTools Mac

What it does. The Wing is owned. The owned 5-port TL-SG1005P is the Wing case Dante switch, connecting the Wing's Dante card, the trunk and the ProTools Mac, three of five ports, or four while the stream-mix laptop stays in use. The ProTools Mac also has USB-C to the Wing for recording.

Why it's there. Three ports fit the 5-port switch, and the new PoE switch goes to Bay A to power the AVIO.

Why not another. An 8-port switch here was planned first (section 3).

Cost. Already owned.

Status. Decided. The ProTools Mac recording path is open (section 4).

Backed by the AVPRO's UPS

What it does. The Wing case strip runs on battery-backed power from the AVPRO over the Wing power link. The Wing, the ProTools Mac and the TL-SG1005P plug into it.

Why it's there. The Wing case can't carry a UPS, so this is the only way to back the Wing.

Cost. Included in the UPS line.

What we give up. For standalone use the Wing goes on a wall outlet.

Status. Decided.

The Wing panel

What it does. If the case can take it, a small D-series plate gives the five cables and the AES50 their own jacks. The genders mirror the AVPRO panel. The power inlet keeps the twist lock, and inside the case a short pigtail adapts it to a 5-15R socket for the Wing case strip's standard plug.

Why it's there. It gives the Wing case the same plug-in panel as the AVPRO.

Why not another. If the case can't take a panel, the connections run out the side of the case, and a TRUE1-to-5-15R jumper feeds the strip.

Cost. About $126, not in the first order. The adapter parts are placeholders until I review them.

Status. Conditional, and likely doable. I'll inspect the case on delivery.

h. Power from the wall

At a service or event two long cords run from wall outlets to the rig. The first feeds the AVPRO's battery backup, and the Wing through it. The second feeds Bay B and the charging station.

Two 125ft power drops

What it does. Each drop is 125ft of 12/3 SOOW with a plug at the wall and a connector body at the rig. Drop 1 feeds only the UPS. Drop 2 feeds the Bay B CPPDU511, which feeds the charging station. The two are built the same, so either can stand in for the other.

Why it's there. Venue distances vary widely, and long is the safe default.

Cost. About $470, estimates.

Status. Decided. The plug and connector parts are assumed, and an equal 15A industrial part can be substituted.

Circuits

What it does. The whole rig draws well under one 15A circuit, so one works. A second circuit is preferred, not required. When a venue has two, each drop goes on a different circuit. We never tie circuits together.

Why it's there. We can't know a venue's circuit count ahead of time.

Cost. No cost.

Status. Decided.

i. Field cables

At a service or event the field cables are the runs out into the room: cameras, the LED wall, the confidence monitor and internet. Each one is labeled and color-coded, and each lands on the rear panel. All field cabling is stored with the two cases.

Camera SDI

What it does. Each wired camera sends HDMI to its BMD converter, which turns it into 1080p SDI. The SDI runs back over coax to the panel and on to the ATEM at the case. We already own all the long SDI runs and spools, and they're 100ft. We run three cameras at every event, two Pocket 4K bodies and the DJI, and more only when we rent them.

Why it's there. The cameras are HDMI out and the switcher is SDI in. Locking, rugged coax handles long runs in a spread-out room.

Why not another. An HDMI-to-converter box near the cameras wasn't chosen, because HDMI doesn't carry far enough.

Cost. Already owned, converters and cables.

What we give up. Each converter runs on its own adapter, so every wired camera position needs mains power.

Status. Decided: we implement with the SDI we own. Whether to switch to AOC is open (section 4).

The camera-cable trial

What it does. Emily runs the SDI cables we already own over a real deploy. The trial checks pull-through, cable and connector reliability, and picture over length. It doesn't test camera control.

Why it's there. It checks the owned cables before we rely on them.

Cost. No cost.

Status. Open. No date is set.

AOC, an open decision

What it does. AOC would replace the SDI coax on the camera runs. The camera's HDMI would go straight into the cable, so there's no BMD converter at each camera, and the converters could live in the Wing case.

Why it's there. AOC is lighter and more flexible than coax, and it runs longer distances without the signal degrading.

Cost. About $150 for a 50m run on a spool, an estimate from my notes with Matt. It isn't in the BOM.

Status. Open decision. We implement with the owned SDI until it's made.

LED wall, confidence monitor and internet runs

What it does. The LED wall takes two Ethernet runs from LED 1 and LED 2. The confidence monitor takes HDMI from CONF OUT. Internet comes from the venue or Starlink into INTERNET IN.

Why it's there. Each field run lands on its own labeled jack.

Cost. Today's LED and internet runs are already owned. They get etherCON carriers at the panel end.

Status. Decided. The LED wall receiver takes standard Ethernet.

3. What we chose not to do

These are the options build/ records as passed on, dropped or parked, with the reason given at the time.

The ProX X-PC10ASTRO power strip	Stacked surge behind a UPS isn't good practice, and the metered CPPDU511 in Bay B already gives us a meter.
An Etsy dual switch mount and the Teranex Mini Rack Shelf	One 1U vented shelf model does the job, keeps every network jumper in Bay A and costs the least.
Rack mounts for the converters	The converters live at the cameras.
An HDMI-to-converter box near the cameras	It's on record but not chosen. HDMI distance is the catch.
A 2000-nit field-monitor tier	It was replaced by the LG on cost. Brightness is open again, so a brighter or used option may come back (section 4).
Three networks	We have two physical networks. The third was a zoning aid.

A CAT6A etherCON cable connector	It belongs to a different family and doesn't mate with the panel jacks.
An 8-port switch in the Wing case	The Wing case uses three ports, so the owned 5-port TL-SG1005P is the right size there. The 8-port PoE switch goes to Bay A instead.
12/3 SOOW for the Wing power link	It's too thick for the TRUE1 cable ends.
A surge strip behind the UPS	No surge behind the UPS. The laptops plug straight into the battery-backed CPS1215RM instead.
Zip ties	Hook-and-loop and the lacing bar are used instead.
Open gaps in reserve rack spaces	Open slots let intake air short-circuit around the gear, so they get vented blanks.
Camera control in this build	It's parked. It needs a return SDI per camera, and whether the owned converters can do it is open.
Stage power in this BOM	It's a separate subsystem and doesn't gate the order.
Using the AVPRO side compartments	The design doesn't use them. That gets confirmed on delivery.

4. What we still don't know

Every item here is open unless it says otherwise. Owners and dates are in the appendix.

What affects the order

- The case and freight price. The $1,650.00 in the total is a placeholder until Matt's quote, and the order can't go in without it. The spend ceiling for that quote is also open. Bianca and I set it before we walk through this with Sunny.
- The connector families. The powerCON and etherCON parts get checked against Neutrik's tables before those lines are ordered.
- The CPS1215RM listing. I need to confirm the Amazon listing is the right strip. It affects that line only.
- The rack rails and screws. The screws are M6 or 10-32, and that needs confirming. It's also open whether the case comes with rails built in or they're added after purchase. If Matt doesn't know, this waits until the case arrives.

What affects the cost

- Field camera cable isn't a cost. We already own all the long SDI runs and spools, at 100ft. Any power, HDMI or data field cables we add later should be 125ft or more.
- Whether to switch field camera cable to AOC is an open decision. AOC runs about $150 for a 50m run on a spool, and it isn't in the BOM.
- The new 8-port PoE switch for Bay A. The BOM carries $19.99 as a placeholder, and a PoE model will cost more than that.
- The extension from Bay B to the charging station isn't costed. Its details are open.
- The count of etherCON cable ends depends on the internet drop's far end. The BOM already buys the higher count.

- Possible: drop the RS1215-RA ($94.98) and feed the charging table by a powerCON jumper from the CPPDU511. The jumper and panel outlet aren't specced yet.
- The Hollyland RX lid mount isn't specced or costed yet.
- The ATEM retention tray isn't costed. We need to build a foam or plywood tray, or secure the ATEM another way, and Matt may have suggestions.
- Lid monitor brightness. The 300-nit LG is the minimum worth considering and may not be bright enough even under a tent. I need to research brighter screens or find a used option, and the recorded fallback is a 1000-nit unit for the LEFT lid only. Brighter screens cost more, so this line may go up.
- Lid legs. I need Matt to confirm whether legs come on the two removable AVPRO lids. If they don't, we add them as a line item. It doesn't gate the order.
- Matt's "regret ask" covers long-lead items, freight consolidation and anything hard to add later. It comes with his quote.

What affects the Wing case

- Whether the Wing case can take a connector plate. I'll inspect it on delivery. If it can, we buy the $125.88 Wing block. Its power adapter parts are placeholders until I review them. If it can't, the connections run out the side of the case.
- The ProTools Mac recording path has to be settled for the case layout. The Mac needs room for both its USB-C and Dante cables.

A few smaller checks don't touch any of these. They cover shelf, monitor and side-door fit on delivery, four equipment label and model reads (the AVIO, the Shure combiner and antennas, and the camera converters, including whether they can return SDI), the drum-kit Dante question, where the UltraStudio mounts (rack-mounted, near the Mac Mini, or the desk near the ATEM), and how the Hollyland RX connects to ATEM IN 2.

5. What it costs

The first order is about $4,600 ($4,641.84). Each category below has one line on what it covers.

Category	Cost	What it covers and where it stands
Cases and freight	$1,650.00	OPEN Matt's estimates for both cases and consolidated freight. The real number comes from his quote.
Panel and connectors	$473.41	ESTIMATE The rear panel plates and jacks, loose spares and the cable ends that fit them.
Cabling	$276.10	ESTIMATE Short internal jumpers, the two data trunks and the short Wing power link.
Power	$1,241.34	ESTIMATE QUAD BOX: DECIDED The UPS and its strip, the Bay B strips, the two wall drops and the charging quad box.
Cooling and mounting	$661.00	ESTIMATE The fan and blanks, three shelves, two drawers, cable management and screws.
Network	$19.99	PLACEHOLDER The new 8-port PoE switch for Bay A. The figure is a placeholder, because the PoE model isn't priced.
Monitors	$320.00	ESTIMATE Two lid monitors and their right-angle adapters.
First order total	**$4,641.84**	
Conditional items	$125.88	CONDITIONAL The Wing panel parts and the power adapter for the Wing case strip, bought only if the Wing case can take a panel. If it can't, the connections run out the side of the case, and a TRUE1-to-5-15R jumper (in the BOM at qty 0) feeds the Wing case strip.
All lines	**$4,767.72**	
Already owned	not in any total	Almost all the gear inside.
Lid legs	not costed	OPEN Open until Matt confirms whether they come with the lids.

6. How it rolls out and the risks

The owned gear moves into the cases in stages, starting from a setup closest to today's. Each stage is proved before the next. That's decided.

Weather is an accepted risk, because we often set up outside with no cover. The plan is a fitted rain cover or poly sheet and clamps in the case, with a two-minute cover-and-kill routine. That plan is still open, and I'll have it in place before the first live deploy.

Appendix

Full BOM (BOM v9, 2026-10-03)

Owned gear isn't in any total. Not in this BOM: camera field SDI cable (already owned, 100ft runs), stage power, the XLR trunk cables (owned), and the extension from Bay B to the charging station (open, not costed). "est" means an estimated price. "PLACEHOLDER" lines are estimates I still have to review.

Group	Item	Model / SKU	Qty	Unit	Ext	Price status
Cases	Rolling dual-bay workstation	ProX XZF-AVPRO2X12U2X4U	1	$500.00	**$500.00**	placeholder, to verify (Matt)
Cases	Wing hydraulic flip case	ProX XZF-BXWING	1	$900.00	**$900.00**	placeholder, to verify (Matt)
Cases	Freight, both cases (consolidated)	-	1	$250.00	**$250.00**	placeholder, to verify (Matt)
AVPRO panel	1U 12-hole D-series plate	My Cable Mart D-series	3	$20.00	**$60.00**	est
AVPRO panel	BNC 75 ohm feedthrough (camera SDI)	Neutrik NBB75DFI	8	$8.00	**$64.00**	est
AVPRO panel	HDMI feedthrough	Neutrik NAHDMI-W-B	1	$25.00	**$25.00**	est
AVPRO panel	etherCON feedthrough	Neutrik NE8FDP-B	6	$12.00	**$72.00**	est
AVPRO panel	XLR female chassis	Neutrik NC3FD-L-B-1	1	$6.00	**$6.00**	est
AVPRO panel	XLR male chassis	Neutrik NC3MD-L-B-1	1	$6.00	**$6.00**	est
AVPRO panel	powerCON TRUE1 chassis outlet	Neutrik NAC3FPX (family TBC, D7)	1	$20.00	**$20.00**	est
AVPRO panel	Feed cord for the POWER > WING outlet	12/3 cord with 5-15P, wired to the outlet	1	$12.00	**$12.00**	est
AVPRO panel	D-hole blanking plate	Neutrik DBA-BL	18	$2.00	**$36.00**	est
Spares	BNC feedthrough, spare	Neutrik NBB75DFI	2	$8.00	**$16.00**	est
Spares	etherCON feedthrough, spare	Neutrik NE8FDP-B	2	$12.00	**$24.00**	est
Spares	XLR female chassis, spare	Neutrik NC3FD-L-B-1	1	$6.00	**$6.00**	est
Spares	XLR male chassis, spare	Neutrik NC3MD-L-B-1	1	$6.00	**$6.00**	est
Cable ends	etherCON cable carrier (standard etherCON, over an RJ45 plug)	Neutrik NE8MX-1 (TBC, D7)	11	$3.31	**$36.41**	est
Cable ends	RJ45 plugs, shielded (pack), for the carrier ends	Shielded Cat6A RJ45 plugs, 10-pk	1	$12.00	**$12.00**	est
Cable ends	powerCON TRUE1 cable connector, male	Neutrik NAC3MX-W (TBC, D7)	2	$18.00	**$36.00**	est
Cable ends	powerCON TRUE1 cable connector, female	Neutrik NAC3FX-W (TBC, D7)	2	$18.00	**$36.00**	est
Power	UPS, 2U pure sine (backs booth + Wing)	CyberPower CP1500PFCRM2U	1	$375.00	**$375.00**	est
Power	Rack PDU from the UPS (basic, no surge)	CyberPower CPS1215RM	1	$59.99	**$59.99**	firm; listing check (G5)
Power	Bay B front PDU, metered, drawer lights	Clear Power CPPDU511	1	$149.99	**$149.99**	firm
Power	Bay B rear strip, camera chargers	Tripp Lite RS1215-RA	1	$94.98	**$94.98**	quoted 2026-08-20
Cooling	1U thermostatic exhaust fan	AC Infinity CLOUDPLATE T1	1	$150.00	**$150.00**	est
Cooling	1U perforated blank panel	Steel perforated (Amazon)	3	$12.00	**$36.00**	est
Mounting	1U vented cantilever shelf, 10in deep	AC Infinity 1U vented (B01C9KYUG8)	3	$25.00	**$75.00**	est
Network	Bay A Dante satellite switch, 8-port PoE	PoE model open	1	$19.99	**$19.99**	placeholder: PoE model not priced
Storage	4U rack drawer	StarTech 4UDRAWER	2	$155.00	**$310.00**	est
Cable mgmt	1U cable lacing bar	StarTech 12S-CABLE-LACING-BAR	1	$25.00	**$25.00**	est
Cable mgmt	Hook-and-loop straps	ONE-WRAP + WrapStrap	1	$40.00	**$40.00**	est

Group	Item	Model / SKU	Qty	Unit	Ext	Price status
Hardware	Rack screws + cage nuts	M6 or 10-32 (open; check the rails)	1	$25.00	**$25.00**	est; waits on G6
Cabling	SDI BNC jumpers, panel to ATEM	Belden 1855A / premade BNC-BNC	8	$10.00	**$80.00**	est
Cabling	Cat6A patch, color-coded (lot)	Monoprice SlimRun Cat6A 10-pk	1	$80.00	**$80.00**	est
Cabling	Trunk cable, shielded Cat6A, 15ft	Shielded Cat6A patch, 15ft	2	$12.00	**$24.00**	est
Cabling	HDMI 2.0 jumper, short	HDMI 2.0, 6-10ft	3	$12.00	**$36.00**	est
Cabling	Short power cord, 5-15P to IEC C13	2-3ft	6	$7.00	**$42.00**	est
Cabling	Umbilical power cable (AVPRO > Wing), 14/3 SJOOW	14/3 SJOOW, cut to length (ft)	15	$0.94	**$14.10**	est
Venue power	Power drop cable, 12/3 SOOW (2 x 125ft)	12/3 SOOW, cut to length (ft)	250	$1.63	**$407.50**	est
Venue power	Edison plug, 5-15P (wall end)	Hubbell HBL5266C	2	$14.00	**$28.00**	est
Venue power	Edison connector body, 5-15R (rig end)	Hubbell HBL5269C	2	$18.00	**$36.00**	est
Venue power	Quad box, 4 outlets, 2ft 12/3 tail with 5-15P	BarnDoor QB-M-2FT metal quad box	1	$89.88	**$89.88**	decided *
Monitors	Lid monitor, 24in matte IPS	LG UltraGear 24GS60F-B	2	$150.00	**$300.00**	est
Monitors	Right-angle HDMI + DC adapters (lot)	90-deg HDMI + DC barrel	1	$20.00	**$20.00**	est
First order total					**$4,641.84**	of which $1,650.00 case + freight placeholders
Wing block (conditional, only if the BXWING can take a panel, N1)						
Wing panel	Small D-series plate (8 holes)	D-series plate	1	$20.00	**$20.00**	est
Wing panel	etherCON feedthrough	Neutrik NE8FDP-B	3	$12.00	**$36.00**	est
Wing panel	XLR male chassis	Neutrik NC3MD-L-B-1	1	$6.00	**$6.00**	est
Wing panel	XLR female chassis	Neutrik NC3FD-L-B-1	1	$6.00	**$6.00**	est
Wing panel	powerCON TRUE1 chassis inlet	Neutrik NAC3MPX (family TBC, D7)	1	$20.00	**$20.00**	est
Wing panel	Inlet-to-strip power pigtail (inside the Wing case)	2ft 14/3 SJOOW + Hubbell HBL5269C 5-15R connector body	1	$19.88	**$19.88**	est; part assumed (Sam to review, N32)
Wing panel	Quick-connect terminals for the inlet tabs (pack)	Insulated female quick-connects sized to the NAC3MPX tabs	1	$8.00	**$8.00**	PLACEHOLDER: Sam to review
Wing panel	Strain relief for the pigtail inside the case	Cable clamp + screw-mount tie anchors	1	$6.00	**$6.00**	PLACEHOLDER: Sam to review
Wing panel	D-hole blanking plate	Neutrik DBA-BL	2	$2.00	**$4.00**	est
Wing panel	FALLBACK ONLY: powerCON TRUE1 to 5-15R jumper	Neutrik NAC3MX-W (TBC, D7) + 2ft 14/3 SJOOW + Hubbell HBL5269C	0	$37.88	**$0.00**	est; qty 0. Only if the connections run out the side of the case: the Wing power link then feeds the Wing case strip through it
Wing block total					**$125.88**	
All lines total					**$4,767.72**	

Locked decisions (DESIGN section 5)

All are decided. Each one changes only through a written proposal that I accept.

#	Decision	Reason
1	We implement with the SDI we already own: a BMD converter at each camera, 1080p, coax to the panel. Whether to switch to AOC is open.	HDMI out, SDI in; locking, rugged and already owned
2	Owned SDI field runs are 100ft. Any power, HDMI or data field cables we add should be 125ft or more.	Venue distances vary widely; long is the safe default
3	Three cameras at every event: two Pocket 4K + DJI; more only when rented	That's what runs today (D9)
4	One rear I/O panel, three Neutrik D-series 12-hole plates on Bay A	One touchpoint; field wear never reaches the gear
5	Panel order and labels (POWER > WING last, TRUNK names)	The fabrication drawing (D13)
6	Genders: AVPRO TALKBACK female, IEM male, POWER an outlet; the Wing panel mirrors them	A mic plugs into the talkback jack; the IEM jack feeds a pack; power flows AVPRO → Wing
7	ATEM IN 2 is always the Hollyland RX, and IN 8 is always the UltraStudio. How each connects is open.	Matches the running ATEM
8	Color code (BUILD-SPEC §12); green vs yellow is the split that matters	Anyone setting up matches colors, not port names
9	Labeling: "match the color, match the number"	Anyone setting up matches colors, not port names
10	One UPS (CP1500PFCRM2U) backs the booth and the Wing over the umbilical	The BXWING can't carry a UPS; this is the only way to back the Wing
11	No surge behind the UPS; the ProX X-PC10ASTRO was passed on	Stacked surge behind a UPS isn't good practice, and Bay B's metered CPPDU511 already gives us a meter
12	Runs on one 15A circuit, two preferred, never tied. Power arrives on two 125ft 12/3 SOOW drops with Edison ends: drop 1 → AVPRO (and the Wing through it), drop 2 → the charging station	The whole rig draws well under 15A; venue circuit counts are unknowable (D20)
13	Bay B power: CPPDU511 front (metered, drawer lights) + RS1215-RA rear (camera chargers), chained, utility side	Front lights the drawers; rear outlets face the chargers; one meter (D3)
14	The desk laptops plug into the battery-backed CPS1215RM strip. Decided.	They keep running if venue power drops
15	Switches: owned TL-SG1005P (5-port) = Wing case Dante switch, 3 ports used (4 while the stream-mix laptop stays in use); owned TL-SG105 = Bay A production switch; new 8-port PoE switch = Bay A Dante satellite at U10, powers the AVIO	The AVIO needs PoE in Bay A, and the Wing case needs only 3 ports
16	Bay A mounting: Resi U11; HD Mini + new 8-port PoE switch U10; TL-SG105 + AX21 U8; all on the same 1U vented shelf; Etsy dual mount and Teranex shelf dropped	Every network jumper stays in Bay A; cheapest shelf (D5, D19)
17	Two networks, not three: Dante (isolated) and Production; internet is the AX21's WAN	That's the physical wiring; "three" was a zoning aid
18	Router is the AX21 (older docs say AX55 for the same router)	D11
19	UltraStudio placement is open: rack-mounted or near the Mac Mini, or the desk near the ATEM. The Hollyland RX mounts on top of the flip-up lid when open and stows in a drawer or with the cameras until setup. The Bay A 4U top is left open.	The receiver won't get good signal inside the rack

#	Decision	Reason
20	Lid monitors: 2 × LG 24GS60F-B, 300 nit matte. It may not be bright enough even under a tent or canopy, and direct sun needs angling. Model reopened for brightness research	D14; right-angle adapters for lid clearance
21	LEFT lid = ATEM multiview day one; RIGHT lid = the ProPresenter Mac's second screen, ready for a later move to a Mac Mini	Multiview can't depend on a laptop
22	Cooling: open back primary; 1U thermostatic fan at U12 exhausting to the back; vented blanks in reserve U's	Low heat load; blanks stop airflow short-circuits
23	Umbilical = 5 short cables: PROD, DANTE, TALKBACK, IEM, POWER (15ft powerCON TRUE1 link, 14/3 SJOOW)	The cases sit side by side; TRUE1 cable ends take 6-12mm cable (D20). AES50 is stage-side
24	All five trunks are short; the cases always sit side by side	Q3, D20. Longer runs can be added later
25	The Wing panel is conditional: planned, pending BXWING inspection. If the case can't take one, the connections run out the side of the case	Nobody has confirmed the case takes a panel, but it's likely doable
26	Stage power is out of the build BOM	Separate subsystem; doesn't gate the order (D8)
27	Case + freight figure comes from the BOM ($1,650), labeled placeholder until Matt quotes	One number everywhere (D6)

All open items

Running-config items are left out. G3 and G4 closed on 2026-09-28. Stage power items (N17, N18) are tracked with the separate stage-power project.

Item	Owner	Due	Gates the order	Status
G1 Case and freight quote: AVPRO price, BXWING price, consolidated freight for both (closed AVPRO is 51.5 × 48.2 × 31.6in). BOM placeholders: $500 / $900 / $250	Matt	2026-10-19	Yes: the order gate	OPEN
G2 One matched powerCON TRUE1 family: AVPRO chassis outlet, both umbilical cable ends, and the Wing chassis inlet (only if the Wing panel happens). Plus the etherCON pair: NE8FDP-B panel jacks with NE8MX-1 carriers (standard etherCON), checked against the Neutrik compatibility table before the BOM calls them firm	Matt / vendor; Sam checks the datasheets	2026-10-19	Yes, for the connector lines	OPEN
G5 CPS1215RM listing: confirm Amazon B00077IG3O is the CPS1215RM	Sam	2026-10-19	That line only	OPEN
G6 Rack rails and thread: tapped 10-32, or square-hole for M6 cage nuts? Both are open. Also confirm whether the AVPRO comes with rails built in or they're added after purchase. Matt may know; otherwise it's checked at delivery	Sam (ask Matt first)	on case delivery (assumed by 2026-11-15)	Screw line only. Order it after delivery if Matt doesn't know	OPEN
G8 Case and freight spend ceiling for Matt's quote. Bianca and Sam set it before the Sunny walkthrough	Sam, Bianca	before the Sunny walkthrough	Not stated	OPEN
N1 BXWING inspection: can it take a panel-mount D-series plate? Yes → buy the Wing block. No → the connections run out the side of the case.	Sam (ask Matt first)	on case delivery (assumed by 2026-11-15)	Wing block only	OPEN WING BLOCK
N8 Camera-cable trial: Emily runs the SDI cables we already own (100ft) over a real deploy. Checks pull-through, cable and connector reliability, and picture over length. No camera control. *Whether to switch field camera cable to AOC is an open decision. AOC would let the BMD converters live in the Wing case.*	Emily (trial); Sam, with Matt (spec and cost)	No date set	No	OPEN
N15 Measure today's setup and teardown time before the cutover, and again after, to test the ~40 → ~15 connections and ~30 minutes each way estimates	Sam	2026-10-04, then at the first event after cutover	No	OPEN

Item	Owner	Due	Gates the order	Status
N16 Weather: accepted risk. Setups are often outside with no cover. Keep a fitted rain cover or poly sheet + clamps in the case and a two-minute cover-and-kill plan. A powered open-back rack in sudden rain is the one fast path to a big loss	Sam	before the first live deploy (assumed by 2026-11-15)	No	RISK ACCEPTED PLAN: OPEN
N19 Where is the AV charging station? Drop 2 feeds the Bay B CPPDU511, which passes power through to a separate charging station on a quad box. The quad box is in the first order. Details of the extension are open. A second wall circuit is preferred, not required.	Sam	Closed	No	DECIDED
N6 Wing talkback and IEM: Wing XLR In 8 is Bianca's talkback; Out 8 is her IEM, per the ELIM Production App.	Tyler	Closed	No	CLOSED
N13 Streaming laptop The app's "video stream laptop" and the switcher laptop are the same machine, now called the streaming laptop.	Sam	Closed	No	CLOSED
G7 Laptop power The desk laptops plug into the battery-backed CPS1215RM strip. The separate laptop strip is dropped from the BOM.	Sam	Closed	No	CLOSED
N29 Power inside the Wing case The powerCON link feeds the Wing case strip; the Wing, the ProTools Mac and the TL-SG1005P plug into it. The inlet keeps its twist lock, and inside the case it adapts to a 5-15R socket for the strip.	Sam	Closed	No	CLOSED
N2 M7: LED wall and internet ends The LED wall receiver takes standard Ethernet. The internet drop's far end is still open. It sets the etherCON end count; the BOM already buys the high count.	Sam	2026-10-04 (next service)	No	OPEN
N3 M3: side compartments Do the AVPRO side doors open to usable storage, and what are the inside dimensions? The design doesn't use them.	Sam (ask Matt/ProX)	On case delivery (assumed by 2026-11-15)	No	OPEN
N4 U10 shelf fit The 10in AC Infinity shelf takes the HD Mini and the new 8-port PoE switch side by side.	Sam	On shelf delivery (assumed by 2026-10-15)	No	OPEN
N5 M5: monitor fit LG 24GS60F-B panel height without stand + right-angle adapter depth vs the 16.1in lid; two widths vs 49.6in.	Sam	On case delivery (assumed by 2026-11-15)	No	OPEN
N7 ProTools Mac recording path Wing USB-C to the ProTools Mac, inside the BXWING, settled for the case layout. The ProTools Mac is also a Dante endpoint on the Wing case switch, so the case needs room for both cables.	Tyler	2026-10-04	No	OPEN
N10 M2: AVIO label Read the AVIO model label (AVIOAO2 per the port map). It's confirmed PoE-powered.	Sam	2026-10-04	No	OPEN
N11 R-019: drum kit Dante Does Omar have a separate Dante device at the drum kit? (yes/no)	Sam	2026-10-04	No	OPEN
N12 R-024: Shure combiner label Read the Shure transmit combiner label (UA844+SWB? typed "ua344").	Sam	2026-10-04	No	OPEN
N14 The "regret ask" Long-lead items, freight consolidation, anything hard to add later.	Matt	2026-10-19, with the quote	No	OPEN
N22 Lid monitor model (brightness) The 300-nit LG may not be bright enough even under a tent or canopy. Research brighter screens or a used option; the recorded fallback is a 1000-nit unit for the LEFT lid only. A brighter screen costs more.	Sam	Not set	Not stated (the monitor line's cost)	OPEN
N23 UltraStudio placement Rack-mounted or near the Mac Mini, or the desk near the ATEM.	Sam	Not set	No	OPEN
N24 Connection routes How the Hollyland RX reaches ATEM IN 2 (the CAM 2 jack is one option), how the UltraStudio reaches IN 8, and the ProPresenter Mac's second-screen route to the RIGHT lid.	Sam	Not set	No	OPEN

Item	Owner	Due	Gates the order	Status
N25 Hollyland RX lid mount On top of the flip-up lid: not specced or costed.	Sam	Not set	Not stated (not costed)	OPEN
N26 ATEM retention tray Open, not costed. Build a foam or plywood tray, or secure the ATEM another way.	Sam (ask Matt for suggestions)	Not set	Not stated (not costed)	OPEN
N27 Bay A 8-port PoE switch model Not priced. The BOM carries $19.99 as a placeholder; a PoE model will cost more.	Sam	Not set	Not stated (the switch line's cost)	OPEN
N28 Charging-station extension From the Bay B CPPDU511 to the quad box at the separate charging station: details open, not costed.	Sam	Not set	Not stated (not costed)	OPEN
N30 Camera converters Record the models and count, and whether they're bidirectional.	Sam	Not set	No	OPEN
N31 Shure antennas Confirm the UA8 reading from the label. Read it with the combiner label (N12).	Sam	Not set	No	OPEN
N32 Wing case power adapter parts Review the placeholder BOM lines 55-57 and 59: inlet-to-strip pigtail, terminals, strain relief, fallback TRUE1-to-5-15R jumper.	Sam	Not set	Wing block only	OPEN
Lid legs: confirm with Matt whether legs come on the two removable AVPRO lids. If not, add them as a line item.	Matt (confirm), then Sam	2026-10-19, with the quote	No	OPEN

Cable map

Each row is one signal chain, and panel names match the rear panel. The map is decided except where a route is marked open.

Video

Pocket 4K (wired) — HDMI — Converter — SDI 100ft — Panel CAM 1 — SDI jumper — ATEM IN 1

Pocket 4K — HDMI — Hollyland TX — wireless — Hollyland RX (on the lid) — SDI (route open) — ATEM IN 2

DJI — HDMI — Converter — SDI 100ft — Panel CAM 3 — SDI jumper — ATEM IN 3

Rented cameras — SDI — Panel CAM 4-7 — SDI jumper — ATEM IN 4-7

ProPresenter Mac — USB-C — UltraStudio (placement open) — SDI — ATEM IN 8

ATEM AUX — SDI — HyperDeck HD Mini — USB-C — SSD

ATEM OUT 8 — SDI — Resi — Cat — AX21 > internet

ATEM multiview — HDMI — LEFT lid

ProPresenter Mac — HDMI — LED wall transcoder — Cat x2 — Panel LED 1-2 — field — LED wall

ProPresenter Mac — USB-C — Anker hub — HDMI — Panel CONF OUT — HDMI field — Confidence monitor

ProPresenter Mac — second screen (route open) — RIGHT lid

Audio and Dante

Stage box (DL251) — AES50 — Wing

Wing Dante card — Cat — Wing case switch (TL-SG1005P, 5-port) — trunk 15ft — DANTE TRUNK — Cat — Bay A satellite — Cat + PoE — AVIO (PoE)

AVIO — XLR pigtails — ATEM Ch 1-2

ProPresenter Mac — USB-C Cat — Bay A satellite

ProTools Mac (in case) —Cat (Dante)— Wing case switch

Bianca's talkback mic —XLR— Panel TALKBACK —XLR 15ft— Wing In 8

Wing Out 8 —XLR 15ft— Panel IEM —XLR— Bianca's IEM

Wing —USB-C— ProTools Mac (in case)

Production network and internet

Venue / Starlink —Cat field— Panel INTERNET IN —Cat— AX21 WAN

AX21 LAN —Cat— TL-SG105 —Cat— ATEM, HD Mini, streaming laptop, Anker hub

AX21 LAN —Cat— Resi

AX21 LAN —Cat— PROD TRUNK —trunk 15ft— Wing CONTROL

AX21 LAN —Cat— Panel SPARE

Power

Wall outlet —5-15P— Drop 1 (125ft 12/3 SOOW) —5-15R— UPS CP1500PFCRM2U —mains— CPS1215RM —5-15P > C13— Bay A + desk gear, lids

CPS1215RM —feed cord— POWER > WING outlet —powerCON 15ft 14/3— Wing case strip —mains— Wing, ProTools Mac, TL-SG1005P

Wall outlet (2nd circuit preferred, not required) —5-15P— Drop 2 (125ft 12/3 SOOW) —5-15R— CPPDU511 (Bay B front) —chained— RS1215-RA (rear) —mains— Camera chargers

CPPDU511 —extension (details open, not costed)— Quad box —mains— Separate charging station

CPS1215RM (battery-backed) —mains— Laptops