



800kVA

Silenced Generator

ENGINE Ref: CUMMINS
ALTERNATOR Ref: MECC ALTE

- Hot dip galvanised sound attenuated enclosure
- Average 70 dBA @ 7 metres
- Powder coated grey raal 7035
- Forklift pockets complete with rubber bumpers
- 4 pole circuit breaker with variable earth leakage protection and on/off switch
- Deep sea 8610 loadshare synch control panel
- Battery isolator
- 1300 litre bunded base fuel tank with 3 way valve
- CT for genset paralleling
- Battery charger
- Plastic coated locks and handles
- Lockable canopy with common single key
- Cummins water separator filter
- Sump oil vac pump
- Oil pressure sensor
- Water temperature sensor
- Central lift point
- Hardwire via copper busbar
- Microswitch protection
- Motorised MCCB
- Racor filter

Standby (kVA)	Prime Power (kVA)	Engine Make Type	Governor	Tank Capacity (Litres)	Fuel Consumption per hour (Litres)			dBA @ 7m	Size (mm)	Wet Weight (kg)	Control Panel
					50%	75%	100%				
880	800	CUMMINS	Electronic	1300	85	121	161	75	L - 5550 H - 2300 W - 2200	10482	Deep Sea 8610 Loadshare

South East Depot

Europa Park,
London Road,
Grays, Essex,
RM20 4DB
T: 01375 366766

Midlands Depot

Fairfield Park,
Off Fairfield Road,
Halesowen,
West Midlands
B62 9JL
T: 0121 559 1818

South West Depot

Bradley Road,
Bristol
BS20 7NZ
T: 0117 901 2199

Scotland Depot

Nasmyth Square
Livingston
West Lothian
EH54 5GG
T: 01506 353 399

North East Depot

Station Lane, Birtley,
Gateshead,
Tyne & Wear
DH2 1AJ
T: 0191 4111 200

Email us: power@johnfhunt.co.uk
johnfhuntpower.co.uk