



# 300kVA

## Silenced Generator

ENGINE Ref: CUMMINS  
ALTERNATOR Ref: MECC ALTE

- Hot dip galvanised sound attenuated enclosure
- Powder coated grey raal 7035
- Bunded 600 litre base fuel tank complete with 3 way valve.
- Central lift point and forklift pockets
- Complete with rubber bumpers
- 4 pole circuit breaker with earth leakage protection
- Hardwire via copper bus bars
- Micro switch protection
- CT for genset paralleling
- External contact for autostart
- Motorised MCCB
- Deep sea 8610 genset synch panel
- Plastic coated locks/handles
- lockable canopy with single common key
- Oil extraction pump
- Battery isolator
- Oil pressure sensor
- Water temperature sensor
- Water jacket heater
- Velcb with on/off switch
- Battery charger
- Cummins water separator filter

Standby (kVA)	Prime Power (kVA)	Engine Make Type	Governor	Tank Capacity (Litre)	Fuel Consumption per hour (Litre)			dBA @ 7m	Size (mm)	Wet Weight (kg)	Control Panel
					50%	75%	100%				
330	300	CUMMINS	Electronic	600	31.95	47.93	63.90	68	L - 3900 H - 2230 W - 1200	4180	Deep Sea 8610

### South East Depot

Europa Park,  
London Road,  
Grays, Essex,  
RM20 4DB  
T: 01375 366766

### Midlands Depot

Fairfield Park,  
Off Fairfield Road,  
Halesowen,  
West Midlands  
B62 9JL  
T: 0121 559 1818

### South West Depot

Bradley Road,  
Bristol  
BS20 7NZ  
T: 0117 901 2199

### Scotland Depot

Nasmyth Square  
Livingston  
West Lothian  
EH54 5GG  
T: 01506 353 399

### North East Depot

Station Lane, Birtley,  
Gateshead,  
Tyne & Wear  
DH2 1AJ  
T: 0191 4111 200

Email us: [power@johnfhunt.co.uk](mailto:power@johnfhunt.co.uk)  
[johnfhuntpower.co.uk](http://johnfhuntpower.co.uk)