$$H \cdot dl = NI \tag{1}$$

where

$$dl = l_c$$

$$B = \mu_0 \mu_r H \tag{2}$$

- $\mu_0 = 4\pi \times 10^{-7}$ (Permeability of free space)
- μ_r = Permeability of the material
- $\mu_r \approx 1$ For air
- μ_r in the range of 2000 to 6000 for magnetic steel

$$\frac{B}{\mu_0 \mu_r} = H \tag{3}$$

$$\frac{B}{\mu_0 \mu_r} \cdot l_c = NI \tag{4}$$

$$B = \frac{\Phi}{A_c} \tag{5}$$

$$\frac{\Phi}{\mu_0 \mu_r A_c} \cdot l_c = NI \tag{6}$$

where

$$\frac{l_c}{\mu_0 \mu_r A_c} = R_{\rm rel}$$

$$\Phi R_{\text{\tiny rel}} = NI \tag{7}$$

$$NI = \Phi R_{\text{\tiny rel}}$$
 (7)

$$NI = \Phi R_{\rm rel}$$

where

NI = Magnetomotive Force (MMF),

 $\Phi = \text{Flux},$

 $R_{\rm rel} = \text{Reluctance of the Magnetic Circuit.}$