PREVIEW

Key	Function
→ I	[mpv] play this line (guessing start pos at cursor), stop at end
∱⊸ા	[mpv] play this line from start (no guessing
\ →ı	[mpv] play this line (from cursor), don't stop
_	[mpv] play line by line from this one till EOF

TIMECODE EDITING

J	Join (timecode) with the next line; If on the first of two http lines with timestamp, will made an EDL line.
I	[split] this line into two, guessing a new timecode
mm	mark/unmark word break point, then I. [split] will use this and cursor together. useful when cut time not predicted well.
û← û→	Roll timecode with the previous line for 1 sec
g0	go to the start of subtitle
g8	go to record_out timecode in prev line
g9	go to record_in timecode
gO	append a gap for 5 secs below current line
gN	append a line for 10 minutes below current line, place cursor to input clipname
gB gb	toggle a line between '[B]' or not.
\ c	toggle conceallevel=0, 1

EDITORIAL DECISION / BBC Paper Edit

	MIAD DECISION / DDC I apei Euit
\ p	Enter cherry-pick mode. tabnew on the left, map <
4	pick this line to Vim tab 1, then mark used
\ P	Enter cherry-pick mode (split horizontally), map 🗇
Ą	pick this line to next window, then mark used
☒	reject this line, mark xxx, then go to next line
⋈ (fn ⋈)	toggle between EDL and xxx; toggle to EDL
V	render those highlighted lines with tsv2roughcut
Vx	export those highlighted lines with tsv2fcpxml

https://github.com/scateu/tsv_edl.vim

MPV IPC CONTROL MODE

\\	<pre>init.mpvinput-ipc-server=/ tmp/mpvsocketpause clipname.mp4</pre>
	and enter IPC Control mode. s ← → ↑ ↓ □ d is redefined, and restored at quit
\\	send quit signal via ipc socket to mpv
_	[mpv ipc] toggle play
← →	move, then [mpv ipc] seek to cursor
↑↓	move, then [mpv ipc] seek; reload when clip changed
_	[mpv ipc] play from this line till EOF
<₽, s	[mpv ipc] seek to cursor
ns	[mpv ipc] search next (n), and seek
S	[mpv ipc] sync playhead: seek vim cursor to nearest of mpv timecode, wrap end
\ S	backwards of sync playhead
→I	seek to cursor, [mpv ipc] always play. if in comment region, jump to next 'EDL'
⊹ਰਾ	seek to line head, then →
gi	[mpv ipc] get current timecode, write record_in. overwrite existing.
go	[mpv ipc] get current timecode, write record_out & clipname. overwrite existing

Org mode/Markdown Folding

→i	When not on a EDL//xxx line. do za on ## Header or * Org head
<u></u>	cycle foldlevel=0,1,2
	if on a EDL line, you have to use za zm zr zo zO zM zR
]]	go to next heading
[[go to previous heading

Syntax

$$\begin{split} & EDL \rightarrow 100:00:01,000 \rightarrow 100:00:05,000 \rightarrow 1|_image_|_subtitles.... \\ & EDL \rightarrow 100:00:01,000 \rightarrow 100:10:01,422 \rightarrow 1|_clipname_|_[B] this is B-Roll \\ & EDL \rightarrow 100:00:01,000 \rightarrow 100:10:01,422 \rightarrow 1|_clipname_|_subtitles.... \end{split}$$