Shreevathsa Acharya

Keychron Q60 · 3434:01C0 · QMK / VIA

Q60 HHKB

The Q60 set up like an HHKB Professional: what Fn does, the extra lighting layer, and how to back up or change the layout.

Script, README and interactive guide: github.com/shrac1234/Q60_HHKB

Hold Fn



Top legend: what the key types normally. Blue legend: what it types while you hold the outlined key.

Fn functions

ARROWS AND PAGING

- Fn [— Up
- Fn / — Down
- Fn ; — Left
- Fn ' — Right
- Fn K — Home
- Fn , — End
- Fn L — Page Up
- Fn . — Page Down

EDITING

- BS — Backspace
- Fn BS — Delete (forward)
- Fn ` — Delete (forward)
- Fn \ — Insert
- Fn Tab — Caps Lock

FUNCTION ROW

- Fn 1 … 0 — F1 to F10
- Fn - = — F11, F12

MEDIA

- Fn A — Volume down
- Fn S — Volume up
- Fn D — Mute
- Fn F — Eject (macOS)

NUMPAD AND SYSTEM

- Fn H J — Numpad * and /
- Fn N M — Numpad + and –
- Fn Enter — Numpad Enter
- Fn I O P — PrtSc, ScrLk, Pause
- Fn Esc — Power

Shreevathsa Acharya

Hold Fn + Right Shift: lighting and NKRO



TURN UP

- `Tab` Backlight on / off
- `Q` Next effect
- `W` Brighter
- `E` Hue forward
- `R` More saturation
- `T` Faster effect

TURN DOWN

- `A` Previous effect
- `S` Dimmer
- `D` Hue back
- `F` Less saturation
- `G` Slower effect

OTHER

- `N` NKRO on / off

Mac / Windows switch

The slide switch on the side picks the base layer. Both use the HHKB bottom row, Alt ◇ Space ◇ Alt; only what ◇ and Alt send differs.

MAC (LAYER 0)

`Option` `Cmd` `Space` `Cmd` `Option`

WINDOWS (LAYER 1)

`Alt` `Win` `Space` `Win` `Alt`

Backing up and changing the layout

ALLOW ACCESS (DO THIS FIRST)

Linux only lets root write to the keyboard's settings interface. This udev rule gives your user access every time the board is plugged in, and lets VIA in Chrome connect:

```
echo 'KERNEL=="hidraw*", ATTRS{idVendor}=="3434", ATTRS{idProduct}=="01c0", MODE="0660", TAG+="uaccess"' | sud
o tee /etc/udev/rules.d/70-keychron-q60.rules
sudo udevadm control --reload && sudo udevadm trigger
```

Quick one-off alternative, lost on every replug or reboot: `sudo chmod a+rw /dev/hidraw9`

SCRIPT COMMANDS

```
python3 hhkb_q60.py backup             # save every layer to q60_backup_<timestamp>.json
python3 hhkb_q60.py apply              # back up (never overwrites), write HHKB layout, verify
python3 hhkb_q60.py restore FILE.json  # write a backup back
```

EDIT SINGLE KEYS IN VIA

Open usevia.app in Chrome or Chromium and authorize the Q60. Layers: 0 Mac, 1 Windows, 2 Fn, 3 Fn + Right Shift, 4 and 5 free.