Sakhi — Module 4 UI & Elements Handoff Specification

Emergency SOS & Personal Safety (SRS Sections 6.1–6.6) • Complete Screen Architecture, Button Routing & Component Tokens

1. Design System Continuity & Visual Language Establishers

Module 4 extends Sakhi's established visual identity from Modules 1–3 (soft blush-lavender surfaces, deep plum primary interactive controls, rounded white cards, pastel icon containers, and warm humanist typography) into high-clarity emergency response screens. To ensure zero cognitive friction during moments of distress, standard navigation and configuration actions remain in **Sakhi Deep Plum (#5A1868)**, while immediate life-safety triggers and **112 National Emergency** actions use high-contrast **Emergency Crimson (#C92A49)**.

Token Name	Hex / Value	UI Element Usage in Module 4	Accessibility & State Rule
Surface Canvas	#FDF8FB	Primary screen background across all 8 Module 4 screens	Maintains warm, non-clinical continuity with Modules 1–3
Card Container	#FFFFFF (Border #EFE3EE)	Station cards, contact rows, workflow steps, checklist items	16dp corner radius, 1dp soft lavender-grey border, 16dp padding
Brand Primary (Plum)	#5A1868	Directions button, active toggles, primary contact badge, Save CTA	WCAG AAA contrast (10.4:1) against white text (#FFFFFF)
Emergency Crimson	#C92A49	Tap SOS central button, top-bar SOS pill, Call 112 CTAs, Live Alert pill	Reserved strictly for SOS activation, 112 calling, and Stop Sharing
Verified / GPS Mint	#1E7E55 (Bg #E3F7ED)	GPS Active banner, distance badges (0.8 km), workflow checkmarks	Displayed only when OS location permission or SMS delivery is confirmed
Compliance Amber	#8A5300 (Bg #FFF3DC)	Mandatory non-notification disclaimer banner (SRS Section 6.4)	Always visible on Nearest Police Station map & unlinked API state
Icon Badges (64dp / 44dp)	#FCE8EC / #E3F7ED / #FFF1DB / #EFE6F7	4 circular category buttons (64dp) and list row leading icons (44dp)	2dp stroke rounded vector icons centered with 50% container ratio

2. Master Button-to-Screen Navigation & Functional Matrix

Every interactive control on the Module 4 Safety Hub and its child screens is mapped below to its exact purpose, required OS/backend operation, and target destination UI screen so engineering teams can wire complete end-to-end navigation without dead-end buttons.

Source Screen	Button / Control Label	Element Type & Style	Functional Purpose & SRS Requirement	Target Screen / Modal Opened
Screen 1: Safety Hub	**Tap SOS** (Center Map) & **SOS** (Top Bar Pill)	88dp pulsing crimson circle & 36dp top-right crimson pill (#C92A49)	Initiates urgent assistance workflow with short confirmation guard (SRS 6.2 & 6.3.1)	Opens **Screen 2: SOS Confirmation (3s Countdown) & Active Workflow**
Screen 1: Safety Hub	**Shortcut** (Top Bar Gear Icon)	24dp deep plum gear icon with label (#5A1868)	Configures OS-level power-button/shake shortcut & safe test mode (SRS 6.2)	Opens **Screen 6: Safety History, Discreet Shortcut & Checklist**
Screen 1: Safety Hub	**Emergency Contacts** (Quick Circle 1)	64dp soft pink circle (#FCE8EC) with crimson group icon	Manages trusted contacts, primary contact, and alert toggles (SRS 6.5)	Opens **Screen 4: Emergency Contacts & Location Management**
Screen 1: Safety Hub	**Nearest Police** (Quick Circle 2)	64dp soft mint circle (#E3F7ED) with green police shield pin	Finds verified nearby police stations with distance, navigation & call (SRS 6.4)	Opens **Screen 3: Nearest Police Stations & Verified Directory**
Screen 1: Safety Hub	**Safety Tips** (Quick Circle 3)	64dp soft peach circle (#FFF1DB) with amber shield-star icon	Displays commute safety guidance and discreet SOS usage instructions	Opens **Screen 7: Emergency Helplines & Personal Safety Tips**
Screen 1: Safety Hub	**Helplines (112)** (Quick Circle 4) & **Emergency Helplines** Row	64dp lavender circle (#EFE6F7) & Quick Safety Action card row 4	Provides one-tap dialing to 112, 1091 Women Helpline, 181, and 108 (SRS 6.3.4)	Opens **Screen 7: Emergency Helplines & Personal Safety Tips**
Screen 1: Safety Hub	**Share my live location** (Row 1)	Full-width card row with pink radar badge & mint "Active" pill	Starts/manages real-time GPS link sharing with consent controls (SRS 6.5.4)	Opens **Screen 5: Share Live Location Map & Consent Controls**
Screen 1: Safety Hub	**SOS Activation History** (Row 2)	Full-width card row with lavender clock-list badge	Displays chronological log of past SOS activations and delivery status (SRS 6.3.7 & 6.5.6)	Opens **Screen 6: Safety History, Discreet Shortcut & Checklist**

Source Screen	Button / Control Label	Element Type & Style	Functional Purpose & SRS Requirement	Target Screen / Modal Opened
Screen 1: Safety Hub	**Safety Checklist & Discreet Trigger** (Row 3)	Full-width card row with amber clipboard-shield badge	Interactive pre-travel checklist and false-trigger prevention test mode (SRS 6.2)	Opens **Screen 6: Safety History, Discreet Shortcut & Checklist**

3. Child Screen Controls, Modals & Admin Routing (SRS 6.2–6.6)

Once a user navigates from the main Safety Hub into any operational screen, every secondary button on those screens executes a deterministic action or opens a dedicated modal state as specified below.

Screen Context	Button / Interactive Control	Action Triggered / UI State Change	SRS Compliance & Engineering Guardrail
Screen 2: SOS Active Workflow	**Trigger SOS Now** vs. **Cancel (I'm Safe)**	Bypasses 3s timer to dispatch alert immediately, or aborts activation and logs as "Cancelled"	Prevents accidental pocket/shake triggers from dispatching false emergency reports (SRS 6.2)
Screen 2: SOS Active Workflow	**Call 112 National Emergency Helpline**	Launches OS native phone dialer pre-populated with `tel:112`	Explicitly informs user if automated police API is not connected (SRS 6.3.4 & 6.4)
Screen 2, 4 & 5	**Stop Location Sharing & End SOS**	Revokes active live-tracking token, stops background GPS polling, marks event Resolved	Fulfills SRS 6.5 requirement to stop location sharing immediately when emergency ends
Screen 3: Nearest Police	**Directions / Navigate** & **Call Station**	Deep-links station coordinates to Google/Apple Maps turn-by-turn nav, or dials station landline	Accompanied by mandatory amber banner clarifying map lookup does not notify police (SRS 6.4)
Screen 4: Emergency Contacts	**+ Add Contact** (Top Right)	Opens the **Add Trusted Emergency Contact Bottom Sheet Modal** (shown on Screen 5)	Validates +91 mobile number, assigns relationship tag, and sends opt-in consent SMS (SRS 6.5.1)

Screen Context	Button / Interactive Control	Action Triggered / UI State Change	SRS Compliance & Engineering Guardrail
Screen 4: Emergency Contacts	**Set as Primary** / **Selected for SOS Alert** Toggle / **Delete Icon**	Promotes contact to Primary badge, toggles inclusion in SOS broadcast, or removes contact	Enforces at least 1 Primary Contact when SOS contact alerts are enabled (SRS 6.5.1–6.5.3)
Screen 6: History & Settings	**Run Safe Test Mode (Avoid False Triggers)**	Simulates discreet shortcut activation locally without sending external SMS/police alerts	Directly satisfies SRS 6.2 requirement to test discreet activation and prevent false alarms
Screen 8: SOS Administration	**6 Admin Management Cards** (Contacts, Directory, 112 API, Status, Logs, Abuse)	Opens role-restricted admin configuration views and delivery/false-trigger audit tables	Strictly restricted via RBAC with mandatory immutable audit logging on every query (SRS 6.6)

4. Mandatory Legal, Privacy & Operational Guardrails for Live Development

When implementing the Module 4 UI screens in Flutter / React Native / Native Android & iOS, developers must enforce five non-negotiable SRS compliance rules in the presentation and state layers:

- **No Unconfirmed Police Notification Claims (SRS 6.3.8, 6.3.9 & 6.4):** The UI must never display "Police Notified" or "Police Dispatched" unless an authorised government 112 ERSS API integration returns a verified cryptographic confirmation receipt. In standard mode, Screen 2 displays an amber status row instructing the user to tap **Call 112**, and Screen 3 displays the prominent amber disclaimer banner above the map.
- **Explicit OS Location & Consent Gating (SRS 6.3.2, 6.3.6 & 6.4):** If OS location permission is denied or set to "Never", the top mint status pill on Screen 1 automatically switches to an amber action banner (*"Location Permission Required for SOS — Tap to Enable"*). Alerts sent to trusted contacts only include the user's name, emergency profile, timestamp, and location link when consented on Screen 5.
- **Accidental Trigger & False-Alarm Protection (SRS 6.2):** Both manual taps and discreet hardware/shake shortcuts route through the 3-second confirmation card on Screen 2 with haptic vibration and a prominent **Cancel (I'm Safe)** button, paired with the sandboxed **Run Safe Test Mode** on Screen 6.
- **User-Controlled Live Location Termination (SRS 6.5):** Active location sharing surfaces a persistent high-visibility **Stop Location Sharing** button across Screen 2, Screen 4, and Screen 5 so the user can terminate tracking with a single tap the moment the emergency ends.
- **Tightly Restricted Admin Event Records (SRS 6.6):** Screen 8 (SOS Administration) is hidden from member builds and accessible only to authenticated platform administrators with explicit `SOS_ADMIN_ROLE` permissions, displaying a persistent audit-log notice banner.