

Arduino to Teensy GPIO Mapping Guide

Teensy Netname Arduino Arduino Netname Teensy

		+5V	+5V		
PTC0	AD0	PA0-22	23-PA1	AD1	PTC1
PTC2	AD2	PA2-24	25-PA3	AD3	PTC3
PTC4	AD4	PA4-26	27-PA5	AD5	PTA5
PTC6	AD6	PA6-28	29-PA7	AD7	PTC7
PTA15	AD15	PC7-30	31-PC6	AD14	PTA14
PTA13	AD13	PC5-32	33-PC4	AD12	PTA12
PTC11	AD11	PC3-34	35-PC2	AD10	PTC10
PTC9	AD9	PC1-36	37-PC0	AD8	PTC8
PTE26	PD7	PD7-38	39-PG2	PG2	PTB1
PTB0	PG1	PG1-40	41-PG0	PG0	PTC5
PTD7	D7	PL7-42	43-PL6	D6	PTD6
PTD5	D5	PL5-44	45-PL4	D4	PTD4
PTD3	D3	PL3-46	47-PL2	D2	PTD2
PTD1	D1	PL1-48	49-PL0	D0	PTD0
PTB19	PB3	PB3-50	51-PB2	PB2	PTB18
PTA17	PB1	PB1-52	53-PB0	PB0	PTA16
		GND	GND		

PTB10	SS
PTB11	SCK
PTB16	MOSI_RX1
PTB17	MISO_TX1
PTE24	KBD_INT
PTE25	KBD_DAT
A21	S1
A22	S2
PTB3	SDA0
PTB2	SCL0

ADDRESS

Arduino	A15	A14	A13	A12	A11	A10	A9	A8	A7	A6	A5	A4	A3	A2	A1	A0
Teensy	PTA15	PTA14	PTA13	PTA12							PTA5					
					PTC11	PTC10	PTC9	PTC8	PTC7	PTC6		PTC4	PTC3	PTC2	PTC1	PTC0

DATA

Arduino	D7	D6	D5	D4	D3	D2	D1	D0
Teensy	PTD7	PTD6	PTD5	PTD4	PTD2	PTD2	PTD1	PTD0