



PROD WATCH

Time to Complete System

User Manual — v1.0

Powered by **SRSSupport** · Hosted by **SRSCloud**

VERSION 1.0

ANDROID TABLET

ALL ROLES



What is Prod Watch?

Prod Watch is a shopfloor timing system. When you start working on an assembly job, press **START**. When you finish, press **STOP**. The system records how long the job took, which workstation it was done on, and which work order it belongs to.

■ **No technical knowledge needed.**

If you can use a smartphone, you can use Prod Watch.

User Roles

Every user has a role that controls what they can see and do.

■ OPERATOR Start/stop own timers · View own history · Cancel within 60s	■ SUPERVISOR All Operator actions · View all history · Cancel/adjust any timer · Wall Board
■ MANAGER All Supervisor actions · Dashboard · Export CSV	■ ADMINISTRATOR All Manager actions · User management · Delete timer records

Signing In

Open **Chrome** on your tablet and go to the Prod Watch web address your supervisor gave you.

- 1 Tap the Username box and type your username**

For example operator1. Usernames are not case-sensitive.
- 2 Tap the Password box and type your password**

Characters appear as dots to keep it private.
- 3 Tap Sign In**

If correct you go to the Timer screen. A red error means something was typed incorrectly.

■ ■ **Too many wrong attempts locks you out for 15 minutes.**

After 10 failed attempts wait 15 minutes or contact your supervisor.

Starting a Job Timer

After signing in you will see the Timer screen. Fill in the job details and tap the green **START** button.

- 1 Enter the Item Number (required)**

Type the part number e.g. PHL-1001, or tap Scan to use the camera.
- 2 Enter the Workstation (optional)**

Type or scan your workstation identifier such as WS-01.



- 3 Enter the W/O Number (optional)**
Type or scan the Work Order number for this job.
- 4 Tick Time Check if this is a measured timing**
Leave unticked for a simple time task.
- 5 Tap the green START button**
The timer starts immediately.

■ ■ **You can only have one timer running at a time.**
Stop your current job before starting a new one.

Form Fields Explained

Field	Required?	What to enter
Item Number	■ Required	The part/assembly number. Letters, numbers, hyphens and underscores only, max 40 chars. Can be scanned.
Workstation	Optional	Workstation identifier e.g. WS-01. Can be scanned. Appears in all history views and exports.
W/O Number	Optional	Work Order number e.g. WO-10042. Can be scanned. Appears in history and CSV for traceability.
Time Check	Optional tick box	Marks this as a measured timing. Shows as a blue Time Check badge on all history entries.

Scanning a Barcode or QR Code

Every field with a Scan button can be filled by scanning a barcode or QR code with the tablet camera.

- 1 Tap the Scan button next to the field you want to fill**
The camera screen opens.
- 2 Allow camera access (first time only)**
Tap Allow when Chrome asks to use the camera.
- 3 Point the camera at the barcode or QR code**
Hold steady between the corner markers. The system reads it automatically.
- 4 The field fills in automatically**
The camera closes and the field is filled. Check it looks correct.

■ **Torch button**
In low light a Torch button appears at the bottom of the camera screen.

Stopping a Job Timer

Once started the screen shows a running clock. Tap **STOP** as soon as you finish the job.

■ ■ **Works across devices and after a refresh.**

If you refresh the page or sign in from a different device, your timer restores automatically with the correct elapsed time.

Cancelling a Timer

Within 60 seconds: Tap Cancel next to STOP. Confirm to cancel or tap Keep Running to go back.

After 60 seconds: Only a Supervisor or above can cancel. They must enter a reason, which is permanently recorded.

■ **All cancellations are permanently recorded.**

Who cancelled it, when, and the reason are stored in the audit trail and cannot be deleted.

Viewing Your History

Tap the menu (■) then History. The default view shows the last 7 days. Each entry shows the item number, workstation, W/O number, start/end times, and duration. A blue Time Check badge marks measured timings.

Supervisor: Viewing All History

As a Supervisor, the History screen has extra filters — search by Operator ID, Item Number, and Status.

■ **Finding stuck timers**

In the Status dropdown select Active (stuck timers) and tap Search. This searches all time so any stuck timer appears regardless of when it started.

Supervisor: Cancelling or Adjusting a Timer

As a Supervisor you can cancel or adjust any timer — including those over 60 seconds old. A reason is always required and is permanently recorded.

■ **All changes are permanently recorded.**

Your name, the date and time, and the reason you gave are stored permanently.

Manager: The Dashboard

Tap ■ then Dashboard. The summary cards show: **Active Now** — timers currently running. **Last 24 Hours** — jobs completed today. **Last 7 Days** — jobs this week. **Item Types** — distinct part numbers recorded.

Use the filters to narrow by date range, item number, or operator, then tap Search.

Manager: Exporting to CSV

On the Dashboard, set your filters and tap Export CSV. The file downloads to your device and opens in Excel or Google Sheets. The export includes all fields: Item Number, Operator, Workstation, W/O Number, Start/End times, Duration, Time Check flag, and Status.

■ **The file opens correctly in Excel.**

The CSV includes special formatting so times and dates display correctly without manual changes.

Wall Board

Tap ■ then Wall Board. Shows all currently running jobs — designed for a monitor or TV on the shopfloor wall. Available to Supervisors, Managers, and Administrators.

Each tile shows the item number, operator name, elapsed time (live), workstation, and W/O number. Tile colours change automatically:

Green border	Job running normally
Amber border	Job has been running more than 2 hours
Red border	Job has been running more than 4 hours

The board auto-refreshes every 5 minutes. Tap Refresh for an instant manual update.

Administrator: Managing Users

Tap ■ then Admin to manage user accounts.

Adding a New User

- 1 Tap + New User**
Top-right of the User Management screen.
- 2 Fill in the details**
Username: letters and numbers only. Full Name: their real name. Password: at least 8 characters. Role: select from the dropdown.
- 3 Tap Create User**
The account is created immediately.

Resetting a Password

- 1 Find the user in the list and tap Reset PW**
- 2 Type a new password (minimum 8 characters) and tap Reset Password**
The user can sign in with the new password straight away.



Deleting a Timer Record

Go to History, find the record, and tap the delete (■) button. A confirmation box appears before anything is deleted.

■ ■ Deletion is permanent and cannot be undone.

The timer record and its audit log are removed from the database permanently.

Troubleshooting

I cannot sign in

Check username and password are typed correctly. Passwords are case-sensitive. After 10 failed attempts wait 15 minutes. Contact your administrator if your account may be disabled.

The Scan button is not working

Make sure you are using Google Chrome (version 83 or later). If camera permission was denied, tap the padlock icon in the address bar, change Camera to Allow, then refresh.

My timer is not showing after a refresh or on a different device


Tap the menu then Timer. The system restores your active timer automatically from the server.

I see the active timer error but cannot stop it

Go to History, set Status to Active (stuck timers), tap Search. Administrators can delete the stuck record using the delete button.

The page is not loading

Check the tablet is connected to Wi-Fi. Pull the page down to refresh. If the problem continues wait 30 seconds and try again.



PROD WATCH

Time to Complete System — User Manual v1.0

Powered by **SRSSupport** · Hosted by **SRSCloud**

Philtronics Ltd