

BrightBeam SLB220 Smart Light Bulb

Introduction

Welcome to the future of lighting with the BrightBeam SLB220 Smart Light Bulb. Transform any room in your home with smart, efficient, and customizable lighting that works seamlessly with your existing smart home ecosystem.

Key Features

- **Voice Control:** Compatible with Amazon Alexa and Google Assistant for hands-free operation.
- **Customizable Lighting:** Over 16 million color options and adjustable brightness levels.
- **Remote Access:** Control your lights from anywhere via the BrightBeam app.
- **Energy Efficient:** Designed to reduce electricity consumption while providing optimal brightness.

Setup Instructions

Unboxing

1. Carefully remove the Smart Light Bulb from the packaging.
2. Ensure you have the BrightBeam app downloaded on your smartphone.
3. Verify the contents: BrightBeam SLB220 bulb, quick-start guide, warranty card.

Installation

1. Turn off the power supply to the light socket.
2. Screw the SLB220 bulb into the socket securely.
3. Turn the power supply back on.

Connecting to Wi-Fi

1. Open the BrightBeam app and create an account if you haven't already.
2. Select 'Add Device' and follow the onscreen instructions.
3. Ensure your phone is connected to a 2.4GHz Wi-Fi network.
4. Turn the bulb on and off three times to enter pairing mode.
5. When the bulb blinks rapidly, tap 'Confirm' in the app.
6. Enter your Wi-Fi password to sync the bulb.

Usage Instructions

Adjusting Brightness and Colors

- Use the BrightBeam app to select brightness levels and colors.
- Save favorite settings for easy access.

Scheduling

- Set custom schedules to automate lighting based on your daily routine.

Integration with Smart Home Systems

- Pair with Alexa or Google Home using the 'Link Device' feature within their respective apps.

Troubleshooting Guide

Wi-Fi Connectivity Issues

- **Issue:** Bulb won't connect to Wi-Fi.
- **Solutions:** Ensure you're connected to a 2.4GHz network. Reset the bulb and router. Disable any VPNs on your phone.

Resetting to Factory Settings

- Turn the bulb on and off five times consecutively. The bulb will blink slowly to indicate a successful reset.

Maintenance

- Keep the bulb firmware updated via the BrightBeam app.
- Avoid using the bulb in temperatures exceeding its operating range of -10 to 40°C (14 to 104°F).

FAQs

- **Q: Can the bulb be used outdoors?**
- **A: No, the SLB220 is rated for indoor use only.**
- **Q: Can I connect multiple bulbs at once?**
- **A: Yes, you can add multiple bulbs to the same app account.**

Technical Specifications

- **Power Consumption:** 9.5 watts
- **Lifespan:** 25,000 hours
- **Lumens:** 800
- **App Compatibility:** iOS and Android

Customer Support

For further assistance, contact our customer support team at support@brightbeam.com or call 1-800-555-0199. Warranty coverage details are available on our website.