

GOOD TRUNCATIONS FOR COMPUTING INTEGRAL BASES

ABSTRACT. We provide good truncation bound that speed up the computation of integral basis.

1. INTRODUCTION

Integral basis are very useful in real life.

Given a polynomial $f \in K[x, y]$ monic in Y , we wish to compute the local contribution to the integral basis at the origin or the local integral basis at the origin.

2. THE DETERMINACY

In this section we show:

- (1) An upper bound for the determinacy can be found fast reducing the polynomial modulo any prime number p .
- (2) If we truncate the polynomial f by standard degree at the determinacy, the characteristic exponents of f will not change.
- (3) The integrality exponent of f can be computed from the characteristic exponents, so we can compute very fast the integrality exponent.

Remark: the coefficients of the Puiseux expansions might change, but in all examples we tried, the coefficients don't change after truncation.

3. LOCAL CONTRIBUTION TO THE INTEGRAL BASIS AT THE ORIGIN

In this section we focus on the computation of the local contribution at the origin.

We use the following result.

Proposition 3.1. (See [1, Proposition 23].) *Let $F \in K[[X]][Y]$, separable of degree d . Suppose given a modular factorisation*

$$F \equiv F_0 F_1 \dots F_s \pmod{X^{N_0}}, \quad N_0 > 2\kappa \tag{1}$$

where $F_0 \in K[[X]][Y]$ is a unit and for all $i \geq 1$ either F_i or its reciprocal polynomial $\tilde{F}_i$ is monic, and

$$\kappa = \kappa(F_0, \dots, F_s) := \max_{I, J} \kappa(F_I, F_J),$$

the maximum of the lifting orders being taken over all disjoint subsets $I, J \subset \{0, \dots, s\}$, with $F_I = \prod_{i \in I} F_i$. Then there exists uniquely determined analytic factors $F_0^, F_1^*, \dots, F_k^*$ such that $F = F_0^* F_1^* \dots F_k^*$, where*

$$F_i^* \equiv F_i \pmod{X^{N'_0 - \kappa}}.$$

Moreover, starting from (1), we can compute the F_i^ up to any precision $N \geq N_0 - \kappa$ in $\mathcal{O}(dN)$ operations over K .*

For computing Puiseux expansions we use the following algorithm:

Algorithm 1 Half-RNP(H, P, n, π)

- 1: **Input:** $P \in \mathbb{K}[Z]$ irreducible; $H \in \mathbb{K}_P[X, Y]$ separable and monic in Y , with $d := \deg_Y(H) > 0$; $n \in \mathbb{N}$ (truncation order); π the current truncated parametrisation (initial call: $P = Z$, $\pi = (X, Y)$)
 - 2: **Output:** All RPEs R_i of H such that $n - v_i \geq r_i$, with precision $(n - v_i)/e_i \geq r_i/e_i$
-

The notation in the algorithm is as follows:

- $\delta = v_X(\text{Res}_Y(F, F_Y))$
- We can consider $\mathbb{K}_P = \mathbb{Q}$, and H is our polynomial f .
- $v_i = v_X((F_i)_Y)$. If f has only one branch, then this number is the integrality exponent. If f has many branches, then v_i can be bigger than the integrality exponent (
- The integer $e_i \in \mathbb{N}$ is the ramification index of F_i , equal to the largest denominator or the number of expansions in the branch.
- The *regularity index* r of a Puiseux series S of F with ramification index e is the least integer $N \geq \min(0, ev_X(S))$ such that, if

$$\lceil S \rceil^{N/e} = \lceil S' \rceil^{N/e}$$

for some Puiseux series S' of F , then $S = S'$. We call $\lceil S \rceil^{r/e}$ the *singular part* of S in F .

- We denote by $(R_i)_{1 \leq i \leq \rho}$ the rational Puiseux expansions of F . To any R_i , we will always associate the following notations:
 - e_i , f_i , and r_i will respectively denote the ramification index, the residual degree, and the regularity index of R_i ,
 - we define $v_i \in \mathbb{Q}$ as $v_X(F_Y(S))$, for any Puiseux series S associated to R_i .

The same notations will be used if S_i (or S_{ijk}) denotes a Puiseux series. If we omit the index i , we will use the notations e , f , and r for the first three integers.

To give general bounds for these numbers we define a new number:

$$\alpha = \sum r_i,$$

the sum taken over all Puiseux branches. This number is bigger than the integrality exponent but not much bigger. And it is clear that $r_i \leq \alpha$.

For example, if we have only one branch with seven Puiseux expansions and one characteristic exponent $1/7$, then $\alpha = 1$ and the characteristic exponent is $6/7$.

We have:

- $r_i \leq \alpha$ (clear by definition)
- $v_i \leq \text{IntExp}_X \leq \alpha$ when there is only one branch, but not in general. Proof: if $F_i = (Y - \gamma_1) \dots (Y - \gamma_r)$ then $(F_i)_Y(\gamma_1) = (1 + \gamma_1)(\gamma_2 - \gamma_1) \dots (\gamma_r - \gamma_1) + 0 + 0 + \dots + 0$. The first factor in the first term has order 0 at X , so the order of the product is equal to IntExp_X (it is the same formula).

The steps are now as follows:

- (1) This proposition says that if we truncate f at precision n in X and we factorize the truncated polynomial $\bar{f}$ in $K[[X]][Y]$, we will get the factors of f with precision $n - \kappa$.
- (2) We are interested in computing the factors with precision at least equal to the integrality exponent in X of f , we call this number IntExp_X . That is, we need $n - \kappa \geq \text{IntExp}_X$.
- (3) In that paper the authors provide the bound $\kappa \leq \delta/2$, where $\delta = 2\text{IntExp}_X$, so $\kappa \leq \text{IntExp}_X$ and it is enough for us to consider $n \geq 2\text{IntExp}_X$.
- (4) For the computation of the integral basis we also need the singular part of the Puiseux expansions. If we want to compute the Puiseux expansions from the factors $f_1, \dots, f_s$, we would need to compute the factors with precision higher than the integrality exponent.

However if we compute the Puiseux expansions from $\bar{f}$, the same proposition says that we will obtain the Puiseux expansions with precision at least IntExp_X , and hence the singular part will be correctly computed.

- (5) I am not sure about this last step. In any case, we can compute the singular part of the Puiseux expansions by truncating at $\alpha + 2 \times \text{IntExp}_X$ (a little larger than $3 \times \text{IntExp}_X$). The argument is as follows:
 - (a) We apply Half-RNP algorithm (page 13) to one factor F_i .
 - (b) In this case $v_i = v_X((F_i)_Y)$ and this is smaller than IntExp_X (the integrality exponent of one branch is smaller than that of the full polynomial).
 - (c) r_i may not be smaller than the integrality exponent but we have $r_i \leq \alpha$.
 - (d) So by the algorithm we need $n \geq v_i + r_i$, and $v_i + r_i \leq \alpha + \text{IntExp}_X$. That is, we need the factors F_i developed to degree $\alpha + \text{IntExp}_X$ and by Proposition 3.1 we can get this by computing a factorization of F modulo $\alpha + 2\text{IntExp}_X$.
- (6) Putting everything together, we can truncate the powers of X of f at order $\alpha + 2\text{IntExp}_X$ and we will be able to compute the correct factors up to the integrality exponent and the singular part of the Puiseux expansions and hence we will compute the correct integral basis.

4. LOCAL INTEGRAL BASIS AT THE ORIGIN

When we are interested in the local integral basis at the origin we can also truncate powers of Y .

One possible approach is the following:

- (1) Applying again [1, Proposition 23] in terms of Y with high enough precision, we obtain that the factors at the origin are uniquely determined and they are the same factors as the factors obtained when we develop the factorization in terms of X , so we are able to recover the correct information.

- (2) The factor g_0 however corresponds to the branches of f at $Y = 0$ and the factor f_0 corresponds to the branches of f at $X = 0$, so we cannot recover the Puiseux expansions of f_0 from the Puiseux expansions of g_0 .
- (3) Hence when we apply a truncation in Y we can expect to compute correctly the local integral basis but not the local contribution.

We now formalize these ideas and calculate the required precision. For this, we need to be able to go from Puiseux expansions in X to Puiseux expansions in Y (N_0 and κ are the numbers to be determined, and they are possibly different for X -truncations and Y -truncations).

- (1) We start with a polynomial $F \in K[X, Y]$ with analytic factorization in $K[[X]][Y]$:

$$F = F_0^* F_1^* \dots F_s^*,$$

where $F_k^* \in K[[X]][Y]$ and F_0^* is the unit corresponding to the branches outside the origin). Let d_k be the degree in Y of F_k^* and let e_k be the largest denominator of the Puiseux expansions of F_k^* .

- (2) If we have a factorization

$$F \equiv F_0 F_1 \dots F_s \pmod{X^{N_0}}, \quad (2)$$

then by Proposition 3.1, $F_k \equiv F_k^* \pmod{X^{N_0 - \kappa}}$.

- (3) Now we truncate in Y . Let $\bar{F}^Y$ be the truncation of F modulo Y^{N_0} . We can factorize this polynomial in $K[[X]][Y]$ as

$$\bar{F}^Y \equiv H_0 H_1 \dots H_s \pmod{X^{N_0}},$$

and we want to know if $H_k \equiv F_k^* \pmod{X^{N_0 - \kappa}}$ for $k > 0$ (we cannot expect $H_0 \equiv F_0^* \pmod{X^{N_0 - \kappa}}$).

- (4) We can also factorize $\bar{F}^Y$ in $K[[Y]][X]$:

$$\bar{F}^Y \equiv G_0 G_1 \dots G_s \pmod{Y^{N_0}}.$$

- (5) Applying Proposition 3.1 to F in $K[[Y]][X]$ we obtain that

$$G_k \equiv G_k^* \pmod{Y^{N_0 - \kappa}}$$

where G_k^* are the analytic factors of F in $K[[Y]][X]$.

By the same argument G_k agrees with the analytic factors of $\bar{F}^Y \pmod{Y^{N_0 - \kappa}}$. Hence: the analytic factors in $K[[Y]][X]$ of F and $\bar{F}^Y$ are the same modulo $Y^{N_0 - \kappa}$.

The question is what precision do we get when we go from these factors to factors in $K[[X]][Y]$.

- (6) Now the key argument is: for fixed $1 \leq k \leq s$, there is a reparametrization (or coordinates change) $(\alpha(X, Y), \beta(X, Y))$ that will transform G_k^* into the corresponding analytic factor F_k^* of $F \in K[[X]][Y]$, that is

$$G_k^*(\alpha(X, Y), \beta(X, Y)) = F_k^*(X, Y).$$

Modulo $X^{N_0 - \kappa}$, we obtain from (2):

$$G_k^*(\alpha(X, Y), \beta(X, Y)) \equiv F_i(X, Y) \pmod{X^{N_0 - \kappa}}.$$

We have to show that if we apply this same reparametrization to G_k we will obtain

$$G_k(\alpha(X, Y), \beta(X, Y)) \equiv H_k \equiv F_k \pmod{X^{N_0 - \kappa}}.$$

(7) By [?, Theorem 5.17], we can write

$$G_k(x, y) = \prod_{i=1}^n (x - \eta(\zeta^i y^{1/n})) = \prod_{i=1}^n (x - \eta(\zeta^i u)),$$

where ζ is a primitive n -th root of unity and $y = u^n$. The corresponding parametrization of the singularity is

$$(\eta(u), u^n)$$

and we want to compute the parametrization $(t^m, \gamma(t))$.

That is, we want to invert the function $x = \eta(u)$ to obtain $y = \gamma(t)$.

So let

$$\eta(u) = (a_0 u^{m_0} + a_1 u^{m_0+1} + a_2 u^{m_0+2} + \dots,$$

$a_0 \neq 0$ (here $n = e_k$ and $m_0 = d_k$).

To invert this transformation we note

$$\begin{aligned} \eta(u) &= u^{m_0} (a_0 + a_1 u + a_2 u^2 + \dots) \\ &= \left(u \sqrt[m_0]{a_0 + a_1 u + a_2 u^2 + \dots} \right)^{m_0} \end{aligned}$$

Let

$$b_0 + b_1 u + b_2 u^2 + \dots = \sqrt[m_0]{a_0 + a_1 u + a_2 u^2 + \dots}$$

be an m_0 -th root of $a_0 + a_1 u + a_2 u^2 + \dots$. In computations, if $a_0 + a_1 u + a_2 u^2 + \dots$ is developed up to precision c , then also $b_0 + b_1 u + b_2 u^2 + \dots$ can be computed with precision c .

Set $q(u) = u(b_0 + b_1 u + b_2 u^2 + \dots) = b_0 u + b_1 u^2 + b_2 u^3 + \dots$ (hence $\eta(u) = q(u)^{m_0}$). Again, $q(u)$ can be computed with precision c .

Finally let $p(t) = c_1 t + c_2 t^2 + \dots$ be the composite inverse of $q(u)$ (which can also be computed with precision c), that is $q(p(t)) = t$ and hence $u = p(t)$.

We obtain the new parametrization

$$(t^{m_0}, p(t)^n).$$

As we have seen, all these transformations can be done without precision loss, hence if the x -Puisseux expansions of $G_i^*(x, y)$ are known with precision c/n , then the y -Puisseux expansions of $F_i^*(x, y)$ are known with precision c/m .

Remark 4.1. The argument for truncations in Y is the following:

- (1) Let $\bar{F}$ be the truncation of F at some degree $K > \alpha_Y + 2\text{IntExp}_Y$ in Y . We want to know a good K .
- (2) By Proposition 23 we can compute the factors in $K[[X]][Y]$ correct up to degree $K - \text{IntExp}_Y \geq \alpha + \text{IntExp}_Y$, and hence we can compute the Y -Puisseux expansions of the truncated polynomial correct up to degree $D = (K - \text{IntExp}_Y)/e_i$.

- (3) Consider a branch where the Puiseux expansions in X have denominator n and the Puiseux expansions in Y have denominator $m = e_i$. Then the polynomial $\eta(U)$ corresponding to that branch is correct up to degree D (the Puiseux expansion $\eta(Y^{1/m})$ is correct to degree D/m and we take $U = Y^{1/m}$).
- (4) Applying the inverse formula we get a polynomial $\gamma(T)$ which is correct up to the same degree D in T . Now we replace $T = X^{1/n}$ to get the Puiseux expansions in X , $\gamma(X^{1/n})$. We get correct Puiseux expansions up to degree D/n .
- (5) We need this number D/n to be bigger than IntExp_X . Question: can we request only $D > \text{IntExp}_X$? (that is, if we know the expansions up to degree D/n can we recover the factor to degree D ? We assume it is possible. If not, we should take $1/n$ instead of m/n in the following steps.
- (6) Consider the smaller m/n over all branches. So we need $Dm/n > \text{IntExp}_X$, hence

$$m/n(K - \text{IntExp}_Y) > \text{IntExp}_X.$$

- (7) This gives

$$K > n/m \text{IntExp}_X + \text{IntExp}_Y,$$

which is the bound we were looking for (this should be something similar to 2IntExp_Y , we could do this computation, but the formula we got is good enough).

5. TIMINGS

We get very good timings.

REFERENCES

- [1] Adrien Poteaux and Martin Weimann. Computing puiseux series: a fast divide and conquer algorithm. *Annales Henri Lebesgue*, 4:1061–1102, 2021.