# 5 · EU declaration of conformity

The EU declaration of conformity is the manufacturer's signed statement that a product meets the CRA essential requirements. Art 28 and Annex V set its content, and Art 13(12) requires it after the technical documentation and the Art 32 procedure, before placing on the market. File the signed original in the technical documentation (Annex VII pt 7) and publish it at the address given in the user information (Annex II pt 6).

## At a glance

| Item | Detail |
|---|---|
| Legal basis | Art 28; Annex V (full form); Annex VI (simplified form); Art 13(12), 13(13), 13(20); Arts 29-30 (CE marking) |
| Needed for | Every product with digital elements placed on the EU market, whatever its class or conformity route |
| Owner | Compliance lead |
| Approver | Executive sponsor or a delegate named in a signed instrument signs. By drawing up the declaration, the manufacturer assumes responsibility for compliance (Art 28(4)) |
| When to create | After the technical documentation is complete and the Art 32 assessment is positive; before CE marking and placing on the market (Art 13(12); Commission FAQ 6.7) |
| When to update | "Updated as appropriate" (Art 28): new standards applied, new certificate, new variants, changed manufacturer details. A substantial modification is a new placing and "might need a new declaration" (FAQ 6.8; guidance pt 116) |
| Retention | 10 years after placing or the support period, whichever is longer (Art 13(13)); keep superseded versions |
| Feeds | Template 4, Annex VII pt 7; Template 6, Annex II pt 6; Template 10, re-declaration after a substantial modification. Fed by Template 1 (class and route) |

# How to complete

1. Take the class and conformity route from Template 1. A Class I product without a fully applied OJ-cited standard, common specification or scheme must use Module B+C or H (Art 32(2)).
2. Confirm the technical documentation (Template 4) and the conformity assessment are complete and positive. Do not sign before that (FAQ 6.7).
3. Fill the Annex V field table. Use one declaration per product, or one per family that clearly identifies the variants (guidance pts 174-177).
4. Adapt the full wording below and translate it into the languages required by the Member States of sale (Art 28(2)).
5. Have the authorised signatory sign. Log the declaration ID, signatory and authority instrument in the evidence index.
6. Publish the full declaration at a stable URL. Print the Annex VI text with that exact address on packaging or in-app screens (Art 13(20)).
7. Affix the CE marking under the rules below and file a copy in the technical file.

# Template

## Annex V fields

| Field | What to enter | Basis | Example: L2 Smart Lock (illustrative) |
|---|---|---|---|
| Declaration ID and version | Internal reference, version number, date of issue. Control field, not an Annex V point | Art 28 ("updated as appropriate") | DoC-HBS-L2-[001], version 1, [date] |
| 1. Product identification | Name, type and information enabling unique identification: model, SKUs, hardware revision, software or firmware versions | Annex V pt 1 | L2 Smart Lock, type L2; 3 SKUs L2-STD, L2-KEY, L2-RTF; hardware rev [x]; firmware [x.y] and later; companion app [x.y] |
| 2. Manufacturer | Name and address of the manufacturer, or of its authorised representative | Annex V pt 2 | Example Group [legal entity], Home & Building Solutions, [street], [postcode] [city], Germany |

| Field | What to enter | Basis | Example: L2 Smart Lock (illustrative) |
|---|---|---|---|
| 3. Sole responsibility | Fixed statement, see wording below | Annex V pt 3 (the KB quotes "provider"; confirm the OJ wording) | Statement as drafted |
| 4. Object of the declaration | Description allowing traceability; a photograph is optional | Annex V pt 4 | Battery-powered smart door lock with app keys and guest access. Uses the Example Group access-management cloud as remote data processing. Photograph [ref] |
| 5. Statement of conformity | Conformity with the relevant Union harmonisation legislation, listing each act covered | Annex V pt 5; Art 28(3) | Regulation (EU) 2024/2847; [other applicable Union act, e.g. radio equipment legislation, with OJ reference] |
| 6. Standards and specifications | Harmonised standards, common specifications or cybersecurity certifications used, with versions; state "in part" where partial | Annex V pt 6 | No CRA harmonised standard cited in the OJ as at 30 Oct 2026. Other specifications applied: [list, each labelled "draft" where it is a draft] |
| 7. Notified body | Where applicable: body name and number, procedure performed, certificate identification | Annex V pt 7 | [Notified body name], number [xxxx]; EU-type examination (Module B), certificate [ID] of [date]; conformity to type (Module C). No CRA notified body was designated at checks to 8 Sep 2026 |

| Field | What to enter | Basis | Example: L2 Smart Lock (illustrative) |
|---|---|---|---|
| 8. Additional information and signature | Variants covered, other useful facts; "signed for and on behalf of", place and date, name, function, signature | Annex V pt 8 | Variants: L2-STD, L2-KEY, L2-RTF. Support period ends [month year] (10 years). Signed for Example Group [legal entity], [city], [date], [name], [function] |

## Full declaration (Annex V) wording

The block below is a drafting model that follows the Annex V points. Only the point 3 statement is quoted from the KB.

```
EU DECLARATION OF CONFORMITY
No. [declaration ID]   Version [n]   [date of issue]

1. Product with digital elements: [product name], type [type or model],
   [SKUs or variants], hardware revision [x], software/firmware version
[x.y],
   [other information enabling unique identification].

2. Name and address of the manufacturer [or its authorised representative]:
   [legal name], [postal address], [country].

3. This declaration of conformity is issued under the sole responsibility
   of the provider.

4. Object of the declaration: [description allowing traceability].
   [Optional: photograph of the product.]

5. The object of the declaration described above is in conformity with the
   relevant Union harmonisation legislation:
   - Regulation (EU) 2024/2847 (Cyber Resilience Act)
   - [other Union act, with OJ reference, where this declaration covers it]

6. References to the harmonised standards, common specifications or
   cybersecurity certifications used, in relation to which conformity
   is declared:
   - [reference, version, date; applied in full / in part]
   [or: None.]
```

```
7. Where applicable: the notified body [name] (number [xxxx]) performed
   [EU-type examination (Module B) / approval of the quality system (Module
H)]
   and issued the certificate [certificate identification], dated [date].

8. Additional information: [variants covered; other information].

Signed for and on behalf of: [manufacturer legal name]
[place of issue], [date of issue]
[name], [function]
[signature]
```

*Point 3 follows the knowledge base wording ("provider"), taken from one mirror of the regulation; confirm it against the Official Journal text before issuing.*

## Simplified declaration (Annex VI) wording

The opening is the Annex VI wording as quoted in the KB. The address must be "the exact internet address" of the full declaration (Art 13(20)).

```
Hereby, [manufacturer legal name] declares that the product with digital
elements type [product type] is in compliance with Regulation (EU) 2024/2847.
The full text of the EU declaration of conformity is available at the
following internet address:
[exact internet address of the full declaration]
```

### Example: L2 Smart Lock (illustrative)

```
Hereby, Example Group [legal entity] declares that the product with digital
elements type L2 Smart Lock (L2-STD, L2-KEY, L2-RTF) is in compliance with
Regulation (EU) 2024/2847.
The full text of the EU declaration of conformity is available at the
following internet address:
https://www.example.com/security/l2/declaration/
```

## CE marking rules

| Rule | What to do | Basis | Example: L2 Smart Lock (illustrative) |
|---|---|---|---|
| Hardware placement | Visibly, legibly and indelibly on the product; else on the packaging and the declaration. May be under 5 mm where the product's nature warrants | Art 30(1)-(2) | On the lock's rear housing plate and on the packaging |
| Software placement | On the declaration or on the accompanying website, in a section consumers can reach directly. No authority has addressed app-store listings | Art 30(1) | Companion app: CE marking on the declaration and on the L2 security page |
| Timing | Before placing on the market, and only after a positive conformity assessment | Art 13(12); FAQ 6.7 | Not before the Module B certificate is issued |
| Notified body number | Follows the CE marking only where the body is involved under Module H | Art 30(4) | Module B+C: CE marking alone. If Module H is chosen instead: CE followed by [body number] |
| Other CE legislation | One marking indicates compliance with all applicable CE legislation | Art 30(5) | One CE marking covers the CRA and [other act] |
| Future labels | Implementing acts on pictograms or support-period marks; none adopted | Art 30(6) | Watch item |

## Languages, scope and updates

| Topic | Rule | Basis |
|---|---|---|
| Languages | The languages required by each Member State where the product is made available | Art 28(2) |

| Topic | Rule | Basis |
|---|---|---|
| One per product | Tied to the individual product rather than the type; a family declaration must clearly identify the variants | Art 28; FAQ 6.8; guidance pts 174-177 |
| Updates | Keep it "updated as appropriate"; a new version after a substantial modification "might need a new declaration" | Art 28; FAQ 6.8 |
| Several Union acts | One declaration, or a dossier of declarations, may cover all applicable acts | Art 28(3) |
| Requests | Market surveillance may request the declaration and all conformity documentation on reasoned request | Art 13(22) |

Guidance C(2026) 5252 is an approved draft; no formal adoption or OJ publication was found as at 30 Oct 2026.

## Common mistakes

- Signing the declaration or affixing the CE marking before a positive assessment. A Class I product cannot self-declare under Module A until a cited standard is applied in full (Art 32(2); FAQ 6.7).
- Adding the notified body number beside the CE marking under Module B+C. It belongs there only under Module H (Art 30(4)).
- No controlled signing authority, so declarations are signed by whoever is asked. Use a signing instrument, a pre-signature checklist and a counter-signature.
- An Annex VI text without the exact internet address, or a declaration URL that breaks during the retention period.
- Treating RED certificates or EN 18031 assessments as CRA conformity. Art 69(1) keeps them valid for RED purposes only.

*Template 5 · v1.0 · 31 Oct 2026 · Not legal advice; confirm wording against the Official Journal text before use.*