

PA Amplifier

NT - 40BPA



PA Amplifier (NT-40BPA)

The product is a versatile audio device featuring plug-and-play USB, FM radio, and wireless remote control. It includes two microphone inputs, one auxiliary input, and one output for linking additional equipment. The device offers transformer-isolated outputs for 100V, 70V, and 4-16 Ohms speakers, ensuring compatibility with various systems. A five-element LED level meter allows for easy sound level monitoring. Key features include muting, individual volume and tone controls, short circuit protection, and individual channel distribution. Available in black or white, it's ideal for public address systems, karaoke, and other audio applications.

TECHNICAL DATA SPECIFICATION

| Model | NT-40BPA |
|---------------|--------------------|
| Line Voltage: | 70-100 v |
| Impedance: | 4-16 Ω |
| Rated Power: | 40 W |
| Zone: | / |
| Dimension: | 380x180x67 |
| Weight: | 2.84 KG |
| Gross Weight: | 3.74 KG |
| Panel Color: | Silver/Black/White |

KEY FEATURES

This audio device offers plug-and-play USB, FM radio, wireless remote, multiple inputs/outputs, transformer-isolated speaker outputs, LED level meter, volume/tone controls, and short circuit protection.

QUICK GUIDE

Connect USB or FM radio, plug in microphones or aux devices, adjust volume/tone, monitor sound via LED, use wireless remote, link equipment with aux output, connect speakers to outputs, and utilize muting.

