

PDM30			
MoTeC Superseal A (34-pin) — MoTeC #65044	female	34-pin	
OUT15	1		
2			
3			
4			
5			
6			
7			
8			
9			
10			
11			
12			
13			
14			
15			
16			
17			
18			
19			
20			
21			
22			
23			
24			
25			
26			
27			
28			
29			
30			
31			
32			
33			
34			

M130			
MoTeC Superseal Cnctr A (34-pin) — MoTeC #65044	female	34-pin	
A01	1		
A02	2		
A03	3		
A04	4		
A05	5		
A06	6		
A07	7		
A08	8		
A12	9		
A13	10		
A14	11		
A15	12		
A16	13		
A17	14		
A18	15		
A19	16		
A20	17		
A21	18		
A22	19		
A27	20		
A28	21		
A29	22		
A30	23		
B01	24		
B02	25		
B03	26		
B04	27		
B05	28		
B07	29		
B13	30		
B15	31		
32			
33			
34			

W97			
1x	20 AWG	18.4 m	
PDM30:1.OUT15 1:blue/white Rear_Backup_Camera:1:+12V			
#97 Rear Backup Camera (BLU/WHIT)			

Rear_Backup_Camera			
Camera connector (PN TBD) 4-pin			
1	+12V		
2	GND		
3	VID+		
4	VID-		

W5			
1x	20 AWG	2.5 m	
M130:3:A03 1:white Ignition_Coil_3:3:SIG			
#5 Ignition Coil 3 (WHT)			

Ignition_Coil_3			
D510C — WPCOL40 / GM 12162000 (4-pin) 4-pin			
1	+12V		
2	GND		
3	SIG		
4	GND2		
Pigtail WPCOL40			

W7			
1x	20 AWG	2.5 m	
M130:4:A04 1:white/white Ignition_Coil_5:3:SIG			
#7 Ignition Coil 5 (WHT/WHT)			

Ignition_Coil_5			
D510C — WPCOL40 / GM 12162000 (4-pin) 4-pin			
1	+12V		
2	GND		
3	SIG		
4	GND2		
Pigtail WPCOL40			

W4a			
1x	18 AWG	4.6 m	
M130:1:A01 1:brown ETB:2:MotorB			
#4a ETB TAC Motor 2 (BRN)			

W4e			
1x	22 AWG	4.6 m	
M130:2:A02 1:grey ETB:5:+5V			
#4e ETB 5V Reference (GRY)			

Ignition_Coil_7			
D510C — WPCOL40 / GM 12162000 (4-pin) 4-pin			
1	+12V		
2	GND		
3	SIG		
4	GND2		
Pigtail WPCOL40			

W8			
1x	20 AWG	2.5 m	
M130:5:A05 1:white/black Ignition_Coil_7:3:SIG			
#8 Ignition Coil 7 (WHT/BLK)			

Ignition_Coil_2			
D510C — WPCOL40 / GM 12162000 (4-pin) 4-pin			
1	+12V		
2	GND		
3	SIG		
4	GND2		
Pigtail WPCOL40			

W9			
1x	20 AWG	2.5 m	
M130:6:A06 1:white/red Ignition_Coil_2:3:SIG			
#9 Ignition Coil 2 (WHT/RED)			

Ignition_Coil_4			
D510C — WPCOL40 / GM 12162000 (4-pin) 4-pin			
1	+12V		
2	GND		
3	SIG		
4	GND2		
Pigtail WPCOL40			

W10			
1x	20 AWG	2.5 m	
M130:7:A07 1:white/blue Ignition_Coil_4:3:SIG			
#10 Ignition Coil 4 (WHT/BLU)			

Ignition_Coil_6			
D510C — WPCOL40 / GM 12162000 (4-pin) 4-pin			
1	+12V		
2	GND		
3	SIG		
4	GND2		
Pigtail WPCOL40			

W11			
1x	20 AWG	2.5 m	
M130:8:A08 1:white/yellow Ignition_Coil_6:3:SIG			
#11 Ignition Coil 6 (WHT/YEL)			

Ignition_Coil_8			
D510C — WPCOL40 / GM 12162000 (4-pin) 4-pin			
1	+12V		
2	GND		
3	SIG		
4	GND2		
Pigtail WPCOL40			

W12			
1x	20 AWG	2.5 m	
M130:9:A12 1:white/violet Ignition_Coil_8:3:SIG			
#12 Ignition Coil 8 (WHT/VIO)			

Ignition_Coil_1			
D510C — WPCOL40 / GM 12162000 (4-pin) 4-pin			
1	+12V		
2	GND		
3	SIG		
4	GND2		
Pigtail WPCOL40			

W24			
1x	20 AWG	2.5 m	
M130:10:A13 1:white/orange Ignition_Coil_1:3:SIG			
#24 Ignition Coil 1 (WHT/ORG)			

Oil_Pressure_Sensor			
3-pin oval sealed — WP0IL40 / GM 12673134 3-pin			
1	+5V		
2	SIG		
3	GND		
Pigtail WP0IL40			

W102			
1x	22 AWG	4.6 m	
M130:11:A14 1:violet Oil_Pressure_Sensor:2:SIG			
#102 Oil Pressure Sensor (ECU) (VIO)			

MAP_Sensor			
Bosch 3-pin sealed — GM 55573248 / ACDelco PT2293 3-pin			
1	+5V		
2	SIG		
3	GND		

W4c			
1x	22 AWG	4.6 m	
M130:11:A14 1:green ETB:3:TPS1			
#4c ETB TPS1 Signal (DK GRN)			

ETB			
6-pin sealed — GM 13580085 mates GM 12605109 6-pin			
1	MotorA		
2	MotorB		
3	TPS1		
4	TPS2		
5	+5V		
6	GND		

W108			
1x	22 AWG	4.6 m	
M130:12:A15 1:violet/white MAP_Sensor:2:SIG			
#108 MAP Sensor (VIO/WHT)			

Fuel_Pressure_Sensor			
3-pin (PN TBD) 3-pin			
1	+5V		
2	SIG		
3	GND		

W112			
1x	22 AWG	4.6 m	
M130:13:A16 1:violet/black Fuel_Pressure_Sensor:2:SIG			
#112 Fuel Pressure Sensor (VIO/BLK)			

W4d			
1x	22 AWG	4.6 m	
M130:14:A17 1:violet ETB:4:TPS2			
#4d ETB TPS2 Signal (PPL)			

Fuel_Injector_1			
EV6/USCAR — WPINJ40 / GM 13352241 (2-pin) 2-pin			
1	+12V		
2	CTRL		
Pigtail WPINJ40			

W4b			
1x	18 AWG	4.6 m	
M130:15:A18 1:yellow ETB:1:MotorA			
#4b ETB TAC Motor 1 (YEL)			

Fuel_Injector_2			
EV6/USCAR — WPINJ40 / GM 13352241 (2-pin) 2-pin			
1	+12V		
2	CTRL		
Pigtail WPINJ40			

W4f			
1x	22 AWG	4.6 m	
M130:31:B15 1:black ETB:6:GND			
#4f ETB Signal Ground (BLK)			

Fuel_Injector_3			
EV6/USCAR — WPINJ40 / GM 13352241 (2-pin) 2-pin			
1	+12V		
2	CTRL		
Pigtail WPINJ40			

W13			
1x	18 AWG	4.6 m	
M130:16:A19 1:green Fuel_Injector_1:2:CTRL			
#13 Fuel Injector 1 (GRN)			

Fuel_Injector_4			
EV6/USCAR — WPINJ40 / GM 13352241 (2-pin) 2-pin			
1	+12V		
2	CTRL		
Pigtail WPINJ40			

W14			
1x	18 AWG	4.6 m	
M130:17:A20 1:green/white Fuel_Injector_2:2:CTRL			
#14 Fuel Injector 2 (GRN/WHT)			

Fuel_Injector_5			
EV6/USCAR — WPINJ40 / GM 13352241 (2-pin) 2-pin			
1	+12V		
2	CTRL		
Pigtail WPINJ40			

W15			
1x	18 AWG	4.6 m	
M130:18:A21 1:green/black Fuel_Injector_3:2:CTRL			
#15 Fuel Injector 3 (GRN/BLK)			

Fuel_Injector_6			
EV6/USCAR — WPINJ40 / GM 13352241 (2-pin) 2-pin			
1	+12V		
2	CTRL		
Pigtail WPINJ40			

W16			
1x	18 AWG	4.6 m	
M130:19:A22 1:green/red Fuel_Injector_4:2:CTRL			
#16 Fuel Injector 4 (GRN/RED)			

Fuel_Injector_5		
EV6/USCAR — WPINJ40 / GM 13352241 (2-pin)		2-pin
1	+12V	
2	CTRL	
Pigtail WPINJ40		