

RED FLAG LIST

Conditions That Require Immediate Action — Do Not Wait. Do Not Guess.

How to Use This List

If you observe any condition on this list, call GigLine at (336) 329-8899 before taking any corrective action. Do not attempt to fix a red flag condition without guidance. Do not minimize it. Do not wait until the end of the shift. These conditions represent the highest-risk situations in small manufacturing and warehouse operations.

ELECTRICAL HAZARDS

CONDITION	CFR CITATION	WHY IT MATTERS / IMMEDIATE ACTION
Exposed wiring or bare conductors	29 CFR 1910.303(b)(1)	Exposed conductors can cause electrocution. Do not touch. Isolate the area.
Overloaded circuits or extension cords as permanent wiring	29 CFR 1910.303(b)(2)	Extension cords are not permanent wiring. This is a fire and electrocution hazard.
Missing or damaged electrical panel covers	29 CFR 1910.303(f)	Open panels expose live conductors. Restrict access immediately.
Electrical equipment near water or wet surfaces	29 CFR 1910.303(g)	Water and electricity is an immediate life-safety issue.

CHEMICAL AND HazCom HAZARDS

CONDITION	CFR CITATION	WHY IT MATTERS / IMMEDIATE ACTION
Unlabeled chemical containers	29 CFR 1910.1200(f)	Any container without a GHS-compliant label must be removed from service immediately.
Missing SDS for a chemical in use	29 CFR 1910.1200(g)	Do not allow use of the chemical until the SDS is obtained and on file.
Chemical spill with no cleanup procedure	29 CFR 1910.1200(h)	Employees must know the emergency response procedure before a spill occurs.
Improper chemical storage (incompatible chemicals together)	29 CFR 1910.1200(e)	Incompatible chemicals stored together can cause fires, explosions, or toxic gas release.

EMERGENCY PREPAREDNESS

CONDITION	CFR CITATION	WHY IT MATTERS / IMMEDIATE ACTION
Blocked or locked exit doors during occupied hours	29 CFR 1910.36(d)(1)	Exit doors must be unlocked and unobstructed at all times when employees are present.
Missing or expired fire extinguishers	29 CFR 1910.157(e)	Extinguishers must be inspected monthly and maintained annually.
No emergency action plan posted or communicated	29 CFR 1910.38(b)	Employees must know evacuation routes and assembly points.
First aid kit missing or depleted	29 CFR 1910.151(b)	A stocked first aid kit must be accessible at all times.

MACHINE AND EQUIPMENT HAZARDS

CONDITION	CFR CITATION	WHY IT MATTERS / IMMEDIATE ACTION
Unguarded moving machine parts	29 CFR 1910.212(a)(1)	Any machine part that can cause injury must be guarded. Stop the machine until guarded.
LOTO (lockout/tagout) not followed during maintenance	29 CFR 1910.147	Failure to lock out energy sources during maintenance is a leading cause of amputations.
Damaged or improvised machine guards	29 CFR 1910.212(a)(2)	Improvised guards are not compliant. Stop the machine and contact GigLine.

PERSONAL PROTECTIVE EQUIPMENT

CONDITION	CFR CITATION	WHY IT MATTERS / IMMEDIATE ACTION
Employees working without required PPE	29 CFR 1910.132(a)	If a hazard assessment requires PPE, employees must use it. No exceptions.
PPE that is damaged, expired, or the wrong type	29 CFR 1910.132(d)	Damaged PPE provides no protection. Replace immediately.

RECORDKEEPING AND COMPLIANCE

CONDITION	CFR CITATION	WHY IT MATTERS / IMMEDIATE ACTION
OSHA 300 log not maintained or not posted in February	29 CFR 1904.29	The OSHA 300 log must be posted February 1 – April 30 each year.

Serious injury or illness not reported to OSHA within required timeframe

**29 CFR
1904.39**

Fatalities must be reported within 8 hours. Amputations, loss of eye, or inpatient hospitalization within 24 hours.

What This Document Proves

Maintaining and distributing a Red Flag List demonstrates that your facility proactively identifies high-risk conditions and has a documented protocol for addressing them. This is evidence of good-faith compliance effort, which OSHA considers when determining penalty amounts.