PV101 Day 3 Lab Worksheet

Wire Stripping and Crimping | Afternoon Lab | 6 students, 2 groups of 3

Name: _____ Group: _____ Date: _____

Purpose

Practice making clean, inspectable wire ends and crimped connections using de-energized training material.

Group Roles

Role	Student	Job
Tool Lead	_____	Uses the tool only after the group agrees.
Quality Inspector	_____	Checks the work before and after crimping.
Recorder	_____	Writes results and notes.

Tool and Material Check

Item	Checked?
Wire stripper	[ ]
Crimper	[ ]
Practice wire	[ ]
Practice connectors	[ ]
Scrap bin	[ ]
Eye protection if clipping wire	[ ]

Safety Agreement

[ ] We are using practice wire only.

[ ] We will not connect to batteries, panels, outlets, vehicles, or unknown equipment.

[ ] We will ask Rich before changing tools, wire sizes, or connector types.

Procedure

1. Pick one piece of de-energized practice wire from the instructor-approved bin.
2. Identify the wire size if it is labeled. If not labeled, ask Rich before choosing the stripper slot.
3. Choose a connector that matches the wire size and lab objective.
4. Set the wire in the correct stripper hole. Close the tool gently, pull straight, and remove the insulation.

5. Inspect the exposed copper. Look for cut strands, crushed strands, too much exposed copper, or too little exposed copper.
6. Insert the wire fully into the connector barrel until it seats properly.
7. Place the connector in the correct crimper die and crimp once with firm, controlled pressure.
8. Perform a tug test by pulling the wire and connector in opposite directions with reasonable hand force.
9. Record whether the connection passed or failed and why.
10. Cut off failed practice connections and redo them as practice, not as punishment. The copper does not have feelings.

Inspection Checklist

Quality check	Pass?	Notes
Correct strip length	Yes / No	
No missing strands	Yes / No	
Connector seated	Yes / No	
Crimp location	Yes / No	
Tug test	Yes / No	
Clean finish	Yes / No	

Peer Inspection

Trade one completed practice connection with the other group. Inspect their work respectfully. You are checking the connection, not roasting the human. Tragic distinction, but necessary.

Other group connection	Pass?	One useful note
Connection #1	Yes / No	_____
Connection #2	Yes / No	_____