



Tertiary Infotech Academy Pte Ltd

UEN: 201200696W

LAB 7 — GENERATE REPORTS AND PART LISTS

For

Technical Drawing with AutoCAD Electrical

TGS Ref No: TGS-2023037466

Conducted by

Tertiary Infotech Academy Pte Ltd

UEN: 201200696W

Version 6.0

Lab 7 — Generate Reports and Part Lists

Topic 03: Reviewing Technical Drawings for Strategic Relevance and Standard Compliance

Maps to: A6, K5 — extract BOM and wire lists, format them to house standards and place them on the drawing

Goal

Run Bill of Material and Wire From/To reports across the project, tailor the fields, save a format file for repeat use, and insert the report as a table on the drawing — the part lists a checker reviews.

Project Bill Of Material for all locations (6 records)

TAGS	QTY	SUB	CATALOG	MFG	DESCRIPTION
CB322	5		EGH3015FFG	EATON	CIRCUIT BREAKER - E125 FRAME
CB324					3-POLE CIRCUIT BREAKER
CB326					15AMPS
CB328					TYPE E125H, FIXED THERMAL & MAGNETI
CB330					690VAC, 250VDC, 15AMPS
DS304	1		194E-A25-1753	AB	IEC LOAD SWITCH 3 POLE
					194E - LOAD SWITCH
					25AMPS
					ON-OFF BASE MOUNTED SWITCH (INCLUDE
					480VAC, 25AMPS
FU309	1		FRS-R-15	BUSSMANN	DUAL ELEMENT FUSE - CLASS RK5
					TIME DELAY, CURRENT LIMITING
					600VAC

What you'll build

A BOM table placed on the drawing plus a saved .SET format file and a CSV export of the report. (Tools: Reports · Bill of Material · Format files (.SET) · Tables · Attributes DWG.)

Starter files (in this folder)

- 5-1_Working_with_Tables.dwg — source:
github.com/PacktPublishing/AutoCAD-2025-Best-Practices-Tips-and-Techniques
- 5-3_Using_Table_Links.dwg — source:
github.com/PacktPublishing/AutoCAD-2025-Best-Practices-Tips-and-Techniques

Step-by-step

1. Run the Reports tool on the Reports tab and choose Bill of Material, processing the whole project.

AEAUDIT → Reports → BOM

2. Adjust the report: include/exclude fields, reorder columns and rename field labels to your house standard.

[Change Report Fields](#)

3. Save the settings as a format file so the same report can be re-run in one click next time.

Save Format File (.SET)

4. Insert the report on the drawing as a table (Put on Drawing) using a table style.

Put on Drawing · TABLESTYLE

5. Export the same report to a file for procurement (CSV/XLS).

Save to File → CSV

6. Run a Wire From/To report and compare it against the wiring you created in Lab 4; open the supplied table drawings to see linked tables.

Reports → Wire From/To

Test it

The BOM table on the drawing matches the CSV export line for line, and re-running the report through your .SET format file reproduces the same layout — the part list is standard-compliant and repeatable.