Activity 5: Execute a Compliance Verification Round

Mapping: K2 · K3 · A2
Objective: Plan, execute and record traceable checks for personnel grounding, resistance, electrostatic field and ioniser performance.

Scenario

Meridian Electronics has four EPAs on two shifts. Recent records show perfect results but several tester failures were repaired without documented product disposition. You must execute a verification round using a simulated data pack.

Roles

- ESD auditor
- area owner
- instrument custodian

Detailed procedure

1. Confirm the verification procedure, current limits and sampling plan from the controlled programme documents.
2. Check each instrument identity, calibration status, battery/zero check and suitable accessories.
3. Record temperature, relative humidity, area, shift and relevant process condition.
4. Review daily wrist-strap and footwear test records for completeness, first-pass failures and response actions.
5. Use the simulated readings to evaluate person/footwear/floor and wrist-strap results.
6. Evaluate point-to-point and point-to-ground resistance readings with method and electrode details.
7. Evaluate field readings at the stated work distance and identify uncontrolled essential insulators.
8. Evaluate positive/negative decay and offset/balance readings at the work position.
9. Classify each result as conforming, nonconforming or insufficient evidence.
10. For every failure, define immediate containment, retest rules, product impact review and escalation.
11. Calculate first-pass pass rate and overdue-check rate; explain what each metric can and cannot prove.
12. Sign the evidence package and retain raw data, calculations and disposition decisions.

Questions

- Why is a retest pass insufficient without investigating the first failure?
- Which contextual data makes a resistance reading defensible?
- Where should ioniser performance be checked?

Evidence to submit

- Completed measurement log
- Failure/disposition records
- Metric calculation
- Signed evidence package

Acceptance criteria

- [ ] Every result includes method, units and conditions
- [ ] Instrument status is verified
- [ ] First-pass failures remain visible
- [ ] Product impact and response are documented

Debrief

Explain which evidence changed your first assumption, which control is most reliable, and what follow-up measurement is needed.