Bill of Materials

RescueSwarm: An Autonomous UAV for
Post-Disaster Search, Localisation and Payload Delivery

First aircraft · 21 September 2026

Submitted to	Dr. Surbhi Sharma and Dr. Mamata Gulati, Faculty Mentors
Submitted by	Swastik Kumar, on behalf of the RescueSwarm team
Accompanies	The first-aircraft brief and its phase-wise approval letters

1. Purpose

This document lists every component needed to build, test and operate the first RescueSwarm aircraft and its ground station, with quantities, unit prices and the supplier each price was taken from. Every price is from a dated Indian listing, and each supplier name in Section 4 links to it. Two lines have no listing and are marked as estimates. The totals are the same as those in the first-aircraft brief and the approval letters, because all three are generated from one parts list.

2. Cost summary

Parts at retail, GST already included (57 lines)	2,03,902
Parts quoted before GST, and estimates (5 lines)	8,719
Parts total, first aircraft (62 lines)	**2,12,621**
GST at 18 % on the pre-GST lines only	1,569
Contingency, 15 %	32,129
Total requested	**INR 2,46,319**

Of the parts, INR 1,39,635 is fitted to the aircraft itself; the rest is test instruments, the RTK base station, flight-test support and the ground station. The request is released in 13 phases, each only after the previous one has produced its result. The first release is INR 3,733, and nothing above INR 26,000 is spent until a motor has been measured on the thrust stand. If this aircraft meets its gates, two more like it would come to about INR 3,32,186; that would be a separate request.

Group	Lines	Amount
Test instruments	6	3,246
Avionics, sensing and RTK positioning	23	1,00,755
Airframe, propulsion and power	19	70,986
Flight-test support	7	29,867
Ground station	7	7,767
Total	**62**	**2,12,621**

3. System configuration

Airframe	Quadrotor, 18 in carbon propellers, Tarot 5008 340 KV motors, carbon-tube arms; about 7 kg take-off mass with four relief kits
Flight control	Holybro Kakute H7 V1.5 running ArduPilot, stacked on a 4-in-1 65 A speed controller
Onboard computing	Raspberry Pi 5 (4 GB) with AI HAT+ (26 TOPS) for person detection; 12.3 MP camera, 6 mm lens
Positioning	Centimetre-level RTK on every aircraft (ZED-F9P, dual-band, with compass); own ground base station, so no internet is needed
Video	Digital downlink (wfb-ng) carrying the camera feed with detections drawn on; one directional ground receiver per aircraft
Links	2.4 GHz ExpressLRS for the safety pilot; 868 MHz LoRa for RTK corrections
Power	6S 16 Ah LiHV lithium-polymer pack, charged on the LiHV profile (4.35 V per cell); AS150 connectors; separate regulators for the computer, the video radio and the servos

4. Bill of materials

All prices are in INR. *Per AC* is the number fitted to one aircraft; a dash means the item is bought once for the whole build. *Qty* is the quantity bought for this aircraft, including spares.

#	Item	Part	Per AC	Qty	Unit	Amount	Source
Test instruments							**3,246**
1	Load-cell amplifier	7Semi HX711 24-bit ADC	–	1	104	104	Robu
2	Load cell	REES52 20 kg load cell + HX711 breakout	–	1	854	854	Amazon India
3	Thrust-stand mast	SURYAKUSH metal 2.1 m tripod	–	1	373	373	Flipkart
4	Fasteners	Hex socket-head assortment M3/M4/M5, SS304	–	1	1,140	1,140	OnlyScrews
5	Threadlocker	Loctite 243, 50 ml	–	1	664	664	Amazon India
6	Throttle source	Servo tester / ESC consistency tester, PPM	–	1	111	111	Robokits
Avionics, sensing and RTK positioning							**1,00,755**
7	Flight controller	Holybro Kakute H7 V1.5, no Bluetooth	1	1	9,269	9,269	Indian Robo Store
8	FC vibration mount	Glass-fibre anti-vibration shock absorber	1	1	161	161	Robu
9	Autopilot log card	SanDisk 32 GB microSDHC, class 10	1	1	1,549	1,549	Robocraze
10	Companion computer	Raspberry Pi 5, 4 GB	1	1	11,049	11,049	Yantronix
11	AI accelerator	Raspberry Pi AI HAT+, 26 TOPS	1	1	11,749	11,749	Robu
12	Compute cooling	Official Raspberry Pi 5 active cooler	1	1	519	519	Robu
13	Storage	SanDisk High Endurance 128 GB microSD	1	1	3,989	3,989	Flipkart
14	GNSS RTK rover	GenX F9P Air: ZED-F9P L1/L2 + helix + QMC5883 compass, ∼20 g	1	1	15,392	15,392	Robokits
15	GNSS RTK base	SmartElex ZED-F9P-04B RTK board, U.FL	–	1	17,965	17,965	Robocraze
16	GNSS antenna, base	LS-125-A L1/L2/L5 survey antenna	–	1	8,123	8,123	Robokits
17	GNSS feeder, base	U.FL to SMA female pigtail, 10 cm	–	1	49	49	Robocraze
18	GNSS cable, base	RG58 50 ohm, 3 m, TNC-M to SMA-M, made locally	–	1	600	600	Estimate[†]
19	RTK base radio	EByte E22-900T22D-V2, SX1262, 22 dBm	–	1	989	989	Robu
20	Height rangefinder	Benewake TFmini-S, 12 m lidar, UART	1	1	2,827	2,827	Indian Robo Store
21	Camera + lens	Arducam 12.3 MP 1/2.3 in HQ module, 6 mm CS lens	1	1	6,799	6,799	Robu
22	Video transmitter	LB-Link BL-M8812EU2, RTL8812EU, 5 GHz 2T2R	1	1	1,849	1,849	Hubtronics
23	Video antennas	6 dBi 5 GHz dipole + 165 mm U.FL lead	2	2	75	150	Robocraze
24	Command receiver	ExpressLRS RX24T, 2.4 GHz	1	1	1,439	1,439	Robu
25	Coordination radio	EByte E22-900T22D-V2, SX1262, 22 dBm	1	1	989	989	Robu
26	BEC, primary	8 A UBEC, 5/6 V out, 2-6S in	1	1	3,939	3,939	Amazon India

continued on next page

#	Item	Part	Per AC	Qty	Unit	Amount	Source
27	BEC, video radio	2-6S 5 V 5 A switching BEC	1	1	959	959	Robu
28	Video radio cooling	Aluminium heatsink 50 x 25 x 10 mm + 3010 5 V fan	1	1	122	122	Robu
29	BEC, secondary	ReadytoSky 2-6S 5V/3A + 12V/3A switchable UBEC	1	1	279	279	Robu
Airframe, propulsion and power							**70,986**
30	Motors	Tarot TL96020, 5008, 340 KV	4	4	4,703	18,812	Robokits
31	Propellers	1855 counter-rotating carbon fibre, CW+CCW pair	4	6	1,641	9,846	Robokits
32	Speed controllers	Hobbywing XRotor FPV G2, 4-in-1, 65 A, 3-6S	1	1	6,500	6,500	RC Mumbai
33	Arm tube	3K carbon fibre, OD25 x ID23 x 1000 mm	2	2	2,259	4,518	Robu
34	Frame plate stock	3K carbon fibre sheet, 300 x 200 x 2 mm	1	1	2,895	2,895	Indian Robo Store
35	Motor mounts	Tarot 25 mm motor mount, TL9602	4	4	1,119	4,476	Robu
36	Arm clamps	T-bolt hose clamps 23-25 mm, SS304, 4 pcs	1	1	3,012	3,012	Amazon India
37	Landing gear	F450/F550 landing skid	1	1	549	549	Robu
38	Suspension springs	5 mm stainless double torsion spring	10	10	2	20	IndiaMART
39	Printed parts	Pro-Range PETG-CF filament, 1.75 mm, 1 kg	–	1	949	949	Robu
40	Release servos	MG90S mini servo, 180 deg	4	4	149	596	Robocraze
41	Battery pack	GenX 22.8V 6S 16000mAh 25C/40C HV LiPo, AS150	1	1	12,197	12,197	Robokits
42	Pack fusing	ANL fuse holder + 150 A ANL fuses	1	1	3,000	3,000	Njour
43	Pack retention	300 mm LiPo strap, reusable	2	2	62	124	Robu
44	Main leads	10 AWG ultra-flexible silicone wire	–	1	149	149	Robu
45	Power connectors	Amass AS150 anti-spark, gold-plated, M/F pair	4	4	533	2,133	zBotic
46	Signal connectors	JST ZH 6-pin, 200 mm leads	1	1	23	23	Robu
47	Antenna feeders	SMA M-F bulkhead RG316, 150 mm + adapters	1	1	1,139	1,139	Desertcart
48	Insulation	PVC heat-shrink sleeve, 150 mm	1	1	47	47	Robu
Flight-test support							**29,867**
49	Safety-pilot transmitter	RadioMaster TX12 MKII ELRS + RP1 receiver	–	1	16,519	16,519	zBotic
50	Battery charger	ToolKitRC M6D, 500 W, 25 A, dual	–	1	7,349	7,349	Robu
51	Cable management	Nylon zip ties, 350 mm, 100 pcs	–	1	135	135	Robu
52	Heat-shrink kit	328 pcs assorted 2:1 heat-shrink	–	1	159	159	Robu
53	Mounting tape	3M VHB 5952, 6 mm x 8.2 m	–	1	560	560	Amazon India
54	Hook and loop	Self-adhesive hook and loop, 25 mm x 2 m	–	1	145	145	Amazon India
55	Consumables	Fasteners, tape, connectors, filament	–	1	5,000	5,000	Estimate†
Ground station							**7,767**
56	Video receivers	LB-Link BL-M8812EU2, RTL8812EU, one per aircraft channel	–	1	1,849	1,849	Hubtronics
57	Receive panels	5.8 GHz 14 dBi directional panel, RP-SMA, 62x55 mm	–	1	566	566	FlyRobo
58	Panel pigtails	U.FL to RP-SMA female pigtail, RG178	–	1	99	99	IndiaMART
59	Receive antennas	6 dBi 5 GHz dipole + U.FL lead, second port	–	1	75	75	Robocraze
60	Receiver USB hub	Transcend HUB3 powered 4-port USB hub + adapter	–	1	2,653	2,653	Flipkart
61	Coordination base	EByte E22-900T22U, SX1262, USB	–	1	1,646	1,646	Hubtronics
62	Base station mount	Photographic tripod and adapter	–	1	879	879	Amazon India
Parts total, first aircraft							**2,12,621**

† No listing. The base antenna cable is to be made up by a local RF cable shop, and consumables are a round allowance. Both are carried as pre-GST and have GST and contingency applied.

5. Battery selection

The battery is the largest single design decision in this parts list. The previous design used a pack built in-house from eighteen cells. A bought lithium-polymer pack avoids spot-welding cells in a student lab. It has to be large enough to keep the mission's energy reserve *after* its own extra weight is counted, because a heavier aircraft needs more power to hover. Each candidate was run through the project's sizing model at its own mass:

Pack	Mass kg	Energy Wh	Take-off mass, kg	Thrust/ weight	Endurance ratio	Landing reserve, Wh
Li-ion 6S3P, in-house (previous)	1.45	292	6.36	2.00	2.02	+1.1
LiPo 12 Ah	1.42	266	6.34	2.01	1.85*	−3.7*
LiPo 13 Ah	1.52	289	6.43	1.98	1.96*	−0.5*
LiPo 14 Ah	1.64	311	6.55	1.94	2.06	+2.5
LiPo 16 Ah LiHV (selected)	**1.88–2.21**	**365**	**6.8–7.1**	**1.8–1.9**	**2.1–2.3**	**+5 to +9**

Endurance ratio is hover time divided by mission time; the design requires at least 2.0. *Landing reserve* is the energy left after the third aircraft waits its turn and descends, and must be positive. * Fails the requirement. The 16 Ah pack's mass is a range because the maker does not publish it.

The 12 and 13 Ah packs fail both requirements, and about 14 Ah is the smallest that passes. The 16 Ah pack is the smallest suitable size on sale in India. Its cost is weight: on the same motors, thrust-to-weight falls from 2.0 to about 1.8–1.9 unless the thrust stand measures at least 3.55 kgf per motor. That measurement is the first gate in Section 6.

6. Test plan

The following are checked when the parts arrive or before first flight. Each is either a measurement this programme exists to make, or a confirmation that a listing cannot give. *Planned* means the test is scheduled at the stage shown; *Open* means an action is still needed before ordering.

#	Item	Check	Acceptance	When	Status
1	Battery mass	Weigh each pack on receipt.	Expected 1.88–2.21 kg. The measured mass replaces the estimate in the take-off mass.	On receipt	Planned
2	Motor thrust	Thrust-stand test of one motor, propeller and speed controller.	$\geq$ 3.55 kgf per motor, which keeps thrust-to-weight at 2.0 at the heaviest expected mass.	Phase 2	Planned
3	Pack fuse	Log peak current on the stand and in the first flights.	The 150 A fuse must hold against a $\sim$136 A peak. This is the tightest electrical margin.	Phase 2	Planned
4	Battery failsafe	Loaded discharge of the received pack at hover current.	Failsafe parameters are set for the 16 Ah LiPo (land with 20 % left). The discharge confirms the voltage backstop fires near 20 %. **No flight before this is done.**	Before first flight	Planned
5	Speed controller (65 A)	Thrust-stand test with 18 in propellers and 340 KV motors.	Current, temperature and freedom from desynchronisation confirmed before more are bought.	Phase 2	Planned
6	Base RTK antenna cable	Obtain a quote from a local RF cable shop.	3 m RG58, 50 Ω, TNC-male to SMA-male. The INR 600 in this BOM is an estimate until quoted.	Before ordering	**Open**
7	Ground video antennas	Install one 14 dBi panel per receiver, aimed at its aircraft, and an omni on the second port.	Confirm polarisation before installation. Measure the range on our own link, not the listing's analog-FPV figure. Set coax lengths from the station layout.	Ground-station build	Planned
8	Video radio power and cooling	Bench-run the BL-M8812EU2 at the set TX power on its 5 A regulator, with heatsink and fan.	Supply holds 5 V without sagging and the radio does not throttle over a mission-length run.	Before first flight	Planned
9	USB hub	Check the supplied power adapter.	Powers the receiver (up to 1.8 A when transmitting), more than a laptop port supplies.	On receipt	Planned

#	Item	Check	Acceptance	When	Status
10	RTK rover (GenX F9P Air)	Check the maker's specification.	Dual-band: GPS L1/L2, Galileo E1/E5b, BDS B1/B2, GLONASS G1/G2; QMC5883 compass.	Before ordering	Verified

7. Basis of prices

- Prices were taken from Indian supplier listings on 19–20 September 2026. Where a supplier blocked automated checking, the same part's price at another Indian retailer was used, and that retailer is the one linked.
- Retail listings already include GST and are used as listed. Pre-GST quotations, B2B listings and estimates have 18 % GST added (INR 1,569).
- A 15 % contingency is applied to the whole, for price movement between now and each phase's purchase.
- Customs duty does not apply: every part is bought from a supplier in India.

8. Team and approval

Name	Department	Batch	Roll No.
Swastik Kumar	Electronics & Communication Engineering	2024–2028	1024060150
Samuel Masih	Computer Science & Engineering	2024–2028	1024170044
Prabhjot Singh	Robotics and Artificial Intelligence Engg.	2024–2028	1024230021
Manan Kapoor	Computer Science & Engineering	2024–2028	1024030467
Manav Pansari	Electronics & Communication Engineering	2024–2028	1024060151
Ravi Kant Raja	Robotics and Artificial Intelligence Engg.	2024–2028	1024230032
Neil Kishore	Mechanical Engineering	2024–2028	1024080017

Dr. Surbhi Sharma
Faculty Mentor
Date:

Dr. Mamata Gulati
Faculty Mentor
Date:

Swastik Kumar
Submitted on behalf of the team
Date: