South Marston, Swindon (S38) - Street Lighting Schedule 800/101 (Drawing 800/001) - Swindon Borough Council
13th November 2024

Unit Ref	Road Name (If available)	Column Height	Lantern Mounting	Column Ref	Column Fiish	Lantern Tilt	Door Lock	Planting Depth	Lantern Manufacturer/Model	Rear Shield	Canopy Colour	CMS Nodes	NEMA Socket	Dimming	LED Driver	Double Pole Isolator	Fuse	Lantern to Isolator Cabling	Electrical Service Type	Highway/Private Ownership	Column Setback Requirements
LC1-1	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-2	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-3	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-4	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-5	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-6	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-7	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-8	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-9	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-10	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-11	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-12	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-13	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-14	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-15	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-16	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-17	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-18	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-19	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-20	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way
LC1-21	New Road	6m	Post Top	CU Phosco	Galvanised	0 Degrees	M10 Hex (SL2)	1.0m	Urbis Axia 3.1 5267 16 LED 480mA 429102 3.15klm WW	N	RAL 9002 (Grey White)	Telensa GPS Enabled Product Code T2E1N-G3	One Piece 7 Pin	Design Class P4 - Step 1 2200 to Midnight 6-% Output, Step 2 Midnight to 6am 40% Output	Philips Xitanium	Lucy Trojan Midi THM0014962, complete with 6mm² brown & blue tails, plus 6mm² earth lead	4A - BS88 MD Fuse	7.25m of 3 core 2.5mm² artic flex	Direct DNO/IDNO	Highway Adoptable	Back of Footpath or 0.8m behind c/way