Phantom Scan — 2026-11 campaign recording checklist (about 3 h 15 min, ONE link state, order fixed)

Data collection only; every outcome is [TO BE MEASURED]. Follows *RECORDING-DATA-SPEC.md* and the frozen *PREREG-2026-11-recording-campaign.md* (both in `reports/presence-eval-2026-11/`). Replaces the short 1 h 10 min sheet for this campaign.

Date _____ Operator _____ campaign_id _____ link_state_id _____ Subject _____

A. Before block 1 (about 20 min)

- ☐ Pre-registration committed and unchanged: `git log -1 -- reports/presence-eval-2026-11/PREREG-2026-11-recording-campaign.md`. Hash (reported as `e3b87ca`, verify) _____ goes in `campaign.json` as `prereg_commit`
- ☐ Folder created: `data/datasets/campaign-2026-11/<campaign_id>/blocks/`; `campaign.json` filled (nodes_expected, node_placement, firmware git_hash, wifi channel, AP BSSID, operator)
- ☐ Both nodes on the **same firmware build** (boot logs checked). **No reflash, no node touched, for the whole campaign**
- ☐ Nodes, router, fan and marks A/B + walk path taped; cables taped. N1–N2 _____ m
- ☐ **Photo BEFORE** of every node in place
- ☐ Warm start: nodes and router on ≥60 min. Dashboard live, all nodes fresh
- ☐ Recorder: dashboard Training Data Capture or `record_dataset.py`. **One recording per block**, labels from the list only. Dashboard session files are **not** evaluation data
- ☐ Start RSSI (dBm) and fps: N1 _____ N2 _____ N3 _____ N4 _____ fps _____
- ☐ Laptop and operator outside the room, door closed; phone in airplane mode, no other Wi-Fi device near the nodes
- ☐ Optional: serial log running per node (`docs/serial-counter-capture.md`)

B. Blocks (fixed order; the second empty closes the campaign)

#	Folder / block_type	Recorder label	Min / plan	Condition	Start UTC ☐ Stop UTC ☐
1	`01_empty_1`	empty	≥60 / **62**	Nobody in room, fan off. **Entry log required**. Check RSSI from outside every 15 min	__:__:__ __:__:__
2	`02_fan_alone`	empty_fan	≥5 / **6**	Fan ON at its taped mark, nobody in room. Entry log required	__:__:__ __:__:__
3	`03_walking`	walking	≥5 / **6**	1 person, fan off. Slow steady walk along the taped path; end on the far mark	__:__:__ __:__:__
4	`04_still`	still	≥5 / **6**	1 person, fan off. Stand still on mark A, facing the baseline, normal breathing	__:__:__ __:__:__
5	`05_empty_2`	empty	≥60 / **62**	As block 1. **Entry log required**. Check RSSI from outside every 15 min	__:__:__ __:__:__
6	`06_fan_with_person`	still ☐ walking ☐	≥**10** / **11**	1 person, fan ON at its mark. **Choose still or walking BEFORE starting**; write it in `block.json`	__:__:__ __:__:__

Plan = minimum + 1–2 min margin; the minimum is checked on recorded frame time. Start the recording first (10 s countdown), then take position (blocks 2–4, 6) or leave the room (blocks 1, 5). Stop by timer or hotkey, never by walking to the laptop inside the room. Total about 153 min recording plus waits.

LINK CHANGE rule. A held RSSI step of **6 dB or more** on any node, or a frame rate below **0.7 ×** that node's reference rate: **stop the recording**, write **LINK CHANGE** + node + RSSI before/after + fps before/after + time in the log and in `link_change_events`, wait **2 min**, check nothing was moved, then start a **NEW block** (new recorder file). A block containing a link change is invalid. The new block gets a new `link_state_id` unless you can show the level returned. Blocks are compared only inside one link state, and **one link state must contain all six block types**. If it happens in block 1 or 5, you restart that hour.

C. Logs and files, per block

- ☐ `block.json` filled: block_id, block_type, recording name, start/stop UTC, link_state_id, person_count, person_present, fan_on, fan_position, subject, link_state_notes (RSSI seen), link_change_events, entry_log, notes
- ☐ `entry-log.txt` (empty blocks and fan alone), one line per event: `YYYY-MM-DDTHH:MM:SSZ who what`. First line `room checked empty`, last line at the end. Log every door, corridor or entry event
- ☐ RSSI per node written at the start of every block
- ☐ Recorder files kept as written: `.jsonl` and the matching `.summary.json` (one per part). Never put campaign files under `data/sessions/`
- ☐ If anything unplanned happens, write it down; do not fix it silently. Never trim by memory, only by the log

D. After the last block (about 15 min)

- ☐ **Photo AFTER**, compared with BEFORE. Any node moved? _____
- ☐ End RSSI: N1 _____ N2 _____ N3 _____ N4 _____
- ☐ Whole campaign folder copied to a second location **before any analysis**
- ☐ Validator first: `python -m scripts.presence_eval.validate_campaign <campaign folder>`. If it refuses, that is a valid outcome: report it, do not work around it
- ☐ Only then: `python -m scripts.presence_eval.run_campaign <campaign folder>`. No threshold is changed from its output
- ☐ Deviations from the plan, with date and reason: _____

Single-antenna hardware: nothing here measures angle, pose or room position. “No motion” is never “empty”. A negative result (“no candidate met the criteria”) is a valid outcome. No accuracy, detection-rate or false-alarm figure may be quoted until measured and reported by `run_campaign`.