
Computational Physics Lecture 4

sieversj@ukzn.ac.za

git clone https://github.com/ukzncompphys/lecture4 2018.git

Simpson's Rule

- Let's integrate a quadratic over three points.
- Draw a straight line between the left and right points. The middle point is now off the straight line by y_{mid}-0.5*(y_{left}+y_{right})



- What is the average value of $(1-x^2)$ between -1 and 1?
- Area is now $1/2*(y_{left}+y_{right})+2/3*(y_{mid}-0.5*(y_{left}+y_{right}))$
- simplify: area= $1/6*y_{left}+2/3*y_{mid}+1/6*y_{right}$.
- for a bunch of points, string together segments, y_{right} become y_{left} of the next segment.
- Simpson's rule: integral= $dx^*(1/6 y_0 + 2/3y_{odd} + 1/3y_{even} + 1/6 y_{last})$

Fourier Transforms

- Functions can be represented in many different ways
- We normally use "real" space f(x)
- Generally, arbitrarily many transforms exist to represent functions in different spaces F(y)=Af(x) for some matrix A and some new variable y. Iff A is invertible, $f(x)=A^{-1}F(y)$
- One important basis nature has picked out is complex exponentials/sines and cosines. Fundamental across physics, particularly quantum mechanics.

Fundamental Definition

- $F(k) = \int f(x) \exp(-2\pi i kx) dx$ (where $k = I/\omega$)
- Integral gets rid of x, replaces with k. New function has amplitude and phase as a function of k.
- Quantum mechanics de Broglie says $p = \hbar k$. So, Fourier transform position to get momentum.
- Fourier transform electric field E(t) to get frequency spectrum.
- Fourier transform to get fast correlations, convolutions, many other things.

DFT (Discrete FT)

- Computers don't do continuous. Not enough RAM for starters...
- Function exists over finite range in x at finite number of points.
- If input function has n points, output can only have n k's.
- Gives rise to discrete Fourier Transform (DFT)
- $F(k)=\sum f(x)\exp(-2\pi ikx/N)$ for N points and $0 \le k \le N$
- What would DFT of f(0)=1, otherwise f(x)=0 look like?
- What would DFT of f(x)=1 look like?
- DFTs have subtle behaviours not seen in continuous, infinite FTs.

Inverse

- One way to think about DFT is as a matrix multiply.
- $F(k)=Af, A_{mn}=exp(2\pi i mn/N)$
- But look $A_{mn} = = A_{nm}$, so matrix is symmetric.
- Also, columns are orthogonal under conjugation: $\sum \exp(-2\pi i kx) \exp(2\pi i k'x) = \sum \exp(2\pi i (k'-k)x)$. N if k'==k, otherwise 0.
- So, A⁻¹=I/N*conj(A). IFT= $I/N \Sigma F(k) \exp(-2\pi i kx)$.
- Get back to where we started by just doing another DFT with a sign flip, then divide by # of data points.
- Alternative: divide by $\sqrt{(N)}$ in both DFT and IFT, (not standard computationally)

Numpy Complex

```
import numpy
def exp_prod(m,n,N):
    #define imaginary unity
    J=numpy.complex(0,1)
    #now rest of code is just like for real numbers
    x=numpy.arange(0.0,N)*2*J*numpy.pi/N
    return numpy.sum(numpy.exp(-1*x*m)*numpy.exp(x*n))
if __name__ == "__main__":
    print exp_prod(0,0,8)
    print exp_prod(2,4,8)
    print exp_prod(3,3,8)
    print exp_prod(0,7,8)
```


```
Jonathans-MacBook-Pro:lecture4 sievers$ python dft_columns.py (8+0j) (-4.28626379702e-16+4.4408920985e-16j) (8+0j) (3.44169137634e-15-1.11022302463e-15j) Jonathans-MacBook-Pro:lecture4 sievers$ ■
```

- Let's check orthogonality, need complex #'s.
- numpy.complex(re,im) will make a complex #
- numpy functions usually defined for complex #'s.

DFTs with Numpy

- Numpy has many Fourier Transform operations
- (for reasons to be seen) they are called *Fast* Fourier Transforms FFT is one way of implementing DFTs.
- FFT's live in a submodule of numpy called FFT
- xft=numpy.fft.fft(x) takes DFT
- x=numpy.fft.ifft(x) takes inverse DFT
- Numpy normalizes such that f==fft(ifft(f))==ifft(fft(f))


DFT in Action



- Right: input Gaussian
- Top: DFT of the Gaussian

```
import numpy
from matplotlib import pyplot as plt

x=numpy.arange(-10,10,0.1)
y=numpy.exp(-0.5*x**2/(0.3**2))
yft=numpy.fft.fft(y)
plt.plot(numpy.abs(yft))
plt.savefig('gauss_dft')
plt.show()
```




Periodicity

- $f(x)=\sum F(k) \exp(-2\pi i kx/N)$
- What is f(x+N)? $\Sigma F(k) \exp(-2\pi i k(x+N)/N)$
- = $\sum F(k) \exp(-2\pi i k) \exp(-2\pi i k x/N)$.
- $\exp(-2\pi i k) = I$ for integer k, so f(x+N) = = f(x)
- DFT's are periodic they just repeat themselves ad infinitum.


Periodicity

```
import numpy
from matplotlib import pyplot as plt

x=numpy.arange(-2,2,0.1)
y=numpy.exp(x)
plt.plot(x,y)
plt.savefig('fft_exp')
plt.show()
yy=numpy.concatenate((y,y))
yy=numpy.concatenate((yy,yy))
yy=numpy.concatenate((yy,yy))
plt.plot(yy)
plt.savefig('fft_exp_repeating*)
plt.show()
```



- You may think you're taking top transform. You're not - you're taking the bottom one.
- In particular, jumps from right edge to left will strongly affect DFT




Aliasing

- $f(x) = \sum F(k) \exp(2\pi i kx/N)$
- What if I had higher frequency, k>N? let $k^*=k-N$ (i.e. k^* low freq.)
- $f(x)=\sum F(k) \exp(2\pi i(k^*+N)x/N)=\sum F(k)\exp(2\pi ix)\exp(2\pi ik^*x/N)$
- for x integer, middle term goes away: $\sum F(k^*+N)\exp(2\pi i k^*x/N)$
- High frequencies behave exactly like low frequencies power has been aliased into main frequencies of DFT.
- Always keep this in mind! Make sure samples are fine enough to prevent aliasing.

Negative Frequencies

- All frequencies that are N apart behave identically
- DFT has frequencies up to (N-I).
- Frequency (N-I) equivalent to frequency (-I). You will do better to think
 of DFT as giving frequencies (-N/2,N/2) than frequencies (0,N-I)
- Sampling theorem: if function is band-limited highest frequency is V then I get full information if I sample twice per frequency, dt=I/(2V). Factor of 2 comes from aliasing.


DFT in Action, Redux



 FFT makes more sense now - negative frequencies have been aliased to high frequency.

```
import numpy
from matplotlib import pyplot as plt

x=numpy.arange(-10,10,0.1)
y=numpy.exp(-0.5*x**2/(0.3**2))
yft=numpy.fft.fft(y)
plt.plot(numpy.abs(yft))
plt.savefig('gauss_dft')
plt.show()
```




Flipping

- What is DFT of f(-x)?
- $\sum f(-x) \exp(-2\pi i kx/N), x^*=-x, \sum f(x^*) \exp(-2\pi i k(-x)/N)$
- DFT(f(-x))= $\sum f(x) \exp(2\pi i kx/N) = \operatorname{conj}(F(k))$

Shifting

- What is FFT(x+dx)? $\sum f(x+dx) \exp(-2\pi i kx/N)$.
- $x^*=x+dx$: $F(k)=\sum f(x^*)\exp(-2\pi i k(x^*-dx)/N)$
- $F(k) = \exp(2\pi i k dx/N) \sum f(x^*) \exp(-2\pi i k x^*/N)$
- So, just apply a phase gradient to the DFT to shift in x

Shifting Example



```
import numpy
from matplotlib import pyplot as plt

x=numpy.arange(-10,10,0.1)
y=numpy.exp(-0.5*x**2/(1.5**2))
N=x.size
kvec=numpy.arange(N)
yft=numpy.fft.fft(y)
J=numpy.complex(0,1)
dx=5.0;
yft_new=yft*numpy.exp(-2*numpy.pi*J*kvec*dx/N)
y_new=numpy.real(numpy.fft.ifft(yft_new))
plt.plot(x,y)
plt.plot(x,y)
plt.savefig('shifted_gaussian')
plt.show()
```

Real Data Symmetry

- If I know F(k), what is F(N-k) if f(x) is real?
- F(N-k)=F(-k) (from alias theorem)
- $F(-k)=\sum f(x)\exp(-2\pi i(-k)x/N)$. let $x^*=-x$
- $F(-k)=\sum f(-x^*)\exp(2\pi i kx^*/N) = \operatorname{conj}(F(k))$ by flipping
- So, if f(x) is real, F(k) = conj(F(N-k))
- If N even, F(N/2)=conj(F(N/2)), so F(N/2) must be real.


```
>>> x=numpy.random.randn(8)
>>> xft=numpy.fft.fft(x)
>>> for xx in xft:
... print xx
...
(-4.53568815727+0j)
(-0.174046761579+2.08827239558j)
(2.15348308858+2.32162497273j)
(-0.423040513854-3.72126858798j)
(2.75685372591+0j)
(-0.423040513853+3.72126858798j)
(2.15348308858-2.32162497273j)
(-0.174046761579-2.08827239558j)
>>>
```

Convolution Theorem

- Convolution defined to be $conv(y)=f\otimes g==\int f(x)g(y-x)dx$
- $\sum_{x} \sum F(k) \exp(2\pi i k x) \sum_{x} conj(G(k')) \exp(2\pi i k' x) \exp(-2\pi i k' y/N)$
- Reorder sum: $\sum \sum F(k) \operatorname{conj}(G(k')) \exp(-2\pi i k' y/N) \sum_{x} \exp(2\pi i (k+k')x)$
- equals zero unless k'==-k. Cancels one sum, conjugates G
- $f \otimes g = \sum F(k)G(k) \exp(2\pi i k y/N) = ift(dft(f)*dft(g))$
- So, to convolve two functions, multiply their DFTs and take the IFT

Convolution Example

```
from numpy import arange,exp,real
from numpy.fft import fft,ifft
from matplotlib import pyplot as plt
def conv(f,g):
    ft1=fft(f)
    ft2=fft(g)
    return real(ifft(ft1*ft2))
x=arange(-10,20,0.1)
f = \exp(-0.5*(x+3)**2/0.5**2)
g=0*x;g[(x>0)&(x<5)]=1
g=g/g.sum()
f=f/f.sum()
h=conv(f,g)
plt.plot(x,f,'b')
plt.plot(x,g,'k')
plt.plot(x,h,'r')
plt.savefig('convolved')
plt.show()
```



Fast Fourier Transform

- How many operations does a DFT take?
- Have an N by N matrix operating on a vector of length N clearly N² operations, right?
- Nope! Otherwise we'd never use them. What's actually going on?
- Note DFT= $\sum f(x) \exp(-2\pi i k x/N) = \sum f_{even}(x) \exp(-2\pi i k (2x)/N) + \sum f_{odd}(x) \exp(-2\pi i k (2x+1)/N)$
- = F_{even} +exp(- $2\pi i k/N$) F_{odd} . Let W_k =exp(- $2\pi i k/N$)
- if k>N/2, then $k^*=k-N/2$ and DFT= $F_{even}+exp(-2\pi i k^*/N+i\pi)F_{odd}=F_{even}-W_kF_{odd}$.

FFT cont'd

- So $F(k)=F_{even}(k)+W_kF_{odd}(k)$ (k<N/2) or $F_{even}(k)-W_kF_{odd}(k)$ (k>=N/2)
- So, can get *all* the frequencies if I have 2 half-length FFTs.
- Well, just do the same thing again. FFT of a single element is itself.
- This algorithm works for arrays whose length is a power of 2
- Popularized by Cooley/Tukey in early computer days. Later found to go back to Gauss in 1805. Changes computational work from n² to nlogn.

Sample FFT

- Routine uses recursion function calls itself. Recursion can be very powerful, but also easy to goof.
- numpy.concatenate will combine arrays - note that they have to be passed in as a tuple, hence the extra set of parenthesis
- Modern FFT routines deal with arbitrary length arrays. Fastest Fourier Transform in the West (FFTW) standard packaged usually used by numpy.

```
from numpy import concatenate, exp, pi, arange, complex
def myfft(vec):
    n=vec.size
    #FFT of length 1 is itself, so quit
    if n==1:
        return vec
    #pull out even and odd parts of the data
    myeven=vec[0::2]
    myodd=vec[1::2]
    nn=n/2;
    j=complex(0,1)
    #get the phase factors
    twid=exp(-2*pi*j*arange(0,nn)/n)
    #get the dfts of the even and odd parts
    eft=myfft(myeven)
    oft=myfft(myodd)
    #Now that we have the partial dfts, combine them with
    #the phase factors to get the full DFT
    myans=concatenate((eft+twid*oft,eft-twid*oft))
    return myans
```

```
>>> import myft
>>> x=numpy.random.randn(32)
>>> xft1=numpy.fft.fft(x)
>>> xft2=myft.myfft(x)
>>> print numpy.sum(numpy.abs(xft1-xft2))
2.33937690259e-13
>>>
```