SHOP GUIDE · 0.1.8

Universal POS: the complete shop guide

Every screen and every setting, explained step by step for shop owners, managers and cashiers.

CONTENTS

Universal POS: the complete shop guide

1. Install the app

2. First start: set up your shop

3. Sign in and find your way around

4. Products, categories, tax rates, import and delete

5. Staff and PINs

6. Selling

7. Payment and the bill

8. Orders, returns and voids

9. Shifts and end of the day

10. Customers, credit and points

11. Stock, suppliers and purchase orders

12. Reports

13. Settings, card by card

14. Printer, scanner, scale and card machines

15. More than one till: shop hub and server

16. Problems and quick answers

17. Restaurant and cafe: tables, kitchen, QR orders

18. Customer links: bills, loyalty page, QR menu

19. Self-checkout kiosk, appearance and shop reset

20. Install, update and back up without internet

Universal POS: the complete shop guide

Version 0.1.4. For shop owners, managers and cashiers. No technical knowledge needed.

This guide explains every screen and every setting of Universal POS, in the order you meet them: install, set up the shop, add products, sell, close the day, and later add printers, scanners, scales, card machines and more tills.

The pictures show a sample shop, **Sharma Kirana Store**. Your screens show your own shop. Most pictures are from a computer; where a phone looks different, a phone picture is shown too.

What Universal POS does

- **Billing**: scan or tap items, take cash, UPI, card, credit or points, print or save the bill.
- **GST**: works out CGST and SGST on every bill, prints a tax invoice or a bill of supply.
- **Stock**: every sale lowers stock; you receive, count and correct stock.
- **Customers**: credit (udhaar) with limits, loyalty points, purchase history.
- **Reports**: sales, tax and payments for any dates; end-of-day cash count.
- **Many tills**: several phones and computers in one shop share products and sales, with or without internet.

It works without internet. Every sale is saved on the device first. Internet is only needed for card machines and for sending data to your server.

Words used in this guide

Word	Meaning
Till	One device that makes bills: a phone, tablet or computer at the counter.
Staff / PIN	Every person who uses the app has a name and a secret 4–6 digit PIN.
Role	What a person may do: **Cashier**, **Manager** or **Admin** (owner).
Shift	The time between opening the cash drawer (with some starting cash) and counting it at the end.

Word	Meaning
Invoice series	A short code for each till, like `A1`. Bills from that till are numbered `A1-000001`, `A1-000002`...
Cart	The bill being made right now, before payment.
Held bill	A bill put aside (paused) so you can serve another customer first.
Void	Cancelling a whole bill.
Return	Taking back some or all items of a bill and paying the money back.
Sync	Devices of the same shop exchanging new sales, products and changes.
Shop hub	One computer in the shop that the other tills sync with over the shop Wi-Fi, even without internet.
Server / cloud	A computer on the internet that keeps a copy of the shop's data and lets the owner see it from a browser.
License	A small file that unlocks the app after the 30-day free trial.

Who can do what

Task	Cashier	Manager	Admin (owner)
Sell, hold bills, take payments	Yes	Yes	Yes
Add a new customer quickly at the till, receive credit payments	Yes	Yes	Yes
Discount above the cashier limit, voids, returns	Manager PIN needed	Yes	Yes
Edit products, customers, import products	Manager PIN needed	Yes	Yes

Task	Cashier	Manager	Admin (owner)
Open the cash drawer without a sale	Manager PIN needed	Yes	Yes
Stock, suppliers, purchase orders, reports	No	Yes	Yes
Printer, scanner, scale settings	No	Yes	Yes
Staff, shop details, selling rules, loyalty, license, card machines, sync	No	No	Yes

"Manager PIN needed" means the app asks a manager or admin to type their PIN on the same screen, right then. The cashier does not need to sign out.

Which device for what

Device	Good for
Android phone or tablet	A till at the counter, a second till at busy times, stock counting on the shop floor
Windows or Linux computer	Main counter till, the shop hub, reports, product entry with a keyboard
Mac	Same as a computer till
iPhone / iPad	A till (printers and scales only through the shop hub or over the network)
Web browser	Owner's view from home: products, orders, reports (needs a server)

1. Install the app

Licences and help: WhatsApp or call **+91 89229 62849**, e-mail **universalpos2026@gmail.com**.

Your supplier gives you the install file for your device. All files have the version in the name, for example `0.1.4`. Use the same version on every till of the shop.

Android phone or tablet

You get a file named like `universal-pos-0.1.4.apk`.

1. Copy the file to the phone: USB cable, memory card, or a file-sharing app.
2. Open the phone's **Files** app and tap the file.
3. Android may say the app is from an unknown source. Tap **Settings**, turn on **Allow from this source**, and go back. This is needed only once.
4. Tap **Install**, then **Open**.

The app needs no Google account, no sign-up and no internet.

Updating: install the new file the same way, or from 0.1.8 use **Settings** → **Updates** with the update file your supplier gives you (chapter 20). Your shop data stays. If Android refuses ("App not installed"), ask your supplier before uninstalling: uninstalling a phone app deletes the data on that phone. Test builds from before 0.1.8 need this once: **Settings** → **Backup** → **Back up now** to a pen drive, uninstall, install 0.1.8, then **Restore from backup** (chapter 20).

Windows computer (Windows 10 or 11, 64-bit)

You get `UniversalPOS-Setup-0.1.4.exe`.

1. Double-click the file.
2. If Windows shows **Windows protected your PC**, click **More info**, then **Run anyway**. (The installer is not signed yet; this is expected.)
3. Click **Next** and **Install**.
4. Open **Universal POS** from the Start menu or the desktop icon.

The first time the shop hub is turned on (chapter 15), Windows asks whether to allow the app on networks: allow it on **private networks**.

Linux computer

Linux	Steps
Ubuntu, Debian, Linux Mint	Double-click `universal-pos_0.1.4_amd64.deb` and click **Install**, or in a terminal: `sudo apt install ./universal-pos_0.1.4_amd64.deb`
Any other Linux	Unpack `universal-pos-0.1.4-linux-x64.tar.gz`, open the folder, run `./install.sh` (no admin password needed). `./uninstall.sh` removes it.

Open **Universal POS** from the applications menu.

For USB or serial printers, scanners and scales on Linux, the computer user must be allowed to use those ports. Ask your supplier to run this once: `sudo usermod -aG lp,dialout <user name>`, then sign out of the computer and in again.

Mac

You get a zip file with **Universal POS.app**.

1. Double-click the zip to unpack it and drag **Universal POS** into **Applications**.
2. The first time only: right-click (or Control-click) the app and choose **Open**, then **Open** again. (The app is not signed with Apple yet, so a normal double-click is refused the first time.)

iPhone and iPad

The iPhone app is not on the App Store yet. Installing it needs an Apple developer account and is done by your supplier. After that, it works like the Android app.

Uninstalling


- **Windows, Linux, Mac:** uninstalling the program does not delete the shop data.
- **Android, iPhone:** uninstalling deletes the data on that device. If the shop syncs with a hub or server, the data is safe there; otherwise do not uninstall.

Screen sizes

Any screen works. A wide window (computer) shows a sidebar on the left; a narrow one (phone, or a small window) shows a menu button at the top instead. Both have the same screens.

2. First start: set up your shop

The first time the app opens, it asks **How do you want to start?**




Choose New shop or Join existing shop

Choice	Pick it when
New shop	This is the shop's first (or only) till. Works without internet.
New outlet of an existing business	A second shop (branch) of a business that already uses Universal POS elsewhere, set up on its own. Type or scan the **Business id** from the first outlet (**Settings → License → Business id**), then fill in the steps as for a new shop. Your supplier can then put both outlets under one account.
Join existing shop	The shop already has Universal POS on another device (a shop hub or a server) and this till should share its products, staff and sales.
Restore from backup	A new or reset device takes over a shop from a backup file (`.posbackup`) and the shop's licence. See chapter 20.

If you are not sure: pick **New shop** on the first device, and **Join existing shop** on every device after that.

New shop

Four short steps. The top shows **Step 1 of 4**, and so on. Click **Next** after each step and **Finish** at the end. **Back** goes to the previous step.



New shop, step 1

Step 1: Shop

Field	What to type	Example
Shop name	The name printed at the top of every bill	Sharma Kirana Store
Address	Shop address, printed on the bill	12 MG Road, Indore
Phone	Shop phone number, printed on the bill	9800000000

Step 2: GST

Field	What to type
GSTIN (optional)	Your 15-character GST number. Leave it empty if the shop is not registered for GST. The app checks that the number is written correctly.
State	The state your shop is in. The first two digits of the GSTIN must match it. It decides CGST + SGST (same state).
GST scheme	**Regular**: bills are tax invoices showing CGST and SGST. **Composition**: bills are "bill of supply" without tax shown. Ask your accountant if unsure; most shops are Regular.

The app creates the common GST rates for you (0%, 3%, 5%, 18%, 40%). You can add or change rates later (chapter 4).

Step 3: First admin (the owner)

Field	What to type
Admin name	The owner's name. It shows on bills you make and in reports.
PIN (4–6 digits)	The owner's secret PIN. Anyone with this PIN can do everything, so keep it private.
Confirm PIN	The same PIN again.

Do not forget this PIN. It is needed to add staff, change settings and approve voids and returns.

Step 4: Invoice series


A short code for this till, for example `A1`. Bills are numbered `A1-000001`, `A1-000002` and so on.

- Every till of the shop needs its **own** code (`A1`, `A2`, `B1` ...). Two tills with the same code would make duplicate bill numbers.
- The series cannot be changed later on this till. Everything else from setup can be changed in **Settings**.

Click **Finish**. The sign-in screen opens (chapter 3).

Join existing shop

Use this on a second (third…) till. The first device must be set up already.



Join existing shop

1. **Server address**: where the shop's data is. - Shop hub in the same shop (chapter 15): click **Find shop hub on this network**. The address fills in by itself (for example `http://192.168.1.10:8787`). If nothing is found, type the address shown on the hub's **Settings** → **Shop hub** card. - Server on the internet: type the address your supplier gave you, for example `https://pos.example.com`.
2. **Pairing code**: an 8-character code. Get it from: - the shop hub: **Settings** → **Shop hub** → **New pairing code**, or - your supplier or the owner, for a server.

A code works **once**, for **15 minutes**. 3. **Invoice series code**: this till's own code (the app suggests one, like `A2`). It must be different from every other till. 4. Click **Join**. The app shows **Pairing…**, **Checking license…** and **Downloading shop data… (number) records**. Keep the app open until the sign-in screen appears. Large shops can take a few minutes.

If the download stops (for example the Wi-Fi dropped), open the app again and click **Continue download**.


Messages you may see when joining

Message	What to do
Wrong or expired pairing code.	Get a new code (they last 15 minutes and work once).
Cannot reach the server. Check the address and the network.	Check the address and that both devices are on the same Wi-Fi (hub) or online (server).
Another till in this shop already uses this invoice series.	Choose another series code.
The shop has reached its device limit. Remove a device first.	The license allows a fixed number of tills; remove an old till on the hub or ask your supplier.
Too many attempts. Wait a minute and try again.	Wait one minute.

3. Sign in and find your way around

Sign in

Every time the app opens (and after **Sign out** or **Switch user**), it asks who is working.




Sign in

1. Click (tap) your name.
2. Type your PIN on the keyboard or the on-screen number pad.

- A wrong PIN is refused. After several wrong tries the app waits a short time before you can try again.
- **Language** at the bottom switches between English and हिन्दी.
- The bottom also shows the app version, for example *Version 0.1.4 (build 5)*. Tell it to your supplier when you ask for help.
- Each person should use their own name and PIN, so every bill shows who made it.

The app can sign out by itself when nobody uses it for some minutes: see **Idle logout** in chapter 13.

The main screen on a computer




Sell screen with the sidebar and the top bar

The sidebar (left)

Item	What it is for	Who sees it
Collapse	Shrinks the sidebar to small icons for more room. Click again (**Expand**) to open it.	Everyone
Sell	Making bills (chapter 6)	Everyone
Orders	Past bills, reprint, returns, voids (chapter 8)	Everyone
Customers	Customer list, credit, points (chapter 10)	Everyone
Shift	Open and close the cash drawer shift (chapter 9)	Everyone (when shifts are on)
Reports	Sales, tax and payments (chapter 12)	Manager, Admin

Item	What it is for	Who sees it
Products (click to open the group)	**All products**, **Categories**, **Tax rates**, **Import** (chapter 4)	Everyone (cashier changes need a manager PIN)
Stock	Stock on hand, receive, count, adjust (chapter 11)	Manager, Admin
Suppliers, **Purchase orders**	Buying from suppliers (chapter 11)	Manager, Admin
Staff	Staff names, roles and PINs (chapter 5)	Admin
Settings	All settings (chapter 13). Each person sees only the cards their role may change.	Everyone
Fullscreen (bottom)	Hides the computer's own window bars. **Exit fullscreen** brings them back.	Everyone

The top bar




The user menu

Item	What it does
Shop name	Your shop's name.
Search products or scan barcode	Type part of a name, a barcode or a SKU. On the keyboard, `/` jumps here.
Trial · 30 days left chip	Days left in the free trial or the license (chapter 13, License). Click it to open Settings.
⚠ with a number	Products that are low or out of stock. Click to see them in Stock.
Cloud icon	Sync status (only when the till syncs with a hub or server): **Synced**, **Syncing…**, **Server not reachable**, **Sync error**. Click to sync now. A crossed-out cloud means this till works on its own.
Printer icon	Shows when a printer is set up. Turns red when printing failed; click it for **Print again**, **Open drawer** or **Printer settings**.
Calculator	A simple calculator.
Refresh	Reloads all lists.
EN / हि	Switches the language.
₹ INR	The shop's currency.
Sun / moon	Light or dark colours.
Your name and role	Opens the menu: your role, **Switch user** (another person signs in; nothing is lost) and **Sign out**.

The main screen on a phone

On a phone the sidebar is hidden. Tap the **menu** button (three lines, top left) to open it. The top bar keeps the search box, the low-stock warning, the **cart** button (with the number of items) and your initial (the user menu).



Phone menu

Keyboard shortcuts (computer)

Key	What it does
Scan with a USB or Bluetooth scanner	Adds the product on the Sell screen at once; no need to click anywhere
`/`	Jump to the search box
A number, then `*` (for example `5*`), then scan or click a product	Adds 5 of that product
`+`	One more of the last item
`Ctrl+N`	New item on the list screen you are on (product, category, customer…)
`Esc`	Back (for example from a product to the list)

4. Products, categories, tax rates, import and delete


Set these up once before you start selling. Open **Products** in the sidebar; it opens four screens: **All products**, **Categories**, **Tax rates** and **Import**.

A cashier can look at products; any change needs a manager's or admin's PIN.

Do them in this order: **tax rates** → **categories** → **products** (a product points to a tax rate and a category).

Tax rates

Products → **Tax rates.** Setup already created GST 0%, 3%, 5%, 18% and 40%. Add one only if you need another rate.




Tax rates

Field	What to type
Name	How it shows in lists, for example `GST 12%`
Rate (%)	The full GST rate, for example `12`. The app splits it into CGST 6% + SGST 6% on the bill.

Prices in this app **include** GST. The bill shows how much of the price is tax.

Categories

Products → Categories. Groups such as Grocery, Dairy, Snacks. Each category becomes a filter button (chip) on the Sell screen, so the cashier finds items faster.




Categories


Click **+** (or `Ctrl+N`), type the **Name**, **Save**. Click a category to rename it.

Products

Products → All products. The list is on the left; the selected product opens on the right (on a phone it opens as its own page). Search by name, barcode or SKU. Click **+** for a new product.



Product list



Product form

The form has these parts:

Image

Choose image picks a photo file from the device (up to 25 MB; it is made smaller automatically). **Change image** replaces it, **Remove image** deletes it. The photo shows on the Sell screen tile, in lists and in the cart. Optional.

Basics

Field	What it means	Example
Name	The name printed on the bill. Required.	Basmati Rice 1kg
Barcode	The number under the barcode stripes. Scanning it adds the product. On phones, the camera button next to it reads the barcode with the camera. If another product already has this barcode, the app warns (**Barcode already in use**); you can still **Save anyway**.	8900001000042
SKU	Your own short code for the product. Typing it in Sell search finds it. For scale stickers it must be 5 digits.	10001
Category	Which chip it appears under on the Sell screen.	Grocery

Pricing

Field	What it means
Price (₹)	The selling price **including GST**. Rupees with up to 2 decimals, e.g. `45` or `45.50`.
MRP (₹)	Maximum retail price printed on the pack. Optional. Cannot be below the price.
Cost (₹)	What you pay the supplier. Optional; used for stock value. Receiving stock can update it.

Tax & HSN

Field	What it means
Tax rate	Which GST rate applies (from **Tax rates**).

Field	What it means
HSN code	The HSN code of the item, printed on tax invoices. Ask your accountant or check the supplier's bill.

Selling

Field	What it means
Unit	Pieces (pcs), Kilogram (kg), Gram (g), Litre (l), Millilitre (ml) or Metre (m). Printed on the bill.
Sold by weight	Turn on for loose items (sugar, dal, vegetables). On Sell, the item asks for its weight (or reads it from the scale). Shown only when **Weighed items** is on in Settings → Feature flags.
Quick key position (0-99)	Puts the product on the **Quick keys** chip of the Sell screen, in this position, for one-tap selling of your fastest items. Empty = not a quick key.

Stock


Field	What it means
Track stock	On (normal): sales lower the stock and you see stock levels. Off for things you do not count (services, carry bags).
Reorder level	"Alert when stock falls to this". When stock reaches this number the product is marked **Low** and counted in the ⚠ warning in the top bar.
Archived	Hides a product you no longer sell. It disappears from Sell but old bills and reports keep it. Turn off to bring it back. **Show archived** in the list shows hidden products.

Click **Save**. Errors are shown in red under the field (for example "Name is required", "MRP cannot be below the price").

Variants (sizes, colours, packs)

For a product sold in several sizes or colours (a T-shirt in S/M/L, detergent in 500 g / 1 kg / 2 kg):

1. Create the product with its name, category and tax rate and turn on **This product has variants**. The "parent" product itself has no price and is never sold. **Save**.
2. The **Variants** card appears. Add each one with **Add variant**: **Variant label** (e.g. `500 g` or `Red / L`), its own barcode, SKU and price.
3. Or click **Create many**: give each option its values, separated by commas (Option 1 = Size: `S, M, L`; Option 2 = Colour: `Red, Blue`). **Price for all** is optional. The preview shows how many new variants will be made (here 6). **Create**.




Product with variants

Each variant has its own stock. On Sell, tapping the product opens a small picker to choose the variant. A variant you stop selling can be **Archive**d and later **Restore**d.

Import many products from a file

Products → **Import** loads hundreds or thousands of products at once from a CSV file. A CSV file can be saved from Excel or Google Sheets (**File** → **Save as / Download** → **CSV**) or exported from another billing program.



Import

The import has five steps, shown at the top:

1. **Pick file**: click **Choose CSV file**.
2. **Map columns**: the app guesses which column of your file is the Name, Barcode, SKU, Price, MRP, Cost, Tax rate, Category, Unit, Sold by weight and HSN. Check each one; set columns you do not need to **Ignore**. At least Name is needed.
3. **Preview**: the first rows as they will be imported. Rows marked **Error** have a problem (shown in words, e.g. "MRP is below the price", "Unknown tax rate: 12%").
4. **Import**: click **Start import**. You can **Pause** and **Resume**; you can even close the app and continue later. A banner at the top shows progress on other screens.
5. **Summary**: rows done, created, updated and errors. **Save error rows** writes the rows with problems to a file: fix them in Excel and import that file.

Good to know:

- A row with the same barcode or SKU as an existing product **updates** that product. Rows with neither a barcode nor a SKU always create a new product, so importing such a file twice makes duplicates.
- Tax rate values must match a rate name or percentage you have (for example `5` or `GST 5%`).
- Categories that do not exist yet are created.
- Sold by weight must be `yes` or `no`.

- Importing the same file twice asks **File already imported** first.
- A sample file with 100 products is available from your supplier (`products-100.csv`) to try the import.

Import categories or stock from a file

The same screen also takes two smaller files. Choose the kind at the top before **Choose CSV file**:

Kind	The file has	What happens
Products	The columns above	As described above
Categories	One category name per row	New names become categories; names you already have are skipped
Stock	Barcode or SKU, a quantity, and optionally a cost	Each row updates that product's stock

For **Stock**, match the columns, then choose what the quantities are:

- **Received**: added to what is on hand, like a delivery. A cost column also updates the product's cost.
- **Counted**: on hand becomes the number in the file, like a stock take. Equal counts change nothing.

Rows whose barcode or SKU matches no product, products that do not track stock and bad numbers are listed in the summary; **Save error rows** writes them to a file. Categories need the right to edit products; stock needs a manager or admin (a cashier is asked for a manager's PIN).

Delete for good (admin)

Signed in as an **admin**, every form has a red **Delete** button: products (with their variants), categories, tax rates, customers, suppliers, draft or cancelled purchase orders, staff, and in restaurants tables, areas, modifier groups and stations. After you confirm, the item disappears from every list on every till, also from **Show archived**, and cannot be brought back. Managers and cashiers do not see the button; they can only archive.

Bills, payments, stock movements and the customer credit ledger are never deleted: they are the shop's GST record. Old bills keep printing the deleted product's name and price as they were. The app refuses a delete, and says why, when:

- a product is on an open table order;
- products still use the category or tax rate;


- a customer still owes money or has loyalty points;
- a purchase order was already ordered or received;
- it is your own account, or the shop's last admin;
- an area still has tables, or a table has an open order.

Not sure? Archive instead: it hides the item the same way and can be undone.

Delete needs 0.1.4 build 6 or newer on every till and on the web panel. An older till keeps the delete and applies it once it is updated.

5. Staff and PINs


Staff in the sidebar (admin only). Add every person who uses the app, each with their own PIN, so every bill, discount, void and stock change shows who did it.



Staff

Add or change a person

Click **+** (or `Ctrl+N`) for a new person, or click a name to change it.



Staff form

Field	What to type
Name	The person's name as it should show on bills and reports
Role	**Cashier**, **Manager** or **Admin** (see below)
PIN (4–6 digits)	Their secret PIN. When changing a person, leave it blank to keep the current PIN.
Confirm PIN	The same PIN again
Archived	Turn on when the person leaves. They can no longer sign in; their old bills keep their name.

Click **Save**.

Roles

Role	Can do
Cashier	Sell, hold bills, take payments, add a customer quickly, receive credit payments. A bigger discount than allowed, voids, returns, product or customer changes, CSV import and opening the drawer need a manager's or admin's PIN on the spot. No stock, purchasing, reports, staff or settings (except language and idle logout).
Manager	Everything a cashier can, plus voids, returns, discounts, products, customers, stock, suppliers, purchase orders, reports and the printer, scanner and scale settings. Cannot change staff or shop settings.
Admin	Everything, including staff, shop details, selling rules, loyalty, license, card machines and sync. The owner is an admin.

The last active admin cannot be archived or made a cashier or manager.

An admin can also **Delete** a person for good (chapter 4, *Delete for good*). Old bills keep their name. You cannot delete your own account or the last admin.

Manager approval

When a cashier does something that needs approval, the **Manager approval** window opens: "A manager or admin must enter their PIN to allow this." The manager picks their name under **Approver** and types their PIN. The cashier stays signed in. The bill or report records who approved.


- "PIN not accepted": wrong PIN.
- "Locked. Try again in … s": too many wrong PINs; wait.
- "No manager or admin with a PIN": add a manager first.

Good habits

- Never share PINs. A cashier using the owner's PIN can do everything.
- Change a PIN at once if someone may have seen it.
- Keep at least two admins (for example owner and a trusted manager), in case one PIN is forgotten.
- Turn on **Idle logout** (chapter 13) on counters where the till is left alone.

6. Selling

Open **Sell** in the sidebar. This is the screen your cashiers use all day.



Sell screen

If shifts are on (chapter 9) and no shift is open, a banner says **Open a shift to start selling**: click **Open shift**, type the cash in the drawer, and continue.

The screen

Part	What it does
Category chips (All, Quick keys, Dairy, Grocery… `+2` = more)	Show only that category's products. **Quick keys** shows your fastest items (set in each product).
Name A–Z / Price	Sort the tiles.

Part	What it does
Product tiles	Name, price, **Stock** left (with **Low** or **Out** warnings), a **+** button. A number in the corner = how many are already in the cart. A product with sizes shows "3 variants" and an arrow.
Search box (top bar)	Type a name, barcode or SKU; pick from the results.
Scan icon next to the chips	Camera scanning (phones and tablets; turn it on in Settings → Barcode scanner).
Cart (right side; on a phone, the cart button in the top bar)	The bill being made.

Add items

Any of these:

- **Scan** the barcode with a scanner. No need to click anywhere first.
- **Tap a tile** (or its **+**). Each tap adds one more.
- **Search** and pick.
- **Camera**: tap the scan icon, hold barcodes in front of the camera one after another, **Done** when finished (details in chapter 14).
- **Several at once**: type the number then `*` (for example `6*`), then scan or tap the product: 6 are added.
- `+` on the keyboard: one more of the last item.

A barcode the app does not know shows **Not found**: check the product's barcode in Products, or search by name.


Products with sizes (variants)

Tapping a product with variants opens a picker; tap the size or colour you are selling.

Loose items sold by weight


- **With a weighing scale connected** (chapter 14): put the item on the scale and tap its tile. The weigh window shows the live weight and adds the item as soon as the weight is steady (or when you tap **Use weight**). **Type weight** lets you enter it by hand if the scale is off.

- **Without a scale**: tapping the tile adds 1 kg. Select the line in the cart and type the real weight with the **QTY** keypad (for example `0.750`).
- **Stickers from a label-printing scale**: just scan the sticker. Its barcode (starting with 2) carries the item and the weight or price.



Loose item in the cart

The cart



Cart

At the top: **Cart**, the number of lines and the total quantity, and three buttons: **Hold bill** (pause icon), **Held bills** (box icon) and **Clear cart** (red bin; asks first).

Each line shows the product, **−** and **+** to change the quantity, the line total and a red bin to remove it. Tap a line to select it for the keypad.

The keypad

Mode	What typing a number does to the selected line
QTY	Sets the quantity (for loose items, the weight in kg, e.g. `0.5`)
PRICE	Sells the item for this price instead (lower than the normal price). The difference counts as a discount.
OFF %	Gives this percent discount on the line


Type the number on the keypad and press the enter key (↵). `×` clears what you typed.

Totals

Subtotal, **Discount**, **Tax** (the GST included in the prices) and the large **Total**.

Discount on the whole bill

Tap **Discount** in the totals. Choose **Amount (₹)** or **Percent (%)**, type it, **Apply**. **Remove discount** takes it off.



Bill discount


A cashier can give up to the **Discount limit for cashiers** (Settings → Selling; 5% if empty). Above that, the **Manager approval** window asks for a manager's or admin's PIN.

Customer

Walk-in customer at the bottom attaches a customer to the bill: search by name or phone, or add a new one with name and phone. A customer is needed for credit, loyalty points, or a tax invoice with the buyer's GSTIN.

Hold a bill (serve someone else first)

A customer forgot something? Tap **Hold bill** (pause icon). Type a **Label (optional)** such as "Blue shirt" and tap **Hold**. The cart empties for the next customer.



Hold this bill

To bring it back: tap **Held bills**, then **Resume** on the bill. If the cart has items at that moment, the app offers **Hold current bill, then resume**. A held bill can be deleted (**Delete held bill**). If a product's price changed while the bill was held, the line shows "price changed".


Held bills stay on this till only.

Take payment

Tap **Proceed to Checkout** (red button). Next chapter.

7. Payment and the bill

From the cart, **Proceed to Checkout** opens the payment screen.



Checkout

Left side: the customer (**Walk-in customer** or the chosen one; tap to change), **Back** to the cart, the items, **Subtotal**, **Discount**, **Tax**, **Total**, and an **Order note** (it stays on this device and prints on the bill).

Right side: how the customer pays.

Fastest cash sale


Proceed to Checkout → **Exact** → **Validate Order.** Three taps.

Payment methods

Method	How to use it
Cash	Tap **Exact** for the exact amount, or the quick amounts **+10 +20 +50 +100**, or type the amount received on the keypad. **Tendered** (received), **Change** (give back) and **Remaining** (still to pay) update as you type.
Card	Take the payment on your card machine, then type the **Approval code (optional)** from the machine's slip. If a card machine is connected (chapter 14), tap **Charge on card terminal** instead: the amount goes to the machine by itself and the approval comes back by itself.
UPI	A QR code with the exact amount appears (**Scan to pay ₹…**). The customer scans it with any UPI app. When their phone shows success, type the **UPI reference (optional)** from their screen and continue. Needs your UPI ID in Settings → Selling, otherwise it says **UPI is not set up**.
Credit	The amount goes on the customer's account (udhaar). Needs a customer on the bill. Over their credit limit (or for a customer without a limit) a manager must approve. The line shows "Owes ₹… · limit ₹…".
Points	Pays with the customer's loyalty points. Shows how many points they have, what one point is worth, the most they can use now and the minimum. **Most possible** uses as many as allowed. Needs loyalty on (Settings → Loyalty) and a customer.

Split payment (part cash, part UPI…)

Tap **Split**. Now each method adds a part payment: type the amount, then **Add cash**, **Add card** or **Add UPI** (and so on). **Payments received** lists them; a part can be removed. **Remaining** shows what is still due. When it reaches ₹0, tap **Validate Order**.



Split payment


Validate Order

Validate Order saves the sale. It is saved on this device at once, even without internet. Then:

- If a printer is set up with automatic printing, the bill prints and, for cash sales, the cash drawer opens.
- The receipt screen opens.

If something needs approval (a big discount, credit over the limit), the **Manager approval** window appears first.

The receipt



Receipt

The bill shows:

Part	What it is
Shop name, address, phone, GSTIN	From Settings → Shop and GST
Tax Invoice or **Bill of Supply**	Tax invoice for Regular GST shops, bill of supply for Composition shops
Invoice number, **Date**, **Cashier**	For example `A1-000123`
Customer, **Buyer GSTIN**, **State**	When a customer is on the bill (GSTIN for business customers)
Items	**Item**, **HSN**, **Qty**, **Rate**, **Amount**
Subtotal, **Discount**, **Round off**, **Total**	Round off appears when cash rounding is on

Part	What it is
GST summary	For each rate: **Taxable** value, **CGST**, **SGST**
Paid, **Tendered**, **Change**	Each payment method
Points and account	**Points earned**, **Points redeemed**, **Points balance**, **On account**, **Account balance**
Note	The order note


Buttons:

- **Print**: prints on the till's printer (chapter 14).
- **Save PDF**: saves the bill as a PDF file to share on WhatsApp or e-mail.
- **New sale**: back to the Sell screen.

A customer from another state: the app shows "Customer is in another state...". The bill still shows CGST and SGST; correct it by hand if IGST applies.

8. Orders, returns and voids


Open **Orders** in the sidebar to find any past bill.



Orders

- **Order history**: every bill, newest first. **Today**: only today's bills.
- **Search by invoice no.**: type all or part of a bill number, for example `000123`.
- Each bill shows its number, time, cashier, number of items, total and status: **Paid**, **Voided**, **Returned** or **Partly returned**.

Click a bill to see it on the right (on a phone, it opens as its own page).



A bill opened


Buttons on a bill:

Button	What it does
Print	Prints the bill again on the till's printer
Save PDF	Saves a copy as a PDF
Return	Customer brings some or all items back
Void	Cancels the whole bill

Returns and voids need a manager or admin. A cashier gets the **Manager approval** window.

Return items

Use this when the customer brings goods back.



Return items


1. Open the bill and click **Return**.
2. For each item, set how many are coming back. "Sold 2, returned 0" shows what is still returnable.
3. Type a **Reason** (optional), for example "damaged pack".
4. The refund is worked out for you, including the item's share of any bill discount. Click **Refund ₹…**.
5. The app says "Returned. Refund ₹… in cash." Give the cash back.

What happens:

- The stock goes back up.
- The bill shows **Partly returned** or **Returned**, with the **Returned items** listed.
- A credit (udhaar) sale's return lowers what the customer owes instead of paying cash; points earned on it are taken back, points spent on it are given back.
- The day's report and the shift's cash count include the refund.

Void a bill

Use this for a wrong bill, a duplicate, or a test sale. It cancels the whole bill.



Void this order?

1. Open the bill and click **Void**.
2. The window says "Voiding cancels the whole sale and puts the stock back. It cannot be undone."
3. Pick a reason: **Wrong items**, **Customer cancelled**, **Duplicate**, **Test sale** or **Other** (then describe it).
4. Click **Void order**.

The bill stays in the list marked **Voided**, with the time and reason, and prints with "VOIDED". Stock goes back. If it was paid in cash, the shift report shows the cash paid back.

A bill that already has returns cannot be voided ("This order has returns and can't be voided"): return the remaining items instead.

Return or void?

Situation	Use
Customer returns 1 of 3 items	**Return**
Customer returns everything a few days later	**Return** (all items)
Cashier made the wrong bill, customer did not take it	**Void**


Situation	Use
Same bill made twice by mistake	**Void** the extra one (reason **Duplicate**)
A practice bill while learning	**Void** (reason **Test sale**)

9. Shifts and end of the day

A **shift** is the time one cash drawer is in use: it starts with the cash already in the drawer and ends when you count the cash. The app then tells you whether the drawer is **Balanced**, **Over** or **Short**.

Shifts are on by default (Settings → Feature flags → **Shifts**). When they are on, nobody can sell until a shift is open.

Open **Shift** in the sidebar.



Shift


Open the shift (start of the day)

1. Count the cash in the drawer (the change you keep for the day).
2. **Shift** → **Open shift**. Type it in **Opening cash (₹)**, for example `2000`.
3. Click **Open shift**.

The screen shows **Current shift**, **Open since** (time) and **Open**.

X report (totals so far, without closing)


Click **X report** at any time to see the totals since the shift opened. Nothing is closed or reset; use it for a mid-day check.



X report

Close the shift (end of the day)

1. Count all the cash in the drawer.
2. **Shift** → **Close shift**. "Count the cash in the drawer and enter the total. The Z report is shown next."
3. Type the total in **Counted cash (₹)** and click **Close shift**.



Close shift

The **Z report** opens. **Save PDF** keeps a copy, **Print** prints it, **Done** goes back.

The X and Z report, line by line

Section	Line	Meaning
Top	**Opened**, **Closed** / **As of**	When the shift started and ended (or the time of an X report)
Sales	**Sales**	Number of bills
	Gross sales	Total of all bills before voids
	Discounts	All discounts given
Tax	**GST 5%**, **GST 18%**…	For each rate: taxable value, CGST and SGST
Payments	Cash, Card, UPI, Credit, Points, **Total**	Money taken by each method


Section	Line	Meaning
Voids and returns	**Voids**	Number and value of voided bills
	Cash refunds (returns)	Cash paid back for returns
	Cash paid back for earlier voids	Cash returned for bills of earlier shifts voided in this one
Credit	**Credit sales**	Sales put on customers' accounts
	Credit payments received	Money customers paid back on their accounts
Cash drawer	**Opening cash**	What you typed when opening
	Cash sales	Cash taken for sales
	Cash credit payments	Cash customers paid on their accounts
	Expected cash	What should be in the drawer: opening + cash sales + cash credit payments − cash refunds
	Counted cash	What you counted
	Over / short	Counted − expected. **Balanced** = exactly right. **Over** = more cash than expected. **Short** = less.

Good habits

- One shift per drawer per day (or per cashier change, if you want each cashier to count).
- If the drawer is **Short**, check voids, returns and change given; look at today's orders.
- Past shifts: in the web panel (chapter 15) the sidebar item is **Shift reports**, listing every closed shift.

10. Customers, credit and points

Open **Customers** in the sidebar: the list on the left (search by name or phone), the selected customer on the right (on a phone, its own page).




Customers

Chips on the list: **Owes ₹…** (credit balance), **Credit up to ₹…** (credit limit), **Business** (has a GSTIN).

Add or change a customer

Click **+** (**New customer**), or click a customer and change the fields. A cashier can add a customer quickly from the cart (name and phone); changing a customer needs a manager.




New customer

Field	What it means
Name	Customer or business name. Required.
Phone	Mobile number; used to find the customer fast. If another customer has the same phone, the app warns (**Phone already used**).
Email	Optional
Address	Optional; printed on tax invoices for business customers
GSTIN (optional)	For a business customer. Their bills become tax invoices with their GSTIN.
State	The customer's state (from the GSTIN). If it is another state than the shop's, the app warns that IGST may apply.
Credit limit (₹)	How much they may owe. Empty = no credit without a manager's approval.
Collects loyalty points	On = they earn and spend points (when loyalty is on for the shop).

Field	What it means
Notes	Anything useful ("prefers delivery", "pays on Saturdays").
Archived	Hides a customer you no longer serve; their history stays.

An admin can **Delete** a customer for good (chapter 4, *Delete for good*), but only when they owe nothing and have no points. Their old bills stay.

A customer's page



Customer details

Part	What it shows
Account and points	**Owes** (credit balance) or **Advance paid**, the **Credit limit**, and their points
Receive payment	Records money they pay back (cash, card or UPI)
Adjust	(Manager) Corrects the balance or points by hand, with a **Reason**

Part	What it shows
Ledger	Every credit sale, payment, adjustment and points change, newest first
Purchases	Their past bills ("12 purchases, ₹8,450", last purchase date). Click one to open it.


Selling on credit (udhaar)

1. Set a **Credit limit (₹)** on the customer (for example `5000`).
2. On Sell, attach the customer (**Walk-in customer** → pick them).
3. At checkout choose **Credit**. It shows "Owes ₹… · limit ₹…".
4. Within the limit: **Validate Order**. Over the limit: a manager approves.

The bill shows **On account** and the new **Account balance**.

Receiving a credit payment

Customer's page → **Receive payment** → **Amount (₹)** → choose cash, card or UPI → a **Reason** note if useful → OK. "Payment of ₹… received". Cash payments count in the shift's expected cash.



Receive payment

Adjust (manager)

For corrections only (a wrong entry, an old balance from your paper book):

- **Credit change (₹)**: `+` = owes more, `-` = owes less.
- **Points change (+ or −)**.
- **Reason**: always write why.

Loyalty points

Turn loyalty on in **Settings** → **Loyalty** (chapter 13): how many points each ₹100 earns, what one point is worth, and the fewest points per redeem. Then:

- A customer who **Collects loyalty points** earns points on every bill (shown on the bill: **Points earned**, **Points balance**).
- At checkout choose **Points** to pay with them.
- Returns take back the points earned on the returned items.

11. Stock, suppliers and purchase orders

These screens are for managers and admins.


How stock works

The app never just "sets" a stock number. Every change is recorded as a movement: **+24 received**, **−1 sale**, **−2 damaged**, **+3 count correction**. The stock on hand is the sum. So you can always see why the number is what it is.

- Every sale lowers stock; every return or void puts it back.
- Selling below zero is allowed (shops often sell before entering the delivery). The product then shows "Negative stock: count to fix".

The Stock screen

Open **Stock**.




Stock

- **Search name, barcode or SKU.**


- Filters: **All**, **Low** (at or below the reorder level), **Out** (zero or less).
- Each row: product, **On hand**, chips **Low**, **Out** or **Not tracked**.

Click a product for its details and actions:



Stock details

Action	When to use it	What you type
Receive	Goods arrived without a purchase order	**Quantity**, **Cost per unit (optional)** (updates the product's cost), **Note (optional)**
Adjust	Any other change: a gift, own use, a correction	**Change (+ or -)**, e.g. `5` or `-2`, and a note
Count	You counted the shelf	**Counted quantity**. The app shows "On hand now: ..." and records the difference ("Count matches stock, nothing changed" if equal).
Damaged	Broken, expired or spoiled goods	**Quantity** and a note



Receive stock


Movements below lists every change: date, reason (**Received**, **Adjustment**, **Count**, **Damaged**, **Opening stock**, **Sale**, **Sale voided**, **Return**, **PO …**), quantity and who did it. **Show more** loads older ones.

Quantities for pieces must be whole numbers; for kg, l and m you can use decimals (`2.5`).

Many products at once: Products → Import → Stock reads a CSV of barcode or SKU and quantity, as stock received or as a shelf count (chapter 4, *Import categories or stock from a file*).

Suppliers

Open **Suppliers**: the people and companies you buy from.




Suppliers

Click **+** (**New supplier**), type the name, phone and other details, **Save**. Search by name or phone.

An admin can **Delete** a supplier in its dialog (chapter 4, *Delete for good*); its purchase orders stay.

Purchase orders

Open **Purchase orders**. A purchase order (PO) is the list of goods you order from a supplier. When the goods arrive, receiving the PO adds them to stock.




Purchase orders

Statuses: **Draft** (being written), **Ordered** (sent to the supplier), **Partly received**, **Received**, **Cancelled**. Filter with the chips at the top.

Create a PO

1. Click **+** (**New purchase order**).
2. **Order details**: choose the **Supplier**, an **Expected date** and a **Note** if needed.
3. **Items**: **Add product**, search and pick it, type the **Quantity** and **Cost** (per unit). Add all products. The **Total** updates.
4. **Save draft** to finish later, or **Mark as ordered** when you send it.
5. **PDF** saves the order as a PDF to send to the supplier (WhatsApp, e-mail).



New purchase order

Receive the goods

1. Open the PO and click **Receive**.
2. For each item type what arrived. "Ordered 20, received so far 10" helps with part deliveries.
3. **Update product cost to the order cost**: on = the products' cost becomes the cost on this order.
4. Confirm. Stock goes up at once. The PO becomes **Received** ("All items received") or **Partly received** ("some items are still outstanding"); receive again when the rest arrives.


Cancel

Cancel order → "PO … will be cancelled. Stock already received stays." → confirm, or **Keep it**.

An admin can also **Delete** a draft or cancelled purchase order for good.

12. Reports

Open **Reports** (managers and admins).



Sales reports

Choose the dates

Click **Today**, **Last 7 days**, **Last 30 days** or **This month**, or pick a start and end date. All numbers below are for those days.

What each block shows

Block	Lines	Meaning
Summary	**Bills**	Number of bills
	Gross sales	Total of all bills
	Voids	Value of voided bills

Block	Lines	Meaning
	Net sales	Gross sales minus voids and returns: what you really sold
	Tax	GST included in net sales
	Returns (refunded)	Money paid back for returns
Takings by method	Cash, Card, UPI, Credit, Points	How customers paid
Tax by rate	**Rate**, **Taxable value**, CGST, SGST	For your GST return. Returns are already taken off.
Top items by quantity		Products sold most (by count or weight)
Top items by amount		Products that brought the most money
Daily sales	**Day**, bills, amount	One line per day

"No sales in this period" means no bills on those days.

Save PDF saves the report as a PDF (for your accountant).

Reports are instant even with years of sales: the app keeps daily totals as it sells.

Which report for what

Question	Where
How much did we sell today?	Reports → **Today** → Summary → Net sales
How much cash should be in the drawer?	**Shift** → **X report** (chapter 9)
GST to pay this month	Reports → **This month** → Tax by rate
Best-selling items	Reports → Top items

Question	Where
Who owes me money?	**Customers** list (Owes chip)
What to reorder?	**Stock** → **Low**

13. Settings, card by card


Open **Settings** in the sidebar. Settings is one long page of cards. Each person sees only the cards their role may change:

Card	Who sees it	Saved for
Shop and GST, Selling, Loyalty	Admin	The whole shop (all tills)
Language & theme, Idle logout	Everyone	This till only
Printer, Barcode scanner, Weighing scale	Manager, Admin	This till only
Feature flags	Everyone (read only)	The whole shop (from the license)
License	Admin	The whole shop
Appearance, Reset shop	Admin	The whole shop (all tills)
Self-checkout	Manager, Admin	This device only
Card terminals	Admin	This till only
Cloud sync, Shop hub	Admin	This till only
About	Everyone	—

"The whole shop" settings reach every till when the tills sync (chapter 15). "This till only" settings must be set on each device.

Most cards have their own **Save** button: changes take effect only after you click it.

Shop and GST




Shop and GST

Field	What it does
Shop name	Printed at the top of every bill and report
Address	Printed on bills
Phone	Printed on bills
GSTIN (optional)	Printed on tax invoices. Empty = not GST registered.
State	Your state; must match the first two digits of the GSTIN
GST scheme	**Regular** = tax invoices with CGST/SGST. **Composition** = bill of supply, no tax shown.

Changing these changes **future** bills only. Old bills keep what they printed.

Selling




Selling

Field	What it does	Usual value
Round cash totals to the nearest rupee	₹227.60 becomes ₹228.00; the bill shows the **Round off** line	On
Discount limit for cashiers (%)	The biggest discount a cashier may give alone. Above it a manager must approve. Empty = 5%.	5
UPI ID (VPA)	Your shop's UPI ID, for example `sharmakirana@upi`. With it, checkout shows a QR code with the exact amount. Without it, UPI shows "UPI is not set up".	Your UPI ID
UPI payee name	The name the customer's UPI app shows when paying	Shop name

Field	What it does	Usual value
Scale barcode carries	Only for stickers from label-printing scales: whether their barcodes carry the **Weight** or the **Price**. Check your scale's setting.	Weight

Loyalty



Loyalty


Field	What it does	Example
Loyalty points	Turns points on or off for the whole shop	On
Points per ₹100 spent	Points a customer earns per ₹100 of a bill	`1` = 1 point per ₹100
Value of 1 point	What one point is worth when paying	`₹1.00`

Field	What it does	Example
Fewest points per redeem	Smallest number of points a customer can use at once	`10`

Example with the values above: a ₹2,500 bill earns 25 points; the customer can later pay ₹25 with them.

Each customer must also have **Collects loyalty points** on (chapter 10).


Language & theme



Language & theme

- **English** / **हिन्दी**: the language of the whole app on this till. Bills print in the same language as the screen labels; product names print as you typed them.
- **Theme**: **Dark** (default, easy on the eyes at the counter), **Light**, or **System** (follows the device).

Idle logout




Idle logout

Off, **5 min**, **15 min** or **30 min**. After that many minutes without a tap or key, the app goes back to the sign-in screen. The cart is kept. Use it on counters where the till is sometimes left alone.


Printer, Barcode scanner, Weighing scale

See chapter 14. These are set on each till.


Sharma Kirana Store
Sharma Kirana Store
Search products or scan barcode
Trial · 30 days left
EN
₹ INR
Ramesh
Admin
Collapse
Sell
Kiosks
Tables
Orders
Customers
Shift
Reports
ADMIN
Products
Stock
Suppliers
Purchase orders
Tables and areas
Kitchen stations
Modifiers
Staff
Settings
PRINTER
No printer set up on this till yet.
Connection
Network (Wi-Fi / LAN)
Printer address
IP address, e.g. 192.168.1.50 (port 9100) or 192.168.1.50:9100
Paper width
58 mm
80 mm
Print mode
Image (₹, Hindi)
Text (fastest)
Print the receipt after every sale
Cut the paper after printing
Blank lines before cut
3
Copies
1
Open the cash drawer after cash sales
For a drawer plugged into the receipt printer.
Drawer socket pin
2
5
Save printer
Test print
Open drawer
BARCODE SCANNER
USB and Bluetooth scanners in keyboard mode work on Sell without any setting.
Serial scanner

Printer

Restaurant



Restaurant settings


Shown when the **Restaurant** flag is on (managers and admins). Details in chapter 17.

Setting	What it does
This device is a	**Till** (opens on Sell), **Waiter** (opens on the table map) or **Kitchen screen** (full-screen kitchen board, no sign-in). Set on each device
Tables and areas, **Modifier groups**, **Kitchen stations**	Open those admin screens
QR ordering by guests	**Off**, **Menu only** (browse, no ordering), **Auto-send** (straight to the kitchen) or **Waiter confirms**
QR code points to	**Shop Wi-Fi** (shop hub), **Mobile data** (cloud server) or **Both**
Print QR table cards	A PDF with one card per table
Service charge	Percent added to table bills as its own line (empty = none, at most 30)

Setting	What it does
Waiters can take payment at the table	Shows **Pay** on waiter devices

Admins press **Save** in the card for the shop settings; the device mode saves at once.


Customer display



Customer display

Turn on **Show the bill to customers**, then open the address shown (or scan its QR) on a second monitor, tablet or phone that faces the customer, and type the **display code** once. **New code** stops displays that used the old one. Set on each till (managers and admins).


Customer links



Customer links

QR to the bill on receipts and the customer display and the **Link address** links start with. Details in chapter 18. Set on each till (managers and admins).

Feature flags




Feature flags

Shows which parts of the app are switched on for your shop, and where that comes from (**Source**: **built-in (all on)** during the trial, **license file** with a license). You cannot change them here; your license decides.

Flag	When on
CSV import	Products → Import is available
Quick keys	The Quick keys chip on Sell and the Quick key field on products
Weighed items	Loose items sold by weight, scale stickers, the Weighing scale card
Hold bills	Hold bill / Held bills on Sell
Restaurant	Tables, orders, kitchen stations and screen, QR ordering, customer display (chapter 17)
Kiosk	Reserved for self-checkout (coming later)

Flag	When on
Connectors	Reserved for online store connections (coming later)
Shifts	Shifts must be opened before selling; X and Z reports

License



License

A new shop runs a **30-day free trial** with everything on. The top bar shows **Trial · … days left**.

Line	Meaning
Status	**Trial**, **Valid**, **Expired (grace period)** or **Read-only**, with days left
Plan, **Shop**, **Devices**, **Expires**, **Issued**, **Features**	What your license says

Line	Meaning
Device slots, **Plan limits**	How many tills, waiter phones, kitchen screens and self-checkouts your plan allows, and how many products, customers and categories (only when your plan sets them)
Tenant ID, **Shop ID**	Your shop's identity. Your supplier needs these two to make your license.

To add or renew a license (WhatsApp or call **+91 89229 62849**, e-mail **universalpos2026@gmail.com**):

1. Press **Request / renew licence** and send the text to your supplier: **WhatsApp**, **Copy**, or let them scan the QR. It holds your Tenant ID, Shop ID and this device.
2. You receive a license file (ending in `.poslicense`) or a block of text.
3. **Import file** and pick the file, or **Paste text**, paste it, **Import**. On a phone or tablet you can also press **Scan QR** and point the camera at the licence QR your supplier shows.
4. "License imported". The status shows **Valid** and the expiry date.

Business id (for a new outlet) shows your Tenant ID as text and QR. Use it when you set up a second outlet of the same business: on the new device choose **New outlet of an existing business** in first setup and scan or type it.

Plan limits only warn. Near a limit the products, customers or categories list shows "... of ... on your plan"; above it, "Plan limit passed. Ask your seller to upgrade." Nothing is blocked or deleted.

Device slots are checked when a device is paired or changes what it is used as (till, waiter, kitchen screen, self-checkout). A paired device needs the server or shop hub to change its role; with no free slot it says "Kiosk devices: 1 of 1 used. Free one or ask your seller." If a renewed license has fewer slots, extra devices keep working with a banner until the admin frees one.

What happens when time runs out:

Situation	What the app does
Trial or license ending soon	The top bar chip counts the days
License expired	Amber banner: "License expired. ... days left before the app becomes read-only." Everything still works for **30 days**.
Trial ended, or 30 days after expiry	**Read-only**: you can see orders, reports and receipts and import a license, but cannot sell or change anything

Situation	What the app does
Device clock set back	"Device clock is behind. The app is read-only until the clock is corrected." Set the right date and time.

Nothing is ever deleted when a license ends.

Messages when importing:


Message	Meaning
This is not a valid license file.	Wrong file, or the text was cut when copying
The license signature is not valid.	The file was changed; ask for a new one
This license is for a different shop.	The license was made for other IDs; send your Tenant ID and Shop ID again

Backup and Updates

Backup (admins and managers): **Back up now** saves an encrypted `.posbackup` file; on a PC **Choose folder** makes a backup there every day by itself (last 7 kept). A reminder appears after 7 days with sales and no backup. If the card says your licence is older than 0.1.8, ask your supplier for a new licence file so backups are locked to it.

Updates (admin; Android, Windows, Linux): **Install update from file** takes the `.posupdate` file from your supplier, checks it, saves a backup and installs. Both are explained step by step in chapter 20.


Card terminals



Card terminals

Connect card machines from Pine Labs, Razorpay, Paytm or Stripe. Chapter 14 explains each field.

Cloud sync




Cloud sync

Connects this till to the shop hub or a server so all tills share data. Chapter 15 explains it.

Line / button	Meaning
Server address, **Pairing code**, **Pair**	Connect this till (chapter 15)
Status	**Synced**, **Syncing…**, **Server not reachable** or **Sync error**
Last sync	When it last synced (**Never** before the first time)
Waiting to upload	Changes on this till not sent yet ("12 events")
Sync now	Sync at once (it also syncs by itself every 30 seconds and after each sale)
Unpair	Stops syncing. "All data stays on this device."

Shop hub (LAN / USB sync)



Shop hub

Makes this device the shop hub that other tills sync with over the shop Wi-Fi. Chapter 15 explains it.

About

Version of the app (for example 0.1.4, build 5) and a line confirming the database is ready. Tell your supplier the version when you ask for help.

Appearance, Self-checkout, Reset shop

See chapter 19.


14. Printer, scanner, scale and card machines

All of these are set up **on each till**, in **Settings** (manager or admin; card machines: admin). Each till has its own printer, scanner and scale. A till without its own (an iPhone, for example) can use the shop hub's printer and scale (chapter 15).

The app never needs internet for the printer, scanner or scale. Card machines need internet.

Receipt printer

Works with almost every thermal receipt printer (58 mm and 80 mm: Epson, TVS, Xprinter, Rongta, Hoin, Retsol and similar; the type is called "ESC/POS").



Printer settings

Step 1: connect the printer to the device

Connection	What to do first	Android	iPhone/iPad	Windows	Linux	Mac
Network (Wi-Fi / LAN)	Find the printer's IP address: switch it off, hold the FEED button while switching on; it prints a self-test page with the address	Yes	Yes	Yes	Yes	Yes
USB	Plug in the cable (on a phone: a USB OTG adapter). On Windows, first install the printer in Windows (its driver, or "Generic / Text Only").	Yes	No	Yes	Yes	Yes
Bluetooth	Pair the printer in the phone's or computer's Bluetooth settings (PIN usually `0000` or `1234`)	Yes	No	Yes	Yes	Yes
Serial (RS-232)	Plug in the serial or USB-serial cable	No	No	Yes	Yes	Yes
Shop hub printer	Nothing: receipts go to the printer of the shop hub (chapter 15)	Yes	Yes	Yes	Yes	Yes

Step 2: Settings → Printer

Field	What to choose
Connection	How the printer is connected (table above)
Printer address	Network: type the IP address, e.g. `192.168.1.50`. Other connections: click **Find** and pick the printer from the list.
Speed (baud)	Serial and computer Bluetooth only. Usually `9600`; some printers use `19200` or `115200` (it is on the self-test page).

Field	What to choose
Paper width	58 mm (small, 2 inch) or 80 mm (big, 3 inch)
Print mode	**Image (₹, Hindi)**: prints the ₹ sign and Hindi, looks like the screen (default). **Text (fastest)**: faster, prints "Rs" instead of ₹ and no Hindi. Try Text if Image is slow or garbled.
Print the receipt after every sale	On = every sale prints by itself
Cut the paper after printing	For printers with a cutter
Blank lines before cut	Extra paper so the last line is not cut off
Copies	How many copies of each bill
Open the cash drawer after cash sales	For a cash drawer plugged into the printer (the cable with a phone-style plug)
Drawer socket pin	If the drawer does not open, change 2 to 5

Click **Test print**: the page shows the settings, a ₹ amount and a Hindi line. If it looks right, click **Save printer**. **Remove printer** deletes the setup on this till.


Everyday use

- After each sale the receipt prints and the drawer opens (cash sales). The sale is always saved first, so a printer problem never loses a sale.
- The **printer icon** in the top bar turns red if printing failed. Click it for **Print again**, **Open drawer** or **Printer settings**.
- Reprint any bill: **Orders** → the bill → **Print**.
- Open the drawer without a sale: printer icon → **Open drawer**. A cashier needs a manager's PIN.

Printer problems

Problem	What to do
Network: "timed out"	Printer and till on the same Wi-Fi/network? IP address right (print a new self-test page; it can change after a power cut)?
Nothing found under USB on Android	Use a USB OTG adapter; allow access when Android asks
Nothing found under Bluetooth	Pair the printer first in the device's Bluetooth settings; switch Bluetooth on
Strange characters	Wrong speed (baud), or try **Text** mode
Receipt too narrow / wide / cut off	Change **Paper width**
Linux: "permission denied"	Your supplier must give the computer user access to printers (chapter 1)
Windows USB printer not listed	Install it in Windows first (Settings → Printers), then **Find** again

Barcode scanner



Scanner settings

Which scanner needs which setting

Scanner	Setting needed	Works on
USB scanner (most scanners, as they come from the box: "keyboard mode")	**None.** Plug in and scan on Sell.	All devices (phone: OTG adapter)
Bluetooth scanner in keyboard mode	Pair it in the Bluetooth settings, then scan	All devices
Phone/tablet camera	Turn on **Camera scan button on Sell**	Android, iPhone, iPad, Mac
Serial / USB-serial scanner (older scanners with a COM port)	**Serial scanner** → **Serial / USB-serial (COM port)**	Android, Windows, Linux, Mac
Bluetooth scanner in serial mode (SPP)	Pair it, then **Serial scanner** → **Bluetooth serial (SPP)**	Android, Windows, Linux, Mac

If your scanner can work in keyboard mode, use that: it needs nothing in the app.

Keyboard-mode scanners

Open **Sell** and scan. You do not need to click a box first. The scanner must send Enter after each code (nearly all do). If scans end up as text in the search box instead of adding the product, the scanner is too slow or sends no Enter: check its manual.

Camera

1. Settings → Barcode scanner → turn on **Camera scan button on Sell** → **Save scanner**.
2. On Sell, tap the scan icon next to the category chips. Allow the camera the first time.
3. Hold each barcode inside the frame. Each item is added to the cart; the title counts them ("Camera scan · 3 added"). The camera stays open until **Done**. The same barcode held still is added once; take it out of view and back to add it again. Unknown barcodes show "Not found".
4. **Torch** lights up dark barcodes; **Switch camera** uses the front camera.

Try the camera in Settings scans one barcode to test. The product form's **Barcode** field also has a camera button.

Serial and Bluetooth-serial scanners

Field	What to choose
Serial scanner	**Serial / USB-serial (COM port)** or **Bluetooth serial (SPP)**. **None (keyboard mode or camera only)** = off.
Scanner port or address	Click **Find** and pick the scanner. On Android, allow USB access when asked; pair Bluetooth scanners first.
Speed (baud)	Usually `9600` (in the scanner's manual)


Save scanner. The status shows **Scanner connected**. Scan something: "Last scan: ..." appears on the card. If the scanner is unplugged it shows **Scanner not connected ... (trying again)** and reconnects by itself within a few seconds; **Connect again** tries at once.

Options for every scanner

Field	What it does
Remove prefix / Remove suffix	Some scanners add extra characters before or after the code. Type them here and they are removed from every scan. The test line shows what was received and what is looked up.
Beep after each scan	A short tone when found, a different one when not found
Vibrate after each scan	Phones only

Weighing scale

The **Weighing scale** card shows only when **Weighed items** is on (Settings → Feature flags).



Scale settings

Two kinds of scales

Scale	How it works	Setup
Label-printing scale (prints a sticker with a barcode)	Weigh at the scale, stick the label, scan it at the till. The barcode carries the item and the weight or price.	Only **Settings** → **Selling** → **Scale barcode carries**. Each product's **SKU** must be the 5-digit item number used on the scale.
Counter scale connected to the till	Put the item on the scale and tap it on Sell; the till reads the weight	This card

Connect a counter scale

Connection	Android	iPhone/iPad	Windows	Linux	Mac
Serial / USB-serial (COM port)	Yes (OTG adapter)	No	Yes	Yes	Yes
Bluetooth serial (SPP)	Yes (pair first)	No	Yes	Yes	Yes
Network (LAN)	Yes	Yes	Yes	Yes	Yes
Shop hub scale (chapter 15)	Yes	Yes	Yes	Yes	Yes

Settings → Weighing scale

Field	What to choose
Scale connection	**No scale**, **Serial / USB-serial (COM port)**, **Bluetooth serial (SPP)**, **Network (LAN)** or **Shop hub scale**
Scale port or address	**Find** and pick, or for a network scale its IP address and port, e.g. `192.168.1.60:4001`
Scale protocol	The "language" of the scale (in its manual under communication / RS-232): **Continuous output (Essae and most scales)**, **CAS**, **Mettler Toledo (MT-SICS)**, **NCI / Avery Berkel**. Not sure? Try Continuous first.

Field	What to choose
Speed (baud) and **Data format**	Serial only. Usually `9600` and `8N1`; some Avery and old CAS scales use `7E1`.
Unit when the scale sends none	kg or g
Add the item as soon as the weight is steady	On: one tap per item. Off: the cashier checks the weight and taps **Use weight**.

Save scale. The card shows the live weight and **Steady** when it settles. Put something on the scale to check. **Zero** sets the scale to zero (MT-SICS and NCI scales only).

Selling with the scale

- Mark loose products **Sold by weight** (chapter 4).
- Put the item on the scale and tap it on Sell. The weigh window shows "Place the item on the scale.", then the weight, **Settling…** and **Steady**. The item is added when steady.
- The weight of the previous item is never used: the window waits for a new reading.
- **Type weight** (**Weight in kg**) when the scale is off or broken.


Scale problems

Problem	What to do
"Scale not connected"	Check the cable or network, the port and the protocol. The app retries every few seconds.
Connected, but no weight	Check speed and data format; for Continuous output set the scale to continuous mode
Weight 1000 times too big or small	Change **Unit when the scale sends none**
Never **Steady**	Keep the item still; set the scale to send a stable signal

Card machines (card terminals)

Instead of typing the amount on the card machine and the approval code in the app, the app can send the amount to the machine and get the approval back by itself. **The app never sees or stores card numbers**: the machine handles the card; the app only learns "approved" (with the code) or "declined".

Without a connected machine, card payments still work: take the payment on the machine and type the approval code at checkout.



Card terminals

Providers

Provider	Country	What you get from the provider
Pine Labs Plutus	India	**Merchant ID**, **Security token**, **Store POS code**, **Terminal IMEI**
Razorpay POS (Ezetap)	India	**Username**, **App key**, **Device ID** (e.g. `1490001234|ezetap_android`)
Paytm EDC	India	**Paytm MID**, **Paytm TID**, **Merchant key**

Provider	Country	What you get from the provider
Stripe Terminal	Outside India	**Restricted secret key** (allowed only Terminal and PaymentIntents), **Reader ID (tmr_...)**, **Currency**
PayPal (Zettle)	Outside India	**Coming later**

Ask the provider to switch on the "cloud" or "push to terminal" integration for your account. They give test details first.

Setup

1. Settings → Card terminals → click a provider to open it.
2. Turn on **Use this terminal**.
3. Fill in every field. While trying the provider's test details, turn on **Test mode (sandbox)** (no real money moves); turn it off with your real details.
4. **Save terminals**. A missing field is refused ("Fill in every field for: ...").

You can turn on more than one provider; at checkout the cashier picks the machine (**Choose the card terminal**).

Taking a card payment

1. Checkout → **Card** (for a split payment, type the part amount first).
2. Tap **Charge on card terminal**.
3. "Waiting for the customer to pay on the terminal...". The customer taps, inserts or swipes the card on the machine.
4. Approved: the payment is added with its code (for example `PL:123456`) and the sale completes as usual.
5. Declined: "Card declined: ..." and nothing is added. Try again or choose another method.
6. **Cancel** stops the payment on the machine ("Payment cancelled. Nothing was charged."). On Paytm, also cancel on the machine.

The provider details are stored only on this till; they are not synced or sent anywhere else.

15. More than one till: shop hub and server

One till works fully on its own; nothing leaves it. When the shop has **two or more tills**, connect them so they share products, prices, customers, staff, stock and sales. There are two ways, and they can be combined.

	Shop hub	Server (cloud)
What it is	One computer in the shop that the other tills sync with	A computer on the internet, run by your supplier
Needs internet	**No**: shop Wi-Fi, a network cable or a USB cable is enough	Yes (tills keep selling offline and sync later)
Owner can look from home	Only if the hub also syncs with a server	Yes, in a web browser
Good for	Shops with weak or no internet; fast sync between counters	Owners who want reports from anywhere; several shops

Recommended for most shops: one computer as the shop hub; if you also want to see the shop from home, connect the hub to a server. Tills always sync with the hub.

Whichever you use: **sales never wait for the network.** Each till saves its sales at once and syncs every 30 seconds and after each sale. If the hub or the internet is down, tills keep selling and catch up later.


Shop hub

Which device should be the hub

- A **Windows, Linux or Mac computer that stays on** during shop hours. An Android tablet also works, but only while the app is open on its screen.
- It must already be set up for the shop (it was the first till, or it joined the shop).
- iPhones and iPads cannot be the hub (they can be tills).

Turn the hub on

On the hub computer: **Settings** → **Shop hub (LAN / USB sync)** (admin).



Shop hub card

1. Turn on **This device is the shop hub**. Leave **Port** at `8787` unless your supplier says otherwise.
2. The card shows **Hub running** and under **Tills connect to:** the address, for example `http://192.168.1.10:8787`.
3. Windows asks once whether to allow the app on networks: allow on **private networks**.

On the card	Meaning
Hub running	Tills can connect now
Tills connect to:	The hub's address(es). Type one on a till if "Find shop hub" does not find it.
"No network found. Connect this device to the shop network."	The computer is not on any network
"The hub could not start: ..."	Usually the port is used by another program: change **Port** (turn the hub off first)
This hub's invoice series	Needed only if the hub also sends data to a server: your supplier uses it once to allow that.

On the card	Meaning
Pairing code for a till	The code a new till types (below)
Paired tills	Every till connected to this hub, with its invoice series. **Remove** disconnects that till at once.

Connect a till to the hub

On the hub: tap **New pairing code**. It shows an 8-character code, "Valid until (time), for one till." (15 minutes, one till).

A new till (nothing set up yet): on the till, **Join existing shop** (chapter 2) → **Find shop hub on this network** (or type the hub's address) → type the pairing code → **Join**. The till downloads everything and is ready.

A till already selling on its own for the same shop: Settings → Cloud sync → Find shop hub on this network (or type the address) → **Pairing code** → **Pair**. Its sales are sent to the hub.

Then make a test: sell something on the till; within half a minute it appears in **Orders** on the hub.

USB cable instead of Wi-Fi

For an Android phone next to the hub computer:

1. Connect the phone to the computer with a USB cable.
2. On the phone, turn on **USB tethering** (Android Settings → Network → Hotspot & tethering).
3. On the phone, **Find shop hub on this network** (or type the hub address shown on the hub card for this connection).

A desktop till with a USB-to-network adapter works the same way.

The hub's printer and scale for other tills

iPhones, iPads and tills without their own printer or scale can use the hub's:

- **Settings → Printer → Connection: Shop hub printer**: receipts print on the hub's printer.
- **Settings → Weighing scale → Scale connection: Shop hub scale**: the weigh window shows the hub scale's weight.

Good to know


Topic	Detail
License	The hub gives tills its license. Each paired till counts towards the license's device limit (the hub counts too).
Safety	The hub talks to tills over the shop network without encryption. Keep the shop Wi-Fi password-protected; never open the hub's port to the internet.
Hub switched off	Tills keep selling; they sync when the hub is back.
A lost or stolen phone	Hub card → **Remove** next to it. It stops syncing at once.

Server (cloud)

Your supplier sets up the server and gives you its **address** (for example `https://pos.example.com`) and **pairing codes**. A server also lets the owner open the shop in a web browser.

Connect a till to the server

Settings → **Cloud sync** (admin):



Cloud sync

1. **Server address**: the address from your supplier.
2. **Pairing code**: a fresh code from your supplier (valid 15 minutes).
3. **Pair**. "Paired with the server". Everything already on this till stays and is uploaded.

After pairing the card shows **Status**, **Last sync** and **Waiting to upload**; **Sync now** syncs at once. **Unpair** stops syncing; all data stays on the till.

A new till can also join straight from the first screen: **Join existing shop** with the server address (chapter 2).

Sync messages

Message	What to do
Synced	All good
Server not reachable	No internet, or the server is down. Sales are kept and sent later. Nothing to do unless it lasts.
"The server refused this device. It may have been removed; pair it again."	The till was removed on the server; get a new pairing code

Message	What to do
"This device already has data for another shop. Use a fresh install to join."	A till belongs to one shop for life
"The shop has reached its device limit."	Remove an old till or ask your supplier for more devices
"The shop has no license on the server yet."	Ask your supplier
Sync error (other messages)	Note the message and tell your supplier

The owner's web panel

With a server, the owner can open the shop in a web browser (Chrome, Edge, Firefox) on any computer, at the address your supplier gives you.

1. Type the **Email** and **Password** your supplier created for you. **Keep me signed in on this computer**: leave it off on a shared computer ("Signing in is then asked again when this tab is closed").
2. **Sign in**. **Choose a shop** if you have more than one.
3. The browser downloads the shop's data (**Connecting**, **Registering this browser…**) and opens the same screens as on a till: products, orders, customers, stock, reports, **Shift reports**.

Switch shop and **Sign out** are in **Settings** → **Admin account**. "This shop has no data yet" means no till has synced to the server yet.

The web panel is for managing and looking; selling is done on the tills.

16. Problems and quick answers

Quick answers

Question	Answer
Do I need internet?	No. Billing, printing, scanning, weighing and the shop hub work without internet. Only card machines and a server need it.
Which version do I have?	Bottom of the sign-in screen, or **Settings** → **About**
Hindi or English?	**EN / हि** in the top bar, or **Language** on the sign-in screen, or Settings → Language & theme
How do I print an old bill?	**Orders** → the bill → **Print** (or **Save PDF**)
How do I share a bill on WhatsApp?	Receipt or Orders → **Save PDF**, then share the file
Cashier needs to give a bigger discount	A manager types their PIN in the **Manager approval** window
Phone lost or broken	Install the app on the new device → **Restore from backup** with your last `.posbackup` file and the shop's licence (chapter 20)
"Install failed" or "not signed by Universal POS" on an update	Use only the update file from your supplier; ask for a new copy. Your data is not touched
"This backup needs the licence your seller issued with it"	Ask your supplier for the current licence file (0.1.8 or later), then restore again
More room on the screen	**Collapse** at the top of the sidebar; **Fullscreen** at the bottom
A new staff member	**Staff** → **+** (chapter 5)
Forgot my PIN	Another admin changes it in **Staff**. If no other admin exists, contact your supplier.

Question	Answer
Change a price	**Products** → the product → **Price (₹)** → **Save**. Other tills get it at the next sync.

Something is wrong

Problem	Cause and fix
"Open a shift to start selling"	Shifts are on: **Shift** → **Open shift** (chapter 9)
A barcode is "Not found"	The product has no barcode or a different one: Products → the product → **Barcode**. Or search by name.
Scanner types into the search box instead of adding	The scanner must send Enter after the code and scan fast; check its settings (chapter 14)
Nothing prints	Printer icon red? Click it → **Print again**. Check power, paper and cable; **Settings** → **Printer** → **Test print** (chapter 14)
Drawer does not open	**Drawer socket pin**: switch 2 ↔ 5; drawer cable plugged into the printer?
₹ or Hindi prints as strange characters	Printer → **Print mode: Text** prints "Rs" and English only
UPI says "UPI is not set up"	Settings → Selling → **UPI ID (VPA)** (admin)
Credit or Points greyed out	Add a customer to the bill first; points need loyalty on
"Manager approval is needed" and no manager present	A manager or admin must type their PIN; there is no way around it
A bill cannot be voided ("has returns")	Return the remaining items instead (chapter 8)
Stock shows a minus number	Sold more than was entered. Receive the delivery or **Count** the shelf (chapter 11)

Problem	Cause and fix
A sale is missing on another till	Wait 30 seconds; check the cloud icon (**Synced**?). On the hub, check that the till is listed under **Paired tills**.
"Find shop hub" finds nothing	Same Wi-Fi as the hub? Hub card says **Hub running**? Some routers block searching: type the hub's address instead.
The app is read-only	Trial or license ended, or the clock is wrong. **Settings** → **License** (chapter 13).
"Device clock is behind"	Set the right date and time on the device (automatic time on)
Weight 1000 times too big or small	Settings → Weighing scale → **Unit when the scale sends none**
The app looks too dark / too bright	Sun/moon icon in the top bar, or Settings → Theme
No **Tables** in the menu	The **Restaurant** flag is off (Settings → Feature flags; your license decides)
Kitchen tickets do not print	**Kitchen stations** → the station → **This device prints** must be on, on the computer with the printer; that computer's printer set up (chapter 14)
Kitchen screen or waiter phone is slow to update	It must sync with the shop hub (chapter 15); without a hub, updates come every 30 seconds
Guests' QR code says ordering is closed	**Settings** → **Restaurant** → **QR ordering** is Off, or the table was archived; for **Mobile data** the cloud server must be updated
Add stays grey on an item with options	A required choice (min 1) is not picked yet
The order says **paid twice**	Two devices took payment offline: void one sale in **Orders** (chapter 8)
Customer display shows "Enter the code" again	The code was changed with **New code**; type the new one

Problem	Cause and fix
Share bill says links need a hub or server	Turn on cloud sync or the shop hub (chapter 15)
A shared link does not open from home	It is a shop Wi-Fi link: set **Settings** → **Customer links** → **Link address** to your cloud server
SMS button missing	SMS needs the cloud server with SMS set up, and a customer phone number on the bill
"Today's SMS limit is reached"	Use WhatsApp or the QR; the limit resets tomorrow
Receipts print without the bill QR	The link was not ready within a few seconds (no connection); share it from the receipt screen

Keeping your data safe

- **Use a hub or a server.** Then every sale also exists on another device. If a till breaks, set up a new one with **Join existing shop** and everything comes back.
- A till on its own (no hub, no server) keeps the only copy of its data. Do not uninstall the app on a phone, and keep the device in good condition.
- Never set a device's clock back.
- Each till must have its own invoice series.

When you contact your supplier


Tell them:

1. The app **version** (sign-in screen or Settings → About).
2. The device (phone model or computer, Android / Windows / Linux / Mac / iPhone).
3. What you did, and the **exact message** (a photo of the screen is best).

17. Restaurant and cafe: tables, kitchen, QR orders

Turn this on for a restaurant, cafe, dhaba or bakery with seating. Shops that only sell at a counter don't need it. It works fully offline on one device, and over the shop network (shop hub) on many. Your licence must include **Restaurant**: if the screens below are missing, see **Settings → Features**.

Set up once (manager or admin)



Tables and areas

Step	Where	What
1	**Admin → Tables and areas**	Add each table (name or number, seats, shape). **Areas** groups them (Ground, Terrace). **Arrange tables** lets you drag them to where they stand
2	**Admin → Modifiers**	Groups like "Size" (pick exactly 1: min 1, max 1) or "Extra toppings" (pick 0 to 3, each with an extra price)

Step	Where	What
3	**Admin** → **All products** → open a product → **Restaurant** card	Pick its modifier groups, whether it shows on the QR menu, and its default course (1 = starters…). Press the card's own **Save**
4	**Admin** → **Kitchen stations**	One station per printer or screen (Kitchen, Bar, Tandoor). Pick the categories it makes; a station with none takes everything else. On the computer with that station's printer, turn on **This device prints this station's tickets**
5	**Settings** → **Restaurant**	Service charge (optional), whether waiters can take payment, and QR ordering

Archive a table, area, modifier group or station you no longer use. An admin can also **Delete** it for good (chapter 4, *Delete for good*); a table with an open order or an area that still has tables cannot be deleted.

This device is a…

Settings → **Restaurant** → **This device is a**:

Mode	Opens on	For
Till	Sell (with **Tables** in the menu)	The counter
Waiter	The table map, phone layout	Waiters' phones
Kitchen screen	The kitchen board, full screen, no sign-in needed	A tablet or screen in the kitchen

Taking an order






Table map

1. **Tables**: each table shows its status: **Free**, **Ordered** (blue), **Served**, **Bill asked** (red). Busy tables show the amount, guests and minutes. A bell with a number means items are ready to serve.
2. Tap a free table → how many guests → the order opens. (**Counter order** = takeaway or no table.)
3. Tap items to add them. Items with modifiers open a sheet: the **Add** button stays grey until every required choice is made. Before adding you can pick the **seat**, the **course**, or **Hold** (keep it until you fire the course).
4. **Send** sends everything new to the kitchen. Held courses show **Fire** next to the course name.
5. Tap a line to **Void** it (a reason is needed; once the kitchen has started it, a manager must approve), to send its course, or to **Mark served** when it is ready.
6. The ⋮ menu: move to another table, merge with another order, change guests, **Guest asked for the bill**, mark everything ready as served, close or cancel (cancel only when nothing was sent).




Order



Modifier group

Every action is saved on the device at once and reaches other devices in about a second on the shop network.


Kitchen



Kitchen screen

- **Printed tickets (KOT)**: the device that owns a station prints each new ticket for that station: the table, ticket number, time, waiter, then every item in large letters with its modifiers, seat and note. No prices.
- **Kitchen screen**: one card per ticket, oldest first. The colour shows the waiting time (normal, then amber after 10 minutes, red after 20). Tap an item to set **Cooking**, then **Ready**. **Bump** marks the whole ticket ready. **Recall** brings back the last 10 bumped tickets. The filter button picks which stations this screen shows.
- Waiters see ready items on the table map (bell) and in the order.

Paying



Pay choices

Pay on the order:

Choice	What happens
Whole bill	One bill for everything not paid yet
Split by seat	One bill per seat, one seat at a time
Split by item	Tick the items this guest pays
Split equally	One bill, paid in 2–10 equal parts (cash, UPI or card each)

The order closes by itself when nothing is left to pay. A service charge (if set) is added as its own line. Waiter phones show **Pay** only when **Waiters can take payment at the table** is on.

If two devices took payment for the same order while offline, the order shows **paid twice**: void one of the sales in **Orders**.

QR ordering by guests

1. **Settings** → **Restaurant** → **QR ordering**: **Auto-send** (straight to the kitchen) or **Waiter confirms**.
2. **QR code points to**: **Shop Wi-Fi** (works without internet, through the shop hub), **Mobile data** (through the cloud server) or **Both** (two codes per card).
3. **Print QR table cards** → check the addresses → **Make PDF** → print and put one card on each table. Keep the hub's address fixed in your router (a "reserved" or "static" address) so printed cards keep working.

Guests scan the card, choose items (with modifiers and notes), and press **Place order**. With **Waiter confirms**, waiters see **QR orders waiting** on the table map: **Review** → **Accept and send** or **Reject** (with a reason the guest sees). Prices always come from the shop, never from the guest's phone.

Customer display

Settings → **Customer display** → **Show the bill to customers**, then open the address shown (or scan its QR) on a second monitor, tablet or phone facing the customer, and type the 6-digit code once. It shows the items and total while you sell, the amount and UPI QR while paying, and a thank-you after the sale.

18. Customer links: bills, loyalty page, QR menu

Customers can keep their bill on their phone, check their points and credit, and (in restaurants) browse the menu, call a waiter, ask for the bill and pay by UPI from the table's QR code. Links need a **shop hub** or a **cloud server** (chapter 15). With only a shop hub, links open on the shop Wi-Fi only.

Share a bill


After a sale, on the receipt screen press **Share bill**. The app makes the link and shows:

Button	What happens
QR code	The customer scans it with their phone camera
WhatsApp	Opens WhatsApp with the customer's number (if the bill has a customer) and a message with the link; press send
SMS	Sends the link by SMS to the customer's number. Shown only when the shop's cloud server has SMS set up
Copy link	Copies it, to paste anywhere

The bill page shows the shop, invoice number, items, GST split and payments, in English or Hindi, and can be printed. If the bill is cancelled later, the page says so after it is shared again. Links work for 90 days.

QR on receipts and the customer display

Settings → Customer links → QR to the bill on receipts and the customer display: every printed receipt ends with a QR to the bill, and the customer display shows it on the thank-you screen. The QR is added only if the link is ready within a few seconds; otherwise the receipt prints without it.



Customer links

Link address: leave it empty to use the server this device syncs with. A till that syncs with the shop hub makes Wi-Fi-only links; type your cloud server's address (for example `https://pos.example.com`) to make links that work anywhere.

Loyalty page

Open a customer → **Loyalty link**. It shows a private page with the customer's points, the credit they owe and their last 20 bills. Share it the same way (QR, WhatsApp, SMS, copy). The page updates by itself after each sale or payment of that customer. **New link** makes a new one; the old link stops working. Anyone who has the link can see the page, so send it only to the customer.

QR menu (restaurants)

Settings → Restaurant → QR ordering by guests has four choices:

Choice	Guests can
Off	Nothing (the QR code says ordering is closed)

Choice	Guests can
Menu only	Browse the menu with photos; no ordering
Auto-send / **Waiter confirms**	Order (chapter 17)

Whenever QR is not **Off**, the guest page also has three buttons:

Button	What waiters see under QR orders waiting	What to do
Call waiter	"Calls a waiter"	**On my way**
Ask for the bill	"Asks for the bill"	**Bring the bill** (the table shows **Bill asked**)
Pay by UPI	"Says paid ₹... by UPI · UTR ..."	Check the payment in your UPI app first, then **Check and take payment**: checkout opens on UPI with the amount and reference filled in

Pay by UPI shows the guest the table's bill and a UPI button with the amount; after paying, the guest types the UPI reference (UTR). Nothing is recorded until staff confirm in checkout.

Product photos come from each product's picture (Products → the product → photo).

19. Self-checkout kiosk, appearance and shop reset

A self-checkout **kiosk** lets customers scan, weigh and pay on their own. One staff member watches every kiosk from the **Kiosks** screen on any other till. Needs the `kiosk` feature in the licence. Setting up the device lock (Android, Windows, Linux, iPad) is described in `docs/kiosk-setup.md`.

Set up a kiosk (manager or admin)

Step	Where	What
1	**Staff**	Add a cashier for each kiosk, for example "Kiosk 1". Reports show the kiosk's sales under this name
2	On the kiosk device: **Settings** → **Self-checkout**	Pick that cashier, the payment methods, welcome text (English and Hindi), how long an untouched basket stays, and whether to ask for a mobile number. **Save**
3	Same card	**Start self-checkout on this device**. The device now shows only the kiosk screen

To leave kiosk mode: hold the shop logo for 3 seconds, type a manager PIN, **Exit self-checkout**.

Payment methods:

Method	What the customer does	Who confirms
Card on the card machine	Taps or inserts the card	The card machine
UPI on the card machine	Scans the QR on the card machine	The card machine
Shop UPI QR, checked by staff	Scans the QR on the kiosk, pays, taps **I have paid**	Staff on the Kiosks screen, after checking their UPI app

No cash, credit, points or discounts on a kiosk. Help requests and the UPI check need a shop hub or a cloud server (chapter 15); without one, staff help only with a PIN on the kiosk.

What the customer sees

1. **Welcome**: the shop logo, the welcome text, **Tap to start** (or just scan an item). **हिन्दी / English** switches the language.
2. **Basket**: scan barcodes, or search and tap items without a barcode; loose items are weighed on the scale. **+** adds one more. **−** or removing an item asks staff first.
3. **Pay**: the methods this kiosk allows, and an optional mobile number for the bill on WhatsApp and loyalty points.
4. **Thank you**: the receipt prints (if a printer is set up) and a QR shows the bill link. After 30 seconds the kiosk is ready for the next customer.

Call staff is always on screen. An item marked **Age check (18+)** (Products → the product → Selling) locks Pay until staff approve. If nobody touches the basket for the set time, the kiosk asks **Still there?** and clears the basket 30 seconds later, but never while a payment runs or staff are deciding.

The Kiosks screen (attendant)

Kiosks in the menu shows a tile per kiosk (shopping, paying, waiting for staff, offline) and the requests waiting for staff, oldest first:

Request	What to do
Calls staff	Go to the kiosk, then **On my way**
Age check: …	Check the customer's age, then **Approve** or **Deny** (denied removes the item)
Remove or reduce: …	**Approve** or **Deny**
Payment failed	Go and help; the customer can try again or pay another way
Says paid ₹… by UPI	Check your UPI app first, then **Approve** (the sale is saved) or **Deny**

A new request makes a sound. Staff can also answer at the kiosk: hold the logo 3 seconds, **Approve what the customer asked**, type a PIN. Whoever answers first wins; the other sees "Already answered by …".

Appearance (admin)

Settings → **Appearance** sets the shop's colours on every till, kiosk and the web panel:

- Six ready colour sets (Default, Ocean, Forest, Sunset, Rose, Slate), or your own: main colour, accent, background (light mode) and the Pay button colour, as `#RRGGBB`. Text on each colour turns black or white so it stays readable.
- **Add shop logo**: shown in the menu, on the sign-in screen, on the kiosk, at the top of printed receipts (printers in picture mode) and on bill links.
- **Reset colours** goes back to the default look.

Reset shop (admin)

Settings → **Reset shop** deletes every product, customer, bill and setting of the shop and starts again with the setup wizard. It is meant for a shop that was set up wrongly or is closing; it cannot be undone.

1. Admin PIN, then type the shop name exactly.
2. **Save backup**: a zip file with every bill and the whole database. The reset stays locked until it is saved. Keep it: bills are your GST record.
3. With a cloud server: the server's admin e-mail and password (the web panel login).
4. **Reset shop**, then a 10-second countdown you can cancel.

With a server, the shop is emptied on the server and every till. A till that was offline shows **This shop was reset** when it next connects and stops syncing; an admin taps **Wipe this device** (a backup of its unsent bills is saved first) and sets it up again.

20. Install, update and back up without internet

Everything here works with no internet and no server: a USB drive or a file is enough.

Install

Device	File	Steps
Android phone or tablet	`universal-pos-0.1.8.apk`	Copy it to the phone (USB cable, SD card or pen drive) → open it in **Files** → allow **Install unknown apps** for Files once → **Install**
Windows 10/11 PC	`UniversalPOS-Setup-0.1.8.exe`	Double-click. Windows may say "Windows protected your PC": press **More info** → **Run anyway** (the installer is not code-signed yet)
Ubuntu/Debian PC	`universal-pos_0.1.8_amd64.deb`	`sudo apt install ./universal-pos_0.1.8_amd64.deb`
Any other Linux	`universal-pos-0.1.8-linux-x64.tar.gz`	Unpack, then run `./universal-pos/install.sh` (no root)
iPhone or iPad	App Store	Install once from the App Store; after that the app works offline

Test builds from before 0.1.8 (Android): the new version is signed with the shop's permanent key, so Android will not install it over an old test build. Back up first (below), uninstall the old app, install 0.1.8, then restore.

Check that a file is genuine (optional): your seller sends `SHA256SUMS`, `SHA256SUMS.sig` and `release-pubkey.pem` with the files; on a PC run `sha256sum -c SHA256SUMS --ignore-missing` (each file must say OK).

Licence

Settings → **Licence**: **Import licence file**, **Paste licence**, or on a phone or tablet **Scan QR**. Your seller can show the licence as a QR code from their panel; point the camera at it.

Back up

Settings → **Backup** → **Back up now** saves one file, for example `ram-stores-2026-10-20-0930.posbackup`. Save it to a pen drive or another computer.

- The file is encrypted. Only the same shop's licence (from your seller, 0.1.8 or later) opens it. If the Backup card says your licence is older, ask your seller for a new licence file.
- On a Windows or Linux PC, **Choose folder** (for example the pen drive): the app then backs up there once a day by itself and keeps the last 7.
- After 7 days with sales and no backup, admins and managers see a reminder at the top of the screen.

Restore on a new device

1. Install the app on the new device. On the first screen pick **Restore from backup**.
2. **Choose backup file** → the shop name, date and number of records appear.
3. Add the shop's licence: **Licence file**, **Paste licence** or **Scan QR**.
4. **Invoice series for this device**: keep the suggestion (for example `A2`) so bill numbers never repeat the old device's.
5. **Restore**. Sign in with your usual PIN. Products, customers, bills, stock and staff are back. Printer and other device settings are set again on the new device.

Update from a pen drive

1. Your seller gives you `universal-pos-update-0.1.9.posupdate` (one file for Android, Windows and Linux).
2. **Settings** → **Updates** → **Install update from file** → pick it. The app checks that the file is genuine and newer.
3. **Back up and install**: the app always saves a backup first, then: - Android first asks where to save the backup (pick a pen drive or Downloads: app storage is lost if the app is ever uninstalled), then opens the installer (allow **Install unknown apps** for Universal POS the first time); - Windows closes the app and runs the installer; open Universal POS again when it finishes; - Linux shows one command to copy into a terminal.

Your data stays on the device. If anything goes wrong during an update, the database update is undone and the backup from step 3 can be restored.

Message	Meaning
"not signed by Universal POS"	The file did not come from your seller or was changed. Do not install it
"not newer than this app"	You already have this version or a later one
"no file for this device"	The update was made without your platform; ask your seller
"This licence is for another shop" (restore)	Use the licence of the shop in the backup