

CONNECTORS

7I76EU CONNECTOR LABELS & PURPOSES

NOTE: BLACK SQUARES INDICATE PIN 1; TABLES MATCH PIN LAYOUT

TB2 Step/Dir
(0 - 3)

Pin	Signal
24	+5VP
23	Dir 3 [+]
22	Dir 3 [-]
21	Step 3 [+]
20	Step 3 [-]
19	GND
18	+5VP
17	Dir 2 [+]
16	Dir 2 [-]
15	Step 2 [+]
14	Step 2 [-]
13	GND
12	+5VP
11	Dir 1 [+]
10	Dir 1 [-]
9	Step 1 [+]
8	Step 1 [-]
7	GND
6	+5VP
5	Dir 0 [+]
4	Dir 0 [-]
3	Step 0 [+]
2	Step 0 [-]
1	GND

TB3 Step/Dir (4),
Encoder, RS-422

Pin	Signal
24	GND
23	GND
22	Unreg Logic Pwr [+] In
21	Unreg Logic Pwr [+] In
20	+5VP
19	RSS-422 TX [-]
18	RSS-422 TX [+]
17	RSS-422 RX [-]
16	RSS-422 RX [+]
15	GND
14	IDX [-]
13	IDX [+]
12	+5VP
11	Enc B [-]
10	Enc B [+]
9	GND
8	Enc A [-]
7	Enc A [+]
6	+5VP
5	Dir 4 [+]
4	Dir 4 [-]
3	Step 4 [+]
2	Step 4 [-]
1	GND

TB1 Field I/O Power

Pin	Signal	Function
8	Ground	VIN, VField, Common
7	Ground	VIN, VField, Common
6	Ground	VIN, VField, Common
5	VIN	Isolated I/O Power 5-28V
4	VField	Field Power 5-28V
3	VField	Field Power 5-28V
2	VField	Field Power 5-28V
1	VField	Field Power 5-28V

TB5 Field I/O

Pin	Signal
24	Output 15
23	Output 14
22	Output 13
21	Output 12
20	Output 11
19	Output 10
18	Output 9
17	Output 8
16	Input 31
15	Input 30
14	Input 29
13	Input 28
12	Input 27
11	Input 26
10	Input 25
9	Input 24
8	Input 23
7	Input 22
6	Input 21
5	Input 20
4	Input 19 / MPG 1B
3	Input 18 / MPG 1A
2	Input 17 / MPG 0B
1	Input 16 / MPG 0A

TB6 Field I/O

Pin	Signal
24	Output 7
23	Output 6
22	Output 5
21	Output 4
20	Output 3
19	Output 2
18	Output 1
17	Output 0
16	Input 15
15	Input 14
14	Input 13
13	Input 12
12	Input 11
11	Input 10
10	Input 9
9	Input 8
8	Input 7
7	Input 6
6	Input 5
5	Input 4
4	Input 3 / Ana 3
3	Input 2 / Ana 2
2	Input 1 / Ana 1
1	Input 0 / Ana 0

P2 JTAG

Pin	Func.	Pin	Func.
1	TMS	2	TDI
3	TDO	4	GND
5	TCK	6	GND
7	/Reset	8	GND
9	/SS	10	+3.3V

TB4 Spindle

Pin	Signal
8	Spindle Dir[+]/Rev[-]
7	Spindle Dir[-]/Rev[-]
6	Spindle Ena[+]/Fwd[+]
5	Spindle Ena[-]/Fwd[-]
4	NC
3	Spindle [+]
2	Spindle Out
1	Spindle [-]

