	MARCONI/ IFR 2031 Frequency plan															
All frequence	cies in MHz															
carrier freq range		BFO	VC00		VCO1		VCO2		VCO3		div	mult		Series	Description	Part No.
0.01	14.5174	104.8576	off		38.940 955		off		off		8	1		AA1/3	Control board	44829/970
14.5174	21.09375	104.8576	off		off		955	1008	off		8	1		AB1	VCO board	44829/542
21.09375	25.09375		675 803		off		off		off		32	1		AB2/2	RF board (ALC)	44829/791
25.09375	29.84375		off		803 955		0	ff	0	off		1		AB3/5	Doubler (multiplier)	44829/772
29.84375	35.46875		off		off		955	1135	0	ff	32	1		AB4/1	BFO board	44829/697
35.46875	42.1875		off		off		0	ff	1135	1350	32	1		AT10	Attenuator	44829/087
42.1875	50.1875		675 803		off		0	off		ff	16	1		AR2/1	Internal Frequency Standard	44829/958
50.1875	59.6875		off		803 955		0	ff	0	ff	16	1				
119.375	141.875		off		off		955	1135	0	ff	16	1				
141.875	168.75		off		off		0	ff	1135	1350	16	1				
84.375	100.375		675 803		off		0	ff	off		8	1				
100.375	119.375		off		803	955	0	ff	off		8	1				
119.375	141.875		off		off		955	1135	0	ff	8	1				
141.875	168.75		0	ff	Of	f	0	ff	1135	1350	8	1				
168.75	200.75		675 803		O	off		ff	off		4	1				
200.75	238.75		0	ff	803	955	0	ff	0	ff	4	1				
238.75	283.75		off		off		955	1135	0	ff	4	1				
283.75	337.5		off		off		0	ff	1135	1350	4	1				
337.5	401.5		675 803		off		off		off		2	1				
401.5	477.5		off		803 955		off		off		2	1				
477.5	567.5		off		off		955	1135	off		2	1				
567.5	675		off		off		0	ff	1135	1350	2	1				
675	803		675 803		off		off		off		1	1				
803	955		off		803 955		0	off		off		1				
955	1135		off		off		955	1135	off		1	1				
1135	1350		off		off		0	ff	1135	1350	1	1				
1350	1606		675 803		off		0	ff	off		1	2				
1606	1910		off		803 955		0	ff	off		1	2				
1910	2270		off		off		955	1135	0	ff	1	2				
2270	2700		off		off		0	ff	1135 1350		1	2				