# Dual-Gang 289-42 Variable Tuning Capacitor

## Seeburg / TRW RETMA Source Code 289 Dual Air Variable Capacitor

### Product Overview

The 289-42 is a vintage dual-gang air variable tuning capacitor manufactured under RETMA manufacturer code 289 (Seeburg Corporation). Designed for broadcast radio, jukebox tuner chassis, and communications gear, it features a precision ball-bearing rear thrust bearing assembly and stamped // C trademark symbol.

### Technical Specifications

| | |
|---|---|
| **Part Number** | 289-42 (Stamped 289-42) |
| **Manufacturer Code** | RETMA / EIA Source Code 289 (Seeburg Corp, Chicago IL) |
| **Trademark Stamp** | Stamped // C (Capacitor Symbol) on front casting plate |
| **Configuration** | Dual-Gang (Two isolated stator sections with common rotor) |
| **Capacitance Range** | Approx. 15 pF min to 365 pF max per section (standard superhet tracking) |
| **Bearing System** | Precision rear ball-bearing race and front sleeve bushing |
| **Frame Construction** | Cast zinc/aluminum end frames with tie-plate rigidity |

### Key Features & Construction

- Precision rear ball-bearing race provides smooth rotation and zero axial play
- Dual gang design supports matched RF amplifier and local oscillator tracking
- Cast end plates with stamped manufacturer part number 289-42
- Phenolic stator insulator strips with integrated solder lug terminals
- Sturdy construction resistant to mechanical warp and frequency drift

### Mechanical & Mounting Details

- Mounting: Four front-plate mounting holes and two base mounting points
- Rotor shaft: 1/4 inch diameter steel shaft with flat notch for knob set screw
- Frame dimensions: approx. 2.75 x 2.50 x 2.75 inches
- Terminal: Lateral solder lugs on stator support brackets