Knight 1255 / RVC273 Dual-Gang Variable Capacitor

Allied Radio Knight-Kit / Radio Condenser Co. (EIA Source Code 282)

Product Overview

The Knight 1255 (manufactured by Radio Condenser Company under EIA code 282) is a precision dual-gang air variable capacitor designed for broadcast AM, shortwave receivers, and communications equipment. It features an integrated large-diameter stamped metal drive wheel intended for dial cord vernier drive systems, providing smooth, high-precision frequency tuning across its 13 pF to 405 pF capacitance span.

Technical Specifications

Part / Model Number	Knight 1255 / RVC 273, 6241 1120
Manufacturer Code	EIA Code 282 (Radio Condenser Company, Camden NJ)
Capacitance Range	13 pF min to 405 pF max per main section
Sections / Gangs	Dual-Gang (AM / Shortwave Receiver Tuning)
Dielectric	Air dielectric with high-Q ceramic/steatite insulation
Drive Mechanism	Large diameter integral dial pulley wheel for cord/vernier drive
Frame Material	Heavy-gauge stamped cadmium-plated steel chassis with front flange
Shaft Type	Center rotor shaft with ball bearing support assembly

Key Features & Construction

- Wide tuning range: 13 pF minimum to 405 pF maximum for multi-band RF tuning
- Large diameter vernier cord drive pulley for anti-backlash dial stringing
- Dual isolated stator sections with solder lug terminals
- Low RF loss steatite insulating spacers for optimal circuit Q factor
- Rear and front ground wiping contacts for low noise operation

Mechanical & Mounting Details

- Panel / chassis mount via front plate threaded mounting holes
- Integral drive pulley diameter: approx. 2.75 inches with cable guide grooves
- Shaft diameter: 1/4 inch brass/steel central shaft
- Overall dimensions: approx. 3.25 x 3.0 x 3.0 inches (including pulley)