

PARTS REFERENCE

ITEM NO	DRAWING REFERENCE	DESCRIPTION	PART NUMBER	QUANTITY
1	E1,E9,E18	DEC 74H53N	IC 9300262	3
2	E2,E5,E6,E7,E12,E25,E27,E31,E36,E39,E45,E47	DEC 7402N	IC 9300204	11
3	E3,E28,E34,E40,E42	DEC 881A	IC 9309713	5
4	E41,E42,E11,E16,E22,E24,E26,E37,E44,E45	DEC 7402N	IC 9305575	10
5	E6,E32	DEC 7402N	IC 9305577	2
6	E7,E11	DEC 74162N	IC 9309664	2
7	E8,E29	DEC 7450N	IC 9305550	2
8	E9,E13,E14,E30,E35	DEC 7450N	IC 9305581	5
9	E15	DEC 7453N	IC 9305582	1
10	E33,E48	DEC 7416N	IC 9305576	2
11	E38	DEC 7416N	IC 9305547	2
12	E41	DEC 350	IC 9309485	1
13	E43	DEC 350	IC 9309487	1
14	E46	DEC 8881	IC 9309705	1
15	C1-C39,C41,C43,C45-C47,C49-C51,C56	01 MF0, 100V, 20%	CAP 0001610	48
16	C42	10000 MME, 100V, 5%	CAP 0002344	1
17	C44,C48	55 MME, 100V, 5%	CAP 0000004	1
18	C52-C55	330 MME, 100V, 5%	CAP 0000023	2
19	R1,R6	6.8 MF0,35V, 20%	CAP 0000067	4
20	R2	47, 1/4 W, 5%	RES 1300202	2
21	R3	5.6 K, 1/4W, 5%	RES 1301874	1
22	R3,R7	170, 1/4W, 5%	RES 1300336	2
23	R4	220, 1/4W, 5%	RES 1300271	1
24	R5	2000, 1/4W, 5%	RES 1300365	1
25	D1	D644 DIODE	1101114	1

NOTES:

1. PIN NOTATION THROUGHOUT IS ORDERED UPON MODULE PLACEMENT IN THE KAI! PROCESSOR. MODULE REFERENCE ALONE IS OBTAINED BY DELETING THE NUMBER (SLOT LOCATION) AFTER THE FIRST LETTER, AND CONVERTING THE FIRST LETTER ACCORDING TO THE PIN NOMENCLATURE CHART AT RIGHT.
2. ALL SIGNALS THAT HAVE MODULE PINS ARE SO NOTED: MULTIPLE NOTATIONS OF THE SAME SIGNALS WITHIN A MODULE HAVE THE PIN NOTED ON EACH. AN INPUT SIGNAL IS NOTED ONLY ONCE PER SHEET UNLESS SEPARATE PINS ARE USED: MULTIPLE INPUTS ARE CONNECTED. MODULE OUTPUT SIGNALS ARE BROUGHT TO THE EXTREME RIGHT OF EACH SHEET.
3. PROCESSOR SIGNAL SOURCE NOTATION (KIO-2, FOR EXAMPLE) IDENTIFIES THE SIGNAL SOURCE (PRINT AND MODULE). THE FIRST NUMBER AFTER THE K INDICATES THE MODULE PRINT SET, WHILE THE SECOND INDICATES THE SHEET WITHIN THE SET. IF ON A PRINT, THE FIRST NUMBER OF THE K PREFIXES COINCIDE FOR A SIGNAL NAME AND THE PRINT (SEE TITLE BLOCK), THE SIGNAL IS GENERATED ON THE MODULE. A DIFFERENCE IN THE FIRST NUMBER OF THE K PREFIXES INDICATES A SIGNAL GENERATED OFF THE MODULE. SIGNALS WITH A "BUS" PREFIX INDICATE A "WIRED OR" SITUATION, AND MULTIPLE SOURCES FOR THE SIGNAL CAN EXIST.
4. DETAILS ON COMPONENTS ARE NOTED IN THE PARTS REFERENCE. PLACEMENT IS NOTED IN THE COMPONENT PLACEMENT DIAGRAM.
5. GND AND +5V ARE USUALLY PIN 7 AND PIN 14, RESPECTIVELY. EXCEPTIONS ARE:



IC TYPE	GND	+5V
DEC 7481	PIN 10	PIN 4
DEC 7482	PIN 11	PIN 4
8251	PIN 8	PIN 16
DEC 8271	PIN 8	PIN 16
DEC 380	PIN 1	PIN 8
DEC 384	PIN 1	PIN 8

6. UNLESS OTHERWISE NOTED: RESISTANCE IS IN OHMS;
CAPACITANCE IS IN PICO FARADS. CAPACITORS WITHOUT
ANY NOTED VALUES ARE .01 MFD.

COMPONENT PLACEMENT


PIN NOMENCLATURE

MODULE	PROCESSOR
--------	-----------



FIRST USED ON OPTION MODEL		QTY.		DESCRIPTION		PART NO.		REV.	
PDP II									
UNLESS OTHERWISE SPECIFIED		DIN		DATE		PARTS LIST			
UNLESS OTHERWISE SPECIFIED		DIN		DATE		digital		EQUIPMENT CORPORATION	
DIMENSIONS IN INCHES		DIN		DATE		MAYNARD MASSACHUSETTS			
TOLERANCES		DIN		DATE					
DECIMALS FRACTIONS ANGLES		DIN		DATE		TITLE			
± .000 ± .001 ± .005		DIN		DATE		STATE CNTL			
FINAL SURFACE QUALITY		DIN		DATE					
REMOVE BURNING AND BREAK SHARP CORNERS		DIN		DATE					
MATERIAL		NEXT HIGHER ASSY		M727		K2-			
#		A-M-L KAIL-0		SIZE CODE		NUMBER		REV.	
				DCS M727-0-1				E.	
FINISH		SCALE		SHEET		OF 3			
#				ETCH REB C D					

This drawing and specifications, herein, are the property of Digital Equipment Corporation and shall not be reproduced or copied in whole or in part as the basis for the manufacture or sale of items without written permission.



REV	CHANGE NO
1	1

DEC FORM NO. 102A

FIRST USED ON OPTION/MODEL		QTY.	DESCRIPTION	PART NO.	ITEM NO.
PDP11					
UNLESS OTHERWISE SPECIFIED		PARTS LIST			
UNLESS OTHERWISE SPECIFIED		digital EQUIPMENT CORPORATION			
DIMENSION IN INCHES		TITLE			
TOLERANCES		STATE CNTL			
DECIMALS FRACTIONS ANGLES		M727 K2-2			
± .005 ± .125 ± .007		SIZE CODE			
FINAL SURFACE QUALITY		NUMBER			
REMOVE BURRS AND BREAK SHARP CORNERS		DCS M727-0-1			
MATERIAL		SCALE NONE			
NEXT HIGHER ASSEMBLY		SHEET 2 OF 3			
A-ML-KA11-0		DIST.			
FINISH		REV E?			

This drawing and specifications, herein, are the property of Digital Equipment Corporation and shall not be reproduced or copied or used in whole or in part as the basis for the manufacture or sale of items without written permission.

D

C

B

A

100%

100%


100%

100%

100%

100%

100%



REV.	CHG.	NO.
1	1	1

DEC 10/74

100%

100%

100%

100%

100%

100%

FIRST USED ON OPTION MODEL PDPII		QTY.	DESCRIPTION	PART NO.	ITER NO.
UNLESS OTHERWISE SPECIFIED		PARTS LIST			
UNLESS OTHERWISE SPECIFIED		TOLERANCES			
DIMENSION IN INCHES		DATE 12-7-69			
DECIMALS FRACTIONS ANGLES		DATE 3-5-70			
= .001 = 1/1000 = 1/1000		DATE 3-5-70			
REMOVE BURRS AND BREAK SHARP		DATE 3-5-70			
COMMENTS		DATE 3-5-70			
MATERIAL		DATE 3-5-70			
NEXT HIGHER ASSEMBLY		DATE 3-5-70			
FINISH		DATE 3-5-70			
SCALE NONE		DATE 3-5-70			
SHEET 3 OF 3		DATE 3-5-70			
DIST.		DATE 3-5-70			
DRN. of Rader		DATE 12-7-69			
CHK. of Rader		DATE 3-5-70			
ENG. of Rader		DATE 3-5-70			
PROB. ENG. of Rader		DATE 3-5-70			
MATERIAL		DATE 3-5-70			
NEXT HIGHER ASSEMBLY		DATE 3-5-70			
FINISH		DATE 3-5-70			
SCALE NONE		DATE 3-5-70			
SHEET 3 OF 3		DATE 3-5-70			
DIST.		DATE 3-5-70			
DRN. of Rader		DATE 12-7-69			
CHK. of Rader		DATE 3-5-70			
ENG. of Rader		DATE 3-5-70			
PROB. ENG. of Rader		DATE 3-5-70			
MATERIAL		DATE 3-5-70			
NEXT HIGHER ASSEMBLY		DATE 3-5-70			
FINISH		DATE 3-5-70			
SCALE NONE		DATE 3-5-70			
SHEET 3 OF 3		DATE 3-5-70			
DIST.		DATE 3-5-70			

DEC 10/74

100%

100%

100%

100%

100%

100%