NAVIGATION / +C THROUGH +C4

Quick reference card

From Pads, select a pad and press **INFO twice** to open its parameters. On a supported parameter, **select + INFO** opens modulation. Page numbers refer to the full reference guide.

Waveform · 2	Pad > INFO. Spread or pinch vertically for 25-3200% amplitude, horizontally for time. A still two-finger tap restores 100% amplitude and horizontal fit.
Stop / reset · 2	On Pads, hold a **Trigger** pad for 3 s to stop it after its usual retrigger. Double-tap a numeric dial to reset its base value and retain its routes.
Speed / Pitch · 3	**Sample > LFO/Spd > SPEED**, 50-200%, one eligible voice. Pitch works across pads and on the Speed voice. SPDBUSY / RETRY concern Speed only.
Tone · 4	**Pad > Tone**. Fidelity, Drive, Filter 2, Res 2 and Slope 1. Select + INFO on Drive, Filter 2 or Res 2 for modulation.
Clip / Slicer · 5-6	**Clip > Pos** for Loop Fade, Shift, Play Len, Sync, Live Flip and Fill every. **Slicer > Pos** for Sync, Sync Grid and **Slice Fit > Cut / Tape**.
GEN · 7-8	**Pad > Gen** for algorithm, steps and timing. **Cnf** for Cond, Proc and Resp Pad. Granular has all GEN controls in Cnf. **Tools > Mstr > Section > GEN Run > Run On** starts the generators.
Delay · 9	**FX1 > INFO > More**. Flutter, Mod Rate, Mod Depth, Phase, Drive, Tone and Return dB. Codec shows Loss and Bandwidth.
Reverb / FX3 · 10	**FX2 > INFO** opens reverb. Tap the selected FX2 cell again for **FX 3**, then INFO. More opens detailed Room/Hall/Chamber controls.
Sends / outputs · 9-11	**Pad > Pos > FX1/2/3 Send**, then INFO. **Tools > Rec > FX Out** routes FX1/2. FX3 Out is on its Plate page or More for the other types.
Modulation · 11-12	**Source** includes KEY, ENV, CHAOS, RAND and NET. Up to 12 saved routes per pad. Slicer Slice Seq responds to source edges.
CV / MIDI · 13, 16	**Tools > Rec > CV In** for Scale, Offset, Quantize and Root. **Tools > MIDI > Monitor** for incoming messages.
Master · 14-15	**Tools > Comp** for compression. **Mstr > Section** for Comp env, Master FX (shaper / Drive / Sweep), Dist Ctrl (Tone / Mix / Level) and Sweep Mod.
Display / reset · 2, 14	**Tools > Disp** for saver, signal wake and line graphic. Double-tap the counter to renumber the next bar. **Tools > Main > RESET** offers Tools or FX.
Recording / update · 16-17	Record dry while monitoring through the pad sends. For installation or rollback, put **BITBOXMK2.bin** in the card root and power up holding INFO.