STUDENT PROJECTS LABORATORY - LOCKOUT / TAGOUT [LOTO] PROCEDURE

ENERGY ISOLATION SPECIFICATION | ASSET: SAW-02 | TAG: 747061

Horizontal Wet/Dry Drop Bandsaw

Authorized LOTO Personnel: Sr. Instructional Lab Supervisor (Max Wright) & Student Research Assistants (SRAs)

Notification Channel: Max Wright - Teams / Text Message | Zone: Zone 4: Cutting, Saws & Drilling (SAW)

STEP 1 - NORMAL MACHINE SHUTDOWN PROCEDURE

Turn power switch to OFF position (Front right face).

STEP 2 - HAZARDOUS ENERGY SOURCES, MAGNITUDES & ISOLATION POINTS

Source #1: Electrical (240V AC)

Isolation Location: Power switch & 240V wall outlet.

Lockout Procedure: Turn switch down to OFF, unplug machine from outlet, and install Rotating Electrical Plug Lockout on power cable.

STEP 3 - STORED / RESIDUAL ENERGY DISSIPATION

Lower saw bow head fully onto horizontal rest stop and close hydraulic feed valve.

STEP 4 - ZERO-ENERGY VERIFICATION ('TRY' STEP)

Turn power switch ON and verify blade does not move.