STUDENT PROJECTS LABORATORY - LOCKOUT / TAGOUT [LOTO] PROCEDURE

ENERGY ISOLATION SPECIFICATION | ASSET: SAW-04 | TAG: MITER-10-01

10" Bevel Compound Miter Saw

Authorized LOTO Personnel: Sr. Instructional Lab Supervisor (Max Wright) & Student Research Assistants (SRAs)

Notification Channel: Max Wright - Teams / Text Message | Zone: Zone 4: Cutting, Saws & Drilling (SAW)

STEP 1 - NORMAL MACHINE SHUTDOWN PROCEDURE

Release handle trigger and allow blade to coast to a complete stop.

STEP 2 - HAZARDOUS ENERGY SOURCES, MAGNITUDES & ISOLATION POINTS

Source #1: Electrical (120V AC)

Isolation Location: 120V wall power cord.

Lockout Procedure: Unplug from wall and secure male plug inside Rotating Electrical Plug Lockout box.

STEP 3 - STORED / RESIDUAL ENERGY DISSIPATION

Wait for saw blade to come to a complete stop and lock head in down position if servicing.

STEP 4 - ZERO-ENERGY VERIFICATION ('TRY' STEP)

Depress handle trigger to verify zero electrical energy.