

Standard Operating Procedure ***Blue M Industrial Oven***

SOP: Blue M Industrial Oven

The Blue M is a high-performance convection oven designed for precision heat-treating, curing, and drying. It utilizes a high-wattage heating element and a horizontal airflow system to maintain strict temperature uniformity. This machine is a precision thermal instrument and is **not explosion-proof**; it must never be used for materials that produce flammable or volatile vapors.

Potential Hazards

- Thermal Burns: Internal temperatures can reach 650F (343C). The door, shelves, and walls remain hazardous long after the cycle ends.
- Explosion/Fire: Strictly Forbidden: Processing flammable solvents, thinners, or volatile chemicals. This oven is a non-vented, non-explosion-proof unit.
- Bearing Failure: Turning off the main power while the oven is at a high temperature >167 F will cause the circulation motor shaft bearings to seize.
- Pressure Build-up: Heating sealed containers can cause them to rupture or explode within the cabinet.

Personal Protective Equipment (PPE)

PPE Item	Requirement
Eye Protection	**Safety Goggles (ANSI Z87.1): Mandatory when opening the door to protect against high-velocity hot air and airborne particulates.**
Thermal Protection	**High-Temperature Insulated Gloves:** Mandatory for handling internal shelving or workpieces. Assume all internal surfaces are hazardous.
Body Protection	**Flame-Resistant Lab Coat/Apron: Recommended to protect skin from accidental contact with the oven exterior (>140F at high setpoints).**
Respiratory	**Ensure local exhaust ventilation is active if the heating process generates non-explosive fumes or odors.**



Standard Operating Procedure ***Blue M Industrial Oven***

Before Use

- **Interior Inspection:** Ensure the oven is clear of old samples and the **bottom diffuser plate** is free of debris.
- **Loading Logic:** Distribute workpieces evenly across shelves. Do not place items directly on the floor of the oven. For flat materials, load **vertically** to minimize airflow obstruction.
- **OTP Calibration:** Set the **Over-Temperature Protection (OTP)** dial to approximately **15C** above your target setpoint. This acts as a mechanical fail-safe if the electronic controller fails.
- **Exhaust Dampers:** Adjust the top exhaust vents based on the process requirements (Open for moisture removal, Closed for rapid heat-up/efficiency).

During Use

- **The "200 Rule":** Avoid opening the door if the internal temperature is above **200F**/93C. Rapid cooling can cause thermal shock to samples and dangerous "burping" of hot air toward the operator.
- **Airflow Monitoring:** Listen for the circulation fan. If the fan stops or makes an unusual grinding noise, shut down the heating elements immediately.
- **Cycle Monitoring:** Periodically check the OTP status. If the OTP light is on, the heaters have been cut off due to an over-temperature event.

After Use

- **CRITICAL COOL-DOWN:** You **must** allow the oven to cool below **167F**/75C with the circulation fan running before turning off the main power switch.
- **Sample Removal:** Use thermal gloves and tongs. Place hot samples on a designated heat-resistant surface or cooling rack.
- **Housekeeping:** Once cooled to room temperature, remove all debris and wipe down shelves. Ensure the door is securely latched.

Emergency Equipment and Procedures

- **Emergency Stop:** Know the location of the main circuit breaker or the power disconnect on the rear/side of the unit.
- **Internal Fire:** Keep the door **CLOSED** to starve the fire of oxygen. Turn off the main power and use a **CO2 or Dry Chemical** extinguisher if necessary.
- **Reporting:** Report all over-temperature trips, motor failures, or injuries to the Laboratory Project Supervisor immediately.



Standard Operating Procedure ***Blue M Industrial Oven***

THE OHIO STATE UNIVERSITY
COLLEGE OF ENGINEERING

Revised 1/9/2025