DIY Wooden Planter

By **Erin Spain**

Difficulty

Easy

This indoor DIY wooden planter is a great addition to any room, and can be customized to any color or finish you choose!

Tools

Kreg Tools

Kreg® Pocket-Hole Jig 520PRO

Kreg 20V Ionic Drive™ 1/2" Compact Drill (Tool Only)

Other Tools

Saw

Materials

Wood Products

1 1x12 Board , 1x12x6

1 1x2 Board , 1x2x6

1 2x2 Board , 2x2x6

Hardware & Supplies

32 1 1/4" Pocket Hole Screws

1 Sanding Block

1 Paint Or Stain

Cut List & Parts

- **4** 1x12 Boards (For Sides) , 1"x12"x12"
- **4** 1x2 Boards (For Bottom Slats) , 1"x2"x13 1/2"
- **4** 2x2 Boards (For Legs) , 2"x2"x15"

Directions

1 Cut Your Wood

Cut your wood to the specified dimensions.

2 Drill Pocket Holes

Drill 3 pocket holes along 2 parallel sides of each 1x12x12 boards, and 1 pocket hole at each end of the 1x2 pieces.

3 Sand

Use a sanding block to sand edges smooth.

4 Attach Legs to Front and Back

Using 1 1/4" pocket hole screws, attach 2 legs to one of the 1x12x12 pieces. Repeat. These will be the front and back of the planter.

5 Attach Sides

Attach remaining 1x12x12 pieces (the sides) to the front and back you assembled in the previous step.

6 Add Bottom Slats

Use 1 1/4" pocket hole screws to attach bottom slats (1x2 pieces). You can use a scrap piece of wood as a spacer or just eyeball it and try to space them as evenly as possible. It will not be visible so doesn't have to be perfect.

7 Paint or Stain

Finish your planter with any paint or stain of your choice.