MIDI MAPPING

A LOOM layout for the MiniLab 3

The Arturia MiniLab 3 has eight endless knobs, four faders, eight pads in two banks, a main encoder that clicks, and 25 keys. LOOM has nine tracks: five audio tracks and four instrument tracks. This layout reaches all nine by working the track that has the focus.

ONE USER PROGRAM

Follow the focus

The pads move the focus and work the focused track. The knobs play its macros, and the faders set its level and sends. All nine tracks are two pad presses away, so one small controller works the whole song.

PAGE 2: THE BOARD
PAGE 3: WHAT EACH CONTROL SENDS
PAGE 4: SETUP

LOOM · MIDI LAYOUTS · ARTURIA MINILAB 3 2 / 4

THE BOARD

Follow the focus

The pads move the focus and work the focused track. The knobs play its macros, and the faders set its level and sends. All nine tracks are two pad presses away, so one small controller works the whole song.

KNOBS, FADERS AND THE MAIN ENCODER

SHIFT · HOLD · OCT − · OCT +

PITCH · MOD

KEYS AND STRIPS NOT MAPPED

MAIN ENCODER

TEMPO — TURN

OPEN — SHIFT + TURN

RENDER — CLICK · FOCUSED

RENDER ALL — SHIFT + CLICK

KNOBS · RELATIVE 1

MACRO 1 FOCUSED · MACRO 2 FOCUSED · MACRO 3 FOCUSED · MACRO 4 FOCUSED

MACRO 5 FOCUSED · MACRO 6 FOCUSED · MACRO 7 FOCUSED · MACRO 8 FOCUSED

FADERS

1	2	3	4
LEVEL FOCUSED	CUE FOCUSED	FX 1 FOCUSED	LEVEL MASTER

PADS

	1	2	3	4	5	6	7	8
BANK A THE FOCUSED TRACK	PREVIOUS TRACK · FOCUS	NEXT TRACK · FOCUS	RING FOCUSED	OVERDUB FOCUSED	STOP FOCUSED	UNDO FOCUSED	REDO FOCUSED	CLEAR HOLD · FOCUSED
BANK B THE SONG	ALL START	ALL STOP	TO TOP PLAYHEAD	PERFORM FROM HERE	MUTE FOCUSED	SOLO FOCUSED	CLEAR ALL SOLOS	ALL CLEAR HOLD 1 S
SHIFT + EITHER BANK	ARPEGGIATOR NOT MAPPED	BANK A / B NOT MAPPED	PROGRAM NOT MAPPED	CLICK ON / OFF	TRANSPORT STOP	TRANSPORT START	RECORD PERFORMANCE	TAP TEMPO NOT MAPPED

Move the focus, then play the track. PREVIOUS and NEXT walk the focus across all nine tracks. RING, OVERDUB, STOP, UNDO, REDO and CLEAR, the knobs, the first three faders and the encoder's click all act on the track that has it.

Shift + Pad 2 switches the bank. Bank A works the focused track. Bank B works the song. Pad 8 clears in both banks, and both clears need a one-second hold.

The knobs follow the focus at once. They are endless and relative, so a macro moves from your first turn. The faders send positions, so after you move the focus a fader waits until it passes the new track's value.

RECORD, RENDER, CLEAR · UNDO AND REDO · START AND PERFORM · FOCUS, CLICK, TEMPO · MUTE AND SOLO · LEVEL AND STOP · SENDS AND MACROS · MINILAB FUNCTION, NOT MAPPED · OPEN, YOURS TO MAP

The keys stay free for the synth and the sampler. Page 4 lists the settings in MIDI Control Center and in LOOM that make the layout work.

THE BOARD

Follow the focus

The pads move the focus and work the focused track. The knobs play its macros, and the faders set its level and sends. All nine tracks are two pad presses away, so one small controller works the whole song.

KNOBS, FADERS AND THE MAIN ENCODER

SHIFT

HOLD

OCT -

OCT +

PITCH

MOD

KEYS AND STRIPS
NOT MAPPED

MAIN ENCODER



TEMPO
TURN

OPEN
SHIFT + TURN

RENDER
CLICK · FOCUSED

RENDER ALL
SHIFT + CLICK

KNOBS · RELATIVE 1

MACRO 1 FOCUSED	**MACRO 2** FOCUSED	**MACRO 3** FOCUSED	**MACRO 4** FOCUSED
MACRO 5 FOCUSED	**MACRO 6** FOCUSED	**MACRO 7** FOCUSED	**MACRO 8** FOCUSED

FADERS

1	2	3	4
LEVEL FOCUSED	**CUE** FOCUSED	**FX 1** FOCUSED	**LEVEL** MASTER

PADS

	1	2	3	4	5	6	7	8
BANK A THE FOCUSED TRACK	**PREVIOUS** TRACK · FOCUS	**NEXT** TRACK · FOCUS	**RING** FOCUSED	**OVERDUB** FOCUSED	**STOP** FOCUSED	**UNDO** FOCUSED	**REDO** FOCUSED	**CLEAR** HOLD · FOCUSED
BANK B THE SONG	**ALL START**	**ALL STOP**	**TO TOP** PLAYHEAD	**PERFORM** FROM HERE	**MUTE** FOCUSED	**SOLO** FOCUSED	**CLEAR ALL** SOLOS	**ALL CLEAR** HOLD 1 S
SHIFT + EITHER BANK	ARPEGGIATOR NOT MAPPED	BANK A / B NOT MAPPED	PROGRAM NOT MAPPED	**CLICK** ON / OFF	**TRANSPORT** STOP	**TRANSPORT** START	**RECORD** PERFORMANCE	TAP TEMPO NOT MAPPED

Move the focus, then play the track. PREVIOUS and NEXT walk the focus across all nine tracks. RING, OVERDUB, STOP, UNDO, REDO and CLEAR, the knobs, the first three faders and the encoder's click all act on the track that has it.

Shift + Pad 2 switches the bank. Bank A works the focused track. Bank B works the song. Pad 8 clears in both banks, and both clears need a one-second hold.

The knobs follow the focus at once. They are endless and relative, so a macro moves from your first turn. The faders send positions, so after you move the focus a fader waits until it passes the new track's value.

RECORD, RENDER, CLEAR · UNDO AND REDO · START AND PERFORM · FOCUS, CLICK, TEMPO · MUTE AND SOLO · LEVEL AND STOP · SENDS AND MACROS · MINILAB FUNCTION, NOT MAPPED · OPEN, YOURS TO MAP

EVERY CONTROL, WITH ITS NUMBER

What each control sends

What to set in MIDI Control Center for each control, all on channel 16. The numbers are ones LOOM's built-in layout leaves free, so a learned control never also moves a built-in one.

PAD BANK A — The focused track

CC, Gate, 127 on and 0 off. Learn each as BUTTON.

PADS	CC 112 PREVIOUS TRACK · FOCUS	CC 113 NEXT TRACK · FOCUS	CC 114 RING FOCUSED	CC 115 OVERDUB FOCUSED	CC 116 STOP FOCUSED	CC 117 UNDO FOCUSED	CC 118 REDO FOCUSED	CC 119 CLEAR HOLD · FOCUSED

PAD BANK B — The song

Pads 1, 2 and 8 send built-in notes and need no learning. Pads 3 to 7 are CC, Gate. Learn each as BUTTON.

PADS	NOTE 120 · BUILT IN ALL START	NOTE 121 · BUILT IN ALL STOP	CC 90 TO TOP PLAYHEAD	CC 91 PERFORM FROM HERE	CC 92 MUTE FOCUSED	CC 93 SOLO FOCUSED	CC 94 CLEAR ALL SOLOS	NOTE 122 · BUILT IN ALL CLEAR HOLD 1 S

SHIFT + PADS — Transport

Pads 4 to 7 send Mackie Control on the MiniLab 3 MCU port and are not editable. Learn each as BUTTON.

PADS	ARP ARPEGGIATOR NOT MAPPED	PAD BANK A / B NOT MAPPED	PROG PROGRAM NOT MAPPED	LOOP · MCU CLICK ON / OFF	■ STOP · MCU TRANSPORT STOP	▶ PLAY · MCU TRANSPORT START	● REC · MCU RECORD PERFORMANCE	TAP TAP TEMPO NOT MAPPED

KNOBS — Macros

CC, Relative 1. Learn as RELATIVE 64: FOCUSED TRACK › MACRO 1 to 8.

KNOBS	CC 30 MACRO 1 FOCUSED	CC 31 MACRO 2 FOCUSED	CC 32 MACRO 3 FOCUSED	CC 33 MACRO 4 FOCUSED	CC 34 MACRO 5 FOCUSED	CC 35 MACRO 6 FOCUSED	CC 36 MACRO 7 FOCUSED	CC 37 MACRO 8 FOCUSED

FADERS AND MAIN ENCODER — Mix, tempo, render

Faders 1 to 3 learn as CONTROLLER: FOCUSED TRACK › LEVEL, LEVEL - CUE and LEVEL - FX 1. Fader 4 is built in. The encoder's turn learns as RELATIVE 64, and its clicks as BUTTON.

CONTROLS	CC 105 LEVEL FOCUSED	CC 106 CUE FOCUSED	CC 107 FX 1 FOCUSED	CC 104 · BUILT IN LEVEL MASTER	CC 108 TEMPO TURN	OFF OPEN SHIFT + TURN	CC 110 RENDER CLICK · FOCUSED	CC 111 RENDER ALL SHIFT + CLICK

RECORD, RENDER, CLEAR · UNDO AND REDO · START AND PERFORM · FOCUS, CLICK, TEMPO · MUTE AND SOLO · LEVEL AND STOP · SENDS AND MACROS · MINILAB FUNCTION, NOT MAPPED · OPEN, YOURS TO MAP

SETUP

Settings that make the layout work

IN MIDI CONTROL CENTER

01 **Build one User Program in MIDI Control Center.**
Set the knobs, faders, pads in both banks and the main encoder as page 3 shows, and store it to User 1. In Device Settings, disable the User Programs you do not use, so Shift + Pad 3 reaches User 1 in fewer presses.

02 **Put every control on channel 16.**
That is LOOM's command channel. Leave the keys on the keyboard channel, which is 1 unless you changed it.

03 **Set the knobs to Relative 1, and Knob Acceleration to None.**
A relative knob sends steps, not a position, so a macro moves the newly focused track's control from your first turn. Without acceleration, a fast turn sends a few steps at a time, which LOOM accepts.

04 **Set every pad to Gate.**
A toggle keeps its own on and off state, which can disagree with LOOM's. A gate sends on, then off, and LOOM keeps the state.

05 **Colour the pads to match this sheet.**
Each pad's colour is set in MIDI Control Center and does not change, so use it to tell RING, UNDO and CLEAR apart.

06 **Set Transport Mode to MCU.**
It is in Device Settings. Shift + Pads 4 to 7 then send Mackie Control on the MiniLab 3 MCU port.

IN LOOM

01 **Leave MIDI CH at 16.**
It is in the side panel's GLOBAL tab, under MIDI.

02 **Point the instrument tracks at the MiniLab 3 MIDI port.**
Set each track's MIDI INPUT to that port, not to Any device. The transport pads send notes 86, 93, 94 and 95 on channel 1 from the MCU port, and a track listening to every device would play them.

03 **Learn the transport pads as BUTTON.**
Hold Shift and press the pad while the card is listening. Map Loop to CLICK, Stop to TRANSPORT STOP, Play to TRANSPORT START and Rec to RECORD.

04 **Learn the rest with + ADD MAPPING.**
Choose the target, touch the control, check the type and press USE. Pads and encoder clicks are BUTTON, knobs and the encoder's turn are RELATIVE 64, and faders are CONTROLLER. MASTER LEVEL and the ALL START, ALL STOP and ALL CLEAR pads are built in and need no learning.

05 **Assign the macros.**
On each track, point MACRO 1 to MACRO 8 at the controls you want under the knobs, in the side panel's MACROS block. An empty macro does nothing.

Two things to check on your unit. If Shift + Pads 4 to 7 send nothing in a User Program, those four targets have no control, and bank B's ALL START and ALL STOP still start and stop the song. If LOOM's card proposes CONTROLLER for the main encoder's turn, it sends positions: map TEMPO as CONTROLLER, or leave the encoder open.