PS:ins params的字段为空串时,表示该槽位在当前用户表达中不存在值

ŧ	指令	指令格式	示例	备注
	Phone.Dial	<pre>{     "ins_name": "action_phone_call",     "ins_params": {         "contact.person": (str),         "telephone.number": (str),         "simcard.id": (str, 1-5)     } }</pre>		contact.person和telephone.number为二选一必填槽; 当simcard.id为空表示默认用第一张卡,如果当前手机有多张卡,应返回特定格式的query"# user selection from xx candidates"给云端对话平台,促使云端触发"simcard.id"填槽话术,对话平台会在用户回复对应实体后,发送新的action_phone_call指令;
	Phone.AnswerCall	<pre>{     "ins_name": "action_answer_call",     "ins_params": {     } }</pre>		
	Phone.RejectCall	<pre>{     "ins_name": "action_end_call",     "ins_params": {     } }</pre>		
	Phone.CheckPhoneBook	<pre>{     "ins_name": "action_search_phone_book",     "ins_params": {         "contact.person": (str),         "contact.person.id": (str),     } }</pre>		当contact.person.id为空,contact.person有多个重名时,应返回特定格式的query"# user selection from xx candidates"给云端对话平台,促使云端触发"contact.person.id"填槽话术,对话平台会在用户回复对应实体后,发送新的action_search_phone_book指令;
	Message.Send	<pre>{     "ins_name": "action_send_message",     "ins_params": {         "contact.person": (str),         "telephone.number": (str),         "simcard.id": (str, 1-5),         "content": (str)     } }</pre>		contact.person和telephone.number为二选一必填槽; 当simcard.id为空表示默认用第一张卡,如果当前手机有多张卡,应返回特定格式的query"# user selection from xx candidates"给云端对话平台,促使云端触发"simcard.id"填槽话术,对话平台会在用户回复对应实体后,发送新的action_send_message指令;